RV1 B10K Dry
RV2 B10K Loop
RV3 B10K −8
RV4 B10K +5
RV5 B10K +8
RV6 B10K Fade
RV7 B10K Texture

R1 R2 R3 R4 R5 R6 R7 1k

C1 C2 C3 C4 C5 C6 C7 100n

C8 10u

C9 100n

U1 Daisy Seed

J1 Freeze footswitch

J2 Clear footswitch

R8 R9 470

D1 Red/Green

J3 In L / Mono (grounded when empty)

J4 In R (normalled from In L)

J5 Out L / Mono

J6 Out R (ring switch = plug detect)

R10 1k

R15 R16 R17 R18 DNP 10k

C10 C11 10u

R11 R12 R13 R14 100k

SW1 Single / Multi

SW2 +5 up / down

H1 H2 H3 H4 M3

Pots: CCW end (1) to GND, CW end (3) to +3V3A, wiper through 1k / 100n RC into the ADC pin.

In R is normalled from In L's jack tip; In L's tip switch grounds it when nothing is plugged in.

Out R plug detect: ring tied to GND, ring—normal contact to OUTR_DETECT. Empty jack: RN touches the ring spring, so the pin reads low; any plug (TS or TRS) lifts it and the 100k pulls high. Low = sum to Out L.

One carrier ground: Seed AGND (pin 20) and DGND (pin 40) both tie to the GND pour
Pots/toggles/LED on top side; Seed + jacks on bottom side; footswitches off-board on JST PH
Generated by gen_schematic.py from one netlist definition — edit the script, not the sheet

Sheet: /
File: carrier.kicad_sch

Title: Daisy Freeze Pedal — carrier board

Size: A3	Date: 2026-10-26	**Rev: A**
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 1/1