RV1 B10K Dry
RV2 B10K Loop
RV3 B10K −8
RV4 B10K +5
RV5 B10K +8
RV6 B10K Fade
RV7 B10K Texture
R1 R2 R3 R4 R5 R6 R7 1k
C1 C2 C3 C4 C5 C6 C7 100n
C8 10u
C9 100n
POT_DRY POT_LOOP POT_SUB POT_FIFTH POT_OCT POT_FADE POT_TEX
ADC_DRY ADC_LOOP ADC_SUB ADC_FIFTH ADC_OCT ADC_FADE ADC_TEX
+3V3A AGND

U1 Daisy Seed
+3V3A ADC_DRY ADC_LOOP ADC_SUB ADC_FIFTH ADC_OCT ADC_FADE ADC_TEX OUTR_DETECT +3V3D DGND
3V3A A0/D15 A1/D16 A2/D17 A3/D18 A4/D19 A5/D20 A6/D21 A7/D22 A8/D23 A9/D24 A10/D25 D26 D27 A11/D28 D29/USB_D− D30/USB_D+ 3V3D VIN DGND
AGND AUDIO_OUT_R AUDIO_OUT_L AUDIO_IN_R AUDIO_IN_L D14 D13 D12 D11 D10 D9 D8 D7 D6 D5 D4 D3 D2 D1 D0
OUT_R OUT_L IN_R IN_L LED_GRN_DRV LED_RED_DRV FS_CLEAR FS_FREEZE TGL_FIFTH_DIR TGL_LAYERS

J3 In L / Mono
J4 In R (normalled from In L)
J5 Out L / Mono
J6 Out R (ring = plug detect)
IN_L IN_R OUT_L OUT_R AGND OUTR_RING OUTR_DETECT

R10 1k
R11 10k +3V3A

J1 Freeze footswitch
FS_FREEZE DGND
J2 Clear footswitch
FS_CLEAR DGND

R8 R9 470
LED_RED_DRV LED_GRN_DRV LED_RED LED_GRN
D1 Red/Green
DGND

R12 0R
AGND DGND

SW1 Single / Multi
SW2 +5 up / down
TGL_LAYERS TGL_FIFTH_DIR DGND +3V3D

H1 H2 H3 H4 M3

Pots: CCW end (1) to AGND, CW end (3) to +3V3A, wiper through 1k / 100n RC into the ADC pin.

In R is normalled from In L through its tip switch, so a mono source feeds both inputs.

Out R plug detect: a TS plug shorts the ring to the sleeve (AGND), pulling OUTR_DETECT low; with nothing plugged in the 100k holds it high and the firmware sums L+R to Out L.

Pots/toggles/LED on top side; Seed + jacks on bottom side; footswitches off-board on JST PH
Generated by gen_schematic.py from one netlist definition — edit the script, not the sheet

Sheet: /
File: carrier.kicad_sch

Title: Daisy Freeze Pedal — carrier board

Size: A3	Date: 2026-10-26	**Rev: A**
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 1/1