RV1 B10K Dry
RV2 B10K Loop
RV3 B10K −8
RV4 B10K +5
RV5 B10K +8
RV6 B10K Fade
RV7 B10K Texture
R1 R2 R3 R4 R5 R6 R7 1k
C1 C2 C3 C4 C5 C6 C7 100n
C8 10u
C9 100n
U1 Daisy Seed
J1 Freeze footswitch
J2 Clear footswitch
R8 R9 470
D1 Red/Green
J3 In L / Mono
J4 In R (normalled from In L)
J5 Out L / Mono
J6 Out R (ring = plug detect)
R10 1k
R11 10k
SW1 Single / Multi
SW2 +5 up / down
H1 H2 H3 H4 M3

Pots: CCW end (1) to GND, CW end (3) to +3V3A, wiper through 1k / 100n RC into the ADC pin.

In R is normalled from In L through its tip switch, so a mono source feeds both inputs.

Out R plug detect: a TS plug shorts the ring to the sleeve (GND), pulling OUTR_DETECT low;

with nothing plugged in the 100k holds it high and the firmware sums L+R to Out L.

One carrier ground: Seed AGND (pin 20) and DGND (pin 40) both tie to the GND pour
Pots/toggles/LED on top side; Seed + jacks on bottom side; footswitches off-board on JST PH
Generated by gen_schematic.py from one netlist definition — edit the script, not the sheet

Sheet: /
File: carrier.kicad_sch

Title: Daisy Freeze Pedal — carrier board

Size: A3	Date: 2026-10-26	**Rev: A**
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 1/1