IS THIS CARD REAL?

A card number checker built on the Luhn algorithm. Catches every single-digit typo and almost every swapped pair.

WORKED EXAMPLE: 79927398713

7	9	9	2	7	3	9	8	7	1	3

AFTER DOUBLING (OVER 9? SUBTRACT 9)

7	9	9	4	7	6	9	7	7	2	3

7+9+9+4+7+6+9+7+7+2+3 = **70**. Divisible by 10, so it passes.

VALID

01

Starting from the right, double every second digit.

02

Any result above 9? Subtract 9 from it.

03

Add it all up. A multiple of 10 means the number is valid.

GITHUB LINK

Checks typos, not balances.

by
- Aaanurag (2620030684)
- Amlan (262040026)