

Quantum Computing - Notes - v0.4.0

260236

May 2026

Preface

Every theory section in these notes has been taken from the sources:

- Course slides. [1]

About:

 [GitHub repository](#)



These notes are an unofficial resource and shouldn't replace the course material or any other book on quantum computing. It is not made for commercial purposes. I've made the following notes to help me improve my knowledge and maybe it can be helpful for everyone.

As I have highlighted, a student should choose the teacher's material or a book on the topic. These notes can only be a helpful material.

Contents

1	Introduction	5
1.1	Complex Numbers	5
1.2	Dirac's Notation	9
2	Single Qubit States	11
2.1	Building and Measuring Qubits (Intuition)	11
2.2	From Polarization to Qubits	15
2.3	Single Qubit Measurement	19
2.4	Superposition	23
2.5	Information Carried by a Single Qubit	30
2.6	State Space of a Single-Qubit System	32
3	Single Qubit Gates	38
3.1	Operations on Qubits	38
3.2	Quantum Logic Gates Overview	42
3.3	Main Single-Qubit Gates	45
3.3.1	Identity Gate (I)	45
3.3.2	Pauli Gates	46
3.3.2.1	Rotations Generated by Pauli Operators	46
3.3.2.2	Pauli-X (NOT) Gate	47
3.3.2.3	Pauli-Z (Phase Flip) Gate	52
3.3.2.4	Pauli-Y Gate	56
3.3.3	Phase Gate (S)	59
3.3.4	Hadamard Gate (H)	61
3.4	Properties	67
3.5	When Does a Gate Create Superposition?	69
3.6	Single-Qubit Quantum Circuits	72
3.7	Outer Product of Kets	74
3.8	Measurement	76
4	Multiple Qubit Gates	82
4.1	Multiple Qubit States	82
4.1.1	Tensor Product	84
4.1.2	Building a Two-Qubit System	88
4.1.3	Separable vs Entangled States	90
4.1.4	Why Entanglement Matters	91
4.1.5	Exercise: Normalization of Tensor Product States	92
4.2	Introduction to Multiple Qubit Gates	93
4.3	Parallel Gates	94
4.4	Hadamard Transform on Multiple Qubits	98
4.5	Main Multi-Qubit Gates	99
4.5.1	Controlled NOT (CNOT) Gate	99
4.5.2	Generic Controlled Gate (CU)	102
4.5.3	SWAP gate	105
4.5.4	Controlled-Controlled-NOT (CCNOT) Gate (Toffoli)	108
4.6	Quantum Circuit Representation	111
4.7	Entanglement	113
4.8	Observables and Measurements	120

4.8.1	Observables: What Are We Measuring?	120
4.8.2	Measurement Operators and Projectors	130
4.8.3	Expectation Value	136
4.8.4	Measuring $ +\rangle$ with the Pauli-Z Observable	138
4.8.5	Recovering Probabilities from Expectation Values	142
4.9	Heisenberg Representation of Quantum Circuits	145
4.10	Clifford Gates	148
4.10.1	Definition	148
4.10.2	Non-Clifford Gates	152
4.10.3	Stabilizer States	155
4.11	Limits of Quantum Information	158
4.11.1	No-Cloning Principle	158
4.11.2	No-Deleting Principle	161
4.11.3	No-Signaling Principle	163
Index		166

1 Introduction

1.1 Complex Numbers

Let's not start from math. Let's start from **physics / computation intuition**. Classical bits are represented by two distinct states: 0 and 1. In quantum computing, we have **qubits**, which are essentially **vector of numbers**. But not just any numbers: a qubit is a vector of **complex numbers**. They are needed because quantum systems have **both magnitude and phase**, and complex numbers can represent both. Real numbers can only represent "*how much*" (magnitude), while complex numbers can represent "*how much*" and "*in which direction / phase*" (magnitude and phase).

❓ Why complex (and not just real) numbers?

1. In quantum computing, we don't store probabilities directly (e.g., 0.5 for a 50% chance). Instead, we store **probability amplitudes**, which are complex numbers. The probability of an outcome is the square of the magnitude of its amplitude:

$$P = |z|^2$$

2. **Interference**. Quantum states can **combine and cancel**. For example, if we have two states with amplitudes z_1 and z_2 , the combined amplitude is:

$$z_{\text{combined}} = z_1 + z_2$$

If z_1 and z_2 have the same magnitude (*how much*) but opposite phases (*in which direction*), they can cancel each other out, leading to zero probability for that outcome. This is a key feature of quantum mechanics that allows for phenomena like quantum interference, which is essential for quantum algorithms.

In general, complex numbers are needed because **quantum states behave like waves**, not like classical values. Waves have both amplitude and phase, and complex numbers are the natural way to represent them mathematically. This is why quantum mechanics and quantum computing rely heavily on complex numbers.

❓ What do we actually need?

Not everything. Just a **minimal toolkit**. A complex number is:

$$z = x + iy$$

Where x is the **real part** and y is the **imaginary part**, and i is the **imaginary unit** satisfying $i^2 = -1$. From a geometric interpretation, we can think of z as a point in the 2D plane, where x is the horizontal coordinate (real axis) and y is the vertical coordinate (imaginary axis).

Polar form

Instead of coordinates (x, y) , we can also represent a complex number in **polar form**:

$$z = re^{i\varphi}$$

Where:

- $r = |z| = \sqrt{x^2 + y^2}$ is the **modulus** (or *magnitude*) of the complex number, representing its **distance from the origin in the complex plane**.
- $\varphi = \arg(z) = \tan^{-1}\left(\frac{y}{x}\right)$ is the **argument** (or *phase angle*), representing the **angle between the positive real axis and the line connecting the origin to the point z in the complex plane**.
- The **exponential form** $e^{i\varphi}$ means that we can represent the complex number as a point on the unit circle in the complex plane, where φ is the angle from the positive real axis. The modulus r then scales this point to its actual distance from the origin.

Using **Euler's formula**:

$$e^{i\varphi} = \cos \varphi + i \sin \varphi$$

We can rewrite z as:

$$z = r(\cos \varphi + i \sin \varphi)$$

This form is particularly useful in quantum computing because it makes it easy to understand how complex numbers can represent both magnitude and phase, which are essential for describing quantum states and their evolution.




Figure 1: Geometric interpretation of a complex number in the complex plane. The arrow represents the complex number z as a vector from the origin to the point (x, y) . The length of the vector is the modulus r , and the angle it makes with the positive real axis is the argument φ .

Complex Conjugate

The **complex conjugate** of a complex number $z = x + iy$ is denoted as $\bar{z}$ and is defined as:

$$\bar{z} = x - iy$$

Geometrically, the complex conjugate $\bar{z}$ is the **reflection** of z **across the real axis in the complex plane**. This means that if z is represented by the point (x, y) , then $\bar{z}$ is represented by the point $(x, -y)$. The real part remains the same, while the imaginary part changes sign. See Figure 2 for a visual representation of this concept.




Figure 2: Geometric interpretation of the complex conjugate: reflection across the real axis.

Magnitude

The **magnitude** (or **modulus**) of a complex number $z = x + iy$ is denoted as $|z|$ and is defined as:

$$|z| = \sqrt{x^2 + y^2}$$

And it can also be expressed using the complex conjugate:

$$|z|^2 = z \cdot \bar{z} = (x + iy)(x - iy) = x^2 + y^2$$

The magnitude represents the **distance** of the point z from the origin in the complex plane. It is **always a non-negative real number**. The magnitude is important in quantum mechanics because the probability of an outcome is given by the square of the magnitude of the corresponding probability amplitude. For

example, if a quantum state has an amplitude of z , the probability of measuring that state is $|z|^2$. This is why the magnitude of complex numbers is crucial in quantum computing, as it directly relates to the probabilities of different outcomes when measuring quantum states.

↻ Rotation in the complex plane

Multiplying a complex number by a complex exponential of the form $e^{i\theta}$ corresponds to a **rotation** in the complex plane:

$$z' = z \cdot e^{i\theta} = r e^{i(\varphi+\theta)}$$

Geometrically, this operation:

- **Preserves the magnitude** $|z|$
- **Adds θ to the phase φ**

Therefore, multiplication by $e^{i\theta}$ rotates the complex number by an angle θ around the origin.




Figure 3: Rotation of a complex number: multiplying by $e^{i\theta}$ rotates the vector by angle θ while preserving its magnitude.

↻ Hermitian (Conjugate Transpose)

Given a complex vector:

$$\mathbf{v} = \begin{bmatrix} a \\ b \end{bmatrix}$$

Its **Hermitian** (or **conjugate transpose**) is defined as:

$$\mathbf{v}^\dagger = [\bar{a} \quad \bar{b}]$$

This operation consists of:

- Taking the **transpose** (column $\rightarrow$ row)
- Taking the **complex conjugate** of each element

1.2 Dirac's Notation

Dirac notation was introduced to make **linear algebra with complex vectors easier, cleaner, and more expressive**, especially for quantum systems.

Let's imagine our work only with standard linear algebra notation, where we have to write out all the vectors and matrices in their full form:

- Vectors:

$$\mathbf{v} = \begin{bmatrix} a \\ b \end{bmatrix}$$

- Conjugate transpose:

$$\mathbf{v}^\dagger = [\bar{a} \quad \bar{b}]$$

- Inner product:

$$\mathbf{v}^\dagger \mathbf{w} = \bar{a}c + \bar{b}d$$

- Matrix-vector multiplication:

$$M\mathbf{v} = \begin{bmatrix} m_{11} & m_{12} \\ m_{21} & m_{22} \end{bmatrix} \begin{bmatrix} a \\ b \end{bmatrix} = \begin{bmatrix} m_{11}a + m_{12}b \\ m_{21}a + m_{22}b \end{bmatrix}$$

This quickly becomes **cumbersome and hard to read**, especially as we deal with more complex quantum systems. In quantum mechanics we constantly write expressions involving inner products, matrix operations, and state transformations.

✔ **Dirac's idea.** Paul Dirac said “*let's give different roles **different symbols***”. So he introduced:

- **Kets** $|v\rangle$ to represent **column vectors** (quantum states).
- **Bras** $\langle v|$ to represent row vectors (**conjugate transposes**).

Where the operators stay in the middle, and we can write everything in a much cleaner way:

- Vectors (**kets**):

$$|v\rangle = \begin{bmatrix} a \\ b \end{bmatrix}$$

Where the entries are complex numbers and usually we **require** $|v\rangle$ to have unit norm (normalized state).

- Conjugate transpose (**bra**):

$$\langle v| = [\bar{a} \quad \bar{b}]$$

- Inner product:

$$\langle v|w\rangle = \bar{a}c + \bar{b}d$$

The result is a scalar (complex number) that tells us how much the two states overlap.

- Matrix-vector multiplication:

$$M|v\rangle = \begin{bmatrix} m_{11} & m_{12} \\ m_{21} & m_{22} \end{bmatrix} \begin{bmatrix} a \\ b \end{bmatrix} = \begin{bmatrix} m_{11}a + m_{12}b \\ m_{21}a + m_{22}b \end{bmatrix}$$

An operator M acting on a state $|v\rangle$ gives us a new state. The result is a new ket.

Even if we ignore physics for now, we can see that Dirac's notation is more expressive and easier to read than standard linear algebra notation.

🔗 What is *Chaining* in Dirac notation?

Chaining means writing multiple operations together in a single expression without needing to write out intermediate steps. For example:

$$\langle x|M|y\rangle$$

It is just a **compact way to combine linear algebra operations** (matrix multiplication and inner products) in a single expression. It allows us to write complex quantum mechanical expressions in a much cleaner and more intuitive way.

Without Dirac notation, we would have to write:

$$\mathbf{x}^\dagger M \mathbf{y}$$

That is a **chain of operations**: take the conjugate transpose of $\mathbf{x}$, multiply it by M , and then multiply the result by $\mathbf{y}$. With Dirac notation, we can write this in a much more compact and readable way as $\langle x|M|y\rangle$.

To read $\langle x|M|y\rangle$, we can think of it as:

1. Start with the ket $|y\rangle$ (a quantum state).
2. Apply the operator M to $|y\rangle$, which gives us a new state $M|y\rangle$.
3. Take the inner product of $\langle x|$ with the new state $M|y\rangle$, which gives us a scalar (complex number) that represents the probability amplitude of transitioning from state $|y\rangle$ to state $|x\rangle$ via the operator M . At first, this might seem abstract, but as we go through more examples and applications in quantum mechanics and quantum computing, it will become much clearer how powerful and intuitive Dirac's notation is for describing quantum systems.

2 Single Qubit States

Before introducing qubits, we briefly describe what we mean by a **quantum system**.

A **Quantum System** is a **physical system** (such as a photon, an electron, or an atom) **whose behavior is described by the laws of quantum mechanics**.

In this course, we will focus on the simplest case: systems that can produce **two possible outcomes** when measured. These are called **two-level systems**, and they form the basis of qubits.

2.1 Building and Measuring Qubits (Intuition)

Before introducing the mathematical formalism of qubits, it is useful to develop an **intuitive understanding** of how a simple quantum system behaves when it is **prepared** and **measured**.

🔍 A Simple Quantum Experiment

Consider a very simple experimental setup:

- A **source** emits a quantum particle (for example, a photon).
- The particle passes through a device.
- A **detector** measures the outcome.

Each time we perform the experiment, the detector returns one of two possible results:

$$0 \quad \text{or} \quad 1$$

This motivates the idea of a **two-level system**, which is the simplest type of quantum system.

💡 Key Observation

If we repeat the same experiment many times under identical conditions, we observe that:

- The outcome is **not deterministic**.
- Instead, it is **probabilistic**.

For example, we might obtain:

- Outcome 0 with probability p
- Outcome 1 with probability $1 - p$

This is fundamentally different from classical systems, where the outcome is determined in advance.

❓ What is a Measurement?

A **Measurement** is the process that:

- Extracts **classical information** from a quantum system;
- Produces a **definite outcome** (e.g., 0 or 1).

An important property of quantum measurement is that it **affects the system itself**. After a measurement is performed, the **system is no longer in its original configuration**.

💡 From Intuition to Formalization

This simple experiment suggests that:

- A quantum system can produce **two possible outcomes**
- The outcomes are governed by **probabilities**
- The system must therefore contain some form of **internal state** that determines these probabilities

In the following example, we will introduce a concrete physical example (photon polarization) that allows us to represent this internal state using **vectors with complex coefficients**.

Example 1: Example of a Two-Level Quantum System

To make the previous discussion more concrete, we introduce a simple physical system that behaves as a two-level quantum system: the **polarization of a photon**.

❓ What is a Photon?

A **Photon** is the elementary particle of light. It carries energy and behaves both as a particle and as a wave. In this course, we will use photons as a simple example of a **quantum system**, since their properties can be easily controlled and measured.

❓ What is Polarization?

Polarization describes the direction in which the electric field of a light wave oscillates. In simple terms, it can be thought of as the **orientation** of the light wave. For a photon, polarization can be visualized as a direction in space. In particular, we consider two basic polarization directions:

- **horizontal** ($\rightarrow$)
- **vertical** ($\uparrow$)

These two directions form a **two-level system**, since a measurement can distinguish between them (i.e., we can determine whether the photon is horizontally or vertically polarized).

💡 Superposition of Polarizations

A photon is not restricted to being only horizontal or vertical. In general, it can be in a **combination** of both states:

$$v = a \rightarrow + b \uparrow$$

Where:

- a and b are **complex coefficients**;
- They determine the behavior of the system when measured.

This is the first example of a **quantum state**: a system described by a linear combination of basic states.

❓ Vector Representation

We can represent these polarization states using vectors:

$$\rightarrow = \begin{bmatrix} 1 \\ 0 \end{bmatrix} \quad \uparrow = \begin{bmatrix} 0 \\ 1 \end{bmatrix}$$


Therefore, a general polarization state becomes:

$$v = \begin{bmatrix} a \\ b \end{bmatrix}$$

This shows that the state of the system can be described as a **vector with complex components**, exactly as introduced in Dirac notation.

📐 Geometric Interpretation

The horizontal and vertical polarization states can be interpreted as two **orthogonal axes** in a two-dimensional space.



The point where the axes intersect represents the origin, and any polarization state can be represented as a **vector starting from the origin**.



In this representation:

- $\rightarrow$ and $\uparrow$ form a **basis**
- Any state is a **linear combination** of these basis states

💡 Measurement with Polarizers

A **Polarizer** is a device that **filters light based on its polarization**.

A polarizer acts like a **filter** that allows only one polarization direction to pass and blocks the other. For example:

- A polarizer aligned with the horizontal direction ($\rightarrow$) will allow horizontally polarized light to pass and block vertically polarized light.
- A polarizer aligned with the vertical direction ($\uparrow$) will allow vertically polarized light to pass and block horizontally polarized light.

If the photon is a combination:

$$v = a \rightarrow + b \uparrow$$

And we use a:

- Horizontal polarizer ($\rightarrow$), the photon will pass with probability $|a|^2$ and be absorbed with probability $|b|^2$.
- Vertical polarizer ($\uparrow$), the photon will pass with probability $|b|^2$ and be absorbed with probability $|a|^2$.

This shows that:

- Probabilities are determined by the amplitudes (i.e., the coefficients a and b).
- Measurement **modifies the state of the system** (e.g., if the photon passes through the horizontal polarizer, it will be in the state $\rightarrow$).

2.2 From Polarization to Qubits

The example of photon polarization (page 12) shows that a physical system can be described using two basic states and their linear combinations. We now **abstract** this idea and introduce a **general model that does not depend on a specific physical system**.

🔍 From Physical States to Abstract States

In the polarization example, we used:

$$\rightarrow \quad \text{and} \quad \uparrow$$

As the two basic states of the system. We now replace them with an abstract notation:

$$\rightarrow \rightsquigarrow |0\rangle \quad \uparrow \rightsquigarrow |1\rangle$$

These are called the **computational basis states**. They are just symbols (used in Dirac notation) that represent the two basic states of the system, without referring to any specific physical implementation.

📖 Definition of a Qubit

A **Qubit** is a **two-level quantum system** whose state can be written as:

$$|\psi\rangle = a|0\rangle + b|1\rangle$$

It is the **unit of quantum information**, analogous to a classical bit. However, unlike a classical bit that can only be in one of two states (0 or 1), a qubit can exist in **infinitely many possible states**. Indeed, any normalized vector of the form:

$$|\psi\rangle = a|0\rangle + b|1\rangle$$

Represents a valid state of a qubit. Some **properties** of the qubit state are:

- The coefficients a and b are **complex numbers** (probability amplitudes). They determine the outcome of a measurement:
 - $|a|^2$ is the probability of measuring the state $|0\rangle$.
 - $|b|^2$ is the probability of measuring the state $|1\rangle$.

Therefore, even though a qubit can be in infinitely many possible states, a measurement (in this basis) can only produce **two possible outcomes**: $|0\rangle$ or $|1\rangle$.

- The state is **normalized**:

$$|a|^2 + |b|^2 = 1$$

Because the probabilities must sum to 1 (i.e., we must get either $|0\rangle$ or $|1\rangle$ when we measure).

- The states $|0\rangle$ and $|1\rangle$ form a **basis** of the vector space describing the qubit.

❓ What is a *basis*? A **Basis** is a set of vectors that allows us to **represent any vector in the space as a linear combination of them**. In quantum computing, $|0\rangle$ and $|1\rangle$ are the **basis vectors** and any qubit state is built from them.

In particular, the states $|0\rangle$ and $|1\rangle$ form an **Orthonormal Basis**, meaning that:

- They are **orthogonal**: $\langle 0|1\rangle = 0$.
❓ Why is orthogonality important? Orthogonality means that the two basis states are completely distinguishable by a measurement (not overlapping). If we measure a qubit in the state $|0\rangle$, we will never get $|1\rangle$, and vice versa.
- They are **normalized**: $\langle 0|0\rangle = \langle 1|1\rangle = 1$.
❓ Why is normalization important? Normalization ensures that the probabilities of measurement outcomes are well-defined and sum to 1. It also means that the basis states have unit length in the vector space, which is a fundamental property for quantum states.

❓ Why This Abstraction Matters

This abstraction is fundamental because it allows us to:

- Describe **any** two-level quantum system (not only photons);
- Use a unified mathematical framework based on vectors;
- Apply the tools of linear algebra to quantum systems.

From now on, we will work with qubits using Dirac notation, without referring to a specific physical implementation.

Example 2: Different Choices of Basis

The computational basis $\{|0\rangle, |1\rangle\}$ is not the only possible choice. A qubit can be described using **any orthonormal basis**.

For example, another important basis is the **Hadamard basis**, defined as:

$$|+\rangle = \frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ 1 \end{bmatrix} \quad |-\rangle = \frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ -1 \end{bmatrix}$$

This shows that the same quantum state can be represented in different bases, depending on the context.

Example 3: Orthogonality of the Hadamard Basis

Show that the Hadamard basis states $|+\rangle$ and $|-\rangle$ are orthogonal.

Proof. Recall:

$$|+\rangle = \frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ 1 \end{bmatrix} \quad |-\rangle = \frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ -1 \end{bmatrix}$$

Orthogonal means that their inner product is zero. So, we need to compute $\langle + | - \rangle$ and show that it equals zero:

$$\langle + | - \rangle = \frac{1}{\sqrt{2}} [1 \quad 1] \cdot \frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ -1 \end{bmatrix} = \frac{1}{2} (1 - 1) = 0$$

Therefore, $|+\rangle$ and $|-\rangle$ are orthogonal.

QED

Example 4: Change of Basis from Standard $\leftrightarrow$ Hadamard

Given a qubit state in the standard basis:

$$|\psi\rangle = a|0\rangle + b|1\rangle$$

We want to express it in the Hadamard basis:

$$|\psi\rangle = x|+\rangle + y|-\rangle$$

Proof. Using the definitions of $|+\rangle$ and $|-\rangle$:

$$|+\rangle = \frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ 1 \end{bmatrix} \quad |-\rangle = \frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ -1 \end{bmatrix}$$

We can write $|\psi\rangle$ in terms of $|+\rangle$ and $|-\rangle$:

$$|\psi\rangle = a|0\rangle + b|1\rangle = a \cdot \begin{bmatrix} 1 \\ 0 \end{bmatrix} + b \cdot \begin{bmatrix} 0 \\ 1 \end{bmatrix} = \begin{bmatrix} a \\ b \end{bmatrix}$$

Now, we express $|\psi\rangle$ as a linear combination of $|+\rangle$ and $|-\rangle$:

$$|\psi\rangle = x|+\rangle + y|-\rangle$$

Substituting the definitions of $|+\rangle$ and $|-\rangle$:

$$= x \cdot \frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ 1 \end{bmatrix} + y \cdot \frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ -1 \end{bmatrix}$$

Combining the terms:

$$= \frac{1}{\sqrt{2}} \begin{bmatrix} x + y \\ x - y \end{bmatrix}$$

We want this to equal $\begin{bmatrix} a \\ b \end{bmatrix}$, so we set:

$$\frac{1}{\sqrt{2}} \begin{bmatrix} x + y \\ x - y \end{bmatrix} = \begin{bmatrix} a \\ b \end{bmatrix}$$

This gives us the system of equations:

$$x + y = \sqrt{2}a, \quad x - y = \sqrt{2}b$$

Adding the two equations:

$$2x = \sqrt{2}(a + b) \implies x = \frac{a + b}{\sqrt{2}}$$

Subtracting the second from the first:

$$2y = \sqrt{2}(a - b) \implies y = \frac{a - b}{\sqrt{2}}$$

It follows that:

$$|\psi\rangle = x|+\rangle + y|-\rangle = \frac{a + b}{\sqrt{2}}|+\rangle + \frac{a - b}{\sqrt{2}}|-\rangle$$

QED

Example 5: Orthogonal State Construction

Given:

$$|v\rangle = a|0\rangle + b|1\rangle$$

Define:

$$|w\rangle = \bar{b}|0\rangle - \bar{a}|1\rangle$$

Show that $|v\rangle$ and $|w\rangle$ are orthogonal.

Proof. To show that $|v\rangle$ and $|w\rangle$ are orthogonal, we need to compute their inner product $\langle w|v\rangle$ and show that it equals zero. First, we write the inner product converting $|w\rangle$ to its corresponding bra:

$$|w\rangle = \bar{b}|0\rangle - \bar{a}|1\rangle \implies \langle w| = b\langle 0| - a\langle 1|$$

Now we compute:

$$\langle w|v\rangle = (b\langle 0| - a\langle 1|) \cdot (a|0\rangle + b|1\rangle)$$

Expanding this expression:

$$= ba\langle 0|0\rangle + bb\langle 0|1\rangle - aa\langle 1|0\rangle - ab\langle 1|1\rangle$$

Using the orthonormality of the basis states:

$$\langle 0|0\rangle = \langle 1|1\rangle = 1, \quad \langle 0|1\rangle = \langle 1|0\rangle = 0$$

We get:

$$\langle w|v\rangle = ba\overset{1}{\langle 0|0\rangle} + \cancel{bb\langle 0|1\rangle} - \cancel{aa\langle 1|0\rangle} - ab\overset{1}{\langle 1|1\rangle} = ba - ab$$

Since a and b are complex numbers, multiplication is commutative, so $ba = ab$. Therefore:

$$\langle w|v\rangle = ba - ab = 0$$

Hence, $|v\rangle$ and $|w\rangle$ are orthogonal.

QED

2.3 Single Qubit Measurement

After introducing the mathematical representation of a qubit, we now describe how information is extracted from it through **measurement**.

🔍 What is *Single Qubit Measurement*?

We have a qubit:

$$|\psi\rangle = a|0\rangle + b|1\rangle$$

Where a and b are complex numbers such that $|a|^2 + |b|^2 = 1$. Measurement answers the question: “*which classical value do we observe?*”.

A measurement takes a **quantum state** as input and produces a **classical outcome** as output. In the case of a single qubit, the possible outcomes are 0 and 1.

⚠️ Measurement rule (computational basis)

The probability of an outcome is the **squared magnitude of the coefficient of the basis vector**:

$$P(0) = |a|^2, \quad P(1) = |b|^2 \quad (\text{in the computational basis})$$

But which coefficients? This is where the **basis** comes in. A state can be written in different ways depending on the basis. For example, take:

$$|\psi\rangle = a|0\rangle + b|1\rangle$$

- If we measure in basis $\{|0\rangle, |1\rangle\}$:
 - Outcome 0 with probability $|a|^2$
 - Outcome 1 with probability $|b|^2$
- If we measure in basis $\{|+\rangle, |-\rangle\}$:
 - Outcome $+$ with probability $|x|^2$
 - Outcome $-$ with probability $|y|^2$

The **coefficients depend on the chosen basis**. Let’s analyze how a basis change affects the coefficients.

🔍 **What is a basis really?** Any measurement device (e.g., a polarizer, page 12) has two preferred states (i.e., the states that it can distinguish). A basis is not just a mathematical construct; it corresponds to **what our measurements device can distinguish**. For example:

- Computational basis, the device distinguishes: *are you $|0\rangle$ or $|1\rangle$?*
- Hadamard basis, the device distinguishes: *are you $|+\rangle$ or $|-\rangle$?*

These are **different physical equations**.

❓ **The math behind the measurement.** Measurement is projecting the state vector onto basis vectors. Forget qubits for a second and imagine a 2D real vector $\vec{v}$, and choose axes:

- **Standard axes:** we project onto x -axis and y -axis. We get components: v_x and v_y .
- **Rotated axes:** we rotate axes by 45° and project onto new axes the same vector $\vec{v}$. We get new components: v_+ and v_- .

Different numbers, same vector. The components are **not intrinsic properties of the vector**, but depend on the chosen axes. Back to qubits, **measurement projects the vector $|\psi\rangle$ onto the measurement axes** (i.e., the basis vectors). So $\langle u|\psi\rangle$ is the projection of $|\psi\rangle$ onto $|u\rangle$, and $|\langle u|\psi\rangle|^2$ is the probability of observing outcome u .

Example 6: Analogy - Measurement as projecting a vector onto different axes

Consider a classical 2D vector pointing diagonally:

$$\vec{v} = \begin{pmatrix} \frac{1}{\sqrt{2}} \\ \frac{1}{\sqrt{2}} \end{pmatrix}$$

Case 1: Standard axes (horizontal/vertical). If we describe the vector using the standard basis:

$$\left\{ \begin{pmatrix} 1 \\ 0 \end{pmatrix}, \begin{pmatrix} 0 \\ 1 \end{pmatrix} \right\},$$

Then the vector has equal components along both axes:

$$\vec{v} = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 \\ 0 \end{pmatrix} + \frac{1}{\sqrt{2}} \begin{pmatrix} 0 \\ 1 \end{pmatrix}$$

- Projection on horizontal axis: $\frac{1}{\sqrt{2}}$
- Projection on vertical axis: $\frac{1}{\sqrt{2}}$

Case 2: Rotated axes (diagonal basis). Now rotate the coordinate system by 45° and use the basis:

$$\left\{ \frac{1}{\sqrt{2}} \begin{pmatrix} 1 \\ 1 \end{pmatrix}, \frac{1}{\sqrt{2}} \begin{pmatrix} 1 \\ -1 \end{pmatrix} \right\}$$

In this basis, the same vector becomes:

$$\vec{v} = 1 \cdot \frac{1}{\sqrt{2}} \begin{pmatrix} 1 \\ 1 \end{pmatrix} + 0 \cdot \frac{1}{\sqrt{2}} \begin{pmatrix} 1 \\ -1 \end{pmatrix} = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 \\ 1 \end{pmatrix}$$

- Projection on first axis: 1
- Projection on second axis: 0

Connection with qubits. A qubit behaves exactly in the same way:

$$|\psi\rangle = \frac{1}{\sqrt{2}}|0\rangle + \frac{1}{\sqrt{2}}|1\rangle = |+\rangle$$

- In basis $\{|0\rangle, |1\rangle\}$: equal projections $\Rightarrow$ probabilistic measurement.
- In basis $\{|+\rangle, |-\rangle\}$: full projection on $|+\rangle \Rightarrow$ deterministic measurement.

💡 The state does not change. What changes is the set of axes (basis) onto which the state is projected. Since measurement probabilities are given by these projections, the outcome depends on the chosen basis.

Given the state:

$$|\psi\rangle = \frac{1}{\sqrt{2}}|0\rangle + \frac{1}{\sqrt{2}}|1\rangle$$

- If we measure in the **computational basis**, we get:

- Outcome 0 with probability $\left|\frac{1}{\sqrt{2}}\right|^2 = \frac{1}{2}$
- Outcome 1 with probability $\left|\frac{1}{\sqrt{2}}\right|^2 = \frac{1}{2}$




Figure 4: Measurement as projection onto basis vectors.

- If we measure in the **Hadamard basis**, we get:
 - Outcome + with probability $|\langle +|\psi\rangle|^2 = 1$
 - Outcome - with probability $|\langle -|\psi\rangle|^2 = 0$




Figure 5: Measurement in the Hadamard basis. The state $|\psi\rangle$ is aligned with $|+\rangle$, so we get outcome $+$ with probability 1. The projection onto $|-\rangle$ is zero, so we get outcome $-$ with probability 0. The axes are rotated by 45° compared to the computational basis.

❓ What happens to the state after measurement? The state **collapses** to the observed outcome. For example, if we measure $|\psi\rangle = a|0\rangle + b|1\rangle$ in the computational basis and observe 0, the state collapses to $|0\rangle$. If we observe 1, the state collapses to $|1\rangle$.

🔗 Two possible situations

As we have seen in page 20, the same state can yield different measurement outcomes depending on the chosen basis. This leads to two important situations:

- **Probabilistic measurement:** If the **state is not aligned with the measurement basis**, we get a probabilistic outcome. For example:

$$|\psi\rangle = \frac{1}{\sqrt{2}}|0\rangle + \frac{1}{\sqrt{2}}|1\rangle$$

Measured in the computational basis gives 0 or 1 with equal probability.

- **Deterministic measurement:** If the **state is aligned with one of the basis vectors**, we get a deterministic outcome. For example:

$$|\psi\rangle = |+\rangle$$

Measured in the Hadamard basis gives $+$ with probability 1 and $-$ with probability 0.

❓ When should we prefer one situation to another? It depends on the task. For example, if we want to encode a classical bit, we prefer deterministic measurement (e.g., $|0\rangle$ or $|1\rangle$). If we want to create superposition states for quantum algorithms, we might want probabilistic measurement (e.g., $|+\rangle$).

Now, if the same quantum state can lead to either deterministic or probabilistic measurement outcomes depending on the chosen basis, we can ask: “*how can be explained this phenomenon?*”. It means that a qubit can simultaneously have non-zero components along multiple basis states. This is a fundamental property of quantum mechanics, and it is what allows quantum computers to perform certain computations more efficiently than classical computers. It is called **superposition**, and we will discuss it in the next section.

2.4 Superposition

We have already seen that:

1. **A qubit is represented as a vector:**

$$|\psi\rangle = a|0\rangle + b|1\rangle$$

Where a and b are complex numbers, and $|0\rangle$ and $|1\rangle$ are the basis states of the qubit.

2. **Measurement probabilities depend on the chosen basis:**

- In the computational basis $\{|0\rangle, |1\rangle\}$, the probabilities of measuring $|0\rangle$ and $|1\rangle$ are $|a|^2$ and $|b|^2$, respectively.
- In another basis, such as the Hadamard basis $\{|+\rangle, |-\rangle\}$, the probabilities of measuring $|+\rangle$ and $|-\rangle$ depend on different coefficients, which can be calculated by expressing $|\psi\rangle$ in terms of the new basis states.

3. **The same state can lead to deterministic or probabilistic outcomes depending on the measurement basis.** For example, if $|\psi\rangle = |0\rangle$, measuring in the computational basis always yield $|0\rangle$ (deterministic):

$$|0\rangle = 1|0\rangle + 0|1\rangle = |0\rangle$$

Whereas measuring in the Hadamard basis yields $|+\rangle$ or $|-\rangle$ with equal probability (probabilistic):

$$|0\rangle = \frac{1}{\sqrt{2}}(|+\rangle + |-\rangle)$$

These observations raise an essential question: “*why can a single state exhibit such different behaviors under different measurements?*”. The answer is **superposition**.

🔍 What is Superposition?

Superposition is a fundamental principle of quantum mechanics that **applies to all quantum systems**, not just qubits.

Definition 1: Superposition

Superposition means that a **system can exist in several possible states at the same time until a measurement is made**. It is **basis-dependent**, meaning a state may be a superposition in one basis but not in another, for example:

$$|v\rangle = \frac{1}{\sqrt{2}}|0\rangle + \frac{1}{\sqrt{2}}|1\rangle$$

Is a superposition with respect to the computational basis $\{|0\rangle, |1\rangle\}$, but it is **not** a superposition in the Hadamard basis $\{|+\rangle, |-\rangle\}$, where it can

be written as:

$$|v\rangle = 1|+\rangle + 0|-\rangle = |+\rangle$$

Formally, let $\{|u\rangle, |u^\perp\rangle\}$ be an orthonormal basis of a single-qubit Hilbert space. A qubit is said to be in **superposition** with respect to this basis if it can be written as:

$$|\psi\rangle = a|u\rangle + b|u^\perp\rangle$$

Where both coefficients a and b are non-zero and satisfy $|a|^2 + |b|^2 = 1$ (normalization condition). If one of the coefficients is zero, the state coincides with one of the basis vectors and the measurements in that basis becomes deterministic, thus it is not a superposition.

More in general, a quantum state $|\psi\rangle$ in a system with multiple possible states can exist in a **linear combination** of these states:

$$|\psi\rangle = c_1|\psi_1\rangle + c_2|\psi_2\rangle + \dots + c_n|\psi_n\rangle$$

Where:

- $|\psi_1\rangle, |\psi_2\rangle, \dots, |\psi_n\rangle$ are **basis states** of the system.
- $c_1, c_2, \dots, c_n$ are **complex probability amplitudes**.
- The system is in **all states at the same time**, with the probability of measuring each state given by $|c_i|^2$.
- The state is **normalized**, meaning:

$$|c_1|^2 + |c_2|^2 + \dots + |c_n|^2 = 1$$

Example 7: Single-Particle Systems (Quantum Mechanics)

In general quantum mechanics, a particle can exist in **multiple positions simultaneously** as a wave function $\Psi(x)$:

$$|\Psi\rangle = \int \Psi(x) |x\rangle dx$$

- The particle is in a **superposition of all possible positions** $|x\rangle$.
- Measurement collapses the wave function to a single position.

❓ How Can a Particle Exist in Multiple States at Once? This question touches the heart of quantum mechanics, where our everyday intuition breaks down. The **key idea** is that a **quantum particle** is not just a tiny ball, it is a **wave function that spreads across multiple possibilities at once**.

1. **Quantum Particles Are Waves, Not Just Points.** In classical physics, we think of particles as tiny, solid objects, like a small ball that always has a precise position and velocity.

In quantum mechanics, however, particles behave more like waves. These waves are described by a wave function $\Psi(x)$, which represents the **probability of finding the particle at different locations**.

The key idea is:

- The **wave function spreads across space**, meaning the **particle does not have a single location** before measurement.
 - Instead, it exists in a superposition of all possible locations.
2. **The Double-Slit Experiment: Proof That a Particle Can Be in Two Places at Once.** The double-slit experiment was first performed by Thomas Young in 1801 to demonstrate the **wave nature of light**. Later, in the 20th century, it was repeated with **electrons, atoms**, and even **large molecules**, revealing that **matter itself exhibits wave-like behavior**. The classical expectation for the double-slit experiment is:

- **Classical Particles** (e.g., tiny balls). Imagine firing small balls at a barrier with two slits:
 - Each ball passes through **either** slit 1 **or** slit 2.
 - On a screen behind the slits, we would observe **two bright bands**, corresponding to the two slits.

The result is a simple pattern of two lines, no interference.

- **Classical Waves** (e.g., Water or Light). If instead we send **waves** (like water waves or classical light):
 - Each wave passes through **both slits simultaneously**.
 - The waves emerging from the slits **interfere: constructive interference** creates bright bands, while **destructive interference** creates dark bands.

The result is an **interference pattern** of alternating bright and dark bands.

The quantum reality is even more surprising:

- **Quantum Particles** (e.g., photons or electrons). When the experiment is performed with **single quantum particles** (photons or electrons), something remarkable happens:
 - (a) **Particles are emitted one at a time.**
 - (b) Each particle is detected as a **localized point** on the screen.
 - (c) After many particles are detected, an **interference pattern gradually emerges**.

This means that each particle behaves as if it passes through **both slits simultaneously**. The particle is described by a **wave function**, representing a **superposition of paths**:

$$|\psi\rangle = \frac{1}{\sqrt{2}} (|\text{slit 1}\rangle + |\text{slit 2}\rangle)$$

The interference pattern arises from the **coherent combination** of these two possibilities.

Suppose we place detectors at the slits to determine **which slit** the particle passes through. The interference pattern **disappears** and the screen now shows **two bands**, just like classical particles. This is because measuring the particle's path **entangles** (i.e., correlates) it with the environment (the detector), leading to **decoherence** (loss of quantum coherence). The superposition:

$$\frac{1}{\sqrt{2}} (|\text{slit 1}\rangle + |\text{slit 2}\rangle)$$

Becomes effectively a **classical mixture**:

$$\frac{1}{2} |\text{slit 1}\rangle \langle \text{slit 1}| + \frac{1}{2} |\text{slit 2}\rangle \langle \text{slit 2}|$$

Without coherence, **interference cannot occur**.

In summary, the double-slit experiment demonstrates the principle of quantum superposition. When quantum particles such as photons or electrons are sent one at a time through two slits, they form an interference pattern on a detection screen. This indicates that each particle behaves as if it travels through both slits simultaneously, corresponding to the superposition:

$$|\psi\rangle = \frac{1}{\sqrt{2}} (|\text{slit 1}\rangle + |\text{slit 2}\rangle)$$

If a measurement is performed to determine which slit the particle passes through, the interference pattern disappears due to decoherence, and the system behaves like a classical probabilistic mixture.

Double Slit Experiment explained! by Jim Al-Khalili



3. **Quantum Superposition: More Than Just Probability.** A common misconception is that a particle in superposition is just **an unknown state**, like a coin that is either heads or tails, but we just don't know which. This is wrong, because quantum superposition is much deeper.

A quantum state is a **combination of all possibilities**. *Until measurement*, the system is in **all possible states at once**.

Mathematically, for an electron in **two locations** x_1 and x_2 :

$$|\psi\rangle = a |x_1\rangle + b |x_2\rangle$$

- The electron is **literally in both places simultaneously**.
- The coefficients a and b are **complex numbers representing the probability amplitudes**.

- **Interference** between these amplitudes **creates quantum effects that cannot be explained by classical probability.**
4. **Superposition in Quantum Computing.** Quantum computing **directly** uses the fact that a particle can be in multiple states at once.
 - A **classical bit** can only be **0 or 1**.
 - A **qubit (quantum bit)** can be in a superposition:

$$|\psi\rangle = a|0\rangle + b|1\rangle$$

This means a quantum computer can **perform many calculations simultaneously**. Therefore, **superposition allows quantum computers to process information exponentially faster than classical computers for certain tasks.**

5. **Why Don't We See Superposition in Everyday Life?** In our daily experience, objects are **not in multiple states at once** because of a process called **quantum decoherence**.

Quantum superposition is **fragile**. When a quantum system interacts with the environment (air, light, etc.), the superposition **collapses into one definite state**. This is why large objects (like humans or cars) do not appear in multiple places at once.

However, experiments (like the Double-Slit experiment) confirm that superposition is real at microscopic scales (electrons, photons, atoms, and even molecules).

The key **properties of Superposition** are:

1. **Linearity:** Any combination of valid quantum states is also a valid quantum state.
2. **Interference:** Quantum states in superposition can interfere, leading to constructive or destructive interference.
3. **Measurement Collapse:** When measured, the superposition collapses into a single outcome.
4. **Phase Information:** Unlike classical probabilities, quantum superpositions include complex phases that affect interference patterns.




Figure 6: Double-slit experiment, superposition of paths. This figure illustrates the **quantum state of the particle before detection**. Instead of choosing a single path, the particle is described by a **superposition**:

$$|\psi\rangle = \frac{1}{\sqrt{2}} (|\text{slit 1}\rangle + |\text{slit 2}\rangle)$$

The particle is **not** traveling through only one slit, instead, it is described by a **coherent combination** of both possibilities. The diagram emphasizes the **quantum state** rather than the final inference pattern.




Figure 7: Wave-like representation of the double-slit experiment, interference of amplitudes. This figure focuses on the **wave nature** of the quantum particle. Each slit acts as a **coherent source**, producing wavefronts that overlap and interfere. If $A_1(x)$ and $A_2(x)$ are the probability amplitudes associated with the two slits, the probability of detecting the particle at position x on the screen is:

$$P(x) = |A_1(x) + A_2(x)|^2 = |A_1(x)|^2 + |A_2(x)|^2 + 2\text{Re}(A_1^*(x)A_2(x))$$

The last term is the **inference term**, which can be positive (bright fringes, **constructive interference**) or negative (dark fringes, **destructive interference**). This illustrates how the superposition of paths leads to the characteristic interference pattern observed in the experiment.

2.5 Information Carried by a Single Qubit

This section addresses a fundamental question: *if a qubit can exist in infinitely many states, how much information can it actually convey?* A general single-qubit state is given by:

$$|\psi\rangle = a|0\rangle + b|1\rangle \quad a, b \in \mathbb{C}, \quad |a|^2 + |b|^2 = 1$$

Because a and b are complex numbers, a qubit can be prepared in **infinitely many distinct states**. This might suggest that a qubit can encode an infinite amount of information. However, this is **not** the case. When we perform a **measurement**, we obtain only a **single classical outcome** (either 0 or 1). Therefore, **a single qubit can yield at most one classical bit of information when measured**. This apparent paradox, **infinite possible states but limited measurable information**, is one of the most important conceptual aspects of quantum information theory.

❓ Why can't we determine the Amplitudes a and b of a single qubit state?

Suppose we are given a qubit in an unknown state $|\psi\rangle$. Can we determine a and b from a single measurement? The answer is **no**, because:

- ✗ **Measurement is probabilistic.** A single measurement provides only one outcome (0 or 1), which is insufficient to determine the amplitudes.
- ✗ **Measurement disturbs the state.** After measurement, the qubit collapses to the observed basis state, preventing further measurements on the original state.
- ✗ **State estimation requires many copies.** To estimate a and b , we need **quantum state tomography**, which relies on performing measurements on **many identically prepared qubits**.

This **irreversible collapse** means that the original information encoded in the amplitudes is generally lost after measurement.

⚠ The No-Cloning Theorem

One might think of copying the qubit before measurement to extract more information. However, quantum mechanics forbids this through the **No-Cloning Theorem**.

Theorem 1 (No-Cloning). *It is impossible to create an identical copy of an arbitrary unknown quantum state.*

Proof. Assume there exists a unitary operator U that can clone any state $|\psi\rangle$:

$$U|\psi\rangle|0\rangle = |\psi\rangle|\psi\rangle \quad \forall |\psi\rangle$$

For two arbitrary states $|\psi\rangle$ and $|\phi\rangle$, linearity of quantum mechanics implies:

$$U(\alpha|\psi\rangle + \beta|\phi\rangle)|0\rangle = \alpha|\psi\rangle|\psi\rangle + \beta|\phi\rangle|\phi\rangle$$

Which is **not equal** to:

$$(\alpha |\psi\rangle + \beta |\phi\rangle)(\alpha |\psi\rangle + \beta |\phi\rangle) = \alpha^2 |\psi\rangle |\psi\rangle + \alpha\beta |\psi\rangle |\phi\rangle + \alpha\beta |\phi\rangle |\psi\rangle + \beta^2 |\phi\rangle |\phi\rangle$$

This contradiction proves that perfect cloning is impossible, since the two expressions cannot be equal for all $|\psi\rangle$ and $|\phi\rangle$. QED

Since we cannot clone a qubit, we cannot create multiple copies to determine its exact state from a single instance.

Feature	Classical Bit	Qubit
Possible states	0 or 1	Qubit
Info from measurement	1 bit	At most 1 bit
Measurement disturbance	No	Yes
Ability to copy	Yes	No (No-Cloning)
State determination	Single observation	Requires many identical copies

Table 1: Comparison of classical bits and qubits in terms of information content and measurement properties.

2.6 State Space of a Single-Qubit System

The **State Space** of a physical system is the set of all possible states that the system can occupy. For a **single qubit**, the state space consists of all vectors of the form:

$$|\psi\rangle = a|0\rangle + b|1\rangle$$

- $a, b \in \mathbb{C}$ are **complex probability amplitudes**.
- $|0\rangle$ and $|1\rangle$ form an **orthonormal basis** (the computational basis).
- The **normalization condition** must hold: $|a|^2 + |b|^2 = 1$. This ensures that the total probability of all measurement outcomes is equal to 1.

Degrees of Freedom of a Qubit

At first glance, the coefficients a and b appear to provide **4 real parameters**:

$$\begin{aligned} a = a_r + ia_i &\Rightarrow a_r, a_i \quad (2 \text{ parameters}) \\ b = b_r + ib_i &\Rightarrow b_r, b_i \quad (2 \text{ parameters}) \end{aligned}$$

So initially, it seems that a qubit has **four degrees of freedom**. However, not all of these correspond to physically distinguishable states.

- **Normalization constraint.** Quantum states must be normalized, which imposes the condition:

$$|a|^2 + |b|^2 = a_r^2 + a_i^2 + b_r^2 + b_i^2 = 1$$

Geometrically, it defines the surface of a **unit sphere in four dimension** (also known as a 3-sphere, S^3). This constraint effectively removes **one degree of freedom**, since the amplitudes must lie on the surface of a 3-sphere in 4-dimensional space.




Figure 8: Analogy between the unit circle S^1 , the ordinary sphere S^2 , and the 3-sphere S^3 . The normalized qubit state lives on S^3 because it is specified by four real coordinates constrained by one equation. In this figure, we can only visualize S^1 and S^2 , while S^3 cannot be directly drawn in three-dimensional space, so we represent it with a dashed ellipse to indicate that it is a higher-dimensional object.

- **Global Phase Equivalence.** Two states that differ only by a **global phase** represent the **same physical qubit**:

$$|\psi'\rangle = e^{i\phi} |\psi\rangle$$

For example:

$$|\psi\rangle = \frac{1}{\sqrt{2}} (|0\rangle + |1\rangle) \quad e^{i\pi/3} |\psi\rangle = \frac{e^{i\pi/3}}{\sqrt{2}} (|0\rangle + |1\rangle)$$

❓ **Why is it physically irrelevant?** Measurement probabilities are given by:

$$P(i) = |\langle i|\psi\rangle|^2$$

If we multiply the state by a global phase:

$$|\langle i|e^{i\gamma}\psi\rangle|^2 = |e^{i\gamma}\langle i|\psi\rangle|^2 = |\langle i|\psi\rangle|^2$$

Because $|e^{i\gamma}| = 1$ for any real γ .

Mathematical proof that $|e^{i\gamma}| = 1$. We can express $e^{i\gamma}$ using Euler's formula:

$$e^{i\gamma} = \cos(\gamma) + i\sin(\gamma)$$

The magnitude of a complex number $z = x + iy$ is given by:

$$|z| = \sqrt{x^2 + y^2}$$

Applying this to $e^{i\gamma}$:

$$\begin{aligned} |e^{i\gamma}| &= \sqrt{(\cos(\gamma))^2 + (\sin(\gamma))^2} \\ &\downarrow \text{using the trigonometric identity} \\ &= \sqrt{\cos^2 \gamma + \sin^2 \gamma} \\ &= \sqrt{1} \\ &= 1 \end{aligned}$$

QED

Therefore, **no experiment can distinguish between $|\psi\rangle$ and $e^{i\phi}|\psi\rangle$** , since **they yield the same measurement probabilities** (due to $|e^{i\phi}| = 1$).

❓ **How does this remove a degree of freedom?** Unlike normalization, the global phase does **not** impose a constrain equation. Instead, it introduces a **redundancy** in our description:

- Many different vectors in S^3 correspond to the **same physical state**.
- All vectors of the norm $e^{i\gamma}|\psi\rangle$ are considered **physically equivalent** to $|\psi\rangle$.

Mathematically, we are **identifying** all these vectors as a single point. This process is called forming a **quotient space**: the set of physically distinct pure qubit states is $S^3 \setminus S^1 \cong S^2$, which is a 2-dimensional surface (the Bloch sphere, see Figure 8, page 32).

After accounting for these constraints, we find that a single qubit state is fully described by **two real parameters** (two degrees of freedom). Therefore, any qubit state can be written in the form:

1. A normalized qubit can be written as:

$$|\psi\rangle = a|0\rangle + b|1\rangle \quad a, b \in \mathbb{C} \quad |a|^2 + |b|^2 = 1$$

2. Any complex number can be written using its **magnitude** and **phase**:

$$a = |a| e^{i\alpha} \quad b = |b| e^{i\beta}$$

Where $|a|$ and $|b|$ are non-negative real numbers, and α and β are real numbers representing the phases. Substituting these into the expression for $|\psi\rangle$ gives:

$$|\psi\rangle = \underbrace{|a| e^{i\alpha}}_a |0\rangle + \underbrace{|b| e^{i\beta}}_b |1\rangle$$

3. We can factor out the common global phase $e^{i\alpha}$:

$$|\psi\rangle = e^{i\alpha} \left(|a| |0\rangle + |b| e^{i(\beta-\alpha)} |1\rangle \right)$$

Since the global phase $e^{i\alpha}$ has **no physical effect**, we can omit it, leading to:

$$|\psi\rangle = |a| |0\rangle + |b| e^{i\phi} |1\rangle$$

Where we define also the **Relative Phase** $\phi = \beta - \alpha$. At this point, the state is characterized by two real magnitudes $|a|$ and $|b|$, and one relative phase ϕ . Mathematically, if:

$$a = |a| e^{i\alpha} \quad b = |b| e^{i\beta}$$

Then:

$$\text{Relative Phase} = \phi = \arg(b) - \arg(a) = \beta - \alpha \quad (1)$$

4. From normalization:

$$|a|^2 + |b|^2 = 1$$

We recognize a familiar trigonometric identity:

$$\cos^2(x) + \sin^2(x) = 1$$

Therefore, we can parametrize the magnitudes using a single angle θ :

$$|a| = \cos\left(\frac{\theta}{2}\right) \quad |b| = \sin\left(\frac{\theta}{2}\right)$$

With $0 \leq \theta \leq \pi$ to ensure that $|a|$ and $|b|$ are non-negative. The reason for using $\frac{\theta}{2}$ instead of θ will become clear when we discuss the Bloch sphere representation (Figure 9, page 36).

5. Substituting the parametrized magnitudes into the state:

$$|\psi\rangle = \underbrace{\cos\left(\frac{\theta}{2}\right)}_{|a|} |0\rangle + e^{i\phi} \underbrace{\sin\left(\frac{\theta}{2}\right)}_{|b|} |1\rangle \quad (2)$$

This is the **canonical parametrization** of a single qubit state.

Regardless of the specific values of θ and ϕ in Equation 2:

- θ : controls the **relative weights of $|0\rangle$ and $|1\rangle$** in the superposition, determining the **probabilities of measuring each state**.
- ϕ : controls the **relative phase between the $|0\rangle$ and $|1\rangle$** components. While it does not affect measurement probabilities, it is crucial for interference effects and the behavior of the qubit under quantum gates (which we will discuss later).

☐ Bloch Sphere Representation of a Qubit

After normalization and removal of the physically irrelevant global phase, a pure single-qubit state depends on only two real parameters. Therefore, it is natural to represent it geometrically as a point on a two-dimensional surface. This surface is the **Bloch sphere**.

Any pure qubit can be written in the form:

$$|\psi\rangle = \cos\left(\frac{\theta}{2}\right) |0\rangle + e^{i\phi} \sin\left(\frac{\theta}{2}\right) |1\rangle,$$

Where:

- $\theta \in [0, \pi]$ is the **polar angle**,
- $\phi \in [0, 2\pi)$ is the **Azimuthal Angle**, representing the **relative phase**.

This expression gives a one-to-one correspondence between pure qubit states and points on the surface of a unit sphere:

- $|0\rangle$ corresponds to the north pole, since $\theta = 0$:

$$|0\rangle = \cos\left(\frac{0}{2}\right) |0\rangle + e^{i\phi} \sin\left(\frac{0}{2}\right) |1\rangle = 1 \cdot |0\rangle + 0 \cdot |1\rangle = |0\rangle$$

- $|1\rangle$ corresponds to the south pole, since $\theta = \pi$:

$$|1\rangle = \cos\left(\frac{\pi}{2}\right) |0\rangle + e^{i\phi} \sin\left(\frac{\pi}{2}\right) |1\rangle = 0 \cdot |0\rangle + e^{i\phi} \cdot 1 \cdot |1\rangle = e^{i\phi} |1\rangle \Rightarrow |1\rangle$$

⚠ Attention! $e^{i\phi} |1\rangle$ becomes $|1\rangle$ after **removing the global phase** (physically unobservable), so $|1\rangle$ is indeed at the south pole. In general, all states of the form $e^{i\phi} |1\rangle$ represent the **same physical state** as $|1\rangle$. Hence, $|1\rangle$ corresponds to the **south pole** of the Bloch sphere.

- States on the equator correspond to equal-weight superpositions of $|0\rangle$ and $|1\rangle$.

In particular:

$$\text{Hadamard} \quad |+\rangle = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle), \quad |-\rangle = \frac{1}{\sqrt{2}}(|0\rangle - |1\rangle),$$

$$\text{Imaginary} \quad |i\rangle = \frac{1}{\sqrt{2}}(|0\rangle + i|1\rangle), \quad |-i\rangle = \frac{1}{\sqrt{2}}(|0\rangle - i|1\rangle),$$

All lie on the equator and differ only by their relative phase.

The Bloch sphere provides an intuitive visualization of a qubit: moving along the vertical direction changes the relative weights of $|0\rangle$ and $|1\rangle$, while rotating around the vertical axis changes the relative phase between them.




Figure 9: Bloch sphere representation of a pure qubit state. The red vector $|v\rangle$ represents a generic qubit state. Measuring $|v\rangle$ along the z -axis gives probabilities determined by θ , while along x or y -axes reveals information about the relative phase ϕ .

On the Bloch sphere, the axes correspond to **three fundamental measurement bases** for a qubit. Each pair of opposite points represents the **eigenstates of one of the Pauli operators** (we will discuss the Pauli operators in more detail in 3.3.2.2, page 47):

- **z -axis, computational basis** $\{|0\rangle, |1\rangle\}$, eigenstates of σ_z . The states are:

$$|0\rangle = \begin{pmatrix} 1 \\ 0 \end{pmatrix} \quad \text{and} \quad |1\rangle = \begin{pmatrix} 0 \\ 1 \end{pmatrix}$$

These states correspond to the classical bit values 0 and 1.

- $|0\rangle$: North pole of the Bloch sphere $(0, 0, 1)$.
- $|1\rangle$: South pole of the Bloch sphere $(0, 0, -1)$.

Measuring along the z -axis answer the question: “*is the qubit $|0\rangle$ or $|1\rangle$?*”.

- **x -axis, Hadamard basis** $\{|+\rangle, |-\rangle\}$, eigenstates of σ_x . The states are:

$$|+\rangle = \frac{1}{\sqrt{2}} (|0\rangle + |1\rangle) \quad \text{and} \quad |-\rangle = \frac{1}{\sqrt{2}} (|0\rangle - |1\rangle)$$

- $|+\rangle$: $+x$ direction on the equator $(1, 0, 0)$, with $\phi = 0$ (no relative phase).
- $|-\rangle$: $-x$ direction on the equator $(-1, 0, 0)$, with $\phi = \pi$ (relative phase of π between $|0\rangle$ and $|1\rangle$).

These states represent **equal superpositions** of $|0\rangle$ and $|1\rangle$ with **relative phase** 0 and π .

- **y -axis, imaginary basis** $\{|i\rangle, |-i\rangle\}$, eigenstates of σ_y . The states are:

$$|i\rangle = \frac{1}{\sqrt{2}} (|0\rangle + i|1\rangle) \quad \text{and} \quad |-i\rangle = \frac{1}{\sqrt{2}} (|0\rangle - i|1\rangle)$$

- $|i\rangle$: $+y$ direction on the equator $(0, 1, 0)$, with $\phi = \frac{\pi}{2}$ (relative phase of $\frac{\pi}{2}$ between $|0\rangle$ and $|1\rangle$).
- $|-i\rangle$: $-y$ direction on the equator $(0, -1, 0)$, with $\phi = -\frac{\pi}{2}$ (relative phase of $-\frac{\pi}{2}$ between $|0\rangle$ and $|1\rangle$).

These states also have equal probabilities of measuring $|0\rangle$ or $|1\rangle$ in the computational basis, but they differ by a **relative phase of $\pm\frac{\pi}{2}$** . This phase is crucial for **interference effects** in quantum algorithms.

3 Single Qubit Gates

3.1 Operations on Qubits

Quantum computing relies on three essential operations:

1. **Logic Gates:** transform quantum states.
2. **Measurements:** extract classical information from qubits.
3. **Initialization Procedures:** prepare qubits in known starting states.

☰ Logic Gates: Reversible Transformations

Quantum **Logic Gates** are the building blocks of quantum circuits. They **manipulate the state of qubits in a controlled and deterministic way**, analogous to classical logic gates (like AND or NOT), but with key quantum differences:

- **Operate on Single or Multiple Qubits.** They can affect one qubit (single-qubit gates) or multiple qubits simultaneously (multi-qubit gates):
 - **Single-Qubit Gates:** These gates, such as the Pauli-X, Y, Z, Hadamard (H), and Phase (S) gates, operate on a single qubit to change its state. We will explore these gates in detail in the next sections.
 - **Multi-Qubit Gates:** These gates, such as the CNOT (Controlled-NOT) and Toffoli gates, operate on multiple qubits and can create *entanglement* (we will discuss this in detail later) between them, which is a key resource in quantum computing.
- **Reversible Transformations.** Unlike many classical gates (e.g., AND), **all quantum gates are reversible**. Mathematically, this means they are represented by **unitary matrices** U , satisfying:

$$U^\dagger U = U U^\dagger = I$$

Where $U^\dagger$ is the conjugate transpose of U , and I is the identity matrix. Because of this reversibility, quantum gates **do not lose information** and the **original state can be recovered** by applying $U^\dagger = U^{-1}$ to the output state. This is a fundamental difference from classical logic gates, which can be irreversible (e.g., AND gate loses information about the inputs).

Finally, this property is related to fundamental principles such as the **no-cloning theorem** (page 30) and the **no-deleting theorem** (we cannot delete quantum information arbitrarily, since it is preserved under unitary transformations).

- **State Evolution.** If a qubit is in the state:

$$|\psi\rangle = a|0\rangle + b|1\rangle$$

Then after applying a gate U , the new state becomes:

$$|\psi'\rangle = U|\psi\rangle = aU|0\rangle + bU|1\rangle$$

This **transformation is deterministic** and **preserves the normalization of the state** (i.e., $|a|^2 + |b|^2 = 1$ remains true after applying U). The specific effect of the gate depends on its matrix representation, which we will explore in the next sections.

We can think of quantum logic gates as **rotations on the Bloch sphere**, smoothly transforming the qubit's state without destroying its quantum nature.

Measurement: Irreversible Collapse of State

Measurement is the process of extracting information from a qubit. Unlike logic gates, measurement is **irreversible** and fundamentally probabilistic.

- **Irreversible Process.** Once a qubit is measured, its original quantum state is **lost**. This distinguishes measurement from unitary gate operations.
- **State Collapse.** Measuring a qubit in the computational basis $\{|0\rangle, |1\rangle\}$ causes the state:

$$|\psi\rangle = a|0\rangle + b|1\rangle$$

To **collapse** to:

- $|0\rangle$ with probability $|a|^2$.
- $|1\rangle$ with probability $|b|^2$.
- **Extraction of Classical Information.** The measurement outcome is a **classical bit** (0 or 1). After measurement, subsequent measurements in the same basis yield the same result with probability 1, since the state has collapsed to a definite state.

Measurement can be described using **projection operators**:

$$M_0 = |0\rangle\langle 0| \quad M_1 = |1\rangle\langle 1|$$

The probability of obtaining outcome k (where $k \in \{0, 1\}$) when measuring $|\psi\rangle$ is given by:

$$\begin{aligned} p_k &= \langle\psi| M_k |\psi\rangle \\ &\downarrow \text{substitute } M_k = |k\rangle\langle k| \\ &= \langle\psi| (|k\rangle\langle k|) |\psi\rangle \\ &\downarrow \text{using the associativity of inner products} \\ &= (\langle\psi|k\rangle) (\langle k|\psi\rangle) \\ &\downarrow \text{since } \langle\psi|k\rangle = (\langle k|\psi\rangle)^* \\ &\quad \text{where } * \text{ denotes complex conjugation} \\ &= (\langle k|\psi\rangle)^* (\langle k|\psi\rangle) \\ &\downarrow \text{which is the definition of squared magnitude, page 7} \\ &= |\langle k|\psi\rangle|^2 \end{aligned}$$

In other words, the probability of measuring outcome k is the **squared magnitude of the amplitude** of $|\psi\rangle$ along the direction $|k\rangle$. And the post-measurement state of the qubit, conditioned on obtaining outcome k , becomes:

$$|\psi_k\rangle = \frac{M_k |\psi\rangle}{\sqrt{p_k}}$$

Measurement is like **asking a question** to the qubit: “are you in state $|0\rangle$ or $|1\rangle$?”. The answer is classical (i.e., 0 or 1), but the act of asking **changes the system**.

Example 1: Calculating Measurement Probabilities

Consider a qubit in the state:

$$|\psi\rangle = a|0\rangle + b|1\rangle$$

With $|a|^2 + |b|^2 = 1$.

- Probability of measuring 0. Using the projector:

$$M_0 = |0\rangle\langle 0|$$

We compute:

$$\begin{aligned} p_0 &= \langle\psi| M_0 |\psi\rangle \\ &= \langle\psi|0\rangle \langle 0|\psi\rangle \\ &= (\langle\psi|0\rangle) (\langle 0|\psi\rangle) \\ &\downarrow \text{since } \langle\psi|0\rangle = (\langle 0|\psi\rangle)^* \\ &= |\langle 0|\psi\rangle|^2 \\ &= |a|^2 \end{aligned}$$

- Probability of measuring 1. Using the projector:

$$M_1 = |1\rangle\langle 1|$$

We compute:

$$\begin{aligned} p_1 &= \langle\psi| M_1 |\psi\rangle \\ &= \langle\psi|1\rangle \langle 1|\psi\rangle \\ &= (\langle\psi|1\rangle) (\langle 1|\psi\rangle) \\ &\downarrow \text{since } \langle\psi|1\rangle = (\langle 1|\psi\rangle)^* \\ &= |\langle 1|\psi\rangle|^2 \\ &= |b|^2 \end{aligned}$$

Initialization: Preparing Known States

The **Initialization** is the process of preparing a qubit in a **known and controlled state**, typically $|0\rangle$ or $|1\rangle$. This step is essential because quantum algorithms require a well-defined starting point. It is implemented through various methods, including:

- **Physical Preparation.** Many quantum technologies naturally relax to the ground state $|0\rangle$. Additional gates (e.g., Pauli-X) can be applied to obtain $|1\rangle$ if needed.
- **Initialization via Measurement.** Measuring a qubit projects it into a basis state. If the outcome is not the desired one, a corrective gate can be applied. For example, if measurement yields $|1\rangle$ but $|0\rangle$ is needed, apply an X gate to flip it to $|0\rangle$.

Initialization is the **first step** in any quantum computation: (1) **prepare** qubits in known states, (2) **apply** them using quantum gates, and (3) **measure** to obtain classical results. It is analogous to **resetting a classical register** before starting a computation in classical computing.

3.2 Quantum Logic Gates Overview

In quantum computing, quantum logic gates are the primary tools used to **manipulate qubits**. These gates perform **unitary transformations** on the state of one or more qubits, meaning they **preserve the norm** of the quantum state and are **reversible**. The **design of quantum algorithms** and the **execution of quantum circuits** rely entirely on the sequential application of these gates.

≡ Types of Quantum Gates

Quantum Gates can be classified into:

- **Single-Qubit Gates:** These gates operate on **individual qubits**, modifying their state in isolation.
- **Multiple-Qubit Gates:** These gates act on **two or more qubits simultaneously**, allowing for entanglement and complex correlations between qubits.

In this section we will focus on single qubit gates.

✖ Mathematical Framework: Qubit as Vectors, Gates as Matrices

To describe quantum superposition mathematically, we require a framework that supports linear combinations of states, probabilities derived from inner products, complex amplitudes and phases, and linear state transformations. The mathematical structure satisfying all these requirements is a **complex Hilbert space**. Thus, a qubit is naturally represented as a **unit vector** in a two-dimensional complex Hilbert space $\mathbb{C}^2$.

Using the Dirac notation, the basis states $|0\rangle$ and $|1\rangle$ form an orthonormal basis for this space, satisfying $\langle 0|0\rangle = \langle 1|1\rangle = 1$ and $\langle 0|1\rangle = \langle 1|0\rangle = 0$. Any qubit state can be expressed as a linear combination of these basis states:

$$|\psi\rangle = a|0\rangle + b|1\rangle \quad \text{with } |a|^2 + |b|^2 = 1$$

Two state vectors that differ only by a global phase factor $e^{i\phi}$ represent the same physical qubit, since measurement probabilities remain unchanged (see page 33).

Choosing the computational basis $\{|0\rangle, |1\rangle\}$, we can represent these states as column vectors:

$$|0\rangle = \begin{bmatrix} 1 \\ 0 \end{bmatrix} \quad |1\rangle = \begin{bmatrix} 0 \\ 1 \end{bmatrix}$$

Therefore, the qubit state can be written as:

$$|\psi\rangle = a|0\rangle + b|1\rangle = \begin{bmatrix} a \\ b \end{bmatrix}$$

This vector representation allows us to apply linear algebra techniques to analyze and manipulate qubits.

Once qubits are represented as vectors, transformations of these states must be **linear operators** acting on the vector space. In a chosen basis, linear operators are represented by **matrices**. To preserve normalization and probabilities, these matrices must be **unitary**:

$$U^\dagger U = U U^\dagger = I$$

Thus, quantum gates – the **building blocks of quantum circuits** – are represented as unitary 2×2 matrices that linearly transform the state vector:

$$|\psi'\rangle = U |\psi\rangle$$

❓ Why Matrices? Because quantum mechanics is inherently linear, any physical evolution of a closed quantum system must be described by a **linear operator**. When expressed in a chosen basis (such as the computational basis $\{|0\rangle, |1\rangle\}$), this operator takes the form of a matrix.

☆ Unitary: The Fundamental Constraint

A matrix U is **unitary** if it satisfies the condition:

$$U^\dagger U = U U^\dagger = I \quad (3)$$

Where:

- $U^\dagger$ is the **Hermitian transpose** (conjugate transpose) of U .
- I is the **identity matrix**.

This property ensures that $U^{-1} = U^\dagger$, meaning every quantum operation is **reversible**, and the transformation preserves the **norm** of the state vector. So, quantum gate **must be unitary** to ensure that the evolution of quantum states is consistent with the principles of quantum mechanics (i.e., linearity, reversibility, and preservation of probabilities).

A **general single-qubit unitary matrix** can be expressed as:

$$U = \begin{pmatrix} \alpha & \beta \\ \gamma & \delta \end{pmatrix} \quad \text{with } \alpha, \beta, \gamma, \delta \in \mathbb{C} \quad \text{and} \quad U^\dagger U = I \quad (4)$$

❓ Why must gates be unitary?

1. **No-Cloning Theorem:** It is impossible to create an identical copy of an unknown qubit. Unitary transformations respect this by not duplicating information.
2. **No-Deleting Theorem:** We cannot delete quantum information arbitrarily. Since unitary gates are invertible, they do not erase information.
3. **Preservation of Probability:** The normalization condition $|a|^2 + |b|^2 = 1$ must hold after any operation, and **only unitary matrices preserve this norm.**

Physical Intuition

In classical circuits, logic gates like AND, OR, NOT process bits deterministically. In quantum circuits:

- Gates **rotate** the quantum state on the **bloch sphere**.
- These rotations correspond to **unitary transformations**.
- The **physical implementation** of quantum gates may vary across hardware (e.g., superconducting qubits, trapped ions), but **mathematically**, the **same unitary matrix describes the gate**.

Quantum gates do not correspond to physical gates in the classical sense. They are **abstract operations** realized by **controlled interactions** in quantum systems.

3.3 Main Single-Qubit Gates

3.3.1 Identity Gate (I)

The **Identity Gate**, denoted I , is the most elementary gate in quantum computing. It performs **no change** to the state of a qubit. Its action on a qubit is trivial, yet it **serves important roles in quantum circuits**, particularly **when managing multi-qubit systems** or **timing synchronization**.

√* Matrix Representation

The Identity gate is represented by the 2×2 **identity matrix**:

$$I = \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix} \quad (5)$$

Applying the Identity gate to any qubit **leaves the state unchanged**. Formally, for a qubit in state $|\psi\rangle$:

$$I|\psi\rangle = |\psi\rangle$$

To better understand its effect, consider its action on the computational basis:

$$\begin{aligned} I|0\rangle &= \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix} \begin{pmatrix} 1 \\ 0 \end{pmatrix} = \begin{pmatrix} 1 \\ 0 \end{pmatrix} = |0\rangle \\ I|1\rangle &= \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix} \begin{pmatrix} 0 \\ 1 \end{pmatrix} = \begin{pmatrix} 0 \\ 1 \end{pmatrix} = |1\rangle \end{aligned}$$

Hence, the Identity gate **preserves the state** of the qubit, including any superposition or entangled state it may be in.

≡ Physical Interpretation

Although it may appear useless at first glance, the Identity gate has **conceptual and practical utility**:

- ✓ It acts as a **placeholder** or “*do nothing*” operation when required by **circuit timing**.
- ✓ In **multi-qubit circuits**, it allows one **qubit to remain unchanged** while other qubits are operated on.
- ✓ In **matrix composition** of gates, it serves to **align dimensions** when performing **tensor products** (e.g., $I \otimes H$ applies Hadamard to the second qubit only).

❓ Bloch Sphere Perspective

In the Bloch sphere (page 36), the **identity gate** represents a **rotation of zero degrees**, meaning the state vector remains exactly where it is. It is the neutral element of quantum transformations.

3.3.2 Pauli Gates

The **Pauli Gates** are a set of fundamental single-qubit quantum gates that play a central role in quantum computing. They are represented by the three **Pauli matrices** X , Y , and Z , and can be interpreted as the quantum analogues of basic operations on a qubit.

Each Pauli gate corresponds to a **rotation of π radians** around one of the principal axes of the Bloch sphere:

- X : rotation around the x -axis (bit flip).
- Z : rotation around the z -axis (phase flip).
- Y : rotation around the y -axis (bit and phase flip).

These operators are **unitary** ($U^\dagger U = U U^\dagger = I$), **Hermitian** ($U = U^\dagger$), and **self-inverse** ($U^2 = I$), and their eigenstates define the three fundamental measurement bases of a qubit. Together, they form the building blocks for describing single-qubit transformations and quantum dynamics. Also, they have eigenvalues ± 1 and satisfy the property:

$$X^2 = Y^2 = Z^2 = I$$

Meaning that applying the same Pauli gate twice returns the qubit to its original state.

3.3.2.1 Rotations Generated by Pauli Operators

In quantum mechanics, rotations of a qubit are generated by the Pauli operators. A rotation around an axis $\hat{n}$ by an angle θ is given by:

$$R_{\hat{n}}(\theta) = e^{-i\frac{\theta}{2}(\hat{n} \cdot \vec{\sigma})} \quad (6)$$

Where $\vec{\sigma} = (X, Y, Z)$ are the Pauli matrices. We will see those matrices in more detail in the next sections, but for now we can just note that they are the generators of rotations around the x , y , and z axes, respectively.

In particular:

$$R_x(\theta) = e^{-i\frac{\theta}{2}X} \quad (7)$$

$$R_y(\theta) = e^{-i\frac{\theta}{2}Y} \quad (8)$$

$$R_z(\theta) = e^{-i\frac{\theta}{2}Z} \quad (9)$$

Using the identity $\sigma^2 = I$, these can be expanded as:

$$R_\alpha(\theta) = \cos\left(\frac{\theta}{2}\right) I - i \sin\left(\frac{\theta}{2}\right) \sigma_\alpha \quad (10)$$

3.3.2.2 Pauli-X (NOT) Gate

The **Pauli-X Gate**, often called the **quantum NOT gate**, is one of the *fundamental* single-qubit quantum gates. It is denoted X and **corresponds to the σ_x Pauli matrix** in quantum mechanics. This gate **flips the state of a qubit, similar to how a classical NOT gate inverts a bit.**

Remark: Pauli Matrix

In quantum mechanics, the **Pauli matrices** are a set of three 2×2 **Hermitian and unitary matrices** that represent **spin operators** for spin- $\frac{1}{2}$ particles and are widely used in quantum computing to describe single-qubit gates. They are:

$$\sigma_x = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \quad \sigma_y = \begin{pmatrix} 0 & -i \\ i & 0 \end{pmatrix} \quad \sigma_z = \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix}$$

Key properties:

- Hermitian: $\sigma_i^\dagger = \sigma_i$ (observable-related)
- Unitary: $\sigma_i^\dagger \sigma_i = I$ (reversible transformations)
- Involution: $\sigma_i^2 = I$
- Non-commuting: $[\sigma_i, \sigma_j] = 2i\varepsilon_{ijk}\sigma_k$ (with ε the Levi-Civita symbol)

√ Matrix Representation

$$X = \sigma_x = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \quad (11)$$

This **matrix swaps** the $|0\rangle$ and $|1\rangle$ **basis states**:

$$X|0\rangle = |1\rangle \quad \text{and} \quad X|1\rangle = |0\rangle \quad (12)$$

≡ Action on a General Qubit

Let's consider a qubit in the general state:

$$|\psi\rangle = a|0\rangle + b|1\rangle$$

Applying the X gate:

$$X|\psi\rangle = aX|0\rangle + bX|1\rangle = a|1\rangle + b|0\rangle = b|0\rangle + a|1\rangle$$

As a result, the **amplitudes** a and b are **swapped**.

≡ Key Properties of X Gate

The Pauli-X gate satisfies several important mathematical properties:

1. **Unitary**. The X gate is unitary, meaning it preserves the inner product and is reversible:

$$XX^\dagger = I$$

2. **Hermitian**. The X gate is also Hermitian, which means it is equal to its own conjugate transpose:

$$X = X^\dagger$$

3. **Self-Inverse**. The X gate is its own inverse, which means that **applying it twice returns the qubit to its original state**:

$$X^{-1} = X \quad \Rightarrow \quad X^2 = I$$

🔗 Geometric Interpretation: Rotation on the Bloch Sphere

The Pauli-X gate corresponds to a **rotation around the x -axis by π radians (180°)** on the Bloch sphere, denoted as $X = R_x(\pi)$.

To understand this, recall the **general qubit state in spherical coordinates**:

$$|\psi\rangle = \cos\left(\frac{\theta}{2}\right)|0\rangle + e^{i\phi}\sin\left(\frac{\theta}{2}\right)|1\rangle$$

After a π rotation around the x -axis:

- $\theta \rightarrow \pi - \theta$
- $\phi \rightarrow -\phi$

This **rotation mirrors the qubit across the x -axis**, flipping its position between $|0\rangle$ and $|1\rangle$, and adjusting the phase accordingly.

⚙️ Rotation Interpretation

From Equation 6 (page 46) and Equation 10 (page 46), a rotation around the x -axis by an angle θ is given by:

$$R_x(\theta) = \cos\left(\frac{\theta}{2}\right)I - i\sin\left(\frac{\theta}{2}\right)X$$

For $\theta = \pi$, we obtain:

$$R_x(\pi) = -iX$$

Therefore, the Pauli-X gate corresponds to a **rotation of π around the x -axis, up to a global phase**:

$$X \equiv R_x(\pi)$$

Since global phases are physically irrelevant, X and $R_x(\pi)$ represent the same physical transformation.




Figure 10: Eigenstates of the Pauli-X gate. Since $|+\rangle$ and $|-\rangle$ lie on the x -axis, they are not moved by a rotation around that axis. The state $|-\rangle$ only acquires a global phase -1 .

Eigenstates

In linear algebra, an **eigenvector** of a matrix (or linear operator) A is a non-zero vector $|v\rangle$ that, when the operator is applied, changes only by a **scalar factor** called the **eigenvalue** λ :

$$A|v\rangle = \lambda|v\rangle$$

In quantum mechanics, we use the term **Eigenstate** instead of eigenvector. So, an eigenstate of an operator U satisfies:

$$U|v\rangle = \lambda|v\rangle$$

An **eigenstate** is a state that remains **unchanged in direction** after the operation is applied, except only its **magnitude** or **phase** may change by a factor of λ . For the Pauli-X gate, solving the eigenvalue equation:

$$X|v\rangle = \lambda|v\rangle$$

Yields two eigenstates:

$$|+\rangle = \frac{|0\rangle + |1\rangle}{\sqrt{2}} \quad \text{with eigenvalue} \quad +1 \Rightarrow X|+\rangle = +1 \cdot |+\rangle = |+\rangle \quad (13)$$

$$|-\rangle = \frac{|0\rangle - |1\rangle}{\sqrt{2}} \quad \text{with eigenvalue} \quad -1 \Rightarrow X|-\rangle = -1 \cdot |-\rangle = -|-\rangle \quad (14)$$

Example 2: Measurement in the X-basis

For example, if a qubit is in the state $|x\rangle$ and we measure it in the X-basis, the outcome is 1 with probability 1.

Proof. We want to show that if the qubit is in the state:

$$|x\rangle = \frac{|0\rangle + |1\rangle}{\sqrt{2}}$$

And we measure it in the X-basis $\{|+\rangle, |-\rangle\}$, then the outcome is +1 with probability 1.

Measuring in the X-basis means using the eigenstates of the Pauli-X operator:

$$|+\rangle = \frac{|0\rangle + |1\rangle}{\sqrt{2}}, \quad |-\rangle = \frac{|0\rangle - |1\rangle}{\sqrt{2}}$$

These correspond to the new possible outcomes: +1 for $|+\rangle$ and -1 for $|-\rangle$.

If the system is in state $|\psi\rangle$, the probability of obtaining the outcome corresponding to basis state $|u\rangle$ is:

$$P(u) = |\langle u|\psi\rangle|^2$$

In our case, the system is in state $|\psi\rangle = |+\rangle$, so:

- Probability of outcome +1 (measuring $|+\rangle$):

$$P(+1) = |\langle +|+\rangle|^2$$

- Probability of outcome -1 (measuring $|-\rangle$):

$$P(-1) = |\langle -|+\rangle|^2$$

Since every normalized state has inner product 1 with itself, we have:

$$\langle +|+\rangle = 1$$

Therefore:

$$P(+1) = |\langle +|+\rangle|^2 = |1|^2 = 1$$

So the probability of getting +1 is 1.

If we calculate the probability of getting -1, first write the bras and kets:

$$|+\rangle = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle), \quad |-\rangle = \frac{1}{\sqrt{2}}(|0\rangle - |1\rangle)$$

Changing the ket $|+\rangle$ to a bra:

$$\langle -| = \frac{1}{\sqrt{2}}(\langle 0| - \langle 1|)$$

Now we can compute the inner product:

$$\begin{aligned}
 \langle -|+\rangle &= \frac{1}{\sqrt{2}} (\langle 0| - \langle 1|) \frac{1}{\sqrt{2}} (|0\rangle + |1\rangle) \\
 &\downarrow \text{bring out the factors} \\
 &= \frac{1}{2} (\langle 0| - \langle 1|) (|0\rangle + |1\rangle) \\
 &\downarrow \text{expand the product} \\
 &= \frac{1}{2} (\langle 0|0\rangle + \langle 0|1\rangle - \langle 1|0\rangle - \langle 1|1\rangle) \\
 &\downarrow \text{use orthonormality } (\langle 0|0\rangle = \langle 1|1\rangle = 1, \langle 0|1\rangle = \langle 1|0\rangle = 0) \\
 &= \frac{1}{2} (1 + 0 - 0 - 1) \\
 &= 0
 \end{aligned}$$

Therefore:

$$P(-1) = |\langle -|+\rangle|^2 = |0|^2 = 0$$

So the probability of getting -1 is 0.

QED

3.3.2.3 Pauli-Z (Phase Flip) Gate

The **Pauli-Z Gate**, also called the **Phase Flip Gate**, is one of the core **Pauli operators** used in quantum computing. It acts **only on the phase** of the qubit, leaving the **$|0\rangle$ amplitude unchanged** but **flipping the sign of the $|1\rangle$ amplitude**.

√* Matrix Representation

$$Z = \sigma_Z = \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix} \quad (15)$$

≡ Action on a General Qubit

For a general state:

$$|\psi\rangle = a|0\rangle + b|1\rangle$$

Applying Z :

$$Z|\psi\rangle = aZ|0\rangle + bZ|1\rangle = a|0\rangle - b|1\rangle$$

As a result, Z **flips the sign of the $|1\rangle$ amplitude**, this is why it's called a **phase flip**. Finally, it's trivial to show that:

$$Z|0\rangle = |0\rangle \quad (\text{unchanged}), \quad Z|1\rangle = -|1\rangle \quad (\text{sign flip})$$

So the **magnitudes** of the amplitudes remain unchanged and the **probabilities of measurement outcomes** in the standard basis are unaffected, but the **relative phase** between $|0\rangle$ and $|1\rangle$ is altered (since b changes to $-b$).

Example 3: Effect on Superposition States

The Hadamard (or X-basis) states are:

$$|+\rangle = \frac{|0\rangle + |1\rangle}{\sqrt{2}}, \quad |-\rangle = \frac{|0\rangle - |1\rangle}{\sqrt{2}}$$

These two states differ **only by their relative phase**:

- $|+\rangle$: relative phase 0.
- $|-\rangle$: relative phase π .

Applying Z on $|+\rangle$:

$$\begin{aligned} Z|+\rangle &= Z \left(\frac{|0\rangle + |1\rangle}{\sqrt{2}} \right) \\ &= \frac{Z|0\rangle + Z|1\rangle}{\sqrt{2}} \\ &= \frac{|0\rangle - |1\rangle}{\sqrt{2}} \\ &= |-\rangle \end{aligned}$$

Applying Z on $|-\rangle$:

$$\begin{aligned} Z|-\rangle &= Z \left(\frac{|0\rangle - |1\rangle}{\sqrt{2}} \right) \\ &= \frac{Z|0\rangle - Z|1\rangle}{\sqrt{2}} \\ &= \frac{|0\rangle + |1\rangle}{\sqrt{2}} \\ &= |+\rangle \end{aligned}$$

The Pauli-Z gate **does not change the probabilities** of measuring $|0\rangle$ or $|1\rangle$ in the computational basis. However, it **changes the relative phase**, transforming $|+\rangle$ into $|-\rangle$ and vice versa.

🔍 Geometric Interpretation: Rotation around the z -axis

On the Bloch sphere, the Pauli-Z gate performs a π radians (180°) **rotation around the z -axis**. In spherical coordinates:

$$|\psi\rangle = \cos\left(\frac{\theta}{2}\right)|0\rangle + e^{i\phi}\sin\left(\frac{\theta}{2}\right)|1\rangle$$

After Z rotation:

- The angle $\phi \rightarrow \phi + \pi$
- This phase shift **changes the sign of the complex amplitude for $|1\rangle$**

Since **measurement probabilities depend on $|a|^2$ and $|b|^2$** , which **remain unchanged**, the Z gate **does not affect measurement outcomes** in the standard basis. It only affects **interference and future gate interactions**.

⚙️ Rotation Interpretation

From Equation 6 (page 46) and Equation 10 (page 46), a rotation around the z -axis by an angle θ is given by:

$$R_z(\theta) = \cos\left(\frac{\theta}{2}\right)I - i\sin\left(\frac{\theta}{2}\right)Z$$

For $\theta = \pi$, we obtain:

$$R_z(\pi) = -iZ$$

Therefore, the Pauli-Z gate corresponds to a **rotation of π around the z -axis, up to a global phase**:

$$Z \equiv R_z(\pi)$$

Since global phases are physically irrelevant, Z and $R_z(\pi)$ represent the same physical transformation.




Figure 11: Eigenstates of the Pauli-Z gate. Since $|0\rangle$ and $|1\rangle$ lie on the z -axis, they are not moved by a rotation around that axis. The state $|1\rangle$ only acquires a global phase -1 .

⌘ Key Properties

1. **Unitary:** $Z^\dagger = Z^{-1} = Z$. Ensuring normalization is preserved.
2. **Hermitian:** $Z^\dagger = Z$. Meaning it is equal to its own conjugate transpose.
3. **Self-Inverse:** $Z^{-1} = Z \Rightarrow Z^2 = I$. Applying the Pauli-Z gate twice returns the original state.
4. **Eigenvalues and Eigenstates.** The Pauli-Z operator has *eigenvalues* $+1$ and -1 , with corresponding *eigenstates* $|0\rangle$ and $|1\rangle$:

$$Z|0\rangle = +1 \cdot |0\rangle, \quad Z|1\rangle = -1 \cdot |1\rangle$$

This means that $|0\rangle$ and $|1\rangle$ are **unchanged in direction** by the action of Z (up to a possible phase factor). In particular:

- $|0\rangle$ is completely unchanged.
- $|1\rangle$ acquires only a phase factor $-1 = e^{i\pi}$.

Therefore, these states are **invariant under the action of Z** (up to global phase), and represent the **natural states of the operator**.

💡 **Geometric Insight.** On the Bloch sphere, the Pauli-Z gate corresponds to a rotation around the z -axis. The eigenstates $|0\rangle$ and $|1\rangle$ lie exactly on this axis (north and south poles). As a consequence, they are **not affected by the rotation**, which explains why they are eigenstates of Z .

In contrast, any state that is not aligned with the z -axis (for example $|+\rangle$, Figure 9) is rotated by the action of Z . This highlights the difference between:

- **Eigenstates:** unchanged (up to phase)
- **Superposition states:** geometrically rotated

3.3.2.4 Pauli-Y Gate

The **Pauli-Y Gate**, denoted Y , is one of the three fundamental **Pauli matrices** in quantum mechanics. It is less intuitive than Pauli-X and Z, but equally important, especially for its role in complex rotations and quantum interference.

√* Matrix Representation

$$Y = \sigma_Y = \begin{pmatrix} 0 & -i \\ i & 0 \end{pmatrix}$$

≡ Action on a General Qubit

At first glance, this looks similar to the Pauli-X gate because it exchanges $|0\rangle$ and $|1\rangle$. But there is something extra: X swaps the two basis states (i.e., $|0\rangle \leftrightarrow |1\rangle$), while Y swaps them **and** multiplies them by a phases of $\pm i$. So Pauli-Y is not just a bit flip (like Pauli-X), it is a bit flip together with a phase modification.

Given a qubit in state:

$$|\psi\rangle = a|0\rangle + b|1\rangle$$

Apply the Y gate:

$$Y|\psi\rangle = aY|0\rangle + bY|1\rangle = a(-i|1\rangle) + b(i|0\rangle) = ib|0\rangle - ia|1\rangle$$

So the **amplitudes are exchanged** (as with Pauli-X), but each one also acquires a **phase factor of i or $-i$** .

🔍 Geometric Interpretation: Rotation on the Bloch Sphere

The Pauli-Y gate corresponds to a **rotation around the y -axis by π radians** (180°). The effect on Bloch sphere coordinates:

- $\theta \rightarrow \pi - \theta$
- $\psi \rightarrow \pi - \psi$

This rotates the qubit across the y -axis, **altering both amplitudes and their phases**.

⚙️ Rotation Interpretation

From Equation 6 (page 46) and Equation 10 (page 46), a rotation around the y -axis by an angle θ is given by:

$$R_y(\theta) = \cos\left(\frac{\theta}{2}\right) I - i \sin\left(\frac{\theta}{2}\right) Y$$

For $\theta = \pi$, we obtain:

$$R_y(\pi) = -iY$$

Therefore, the Pauli-Y gate corresponds to a **rotation of π around the y -axis, up to a global phase**:

$$Y \equiv R_y(\pi)$$

Since global phases are physically irrelevant, Y and $R_y(\pi)$ represent the same physical transformation.

≡ Pauli-Y as a Composite Gate

A very useful identity is:

$$Y = iXZ \quad (16)$$

This means that Pauli-Y can be understood as the combination of:

1. A Pauli-Z gate (phase flip);
2. Followed by a Pauli-X gate (bit flip);
3. Up to a global phase factor of i .

$$XZ = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix} = \begin{pmatrix} 0 & -1 \\ 1 & 0 \end{pmatrix}$$

Now, multiply by i :

$$iXZ = i \begin{pmatrix} 0 & -1 \\ 1 & 0 \end{pmatrix} = \begin{pmatrix} 0 & -i \\ i & 0 \end{pmatrix} = Y$$

This identity confirms that **Pauli-Y can be viewed as a combination of Pauli-X and Pauli-Z with a global phase factor i** , which does not affect measurement outcomes.

≡ Eigenstates of Y Gate

To find the eigenstates, we solve:

$$Y |v\rangle = \lambda |v\rangle$$

Where λ is the eigenvalue. The result is:

$$|i\rangle = \frac{1}{\sqrt{2}} (|0\rangle + i|1\rangle) \quad (17)$$

$$|-i\rangle = \frac{1}{\sqrt{2}} (|0\rangle - i|1\rangle) \quad (18)$$

With eigenvalues:

$$Y |i\rangle = +1 |i\rangle \quad Y |-i\rangle = -1 |-i\rangle \quad (19)$$

⋮ Key Properties of Y Gate

1. **Unitary**: $Y^\dagger Y = I$. So it is a valid quantum gate that preserves normalization.
2. **Hermitian**: $Y^\dagger = Y$. So it is also an observable, meaning it corresponds to a measurable quantity in quantum mechanics.
3. **Self-inverse**: $Y^2 = I$. Applying the Y gate twice returns the qubit to its original state.




Figure 12: Eigenstates of the Pauli-Y gate. Since $|i\rangle$ and $|-i\rangle$ lie on the y -axis, they are not moved by a rotation around that axis. The state $|-i\rangle$ only acquires a global phase -1 .

3.3.3 Phase Gate (S)

The **Phase Gate (S)** is a single-qubit gate that **adds a phase shift of $\frac{\pi}{2}$ (90°) to the amplitude of the $|1\rangle$ state**. It leaves $|0\rangle$ **unchanged**, like the Pauli-Z gate, but instead of a sign flip (π phase), it **introduces a complex phase factor i** .

√ Matrix Representation

$$S = \begin{pmatrix} 1 & 0 \\ 0 & i \end{pmatrix} \quad (20)$$

≡ Action on a General Qubit

For a state:

$$|\psi\rangle = a|0\rangle + b|1\rangle$$

Apply S :

$$S|\psi\rangle = a|0\rangle + ib|1\rangle$$

Only the $|1\rangle$ **amplitude gains a phase of i** , affecting interference but **not measurement probabilities** in the computational basis.

$$S|0\rangle = |0\rangle \quad (\text{unchanged}), \quad S|1\rangle = i|1\rangle \quad \left(\text{phase} + \frac{\pi}{2}\right)$$

🌀 Geometric Interpretation: Rotation around z -axis ($\frac{\pi}{2}$)

On the Bloch sphere, S performs a rotation of $\frac{\pi}{2}$ radians around the z -axis. This rotation **shifts the phase angle $\phi \rightarrow \phi + \frac{\pi}{2}$** , altering **how the qubit interferes** in later operations, especially when **Hadamard gates** are involved. In Figure 13, we see how S transforms the state $|+\rangle$ (on the x -axis) into $|i\rangle$ (on the y -axis) through a $\frac{\pi}{2}$ rotation around the z -axis, demonstrating the phase shift's effect on the qubit's state.

↔ Relationship to Pauli-Z

S is often called the **square root of Z** because applying it twice yields the Pauli-Z gate: $S = \sqrt{Z}$. Pauli-Z is a **full phase flip**:

$$e^{i\pi} = -1$$

The S gate is a **partial phase shift**:

$$e^{i\frac{\pi}{2}} = i$$

So:

$$Z = e^{i\pi \cdot |1\rangle\langle 1|} \quad \text{and} \quad S = e^{i\frac{\pi}{2} \cdot |1\rangle\langle 1|}$$

Same transformation, but different phase angles. Let's verify $S^2 = Z$:

$$S \cdot S = \begin{pmatrix} 1 & 0 \\ 0 & i \end{pmatrix} \cdot \begin{pmatrix} 1 & 0 \\ 0 & i \end{pmatrix} = \begin{pmatrix} 1 & 0 \\ 0 & i^2 \end{pmatrix} = \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix} = Z$$




Figure 13: Geometric interpretation of the Phase gate S . The gate performs a rotation of $\frac{\pi}{2}$ around the z -axis, transforming $|+\rangle$ into $|i\rangle$.

Eigenvalues and Eigenstates

The Phase gate S is diagonal in the computational basis, so its eigenstates are $|0\rangle$ and $|1\rangle$:

$$S|0\rangle = 1 \cdot |0\rangle, \quad S|1\rangle = i \cdot |1\rangle$$

Thus, the eigenvalues of S are:

$$\lambda_0 = 1, \quad \lambda_1 = i$$

This means that $|0\rangle$ remains unchanged, while $|1\rangle$ acquires a phase factor $i = e^{i\frac{\pi}{2}}$.

Key Properties

1. **Unitary:** $S^\dagger = S^{-1}$, so normalization is preserved.
2. **Not Hermitian:** $S^\dagger \neq S$, therefore S is not an observable, it is only a transformation.
3. **Inverse:**

$$S^{-1} = S^\dagger = \begin{pmatrix} 1 & 0 \\ 0 & -i \end{pmatrix}$$
4. **Relation with Pauli-Z:** $S^2 = Z$, meaning that S is the square root of the Pauli-Z gate.
5. **Periodicity:** $S^4 = I$, since $i^4 = 1$.
6. **Phase Shift:** S applies a relative phase of $\frac{\pi}{2}$ to the $|1\rangle$ component.

3.3.4 Hadamard Gate (H)

The **Hadamard Gate (H)** changes the basis representation of the qubit. More concretely:

$$H : \{|0\rangle, |1\rangle\} \longleftrightarrow \{|+\rangle, |-\rangle\}$$

It maps computational basis states into equal superpositions and vice versa, allowing phase information to be transformed into measurable probabilities.

√* Matrix Representation

$$H = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 & 1 \\ 1 & -1 \end{pmatrix} \quad (21)$$

≡ Action on Basis States

$$H|0\rangle = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle) = \frac{|0\rangle + |1\rangle}{\sqrt{2}} = |+\rangle \quad (22)$$

$$H|1\rangle = \frac{1}{\sqrt{2}}(|0\rangle - |1\rangle) = \frac{|0\rangle - |1\rangle}{\sqrt{2}} = |-\rangle \quad (23)$$

The $|+\rangle$ and $|-\rangle$ states are known as the **Hadamard basis**, or **superposition states**, with **equal probability amplitudes** for $|0\rangle$ and $|1\rangle$.

≡ Superposition and Measurement

After applying H to $|0\rangle$, the resulting qubit is:

$$|\psi\rangle = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle)$$

This state is a **superposition** of $|0\rangle$ and $|1\rangle$, meaning that the qubit does not have a definite classical value prior to measurement. Instead, it is described by **probability amplitudes** associated with each basis state.

Upon measurement in the computational basis, the state collapses probabilistically:

• **Probability of 0:**

• **Probability of 1:**

$$\left| \frac{1}{\sqrt{2}} \right|^2 = \frac{1}{2} \qquad \frac{1}{2}$$


After the measurement:

- The qubit collapses to $|0\rangle$ with probability $\frac{1}{2}$, or to $|1\rangle$ with probability $\frac{1}{2}$.
- The original superposition is **destroyed**, and cannot be recovered.

🔍 Bloch Sphere Interpretation

On the Bloch sphere, the **Hadamard gate performs two sequential rotations**:

1. **Rotation around the y -axis by $\frac{\pi}{2}$ radians (90°): $R_y\left(\frac{\pi}{2}\right)$.**



The y -axis stays fixed. So the states on the y -axis $|i\rangle$ and $|-i\rangle$ do not move. Instead, the z -axis rotated toward the x -axis: $|0\rangle \rightarrow |+ \rangle$ and $|1\rangle \rightarrow -|- \rangle$. So the first step already moves the computational basis from the z -axis to the x axis.

We can verify the matrix representation of $R_y\left(\frac{\pi}{2}\right)$ by using the exponential of the Pauli Y matrix (see page 46):

$$\begin{aligned}
 R_y(\theta) &= e^{-i\frac{\theta}{2}Y} \\
 &= \cos\left(\frac{\theta}{2}\right) I - i \sin\left(\frac{\theta}{2}\right) Y \\
 &= \cos\left(\frac{\theta}{2}\right) \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix} - i \sin\left(\frac{\theta}{2}\right) \begin{pmatrix} 0 & -i \\ i & 0 \end{pmatrix} \\
 &= \begin{pmatrix} \cos\left(\frac{\theta}{2}\right) & -\sin\left(\frac{\theta}{2}\right) \\ \sin\left(\frac{\theta}{2}\right) & \cos\left(\frac{\theta}{2}\right) \end{pmatrix}
 \end{aligned}$$

Now, substituting $\theta = \frac{\pi}{2}$ gives us the expected matrix for the first step of the Hadamard decomposition:

$$R_y\left(\frac{\pi}{2}\right) = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 & -1 \\ 1 & 1 \end{pmatrix}$$

- Apply it to $|0\rangle = \begin{pmatrix} 1 \\ 0 \end{pmatrix}$:

$$\begin{aligned}
 R_y\left(\frac{\pi}{2}\right)|0\rangle &= \frac{1}{\sqrt{2}} \begin{pmatrix} 1 & -1 \\ 1 & 1 \end{pmatrix} \begin{pmatrix} 1 \\ 0 \end{pmatrix} \\
 &= \frac{1}{\sqrt{2}} \begin{pmatrix} 1 \\ 1 \end{pmatrix} \\
 &= \frac{1}{\sqrt{2}} \left(\begin{pmatrix} 1 \\ 0 \end{pmatrix} + \begin{pmatrix} 0 \\ 1 \end{pmatrix} \right) \\
 &= \frac{1}{\sqrt{2}} (|0\rangle + |1\rangle) \\
 &= \frac{|0\rangle + |1\rangle}{\sqrt{2}} \\
 &= |+\rangle
 \end{aligned}$$

So $|0\rangle$, the north pole of the Bloch sphere, is rotated to the $+x$ -axis, which is the $|+\rangle$ state.

- Apply it to $|1\rangle = \begin{pmatrix} 0 \\ 1 \end{pmatrix}$:

$$\begin{aligned}
 R_y\left(\frac{\pi}{2}\right)|1\rangle &= \frac{1}{\sqrt{2}} \begin{pmatrix} 1 & -1 \\ 1 & 1 \end{pmatrix} \begin{pmatrix} 0 \\ 1 \end{pmatrix} \\
 &= \frac{1}{\sqrt{2}} \begin{pmatrix} -1 \\ 1 \end{pmatrix} \\
 &= \frac{1}{\sqrt{2}} \left(\begin{pmatrix} 0 \\ 1 \end{pmatrix} - \begin{pmatrix} 1 \\ 0 \end{pmatrix} \right) \\
 &= \frac{1}{\sqrt{2}} (|1\rangle - |0\rangle) \\
 &= -\frac{|0\rangle - |1\rangle}{\sqrt{2}} \\
 &= -|-\rangle
 \end{aligned}$$

This means that $|1\rangle$, the south pole of the Bloch sphere, moves to the $-x$ -axis, but with a global phase of -1 . Since global phases do not affect measurement outcomes, we can ignore it and say that $|1\rangle$ is effectively rotated to the $-x$ -axis, which is the $|-\rangle$ state. In simple terms: $-|-\rangle \equiv |-\rangle$ up to a global phase.

2. **Rotation around the x -axis by π radians (180°).** This step is represented by the operator $R_x(\pi)$, which can be expressed as:

$$R_x(\pi) = e^{-i\frac{\pi}{2}X} = \cos\left(\frac{\pi}{2}\right)I - i\sin\left(\frac{\pi}{2}\right)X = -iX$$

Applying $R_x(\pi)$ to the states on the x -axis ($|+\rangle$ and $|-\rangle$) does not change their position on the Bloch sphere, but it does introduce a phase factor

(which becomes a global phase only when applied to the entire state):

$$\begin{aligned} R_x(\pi) |+\rangle &= -iX |+\rangle = -i |+\rangle \\ R_x(\pi) |-\rangle &= -iX |-\rangle = -i(-|-\rangle) = i |-\rangle \end{aligned}$$

Applying $R_x(\pi)$ to the superposition state $a |+\rangle - b |-\rangle$ (obtained from the first rotation) gives us:

$$\begin{aligned} &a |+\rangle - b |-\rangle \\ R_x(\pi)(a |+\rangle - b |-\rangle) &= a(-i |+\rangle) - b(i |-\rangle) \\ &= -ia |+\rangle - ib |-\rangle \\ &= -i(a |+\rangle + b |-\rangle) \end{aligned}$$

Since global phases $-i$ do not affect measurement outcomes, we can ignore them and say that $|+\rangle$ and $|-\rangle$ remain on the x -axis. The second rotation does not change the position of the states on the Bloch sphere, but it is necessary to ensure that the transformation matches the Hadamard gate at the operator level, preserving the correct relative phase for all superpositions.

❓ Why is the second rotation necessary? We **cannot** simply change $-|-\rangle$ to $|-\rangle$ inside a superposition, because that would change only one component and therefore change the **relative phase**. The fix comes from applying $R_x(\pi)$. After the first rotation, we have:

$$a |+\rangle - b |-\rangle$$

Now, applying the Pauli-X operator using the rotation $R_x(\pi)$ (page 46):

$$R_x(\pi) = -iX = -i \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \quad \text{with} \quad X |+\rangle = |+\rangle, \quad X |-\rangle = -|-\rangle$$

Applying $R_x(\pi)$ to the superposition gives us:

$$\begin{aligned} R_x(\pi)(a |+\rangle - b |-\rangle) &= -iX(a |+\rangle - b |-\rangle) \\ &= -i(aX |+\rangle - bX |-\rangle) \\ &= -i(a |+\rangle - b(-|-\rangle)) \\ &= -i(a |+\rangle + b |-\rangle) \end{aligned}$$

Now the factor $-i$ multiplies the **entire state**, so it is a global phase:

$$-i(a |+\rangle + b |-\rangle) \equiv a |+\rangle + b |-\rangle$$

So the important point is:

$$a |+\rangle - b |-\rangle \not\equiv a |+\rangle + b |-\rangle$$

But:

$$R_x(\pi)(a |+\rangle - b |-\rangle) = -i(a |+\rangle + b |-\rangle) \equiv a |+\rangle + b |-\rangle$$

💡 Insight. The second rotation **does not affect the geometric position** of the states, but **corrects the relative phase** structure, ensuring that the transformation is a valid unitary operator acting consistently on the entire Hilbert space.




Figure 14: Second step of the Hadamard decomposition: rotation by π around the x -axis. States on the x -axis are not moved on the Bloch sphere; only global phases are introduced.

This brings $|0\rangle$ to the $+x$ -axis ($|+\rangle$) and $|1\rangle$ to the $-x$ -axis ($|-\rangle$). As a result, **qubit moves from pole to equator**, entering **maximum superposition**.

Eigenvalues and Eigenstates

The Hadamard operator has eigenvalues:

$$\lambda = +1, \quad \lambda = -1$$

with corresponding eigenstates given by the solutions of:

$$H|v\rangle = \lambda|v\rangle$$

These eigenstates are superpositions of $|0\rangle$ and $|1\rangle$, and are aligned along an axis halfway between the x and z directions on the Bloch sphere. Precisely, the eigenvectors are:

$$\begin{aligned} |v_+\rangle &= \cos\left(\frac{\pi}{8}\right)|0\rangle + \sin\left(\frac{\pi}{8}\right)|1\rangle \\ |v_-\rangle &= \sin\left(\frac{\pi}{8}\right)|0\rangle - \cos\left(\frac{\pi}{8}\right)|1\rangle \end{aligned}$$

Where $|v_+\rangle$ corresponds to the eigenvalue $+1$ and $|v_-\rangle$ corresponds to the eigenvalue -1 ; the cosine and sine factors ensure normalization of the eigenstates.

Unlike Pauli gates, the Hadamard eigenstates lie along a **diagonal axis between the computational basis z and the Hadamard basis x** , reflecting its role as a **basis transformation** rather than a simple bit or phase flip.




Figure 15: Bloch sphere interpretation of the Hadamard gate. The gate maps $|0\rangle$ to $|+\rangle$ and $|1\rangle$ to $|-\rangle$, moving computational basis states from the z -axis to the x -axis.

⌘ Key Properties

1. **Unitary:** $H^\dagger H = I$, so normalization is preserved.
2. **Hermitian:** $H^\dagger = H$, therefore it corresponds to an observable.
3. **Self-inverse:** $H^2 = I$. Applying the Hadamard gate twice returns the original state.
4. **Basis transformation:** H maps the computational basis $\{|0\rangle, |1\rangle\}$ to the Hadamard basis $\{|+\rangle, |-\rangle\}$:

$$H|0\rangle = |+\rangle, \quad H|1\rangle = |-\rangle$$

5. **Interference enabler:** H converts phase differences into amplitude differences, making them observable through measurement.
6. **Axis mixing:** H transforms Pauli operators as:

$$HZH = X, \quad HXH = Z$$

3.4 Properties

Single-qubit gates exhibit a rich set of mathematical and geometric properties, all of which stem from their nature as unitary transformations on a two-level quantum system. Understanding these properties is key to **predicting gate behavior**, **designing quantum circuits**, and **analyzing quantum algorithms**.

1. All Quantum Gates Are Equivalent to Rotations

A profound insight in quantum computing is that **every single-qubit unitary gate corresponds to a rotation of the qubit's state vector on the Bloch sphere**.

- **Bloch Sphere** is a geometric representation of a qubit's state, where any point on the sphere represents a valid pure state.
- A **unitary operation** on qubit results in **rotating the vector** on this sphere **without changing its length** (preserving probability).

Some examples of rotations:

- **X Gate** → Rotation π around x-axis (section 3.3.2.2, page 47)
- **Z Gate** → Rotation π around z-axis (section 3.3.2.3, page 52)
- **Y Gate** → Rotation π around y-axis (section 3.3.2.4, page 56)
- **S Gate** → Rotation $\frac{\pi}{2}$ around z-axis (section 3.3.3, page 59)
- **H Gate** → Rotation $\frac{\pi}{2}$ around y, then π around x (section 3.3.4, page 61)

🔗 Why is this important? Quantum computation is fundamentally about **state rotations**, understanding gates as rotations helps visualize **interference**, **phase shifts**, and **entanglement creation**.

2. Reversibility: Applying a Gate Twice

Many single-qubit gates, especially the Pauli gates, exhibit the property of **involution**: applying the same gate twice **returns the qubit to its original state**. Mathematically it can be expressed as:

$$X^2 = Y^2 = Z^2 = I$$

This is due to the fact that **two 180° rotations around the same axis bring the vector back** to its original position on the Bloch sphere.

Proof that X Gate has involution.

$$X^2 = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} = \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix} = I$$

These identities confirm that **Pauli gates are their own inverses**, and **all unitary gates are reversible**. QED

3. Global Phases Do Not Matter

Quantum gates may **introduce a global phase** (a constant complex factor $e^{i\phi}$) to a state. Physically, **global phases are unobservable**, meaning they do **not affect measurement probabilities**. For example:

- States $|\psi\rangle$ and $e^{i\phi}|\psi\rangle$ are physically indistinguishable.
- The Y gate = iXZ , where i is a global phase that can be ignored in practice.

4. Composite Gates and Commutativity

- Gates can be **combined by matrix multiplication** (note: non commutative in general).
- **Order matters:** $AB \neq BA$ for most gates.
- Exception: **Gate Z and Gate S** are **commuted** because they are both **diagonal phase gates**.

Property	Pauli Gates (X, Y, Z)	Phase Gate (S)	Hadamard (H)
Rotation Axis	x, y, z (π radians)	z ($\frac{\pi}{2}$ radians)	y ($\frac{\pi}{2}$) + x (π)
Involution $G^2 = I$	✓	✗ ($S^2 = Z$)	✓
Self-adjoint $G = G^\dagger$	✓	✗	✓
Unitary	✓	✓	✓
Phase Introduction	Z, S	i for $ 1\rangle$	✓ (interference)
Creates Superposition?	✗ (X, Y, Z alone)	✗	✓

Table 2: Summary of Properties.

3.5 When Does a Gate Create Superposition?

In this section, we will answer the question: *when does a quantum gate create superposition?* More precisely, if we start from a **basis state** $|0\rangle$ or $|1\rangle$, when does a gate produce:

$$a|0\rangle + b|1\rangle \quad \text{with} \quad a, b \neq 0?$$

? What does “*create superposition*” really mean? It means that the output must contain **both basis states**. So:

- $\begin{pmatrix} 1 \\ 0 \end{pmatrix}$ is not a superposition, it’s just $|0\rangle$.
- $\begin{pmatrix} 0 \\ 1 \end{pmatrix}$ is not a superposition, it’s just $|1\rangle$.
- $\begin{pmatrix} a \\ b \end{pmatrix}$ with $a, b \neq 0$ is a superposition, because it contains both $|0\rangle$ and $|1\rangle$ components. Indeed, we can write it as:

$$a|0\rangle + b|1\rangle = a \begin{pmatrix} 1 \\ 0 \end{pmatrix} + b \begin{pmatrix} 0 \\ 1 \end{pmatrix} = \begin{pmatrix} a \\ b \end{pmatrix}$$

? How does a matrix act on a basis state?

The main idea is that **each column of the matrix tells us where a basis vector goes**. For example, for a matrix:

$$A = \begin{pmatrix} a_{11} & a_{12} \\ a_{21} & a_{22} \end{pmatrix}$$

The first column $\begin{pmatrix} a_{11} \\ a_{21} \end{pmatrix}$ tells us where $|0\rangle$ goes, and the second column $\begin{pmatrix} a_{12} \\ a_{22} \end{pmatrix}$ tells us where $|1\rangle$ goes. In general, a **gate creates superposition if one of its columns has two non-zero entries**.

⚠ Constraint: Unitarity

Not every matrix can be a valid quantum gate. Quantum gates must be **unitary**, meaning:

$$A^\dagger A = I$$

This imposes strong constraints on the matrix entries. In particular, the columns must be:

- **Normalized**, total probability is 1: $\|\psi\|^2 = |a|^2 + |b|^2 = 1$
- **Orthogonal**, inner product is zero: $\langle v|w\rangle = 0$

As a consequence, some matrices that appear to create superposition are **not physically allowed**, because they are not unitary.

💡 Key Insight

Superposition arises from the **mixing of basis states**. Therefore:

- A gate **creates superposition** if at least one of its columns contains **two non-zero entries**.
- A gate **cannot create superposition** if its columns contain only one non-zero entry (as in diagonal or triangular matrices).

In particular:

- Gates like H (Hadamard) create superposition because they mix $|0\rangle$ and $|1\rangle$.
- Gates like X , Y , Z or S do not create superposition because they only modify phases and do not mix basis states.

Proof that A cannot create superposition. Consider the gate:

$$A = \begin{pmatrix} a_{11} & a_{12} \\ 0 & a_{22} \end{pmatrix}$$

To create superposition from a basis state, at least one column of A must contain two non-zero entries.

Applying A to $|0\rangle$ gives:

$$A|0\rangle = \begin{pmatrix} a_{11} & a_{12} \\ 0 & a_{22} \end{pmatrix} \cdot \begin{pmatrix} 1 \\ 0 \end{pmatrix} = \begin{pmatrix} a_{11} \cdot 1 + a_{12} \cdot 0 \\ 0 \cdot 1 + a_{22} \cdot 0 \end{pmatrix} = \begin{pmatrix} a_{11} \\ 0 \end{pmatrix} = a_{11} |0\rangle$$

Therefore, $|0\rangle$ is not mapped to a superposition because the second entry is zero.

Applying A to $|1\rangle$ gives:

$$A|1\rangle = \begin{pmatrix} a_{11} & a_{12} \\ 0 & a_{22} \end{pmatrix} \cdot \begin{pmatrix} 0 \\ 1 \end{pmatrix} = \begin{pmatrix} a_{11} \cdot 0 + a_{12} \cdot 1 \\ 0 \cdot 0 + a_{22} \cdot 1 \end{pmatrix} = \begin{pmatrix} a_{12} \\ a_{22} \end{pmatrix} = a_{12} |0\rangle + a_{22} |1\rangle$$

This would be a superposition only if both $a_{12} \neq 0$ and $a_{22} \neq 0$.

However, since A is a quantum gate, it must be unitary (property of quantum gates):

$$A^\dagger A = I$$

Assuming A is real, we have $A^\dagger = A^T$, so:

$$A^T = \begin{pmatrix} a_{11} & 0 \\ a_{12} & a_{22} \end{pmatrix}$$

Hence:

$$A^T A = \begin{pmatrix} a_{11} & 0 \\ a_{12} & a_{22} \end{pmatrix} \cdot \begin{pmatrix} a_{11} & a_{12} \\ 0 & a_{22} \end{pmatrix} = \begin{pmatrix} a_{11}^2 & a_{11}a_{12} \\ a_{11}a_{12} & a_{12}^2 + a_{22}^2 \end{pmatrix}$$

Since A is unitary (i.e., $A^\dagger A = I$), this matrix must equal the identity:

$$\begin{pmatrix} a_{11}^2 & a_{11}a_{12} \\ a_{11}a_{12} & a_{12}^2 + a_{22}^2 \end{pmatrix} = \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix}$$

Therefore, to satisfy this equality, the following equations must hold:

$$\begin{cases} a_{11}^2 = 1 \\ a_{11}a_{12} = 0 \\ a_{12}^2 + a_{22}^2 = 1 \end{cases}$$

From $a_{11}^2 = 1$, we get $a_{11} = \pm 1$, so $a_{11} \neq 0$. Therefore, from $a_{11}a_{12} = 0$, it follows that:

$$a_{12} = 0$$

Substituting this into the last equation gives:

$$a_{22}^2 = 1 \quad \Rightarrow \quad a_{22} = \pm 1$$

Hence the matrix becomes diagonal:

$$A = \begin{pmatrix} \pm 1 & 0 \\ 0 & \pm 1 \end{pmatrix}$$

Since A is diagonal, it only modifies the phases of $|0\rangle$ and $|1\rangle$, without mixing them. Thus, when we apply A to $|0\rangle$ and $|1\rangle$, we get:

$$A|0\rangle = \pm|0\rangle, \quad A|1\rangle = \pm|1\rangle$$

So neither $|0\rangle$ nor $|1\rangle$ is mapped to a superposition, because the output states are just $|0\rangle$ or $|1\rangle$ (up to a global phase). Thus, A cannot create superposition (i.e., it cannot produce a state with both $|0\rangle$ and $|1\rangle$ components). QED

3.6 Single-Qubit Quantum Circuits

A **Quantum Circuit** is a **mathematical model** for quantum computation, **composed of sequential operations applied to qubits**. In other words, a quantum circuit is a **model of computation** that describes **how a quantum state evolves step by step**. The operations in a quantum circuit include initializations, unitary gates, and measurements. In this section, we focus on **circuits involving a single qubit**, which form the foundation for understanding multi-qubit systems.

≡ Circuit Elements

A quantum circuit typically consists of three main elements:


1. **Initialization** (initial state)
 - Qubit is prepared in a **known state**, typically $|0\rangle$ or $|1\rangle$.
 - Essential **starting point** for any computation.
2. **Gates**
 - Single-qubit **unitary operations** (e.g., X, Z, H, S).
 - Transform the qubit's state **reversibly**.
3. **Measurement**
 - **Irreversible process**.
 - Collapses the qubit to $|0\rangle$ or $|1\rangle$ with probabilities dictated by the quantum state's amplitudes.

✂ Quantum Circuit Diagram: Visual Language


- **Horizontal lines** represent the **timeline of a single qubit**.

$$|v_{\text{in}}\rangle \text{ ————— } |v_{\text{out}}\rangle$$

- **Boxes** on the line represent **gates** (letters) or **measurements** (tachometer icon).



- **Double lines** (if present) represent **classical information** (e.g., measurement result).



- ⚠ Left to right:** The circuit evolves over time from left (input) to right (output).

Gate Sequence: Serial Gates

Consider two gates A and B applied in sequence:

$$|v_{\text{in}}\rangle \longrightarrow \boxed{A} \longrightarrow \boxed{B} \longrightarrow |v_{\text{out}}\rangle$$

1. First apply A, then B.
2. **⚠ Attention:** the **order of matrix multiplication is reversed** when we write the combined effect of the gates as a single matrix. The gate that is applied **last** (B) appears **first** in the product.

$$v_{\text{out}} = BAv_{\text{in}}$$

❓ Why? Because first apply A to the input state v_{in} , then apply B to the result of Av_{in} .

3. The **combined effect** of the two gates is equivalent to a single gate $C = BA$:

$$|v_{\text{in}}\rangle \longrightarrow \boxed{BA} \longrightarrow |v_{\text{out}}\rangle \quad \equiv \quad |v_{\text{in}}\rangle \longrightarrow \boxed{A} \longrightarrow \boxed{B} \longrightarrow |v_{\text{out}}\rangle$$

$$v_{\text{out}} = Cv_{\text{in}} = BAv_{\text{in}}$$

Obviously, if we merge the gates into a single gate C , we must respect the order of operations, which is why $C = BA$ and not AB .

Example 4: Hadamard followed by Hadamard

Let's compute H followed by H to $|0\rangle$:

$$|0\rangle \longrightarrow \boxed{H} \longrightarrow \boxed{H} \longrightarrow |v_{\text{out}}\rangle$$

1. Apply H:

$$\begin{aligned} H|0\rangle &= \frac{1}{\sqrt{2}} \cdot \begin{pmatrix} 1 & 1 \\ 1 & -1 \end{pmatrix} \cdot \begin{pmatrix} 1 \\ 0 \end{pmatrix} \\ &= \frac{1}{\sqrt{2}} \cdot \begin{pmatrix} 1 \\ 1 \end{pmatrix} \\ &= \frac{1}{\sqrt{2}} \cdot \left(\begin{pmatrix} 1 \\ 0 \end{pmatrix} + \begin{pmatrix} 0 \\ 1 \end{pmatrix} \right) \\ &= \frac{1}{\sqrt{2}} (|0\rangle + |1\rangle) = |+\rangle \end{aligned}$$

2. Applying H again, we **restore the original state due to the involution properties** ($H^2 = I$):

$$H(H|0\rangle) = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 & 1 \\ 1 & -1 \end{pmatrix} \cdot \frac{1}{\sqrt{2}} \begin{pmatrix} 1 \\ 1 \end{pmatrix} = \frac{1}{2} \begin{pmatrix} 2 \\ 0 \end{pmatrix} = \begin{pmatrix} 1 \\ 0 \end{pmatrix} = |0\rangle$$

3.7 Outer Product of Kets

In quantum mechanics, **Bra-Ket notation** (introduced by Dirac) is a concise and powerful tool for representing quantum states and operations. It uses **kets** $|\psi\rangle$ for **vectors** (states), and **bras** $\langle\psi|$ for their **Hermitian adjoints** (dual vectors).

Given two kets:

$$|a\rangle = \begin{pmatrix} a_1 \\ a_2 \end{pmatrix} \quad |b\rangle = \begin{pmatrix} b_1 \\ b_2 \end{pmatrix}$$

The **Outer Product** $|a\rangle\langle b|$ is a **matrix**, formed by:

$$|a\rangle\langle b| = |a\rangle \otimes \langle b| = \begin{pmatrix} a_1 \\ a_2 \end{pmatrix} (\overline{b_1} \quad \overline{b_2}) = \begin{pmatrix} a_1\overline{b_1} & a_1\overline{b_2} \\ a_2\overline{b_1} & a_2\overline{b_2} \end{pmatrix} \quad (24)$$

Where the symbol $\otimes$ is the **tensor product operator**. This operation **maps a vector to a matrix**.

❓ Why is the outer product useful? Because **all quantum gates can be written using outer products of kets**. For example, the **Pauli-X gate** can be expressed as:

$$X = |0\rangle\langle 1| + |1\rangle\langle 0| = \underbrace{\begin{pmatrix} 1 \\ 0 \end{pmatrix} \begin{pmatrix} 0 & 1 \end{pmatrix}}_{\begin{pmatrix} 0 & 1 \\ 0 & 0 \end{pmatrix}} + \underbrace{\begin{pmatrix} 0 \\ 1 \end{pmatrix} \begin{pmatrix} 1 & 0 \end{pmatrix}}_{\begin{pmatrix} 0 & 0 \\ 1 & 0 \end{pmatrix}} = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix}$$

The **Inner Product** $\langle b|a\rangle$ is a scalar:

$$\langle b|a\rangle = \overline{b_1}a_1 + \overline{b_2}a_2 \quad (25)$$

So:

- **Inner product** $\rightarrow$ **projection**, result is number (scalar).
- **Outer product** $\rightarrow$ **matrix**, result is operator.

📌 Associativity between outer and inner products

A key property of the outer product is how it interacts with inner products. Specifically:

$$(|a\rangle\langle b|)|c\rangle = |a\rangle(\langle b|c\rangle) \quad (26)$$

This identity shows that the outer product acts as an operator: it first computes the inner product $\langle b|c\rangle$ (a scalar), and then scales the vector $|a\rangle$.

Proof the Associativity. In this proof, we will demonstrate that applying the outer product $|a\rangle\langle b|$ to a ket $|c\rangle$ is equivalent to scaling $|a\rangle$ by the inner product $\langle b|c\rangle$.

Let's define:

$$|a\rangle = \begin{pmatrix} a_1 \\ a_2 \end{pmatrix} \quad |b\rangle = \begin{pmatrix} b_1 \\ b_2 \end{pmatrix} \quad |c\rangle = \begin{pmatrix} c_1 \\ c_2 \end{pmatrix}$$

1. Compute **inner product** $\langle b|c\rangle$:

$$\langle b|c\rangle = \overline{b_1}c_1 + \overline{b_2}c_2 = \alpha$$

Where α is a **scalar** value.

2. Multiply **scalar** α with $|a\rangle$ (vector):

$$|a\rangle \alpha = \begin{pmatrix} a_1 \\ a_2 \end{pmatrix} \alpha = \begin{pmatrix} a_1 \cdot \alpha \\ a_2 \cdot \alpha \end{pmatrix} = \begin{pmatrix} a_1 \cdot (\overline{b_1}c_1 + \overline{b_2}c_2) \\ a_2 \cdot (\overline{b_1}c_1 + \overline{b_2}c_2) \end{pmatrix}$$

3. Compute outer product $|a\rangle\langle b|$ (matrix):

$$|a\rangle\langle b| = \begin{pmatrix} a_1 \\ a_2 \end{pmatrix} \begin{pmatrix} \overline{b_1} & \overline{b_2} \end{pmatrix} = \begin{pmatrix} a_1\overline{b_1} & a_1\overline{b_2} \\ a_2\overline{b_1} & a_2\overline{b_2} \end{pmatrix}$$

4. Multiply $|a\rangle\langle b|$ by $|c\rangle$:

$$(|a\rangle\langle b|)|c\rangle = \begin{pmatrix} a_1\overline{b_1} & a_1\overline{b_2} \\ a_2\overline{b_1} & a_2\overline{b_2} \end{pmatrix} \begin{pmatrix} c_1 \\ c_2 \end{pmatrix} = \begin{pmatrix} a_1 \cdot (\overline{b_1}c_1 + \overline{b_2}c_2) \\ a_2 \cdot (\overline{b_1}c_1 + \overline{b_2}c_2) \end{pmatrix}$$

The second and fourth steps yield the same result. This proves that **outer product applied to a ket is equivalent to inner product $\langle b|c\rangle$ scaled by $|a\rangle$** . QED

3.8 Measurement

In quantum computing, **measurement** is a special type of operation that differs fundamentally from unitary gates. While gates perform reversible transformations, **measurement is irreversible**. It allows us to **gain information about the state of a qubit**, but at the price of **collapsing the quantum state**.

√* Measurement Operator: Matrix Form

A **measurement operator** is a **non-unitary, non-invertible** matrix. For a measurement **along a specific direction**, represented by a ket $|k\rangle$, the associated **projector** is (outer product):

$$M_k = |k\rangle\langle k| = \begin{pmatrix} k_1 \\ k_2 \end{pmatrix} \begin{pmatrix} \overline{k_1} & \overline{k_2} \end{pmatrix} = \begin{pmatrix} k_1\overline{k_1} & k_1\overline{k_2} \\ k_2\overline{k_1} & k_2\overline{k_2} \end{pmatrix} \quad (27)$$

This is called a **Projection Operator**, it projects any vector **onto the direction of** $|k\rangle$.

Definition 1: Projection Operator

A **Projection Operator** (or simply **Projector**) is a linear operator that **extracts the component of a quantum state along a specific direction** (or subspace).

For a normalized state $|k\rangle$, the projector onto $|k\rangle$ is defined as:

$$P_k = |k\rangle\langle k| \quad (28)$$

When applied to an arbitrary state

$$|v\rangle = \sum_j c_j |j\rangle,$$

The projector returns only the component of $|v\rangle$ parallel to $|k\rangle$:

$$P_k |v\rangle = (|k\rangle\langle k|) |v\rangle = \langle k|v\rangle |k\rangle$$

For example, let's suppose the state:

$$|v\rangle = a |k\rangle + b |k_\perp\rangle$$

Where $|k\rangle$ is the direction we want to keep and $|k_\perp\rangle$ is the direction we want to discard that is orthogonal to $|k\rangle$ (i.e., $\langle k|k_\perp\rangle = 0$). The projector P_k will keep the component $a |k\rangle$ and remove the component $b |k_\perp\rangle$:

$$\begin{aligned} P_k |v\rangle &= |k\rangle\langle k| (a |k\rangle + b |k_\perp\rangle) \\ &= a |k\rangle\langle k|k\rangle + b |k\rangle\langle k|k_\perp\rangle \\ &\downarrow |k\rangle \text{ is normalized, then } \langle k|k\rangle = 1 \\ &\quad \text{and } |k_\perp\rangle \text{ is orthogonal to } |k\rangle, \text{ then } \langle k|k_\perp\rangle = 0 \\ &= a |k\rangle \underbrace{\langle k|k\rangle}_{=1} + b |k\rangle \underbrace{\langle k|k_\perp\rangle}_{=0} \\ &= a |k\rangle + b |k\rangle \cdot 0 \\ &= a |k\rangle \end{aligned}$$

Therefore, a **projector acts as a filter**: it keeps the part of the state aligned with $|k\rangle$ and removes all orthogonal components. For example, suppose:

$$|v\rangle = 0.8|0\rangle + 0.6|1\rangle$$

Project onto $|0\rangle$:

$$|0\rangle\langle 0|v\rangle = |0\rangle\langle 0|(0.8|0\rangle + 0.6|1\rangle) = 0.8|0\rangle$$

The $|1\rangle$ part disappears because it is orthogonal to $|0\rangle$, while the $|0\rangle$ part is preserved (but scaled by the coefficient 0.8).

Projection operators satisfy the **idempotence property**:

$$P_k^2 = P_k$$

Meaning that applying the same projector twice has the same effect as applying it once.

⚠ Effect of Measurement

Given a qubit $|\psi\rangle$, applying M_k yields the **(unnormalized) projected vector**:

$$|\psi_k\rangle = M_k|\psi\rangle = |k\rangle\langle k|\psi\rangle = (|k\rangle\langle k|)|\psi\rangle \quad (29)$$

To obtain the **new normalized state**, we **divide by the square root of the probability**:

$$|\psi_k^{\text{norm}}\rangle = \frac{M_k|\psi\rangle}{\sqrt{\langle\psi|M_k|\psi\rangle}} = \frac{\langle k|\psi\rangle \cdot |k\rangle}{\sqrt{|\langle k|\psi\rangle|^2}} = |k\rangle \quad (30)$$

So after measurement, the qubit **collapses** to $|k\rangle$, the **eigenstate corresponding to the measurement outcome**.

✓ Why Normalization is Needed

After applying the measurement operator $M_k = |k\rangle\langle k|$ (Equation 27) to a state $|\psi\rangle$ (Equation 29), we obtain:

$$|\psi_k\rangle = M_k|\psi\rangle = |k\rangle\langle k|\psi\rangle$$

This vector is generally **not normalized**. Its norm is:

$$\| |\psi_k\rangle \|^2 = \langle\psi|M_k|\psi\rangle = |\langle k|\psi\rangle|^2 = p_k$$

Where p_k is the **probability of obtaining outcome k** .

Deepening: Why $\| |\psi_k\rangle \|^2 = p_k$?

We want to show:

$$\| |\psi_k\rangle \|^2 = \langle\psi|M_k|\psi\rangle = |\langle k|\psi\rangle|^2 = p_k$$

1. **Definition of squared norm.** The squared norm of a ket is:

$$\| |\psi_k\rangle \|^2 = \langle \psi_k | \psi_k \rangle$$

Since $|\psi_k\rangle = M_k |\psi\rangle$, we can write:

$$\| |\psi_k\rangle \|^2 = \underbrace{(M_k |\psi\rangle)^\dagger}_{\langle \psi_k |} \underbrace{(M_k |\psi\rangle)}_{|\psi_k\rangle}$$

We have only expanded the definition of the squared norm and substituted $|\psi_k\rangle$.

2. **Take the dagger $\dagger$.** The dagger of a product of operators is the product of the daggers in reverse order:

$$(AB)^\dagger = B^\dagger A^\dagger$$

Applying this to $(M_k |\psi\rangle)^\dagger$:

$$(M_k |\psi\rangle)^\dagger = \langle \psi | M_k^\dagger$$

And substituting back into the expression for the squared norm:

$$\| |\psi_k\rangle \|^2 = \langle \psi | M_k^\dagger M_k | \psi \rangle$$

3. **Use the Hermitian property of M_k** (explained later page 80). Since M_k is Hermitian, we have $M_k^\dagger = M_k$. Therefore:

$$\| |\psi_k\rangle \|^2 = \langle \psi | M_k M_k | \psi \rangle$$

4. **Use the idempotent property of M_k** (explained later page 81). Since M_k is idempotent, we have $M_k^2 = M_k$. Therefore:

$$\| |\psi_k\rangle \|^2 = \langle \psi | M_k | \psi \rangle$$

5. **Substitute the definition of M_k .** Since $M_k = |k\rangle \langle k|$, we can write:

$$\| |\psi_k\rangle \|^2 = \langle \psi | (|k\rangle \langle k|) | \psi \rangle = \langle \psi | k \rangle \langle k | \psi \rangle$$

6. **Use the property of inner products.** The inner product $\langle \psi | k \rangle$ is the complex conjugate of $\langle k | \psi \rangle$:

$$\langle \psi | k \rangle = \overline{\langle k | \psi \rangle}$$

Therefore (page 7):

$$\| |\psi_k\rangle \|^2 = \overline{\langle k | \psi \rangle} \langle k | \psi \rangle = |\langle k | \psi \rangle|^2 = p_k$$

This is exactly the probability p_k of obtaining outcome k when measuring the state $|\psi\rangle$ with the measurement operator M_k .

⚠ Important. The result of a measurement must be a valid quantum state, and therefore it must be **normalized** (i.e., have unit norm).

To restore normalization, we divide the projected vector by its norm:

$$|\psi_k^{\text{norm}}\rangle = \frac{|\psi_k\rangle}{\| |\psi_k\rangle \|} = \frac{|k\rangle \langle k|\psi\rangle}{\sqrt{|\langle k|\psi\rangle|^2}}$$

Observe that:

$$\frac{\langle k|\psi\rangle}{|\langle k|\psi\rangle|}$$

Is a complex number of magnitude 1, i.e., a **global phase**. **Since global phases do not affect physical states**, we conclude:

$$|\psi_k^{\text{norm}}\rangle = |k\rangle$$

💡 Interpretation Measurement can be understood as a two-step process:

1. **Projection:** extract the component of $|\psi\rangle$ along $|k\rangle$ (this determines the probability p_k).
2. **Renormalization:** rescale the result to obtain a valid quantum state.

📊 Probability of Outcome

The **probability of measuring the qubit in the state $|k\rangle$** is:

$$p_k = \langle \psi | M_k | \psi \rangle = |\langle k | \psi \rangle|^2 = \underbrace{|\bar{k}_1 \cdot \psi_1 + \bar{k}_2 \cdot \psi_2|^2}_{|\langle k | \psi \rangle|^2 \text{ expanded}} \quad (31)$$

This is the **Born rule**, a fundamental postulate of quantum mechanics. It states that the probability of obtaining a specific measurement outcome is given by the **squared magnitude of the inner product between the state being measured and the eigenstate corresponding to that outcome**. In other words, it quantifies how much the state $|\psi\rangle$ (*the state being measured*) overlaps with the state $|k\rangle$ (*the eigenstate corresponding to the outcome*). The more $|\psi\rangle$ is aligned with $|k\rangle$, the higher the probability of measuring k . Conversely, if $|\psi\rangle$ is orthogonal to $|k\rangle$, the probability of measuring k is zero. For example:

$$\begin{aligned} p_0 &= \langle \psi | M_0 | \psi \rangle = |\langle 0 | \psi \rangle|^2 = |1 \cdot \psi_1 + \cancel{0 \cdot \psi_2}|^2 = |\psi_1|^2 \\ p_1 &= \langle \psi | M_1 | \psi \rangle = |\langle 1 | \psi \rangle|^2 = |\cancel{0 \cdot \psi_1} + 1 \cdot \psi_2|^2 = |\psi_2|^2 \end{aligned}$$

These probabilities measure the likelihood of obtaining the outcomes 0 and 1 when measuring the qubit $|\psi\rangle$ in the computational basis.

Remark: $\langle \psi | M_k | \psi \rangle$

This is called a quadratic form in linear algebra, and in quantum mechanics it represents the **probability of the measurement outcome** k when **measuring the qubit** $|\psi\rangle$ with **measurement operator** M_k . Suppose a qubit ψ :

$$|\psi\rangle = \begin{pmatrix} a \\ b \end{pmatrix} \quad \text{with } |a|^2 + |b|^2 = 1 \text{ (normalization condition)}$$

If we apply the measurement operator M_0 :

$$M_0 |\psi\rangle = \begin{pmatrix} 1 & 0 \\ 0 & 0 \end{pmatrix} \begin{pmatrix} a \\ b \end{pmatrix} = \begin{pmatrix} a \\ 0 \end{pmatrix}$$

And we finally calculate the bra $\langle \psi |$:

$$\langle \psi | \begin{pmatrix} a \\ 0 \end{pmatrix} = (\bar{a} \quad \bar{b}) \begin{pmatrix} a \\ 0 \end{pmatrix} = \bar{a} \cdot a = |a|^2$$

In other words, this is the probability of measuring 0: p_0 .

Standard Basis Measurement

In quantum computing, we usually measure in the **computational basis** $\{|0\rangle, |1\rangle\}$. The **projectors** are:

$$M_0 = |0\rangle \langle 0| = \begin{pmatrix} 1 & 0 \\ 0 & 0 \end{pmatrix} \quad M_1 = |1\rangle \langle 1| = \begin{pmatrix} 0 & 0 \\ 0 & 1 \end{pmatrix} \quad (32)$$

For a **general qubit** $|\psi\rangle = a|0\rangle + b|1\rangle$, the **probabilities** are:

$$p_0 = |a|^2 \quad p_1 = |b|^2 \quad (33)$$

After measurement, the qubit **collapses to** $|0\rangle$ **with probability** $|a|^2$, or to $|1\rangle$ **with probability** $|b|^2$.

Key Properties of Measurement Operator

- **Hermitian:** $M_k^\dagger = M_k$, which means that M_k is equal to its conjugate transpose. This implies that M_k has real eigenvalues and orthogonal eigenvectors.

$$\begin{aligned} M_k^\dagger &= (|k\rangle \langle k|)^\dagger \\ &\downarrow \text{ use the rule } (AB)^\dagger = B^\dagger A^\dagger \\ &= (\underbrace{|k\rangle}_A \underbrace{\langle k|}_B)^\dagger \\ &= (\langle k|)^\dagger (|k\rangle)^\dagger \\ &= |k\rangle \langle k| \\ &= M_k \end{aligned}$$

- **Idempotent**: once applied, **applying it again does nothing**:

$$M_k^2 = M_k$$

A simple proof:

$$M_k^2 = |k\rangle |k\rangle \langle k| \langle k| = |k\rangle \langle k| = M_k$$

This reflects that **after projection, the qubit is already in the state $|k\rangle$** .

- **Non-unitary** and **Non-reversible**: **measurement destroys superposition and cannot be undone.**

4 Multiple Qubit Gates

4.1 Multiple Qubit States

Now that we have a solid understanding of single qubits and their states, we can transition to discussing many qubits as one joint system, rather than just one vector with one qubit.

With **one qubit**, life is simple because the state of the system can be described by a single vector in a two-dimensional complex vector space:

$$|v\rangle = a|0\rangle + b|1\rangle$$

With **two qubits**, something radical happens. We can no longer describe the system by looking at each qubit separately. Instead, we must describe **one global state** that captures the behavior of both qubits together. For example:

$$|v\rangle = c_0|00\rangle + c_1|01\rangle + c_2|10\rangle + c_3|11\rangle$$

This is not just a simple combination of two single-qubit states.

⚠ Exponential Explosion. The first thing to notice is that the number of amplitudes needed to describe the state of a system grows exponentially with the number of qubits.

- For 1 qubit, we need 2 amplitudes: a and b .
- For 2 qubits, we need 4 amplitudes: c_0 , c_1 , c_2 , and c_3 .
- For 3 qubits, we need 8 amplitudes: d_0 , d_1 , d_2 , d_3 , d_4 , d_5 , d_6 , and d_7 .
- For n qubits, we need 2^n amplitudes to fully describe the state of the system.

This is why quantum computing is so powerful: it can **process many possibilities at the same time** and **manipulate them so that only the correct ones survive**. This will become clear when we introduce entanglement (page 91).

📖 The Key New Phenomenon: Entanglement

Entanglement is the key new phenomenon when dealing with multiple qubits. It refers to quantum states that cannot be expressed as a tensor product of individual qubit states. For example, the state:

$$\frac{1}{\sqrt{2}}(|00\rangle + |11\rangle)$$

Is an entangled state. In such cases, the system must be described globally, and it is not possible to assign independent quantum states to each qubit.

If one qubit is measured, the outcome is random, but it determines the outcome of the other qubit due to the structure of the global state. This leads to strong

correlations between measurements results. However, this does not imply any form of information transfer between the qubits.

Entanglement is a fundamental resource in quantum computing, enabling correlations that have no classical counterpart, especially when combined with interference effects in quantum algorithms.

- Entanglement does not mean that one qubit sends information to the other. The observed correlations arise from the collapse of a **global quantum state**, not from communication between subsystems.
- Before measurement, individual qubits in an entangled state do **not have a well-defined state**. Only the joint system is well-defined.
- Each qubit individually appears **random**, but measurement outcomes are **correlated**.
- Entanglement alone is not the source of quantum computational power; it becomes powerful when combined with **interference** and quantum operations.

⚙️ New tools we need

To handle this new world of multiple qubits, we need new mathematical tools. We will introduce the **tensor product**, which allows us to construct the joint state of multiple qubits; we will also introduce the **multi-qubit gates**, which are operations that can manipulate the joint state of multiple qubits simultaneously; and we will discuss how to **measure** multiple qubits and understand the resulting probabilities.

4.1.1 Tensor Product

Let's start with something simple. As in previous sections, we have a simple one-qubit state. Now, we want to **add a second qubit to the system** to create a multi-qubit state. For simplicity, we will use only two qubits. *How do we describe the **combined system**?* Simply keeping them separate is not enough because we would miss correlations between the two qubits. **We need a way to combine the two qubits into a single object.** The tool for doing so is the **tensor product**.

Example 1: Dice Analogy

Imagine we have two dice. Each die can be in one of six states (1, 2, 3, 4, 5, or 6). If we want to describe the combined state of both dice, we can't just list their individual states separately. Instead, we need to consider all possible combinations of their states. The tensor product allows us to create a new space that includes all these combinations, giving us a complete description of the system.

The **Tensor Product** is a **mathematical operation** that **takes two vectors** (or more generally, two mathematical objects):

$$|v_A\rangle = a_0|0\rangle + a_1|1\rangle \quad |v_B\rangle = b_0|0\rangle + b_1|1\rangle$$

And **produces a new vector** that represents the combined state of the two systems:

$$\begin{aligned} |v_A\rangle \otimes |v_B\rangle &= (a_0|0\rangle + a_1|1\rangle) \otimes (b_0|0\rangle + b_1|1\rangle) \\ &= a_0b_0|00\rangle + a_0b_1|01\rangle + a_1b_0|10\rangle + a_1b_1|11\rangle \end{aligned} \quad (34)$$

Here, the resulting state $|v_A\rangle \otimes |v_B\rangle$ is a **superposition of all possible combinations of the states of the two qubits**.

❓ Why amplitudes multiply? For example, why is the amplitude of $|00\rangle$ equal to a_0b_0 ? A qubit is a vector:

$$|v_A\rangle = \begin{pmatrix} a_0 \\ a_1 \end{pmatrix}, \quad |v_B\rangle = \begin{pmatrix} b_0 \\ b_1 \end{pmatrix}$$

The tensor product is **defined** as:

$$|v_A\rangle \otimes |v_B\rangle = \begin{pmatrix} a_0b_0 \\ a_0b_1 \\ a_1b_0 \\ a_1b_1 \end{pmatrix} \quad (35)$$

So amplitudes multiply because **that's how the tensor product is defined**. **But why is it defined like that?** Because we want a rule that satisfies two requirements:

1. **Linearity.** Quantum mechanics is linear:

$$(a_0|0\rangle + a_1|1\rangle) \otimes |v_B\rangle = a_0(|0\rangle \otimes |v_B\rangle) + a_1(|1\rangle \otimes |v_B\rangle)$$

The tensor product must be **bilinear**, i.e., linear in each argument, so that superpositions are preserved when combining quantum states.

2. Basis consistency:

$$|0\rangle \otimes |0\rangle = |00\rangle, \quad |0\rangle \otimes |1\rangle = |01\rangle, \quad |1\rangle \otimes |0\rangle = |10\rangle, \quad |1\rangle \otimes |1\rangle = |11\rangle$$

The tensor product must map basis states of individual systems to a consistent basis of the joint system (e.g., $|i\rangle \otimes |j\rangle = |ij\rangle$), preserving the structure of the state space.

This structure ensures that probabilities factorize correctly for independent systems.

⚠ Not all states can be factored

Given two qubits, their joint state lives in a 4-dimensional vector space. However, **not all states** in this 4-dimensional space can be written as a tensor product of two single-qubit states. Precisely, if a multi-qubit state can be written as a **tensor product**, then it is **separable**, and we can recover the individual qubit states. But if it is **not a tensor product**, then it is **entangled**, and we cannot assign well-defined quantum states to each qubit individually.

In general, exists a **necessary (and sufficient) condition** for being a tensor product for two qubits. Given a 2-qubit state:

$$|\psi\rangle = (c_0, c_1, c_2, c_3)$$

Where c_0, c_1, c_2, c_3 are the amplitudes of the basis states $|00\rangle, |01\rangle, |10\rangle, |11\rangle$, respectively. The state $|\psi\rangle$ can be written as a tensor product of two single-qubit states if and only if:

$$c_0 c_3 = c_1 c_2 \tag{36}$$

Equivalently, if we reshape the coefficients into a matrix

$$C = \begin{pmatrix} c_0 & c_1 \\ c_2 & c_3 \end{pmatrix}$$

The state is separable if and only if $\det(C) = 0$. More generally, for n -qubit states, there is **no single simple scalar condition** that characterizes separability. A state is separable **if and only if it can be written as a tensor product of n single-qubit states**, which is a more complex condition to verify. So, the **2-qubit case is simpler to analyze**, but for larger systems, determining whether a state is separable or entangled can be more challenging.

Let's make this more concrete with two examples:

✓ Let's start from a 4D vector:

$$|\psi\rangle = \begin{pmatrix} \frac{1}{2} \\ \frac{1}{2} \\ \frac{1}{2} \\ \frac{1}{2} \end{pmatrix} = \frac{1}{2} (|00\rangle + |01\rangle + |10\rangle + |11\rangle)$$

We can check if it is a tensor product by verifying the condition in Equation 36:

$$c_0 c_3 = \frac{1}{2} \cdot \frac{1}{2} = \frac{1}{4}, \quad c_1 c_2 = \frac{1}{2} \cdot \frac{1}{2} = \frac{1}{4}$$

Since $c_0 c_3 = c_1 c_2$, the state is a tensor product and thus separable.

Now, we can find the two single-qubit states whose tensor product gives us $|\psi\rangle$. We try:

$$|v_A\rangle = \begin{pmatrix} a_0 \\ a_1 \end{pmatrix}, \quad |v_B\rangle = \begin{pmatrix} b_0 \\ b_1 \end{pmatrix}$$

We want:

$$(a_0 b_0, a_0 b_1, a_1 b_0, a_1 b_1) = \left(\frac{1}{2}, \frac{1}{2}, \frac{1}{2}, \frac{1}{2} \right) \Rightarrow \begin{cases} a_0 b_0 = \frac{1}{2} \\ a_0 b_1 = \frac{1}{2} \\ a_1 b_0 = \frac{1}{2} \\ a_1 b_1 = \frac{1}{2} \end{cases}$$

Solving this system of equations, we find:

$$a_0 = b_0 = \frac{1}{\sqrt{2}}, \quad a_1 = b_1 = \frac{1}{\sqrt{2}}$$

And this works because:

$$\begin{cases} a_0 b_0 = \frac{1}{\sqrt{2}} \cdot \frac{1}{\sqrt{2}} = \frac{1}{2} \\ a_0 b_1 = \frac{1}{\sqrt{2}} \cdot \frac{1}{\sqrt{2}} = \frac{1}{2} \\ a_1 b_0 = \frac{1}{\sqrt{2}} \cdot \frac{1}{\sqrt{2}} = \frac{1}{2} \\ a_1 b_1 = \frac{1}{\sqrt{2}} \cdot \frac{1}{\sqrt{2}} = \frac{1}{2} \end{cases}$$

Therefore:

$$|\psi\rangle = \left[\frac{1}{\sqrt{2}} (|0\rangle + |1\rangle) \right] \otimes \left[\frac{1}{\sqrt{2}} (|0\rangle + |1\rangle) \right]$$

The global 2-qubit state can be written as **two independent qubit states**, confirming that it is separable.

$$|\psi\rangle = \begin{pmatrix} \frac{1}{2} \\ \frac{1}{2} \\ \frac{1}{2} \\ \frac{1}{2} \end{pmatrix} = \left[\frac{1}{\sqrt{2}} (|0\rangle + |1\rangle) \right] \otimes \left[\frac{1}{\sqrt{2}} (|0\rangle + |1\rangle) \right]$$

✗ Let's start from a different 4D vector:

$$|\psi\rangle = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 \\ 0 \\ 0 \\ 1 \end{pmatrix} = \frac{1}{\sqrt{2}} (|00\rangle + |11\rangle)$$

We check the condition for separability:

$$c_0 c_3 = \frac{1}{2}, \quad c_1 c_2 = 0$$

Since $c_0c_3 \neq c_1c_2$, the state is not a tensor product and thus is **not separable**. This state is an example of an **entangled state** (**Entanglement** phenomenon), where the two qubits are correlated in such a way that we cannot describe them independently. We will see more about entanglement in the next section, but for now, the key takeaway is that not all multi-qubit states can be factored into tensor products of single-qubit states, and this is a fundamental aspect of quantum mechanics that leads to phenomena like entanglement.

In summary, the tensor product generates only a subset of the full 4-dimensional space of two-qubit states. Separable states have a special multiplicative structure and lie on a lower-dimensional manifold within this space. Most states in the full space do not satisfy this structure and are therefore entangled.

4.1.2 Building a Two-Qubit System

In the previous sections, we have seen how to represent the state of a single qubit using a two-dimensional complex vector. Now, we want to extend this representation to a system of two qubits. To do this, we will use the concept of the tensor product seen in the previous section.

We start from two independent qubits:

$$|v_A\rangle = a_0 |0\rangle + a_1 |1\rangle \quad \text{and} \quad |v_B\rangle = b_0 |0\rangle + b_1 |1\rangle$$

And our **goal is to find a state that encodes all joint possibilities** of the two qubits:

- Both qubits are in state $|0\rangle$: $|00\rangle$
- The first qubit is in state $|0\rangle$ and the second in state $|1\rangle$: $|01\rangle$
- The first qubit is in state $|1\rangle$ and the second in state $|0\rangle$: $|10\rangle$
- Both qubits are in state $|1\rangle$: $|11\rangle$

To represent these joint possibilities, we will use the tensor product of the two qubits' states:

$$|v_A v_B\rangle = |v_A\rangle \otimes |v_B\rangle$$

Expanding this expression, we get:

$$\begin{aligned} |v_A v_B\rangle &= (a_0 |0\rangle + a_1 |1\rangle) \otimes (b_0 |0\rangle + b_1 |1\rangle) \\ &= a_0 b_0 |00\rangle + a_0 b_1 |01\rangle + a_1 b_0 |10\rangle + a_1 b_1 |11\rangle \end{aligned} \quad (37)$$

This state $|v_A v_B\rangle$ is a linear combination of the four possible joint states of the two qubits. Each term in the expansion corresponds to one of the joint possibilities, and the coefficients $a_0 b_0$, $a_0 b_1$, $a_1 b_0$, and $a_1 b_1$ represent the probability amplitudes of each joint state.

We are no longer describing two systems separately, we are describing **one system with 4 possible outcomes**.

General Two-Qubit State

In Equation 37 we built a two-qubit state starting from a **very specific structure**, where the coefficients of the state were products of the coefficients of the individual qubits (i.e., $a_i b_j$). However, we can also consider a more **general two-qubit state**, where the coefficients are not necessarily products of the individual qubits' coefficients:

$$|v\rangle = c_0 |00\rangle + c_1 |01\rangle + c_2 |10\rangle + c_3 |11\rangle \quad (38)$$

Where c_0 , c_1 , c_2 , and c_3 are **arbitrary complex numbers** that represent the probability amplitudes of each joint state.

Obviously, this general two-qubit state **must satisfy the normalization condition**:

$$|c_0|^2 + |c_1|^2 + |c_2|^2 + |c_3|^2 = 1 \quad (39)$$

This means that the sum of the probabilities of all joint states must equal 1, ensuring that the state is properly normalized.

We can also generalize deeper to n qubits, where the state of the **system is a linear combination** of 2^n **basis states**, and the **coefficients** are arbitrary **complex numbers** that satisfy the normalization condition. Mathematically, we can express this as:

$$|v\rangle = \sum_{k=0}^{2^n-1} c_k |k\rangle \quad (40)$$

Where $|k\rangle$ represents the basis states of the n -qubit system, and c_k are the corresponding probability amplitudes. As we have already discussed at page 82, this general form **illustrates the exponential growth of the state space as the number of qubits increases**. However, we can write our one- and two-qubit states as special cases from this general form:

- For $n = 1$ qubit, we have $2^1 = 2$ basis states: $|0\rangle$ and $|1\rangle$, and the state can be written as:

$$|v\rangle = c_0 |0\rangle + c_1 |1\rangle$$

- For $n = 2$ qubits, we have $2^2 = 4$ basis states: $|00\rangle$, $|01\rangle$, $|10\rangle$, and $|11\rangle$, and the state can be written as:

$$|v\rangle = c_0 |00\rangle + c_1 |01\rangle + c_2 |10\rangle + c_3 |11\rangle$$

In summary, a general two-qubit state is a normalized superposition (i.e., the *coefficients satisfy the normalization condition*) of the four basis states (i.e., $|00\rangle$, $|01\rangle$, $|10\rangle$, and $|11\rangle$). Unlike tensor product states, its coefficients are arbitrary and *may not* factorize, leading to entanglement and non-classical correlations between the qubits (like the state in Example at page 86).

4.1.3 Separable vs Entangled States

Let the general state of a two-qubit system be (as defined in Equation 38, page 88):

$$|v\rangle = c_0 |00\rangle + c_1 |01\rangle + c_2 |10\rangle + c_3 |11\rangle$$

The question is: *can we interpret this as two independent qubits?* The answer is **not always**. As we saw on page 84, the answer depends on whether the states are separable or entangled.

☐ Separable States

A state is **separable** if it can be written as a tensor product of two **single-qubit states**. In other words, there exist single-qubit states $|v_A\rangle$ and $|v_B\rangle$ such that:

$$|v\rangle = |v_A\rangle \otimes |v_B\rangle$$

So the system can be split into one state for qubit A and one state for qubit B , and the global state is just the combination of these two states. As consequence, the coefficients factorize as:

$$c_0 = a_0 b_0, \quad c_1 = a_0 b_1, \quad c_2 = a_1 b_0, \quad c_3 = a_1 b_1$$

☐ Entangled States

A state is **entangled** if it cannot be written as a tensor product of two **single-qubit states**. In other words, there do not exist single-qubit states $|v_A\rangle$ and $|v_B\rangle$ such that:

$$|v\rangle \neq |v_A\rangle \otimes |v_B\rangle$$

In this case, the state cannot be separated into two independent qubits, and the coefficients do not factorize as above. *The system is simply one single entity.* For example, the Bell state (we will see in future sections) is an entangled state:

$$|\Phi^+\rangle = \frac{1}{\sqrt{2}} (|00\rangle + |11\rangle)$$

And the demonstration was written on page 86. In other words, we can only say that the system is in state $|\Phi^+\rangle$, but we cannot say that qubit A is in some state and qubit B is in some state, because the state of the system does not factorize into two independent states.

At this stage, entanglement is introduced as a structural property of quantum states. Its physical meaning and implications become clear only when studying measurement and quantum circuits in later sections.

⚡ Difference. With **separable** states, the *information is stored in the individual qubits*. In contrast, with **entangled** states, the *information is stored in the correlations between the qubits*.

4.1.4 Why Entanglement Matters

Let's answer to the question "*why entanglement matters*" step by step. First of all, the **complexity of quantum states grows exponentially** with the number of qubits, as we have introduced at page 82. As consequence, to describe the system, we need 2^n complex numbers, where n is the number of qubits. This means that for a system of 50 qubits, we would need 2^{50} complex numbers to describe its state, which is an astronomically large number (approximately 1.13×10^{15}). It could be a **problem for classical computers**, but **quantum computers can handle this complexity naturally**.

The reason why quantum computers can handle this complexity naturally is not that they explicitly store all these amplitudes as a classical computer would. Rather, the quantum system itself physically evolves in this exponentially large state space.

Entanglement matters because **most quantum states cannot be decomposed into independent single-qubit states**. In fact, the set of separable states, i.e., states that can be written as a tensor product of individual qubit states, is **very small compared to the set of all possible states**. For two qubits, separable states must satisfy:

$$c_0 c_3 = c_1 c_2$$

Which is a strong structural constraint. Therefore, **most two-qubit states do not satisfy this condition and are entangled**.

❓ But why does this matter? Because **entanglement prevents the system from being compressed into simpler independent components**. The **state must be described globally**. This global structure is difficult to simulate classically, but **quantum mechanics allows us to manipulate it directly through quantum operations**. This is one of the reasons why quantum computers can solve certain problems more efficiently than classical computers.

In summary, entanglement is a fundamental feature of quantum mechanics that prevents a multi-qubit system from being decomposed into independent subsystems. As the number of qubits increases, the state space grows exponentially, and entanglement forces a global description of the system. This global structure can be exploited by quantum algorithms to achieve computational advantages over classical approaches.

4.1.5 Exercise: Normalization of Tensor Product States

Given two qubits in the states $|v_A\rangle$ and $|v_B\rangle$ respectively:

$$|v_A\rangle = a_0 |0\rangle + a_1 |1\rangle, \quad |v_B\rangle = b_0 |0\rangle + b_1 |1\rangle$$

And the combined state of the two qubits is given by the tensor product:

$$|v_A v_B\rangle = |v_A\rangle \otimes |v_B\rangle = a_0 b_0 |00\rangle + a_0 b_1 |01\rangle + a_1 b_0 |10\rangle + a_1 b_1 |11\rangle$$

Show that:

$$|a_0 b_0|^2 + |a_0 b_1|^2 + |a_1 b_0|^2 + |a_1 b_1|^2 = 1$$

Proof. To show that the sum of the squares of the coefficients equals 1, we start expanding the expression:

$$|a_0 b_0|^2 + |a_0 b_1|^2 + |a_1 b_0|^2 + |a_1 b_1|^2$$

Using the property:

$$|xy|^2 = |x|^2 |y|^2$$

Applying this property to each term, we get:

$$\begin{aligned} &= |a_0|^2 |b_0|^2 + |a_0|^2 |b_1|^2 + |a_1|^2 |b_0|^2 + |a_1|^2 |b_1|^2 \\ &= |a_0|^2 (|b_0|^2 + |b_1|^2) + |a_1|^2 (|b_0|^2 + |b_1|^2) \end{aligned}$$

Since $|v_B\rangle$ is a valid quantum state and must be normalized, we have:

$$|b_0|^2 + |b_1|^2 = 1$$

Substituting this back into our expression, we get:

$$\begin{aligned} &= |a_0|^2 \cdot 1 + |a_1|^2 \cdot 1 \\ &= |a_0|^2 + |a_1|^2 \end{aligned}$$

Since $|v_A\rangle$ is also a valid quantum state and must be normalized, we have:

$$|a_0|^2 + |a_1|^2 = 1$$

Therefore, we conclude that:

$$|a_0 b_0|^2 + |a_0 b_1|^2 + |a_1 b_0|^2 + |a_1 b_1|^2 = 1$$

The combined state $|v_A v_B\rangle$ is also a valid quantum state and must be normalized, which is consistent with our result. QED

This exercise demonstrates that the **tensor product of two normalized quantum states is also normalized**, because the squared amplitudes factorize and the normalization conditions of the individual states ensure that the total probability remains 1.

4.2 Introduction to Multiple Qubit Gates

Until now, we learned that a quantum state is a vector in a complex vector space, and for 2 qubits, the state is a vector in $\mathbb{C}^4$:

$$|v\rangle = c_0 |00\rangle + c_1 |01\rangle + c_2 |10\rangle + c_3 |11\rangle$$

Now the question is: *how do we change this state?*

 **The key idea.** A **quantum gate** is just a rule that transforms one state into another. For 1 qubit we already know (page 38):

$$|v'\rangle = U |v\rangle$$

Where U is a 2×2 unitary matrix. For example, the Hadamard gate H (page 61) transforms the state $|0\rangle$ into $|+\rangle$:

$$H |0\rangle = |+\rangle$$

 **What about 2 qubits?** For 2 qubits, we need a 4×4 unitary matrix to transform the state:

$$|v'\rangle = U |v\rangle \quad \text{with} \quad |v\rangle = \begin{pmatrix} c_0 \\ c_1 \\ c_2 \\ c_3 \end{pmatrix}, \quad U = \begin{pmatrix} u_{00} & u_{01} & u_{02} & u_{03} \\ u_{10} & u_{11} & u_{12} & u_{13} \\ u_{20} & u_{21} & u_{22} & u_{23} \\ u_{30} & u_{31} & u_{32} & u_{33} \end{pmatrix}$$

This means that the gate can change **all amplitudes at once**, not just one at a time as in the single-qubit case. This is the important difference between single and multi-qubit gates: with 1 qubit, we modify only 2 amplitudes, but with 2 qubits, we can modify all 4 amplitudes **simultaneously**. And now, the transformation can mix amplitudes, create correlations, and even generate entanglement between the qubits.

In simple terms, a multi-qubit gate is just a transformation of a larger state vector. Nothing more, nothing less. However, this simple idea has important implications: it allows us to manipulate the global state of a quantum system, including correlations between qubits, which can lead to computational advantages over classical approaches.

4.3 Parallel Gates

Now that we have a way to represent the state of multiple qubits, we can also represent the operations (gates) that act on them. In particular, if we have two qubits $|v_A\rangle$ and $|v_B\rangle$, and two gates A and B , what happens when we want to apply A to $|v_A\rangle$ and B to $|v_B\rangle$ simultaneously?

The answer is given by the **tensor product of quantum gates**:

$$(A \otimes B)(|v_A\rangle \otimes |v_B\rangle) = (A|v_A\rangle) \otimes (B|v_B\rangle) \quad (41)$$

This means that the combined operation of applying A to $|v_A\rangle$ and B to $|v_B\rangle$ is represented by the tensor product of the two gates, $A \otimes B$. So, **applying gates in parallel** corresponds to the tensor product of the individual gates.




Figure 16: Parallel gates as a tensor product operation.

In simple terms, instead of applying A and B separately, we build one big matrix $A \otimes B$ that acts on the **whole system**. Note that a state is represented as a column vector (e.g., size 4 for two qubits), and a gate is represented as a square matrix (e.g., size 4×4 for two qubits). So *parallel gates* are simply one big transformation of the global state of the system.

❓ What if we want to apply a gate to only one qubit?

Suppose we want to **apply a gate A to the first qubit $|v_A\rangle$ while leaving the second qubit $|v_B\rangle$ unchanged**. We can represent this as:

$$(A \otimes I)(|v_A\rangle \otimes |v_B\rangle) = (A|v_A\rangle) \otimes |v_B\rangle \quad (42)$$

Here, I is the **identity gate** (page 45) that acts on the second qubit, meaning it **leaves it unchanged**. So, to apply a gate to just one qubit in a multi-qubit system, we use the tensor product of that gate with the identity operator on the other qubits.

Example 2: $H \otimes X$

Let's consider the gates H (Hadamard, page 61):

$$H = \frac{1}{\sqrt{2}} \begin{pmatrix} 1 & 1 \\ 1 & -1 \end{pmatrix}$$

And X (Pauli-X, page 47):

$$X = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix}$$

The tensor product $H \otimes X$ is calculated as follows:

$$\begin{aligned} H \otimes X &= \frac{1}{\sqrt{2}} \left(\begin{pmatrix} 1 & 1 \\ 1 & -1 \end{pmatrix} \otimes \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \right) \\ &= \frac{1}{\sqrt{2}} \begin{pmatrix} 1 \cdot X & 1 \cdot X \\ 1 \cdot X & -1 \cdot X \end{pmatrix} \\ &= \frac{1}{\sqrt{2}} \begin{pmatrix} 1 \cdot \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} & 1 \cdot \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \\ 1 \cdot \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} & -1 \cdot \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \end{pmatrix} \\ &= \frac{1}{\sqrt{2}} \begin{pmatrix} 0 & 1 & 0 & 1 \\ 1 & 0 & 1 & 0 \\ 0 & 1 & 0 & -1 \\ 1 & 0 & -1 & 0 \end{pmatrix} \end{aligned}$$

Now, if we apply $H \otimes X$ to a simple two-qubit state, say $|00\rangle$:

$$\begin{aligned} (H \otimes X) |00\rangle &= \frac{1}{\sqrt{2}} \begin{pmatrix} 0 & 1 & 0 & 1 \\ 1 & 0 & 1 & 0 \\ 0 & 1 & 0 & -1 \\ 1 & 0 & -1 & 0 \end{pmatrix} \begin{pmatrix} 1 \\ 0 \\ 0 \\ 0 \end{pmatrix} \\ &= \frac{1}{\sqrt{2}} \begin{pmatrix} 0 \cdot 1 + 1 \cdot 0 + 0 \cdot 0 + 1 \cdot 0 \\ 1 \cdot 1 + 0 \cdot 0 + 1 \cdot 0 + 0 \cdot 0 \\ 0 \cdot 1 + 1 \cdot 0 + 0 \cdot 0 + -1 \cdot 0 \\ 1 \cdot 1 + 0 \cdot 0 + -1 \cdot 0 + 0 \cdot 0 \end{pmatrix} \\ &= \frac{1}{\sqrt{2}} \begin{pmatrix} 0 \\ 1 \\ 0 \\ 1 \end{pmatrix} \\ &= \frac{1}{\sqrt{2}} \begin{pmatrix} 0 \\ 1 \\ 0 \\ 0 \end{pmatrix} + \frac{1}{\sqrt{2}} \begin{pmatrix} 0 \\ 0 \\ 0 \\ 1 \end{pmatrix} \\ &= \frac{1}{\sqrt{2}} |01\rangle + \frac{1}{\sqrt{2}} |11\rangle \end{aligned}$$

This can be visually represented as parallel gates acting on the two qubits:

$$\left. \begin{array}{l} |0\rangle \text{ --- } \boxed{H} \text{ --- } H|0\rangle \\ |0\rangle \text{ --- } \boxed{X} \text{ --- } X|0\rangle \end{array} \right\} (H|0\rangle) \otimes (X|0\rangle) = |+\rangle \otimes |1\rangle$$

Or as a single global gate:

$$\left. \begin{array}{l} |0\rangle \text{ --- } \boxed{H \otimes X} \text{ --- } \\ |0\rangle \text{ --- } \boxed{H \otimes X} \text{ --- } \end{array} \right\} (H \otimes X)|00\rangle = |+\rangle$$

Where $|+\rangle$ is $|+\rangle \otimes |1\rangle$. Note that applying the Hadamard gate to the qubit $|0\rangle$ creates the superposition state $|+\rangle = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle)$, while applying the X gate to $|0\rangle$ flips it to $|1\rangle$.

Example 3: $I \otimes X$

Now, let's consider applying the identity gate I to the first qubit and the X gate to the second qubit. The tensor product is:

$$\begin{aligned} I \otimes X &= \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix} \otimes \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \\ &= \begin{pmatrix} 1 \cdot \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} & 0 \cdot \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \\ 0 \cdot \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} & 1 \cdot \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix} \end{pmatrix} \\ &= \begin{pmatrix} 0 & 1 & 0 & 0 \\ 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{pmatrix} \end{aligned}$$

Applying this to the state $|00\rangle$ gives:

$$\begin{aligned} (I \otimes X)|00\rangle &= \begin{pmatrix} 0 & 1 & 0 & 0 \\ 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{pmatrix} \begin{pmatrix} 1 \\ 0 \\ 0 \\ 0 \end{pmatrix} \\ &= \begin{pmatrix} 0 \cdot 1 + 1 \cdot 0 + 0 \cdot 0 + 0 \cdot 0 \\ 1 \cdot 1 + 0 \cdot 0 + 0 \cdot 0 + 0 \cdot 0 \\ 0 \cdot 1 + 0 \cdot 0 + 0 \cdot 0 + 1 \cdot 0 \\ 0 \cdot 1 + 0 \cdot 0 + 1 \cdot 0 + 0 \cdot 0 \end{pmatrix} \\ &= \begin{pmatrix} 0 \\ 1 \\ 0 \\ 0 \end{pmatrix} \\ &= |01\rangle \end{aligned}$$

This means that applying I to the first qubit leaves it unchanged as $|0\rangle$, while applying X to the second qubit flips it from $|0\rangle$ to $|1\rangle$, resulting in the combined state $|01\rangle$. Visually, this can be represented as:

$$\left. \begin{array}{l} |0\rangle \text{ --- } \boxed{I} \text{ --- } I|0\rangle \\ |0\rangle \text{ --- } \boxed{X} \text{ --- } X|0\rangle \end{array} \right\} |0\rangle \otimes (X|0\rangle) = |0\rangle \otimes |1\rangle$$

Or as a single global gate:

$$\left. \begin{array}{l} |0\rangle \text{ --- } \\ |0\rangle \text{ --- } \end{array} \right\} \boxed{I \otimes X} \left. \begin{array}{l} \text{---} \\ \text{---} \end{array} \right\} (I \otimes X) |00\rangle = |01\rangle$$

4.4 Hadamard Transform on Multiple Qubits

Applying the Hadamard gate to every qubit is a useful tool in quantum computing, as it creates a superposition of all possible states. Now, let's see how this is done.

We already know that applying the Hadamard gate to a single qubit in the state $|0\rangle$ gives us:

$$H|0\rangle = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle)$$

This means that H creates a **balanced superposition** of the two basis states $|0\rangle$ and $|1\rangle$.

Now, if we apply this idea to two qubits, we can apply the Hadamard gate to each qubit individually. This is done using the tensor product of the Hadamard gates, for example:

$$(H \otimes H)|00\rangle = H|0\rangle \otimes H|0\rangle$$

So it is equivalent to applying the Hadamard gate to each qubit separately. Expanding this, we get:

$$\begin{aligned} (H \otimes H)|00\rangle &= H|0\rangle \otimes H|0\rangle \\ &= \left(\frac{1}{\sqrt{2}}(|0\rangle + |1\rangle)\right) \otimes \left(\frac{1}{\sqrt{2}}(|0\rangle + |1\rangle)\right) \\ &= \frac{1}{2}(|0\rangle + |1\rangle) \otimes (|0\rangle + |1\rangle) \\ &= \frac{1}{2}(|00\rangle + |01\rangle + |10\rangle + |11\rangle) \end{aligned}$$

This means that **applying Hadamard gate in parallel generates all possible combinations of the basis states** for the two qubits, creating a superposition of all four possible states.

In general, for n qubits, **applying the Hadamard gate to each qubit will create a superposition of all 2^n possible states**. The resulting state can be expressed as:

$$(H^{\otimes n})|0\rangle^{\otimes n} = \frac{1}{2^{\frac{n}{2}}} \sum_{k=0}^{2^n-1} |k\rangle = \frac{1}{\sqrt{2^n}} \sum_{k=0}^{2^n-1} |k\rangle \quad (43)$$

Where $|k\rangle$ represents the basis states of the n -qubit system, and the **sum runs over all possible combinations of the basis states**.

$$\left. \begin{array}{l} |0\rangle \text{---} \boxed{H} \text{---} \\ |0\rangle \text{---} \boxed{H} \text{---} \end{array} \right\} (H \otimes H)|00\rangle = \frac{1}{2}(|00\rangle + |01\rangle + |10\rangle + |11\rangle)$$

In summary, **Hadamard on all qubits spreads the state over the entire space of possible states**, creating a uniform superposition that is fundamental in many quantum algorithms.

4.5 Main Multi-Qubit Gates

4.5.1 Controlled NOT (CNOT) Gate

The **Controlled NOT (CNOT) Gate** is a **two-qubit gate** composed of:

- A **control qubit** that **determines** whether the **NOT operation is applied or not**.
- A **target qubit** that is **flipped** (NOT operation) if the control qubit is in the state $|1\rangle$, and remains unchanged if the control qubit is in the state $|0\rangle$.

In simple terms, it is a gate that **performs a NOT operation on the *target* qubit only when the *control* qubit is in the state $|1\rangle$** .

≡ Action on Basis States

The CNOT gate acts on the computational basis states as follows:

Input	Output
$ 00\rangle$	$ 00\rangle$
$ 01\rangle$	$ 01\rangle$
$ 10\rangle$	$ 11\rangle$
$ 11\rangle$	$ 10\rangle$

If the first qubit (control) is $|0\rangle$, the second qubit (target) remains unchanged. If the first qubit is $|1\rangle$, the second qubit is flipped: $|0\rangle \leftrightarrow |1\rangle$.

√* Matrix Representation

The CNOT gate can be represented as a 4×4 unitary matrix in the computational basis $\{|00\rangle, |01\rangle, |10\rangle, |11\rangle\}$:

$$\text{CNOT} = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{bmatrix} \quad (44)$$

This matrix indicates that the first two basis states $|00\rangle$ and $|01\rangle$ are unchanged, while $|10\rangle$ and $|11\rangle$ are swapped, reflecting the action of the CNOT gate on the target qubit based on the state of the control qubit.

≡ Action on General States


For a general two-qubit state $|v\rangle = c_0 |00\rangle + c_1 |01\rangle + c_2 |10\rangle + c_3 |11\rangle$, the CNOT gate transforms it as follows:

$$\text{CNOT} |v\rangle = c_0 |00\rangle + c_1 |01\rangle + c_2 |11\rangle + c_3 |10\rangle \quad (45)$$

The amplitudes c_0 and c_1 remain unchanged, while c_2 and c_3 are **swapped**, demonstrating the conditional nature of the CNOT gate based on the state of the control qubit.

✂ Circuit Representation

In quantum circuit diagrams, the CNOT gate is typically represented with a solid dot on the control qubit line and a plus sign $\oplus$ (indicating the NOT operation) on the target qubit line, connected by a vertical line.



Here, $|v_A\rangle$ is the control qubit and $|v_B\rangle$ is the target qubit. The output state of the target qubit is the result of the XOR operation between the control and target qubits, reflecting the conditional flipping of the target qubit based on the state of the control qubit.

In summary, if the control qubit is $|1\rangle$, apply NOT (Pauli-X) to the target qubit; otherwise do nothing.

⚙ Properties

- **Unitary**

$$\text{CNOT}^\dagger \cdot \text{CNOT} = \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{pmatrix}^\dagger \cdot \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{pmatrix} = I$$

CNOT gate is unitary, so it is a valid quantum gate that preserves normalization of quantum states, and the total probability of all outcomes remains 1.

- **Reversible**

$$\text{CNOT}^{-1} = \text{CNOT}^\dagger = \text{CNOT}$$

The CNOT gate is reversible, meaning that applying the CNOT gate twice will return the system to its original state:

$$\text{CNOT}(\text{CNOT}(|\psi\rangle)) = |\psi\rangle$$

In other words, we can **always undo a CNOT operation without loss of information**.

- **Conditional Operation**

$$\text{CNOT}(|v_A\rangle \otimes |v_B\rangle) \neq \text{CNOT}|v_A\rangle \otimes \text{CNOT}|v_B\rangle$$

The CNOT gate is a conditional operation, meaning that the **action on the target qubit depends on the state of the control qubit**. This is different from parallel gates, where each qubit is acted upon independently:

$$(H \otimes X)|00\rangle = (H|0\rangle) \otimes (X|0\rangle)$$

CNOT **breaks parallelism** because it introduces interaction: the **evolution of one qubit depends on another**, so the **system can no longer be described as independent parts**.

- **Entangling.** CNOT creates *entanglement* **if and only if** the input state has superposition on the control qubit (in the computational basis).

For example:

$$(H \otimes I) |00\rangle = \frac{1}{\sqrt{2}} (|00\rangle + |10\rangle)$$


Applying CNOT to this state:

$$\text{CNOT} \left(\frac{1}{\sqrt{2}} (|00\rangle + |10\rangle) \right) = \frac{1}{\sqrt{2}} (|00\rangle + |11\rangle)$$


The resulting state is an entangled state (cannot be factored into a tensor product, page 85), demonstrating that CNOT can create entanglement from a superposition state of the control qubit.

✂ Multiple CNOT Gates

Multi-CNOT notation means applying several CNOT gates that share the same control qubit, and these can be represented equivalently as sequential gates or as a single control connected to multiple targets. Visually, this can be represented as:



But it can also be represented as:



The **order of the CNOT gates does not matter** because they **commute when they share the same control qubit**, meaning that the final state of the system will be the same regardless of the order in which the CNOT gates are applied.

4.5.2 Generic Controlled Gate (CU)

The **Generic Controlled Gate (CU)** is a **two-qubit gate** composed of:

- A **control qubit** that determines **whether** the operation is **applied or not** (first qubit).
- A **target qubit** **on which the operation is applied** if the control qubit is in the state $|1\rangle$ (second qubit).
- A **unitary operation** U that is **applied to the target qubit** when the control qubit is in the state $|1\rangle$.

It **generalizes the CNOT gate** (page 99, $U = X$) by allowing **any unitary operation** U to be applied to the target qubit, rather than just the NOT operation.

≡ Action on Basis States

The action of the CU gate on the computational basis states can be described as follows:

Input	Output
$ 00\rangle$	$ 00\rangle$
$ 01\rangle$	$ 01\rangle$
$ 10\rangle$	$ 1\rangle \otimes U 0\rangle$
$ 11\rangle$	$ 1\rangle \otimes U 1\rangle$

If the control qubit is $|0\rangle$, the target qubit remains unchanged. If the control qubit is $|1\rangle$, the unitary operation U is applied to the target qubit, transforming $|0\rangle$ to $U|0\rangle$ and $|1\rangle$ to $U|1\rangle$.

√ Matrix Representation

The CU gate can be represented as a 4×4 unitary matrix in the computational basis $\{|00\rangle, |01\rangle, |10\rangle, |11\rangle\}$:

$$CU = C_U = \begin{bmatrix} I & 0 \\ 0 & U \end{bmatrix} = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & U_{00} & U_{01} \\ 0 & 0 & U_{10} & U_{11} \end{bmatrix} \quad (46)$$

Where $U_{00}, U_{01}, U_{10}, U_{11}$ are the elements of the 2×2 unitary matrix U that acts on the target qubit when the control qubit is $|1\rangle$. For the first two basis states $|00\rangle$ and $|01\rangle$, the identity operation I is applied, leaving them unchanged. For the last two basis states $|10\rangle$ and $|11\rangle$, the unitary operation U is applied to the target qubit, resulting in the transformation defined by U .

≡ Action on General States

Let's consider two general single-qubit states:

$$|v_A\rangle = a_0 |0\rangle + a_1 |1\rangle \quad |v_B\rangle = b_0 |0\rangle + b_1 |1\rangle$$

Combining these states into a two-qubit state, we have:

$$|v\rangle = |v_A\rangle \otimes |v_B\rangle = a_0 |0\rangle |v_B\rangle + a_1 |1\rangle |v_B\rangle$$


Applying the CU gate to this state, we get:

$$\begin{aligned} \text{CU} |v\rangle &= \text{CU}(a_0 |0\rangle |v_B\rangle + a_1 |1\rangle |v_B\rangle) \\ &= a_0 \text{CU}(|0\rangle |v_B\rangle) + a_1 \text{CU}(|1\rangle |v_B\rangle) \\ &= \underbrace{a_0 |0\rangle |v_B\rangle}_{\text{unchanged}} + \underbrace{a_1 |1\rangle U |v_B\rangle}_{\text{transformed}} \end{aligned}$$

This shows that the CU gate applies the unitary operation U to the target qubit only when the control qubit is in the state $|1\rangle$, while leaving the target qubit unchanged when the control qubit is in the state $|0\rangle$. Each component of the superposition evolves independently according to the value of the control qubit, resulting in a new superposition where different branches have undergone different transformations.

✂ Circuit Representation

In quantum circuit diagrams, the CU gate is typically represented with a **control dot on the control qubit** and a **box labeled with the unitary operation U on the target qubit**. The control dot indicates that the operation is conditional on the state of the control qubit. The circuit representation of the CU gate is as follows:



In summary, if the control qubit is $|1\rangle$, we apply U to the target qubit; otherwise do nothing.

⚙ Properties

The CU gate has the same properties as the CNOT gate because it is a generalization of the CNOT gate. Specifically:

- **Unitary**

$$\text{CU}^\dagger \text{CU} = I$$

- **Reversible**

$$\text{CU}^{-1} = \text{CU}^\dagger$$

- **Conditional Operation**

$$\text{CU}(|v_A\rangle \otimes |v_B\rangle) \neq \text{CU}|v_A\rangle \otimes \text{CU}|v_B\rangle$$

It does not act independently on each qubit, but rather applies a transformation to the target qubit based on the state of the control qubit.

- **Entangling.** The CU gate can create entanglement between the control and target qubits if the unitary operation U and the input state are chosen appropriately. For example, when $U = X$ (i.e., the CNOT gate), we have:

$$\text{CNOT}(|+\rangle |0\rangle) = \frac{1}{\sqrt{2}}(|00\rangle + |11\rangle)$$

4.5.3 SWAP gate

The **SWAP gate** is a **two-qubit gate** that **exchanges the states of two qubits** and has **no control/target distinction**, it is **symmetric**. It simply swaps:

$$|v_A\rangle \otimes |v_B\rangle \xrightarrow{SWAP} |v_B\rangle \otimes |v_A\rangle \quad (47)$$

≡ Action on Basis States

The SWAP gate acts on the basis states as follows:

Input	Output
$ 00\rangle$	$ 00\rangle$
$ 01\rangle$	$ 10\rangle$
$ 10\rangle$	$ 01\rangle$
$ 11\rangle$	$ 11\rangle$

It essentially **swaps the second and third basis states**, while leaving the first and fourth unchanged.

√* Matrix Representation

The matrix representation of the SWAP gate in the computational basis $\{|00\rangle, |01\rangle, |10\rangle, |11\rangle\}$ is:

$$SWAP = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \end{bmatrix} \quad (48)$$

This matrix clearly shows the **swapping of the second and third basis states**, while the first and fourth remain unchanged.

≡ Action on General States

Let's consider two arbitrary single-qubit states:

$$|v_A\rangle = a_0 |0\rangle + a_1 |1\rangle, \quad |v_B\rangle = b_0 |0\rangle + b_1 |1\rangle$$

The tensor product of these states is:

$$|v_A\rangle \otimes |v_B\rangle = a_0 b_0 |00\rangle + a_0 b_1 |01\rangle + a_1 b_0 |10\rangle + a_1 b_1 |11\rangle$$

Applying the SWAP gate to this state gives:

$$\begin{aligned} SWAP(|v_A\rangle \otimes |v_B\rangle) &= a_0 b_0 |00\rangle + a_1 b_0 |01\rangle + a_0 b_1 |10\rangle + a_1 b_1 |11\rangle \\ &= (b_0 |0\rangle + b_1 |1\rangle) \otimes (a_0 |0\rangle + a_1 |1\rangle) \\ &= |v_B\rangle \otimes |v_A\rangle \end{aligned}$$

This confirms that the SWAP gate indeed **exchanges the states of the two qubits**, as expected.

✂ Circuit Representation

In quantum circuit diagrams, the SWAP gate is typically represented by two crossed lines with $\times$ symbols at the crossing point:

$$\begin{array}{ccc} |v_A\rangle & \text{---} \times & |v_B\rangle \\ |v_B\rangle & \text{---} \times & |v_A\rangle \end{array}$$

This notation visually emphasizes the **swapping of the two qubits' states**.

⚙ Properties

- **Unitary**

$$\text{SWAP}^\dagger \text{SWAP} = I$$

This means that the SWAP gate preserves the inner product and is reversible.

- **Reversible (self-inverse)**

$$\text{SWAP}^2 = I$$

This means that applying the SWAP gate twice will return the system to its original state.

- **Symmetric (no control/target)**. The SWAP gate does not distinguish between the two qubits; it treats them symmetrically. This is in contrast to gates like CNOT, which have a clear control and target qubit.
- **Does NOT create entanglement**. The SWAP gate simply exchanges the states of two qubits and does **not introduce any new correlations** between them. If the input state is separable (not entangled), the output state will also be separable (and vice versa).
- **Can be decomposed into 3 CNOT gates**. The **SWAP gate can be implemented using three CNOT gates**, which is important for practical implementations on quantum hardware that may not have a native SWAP gate.

Proof. We want to transform:

$$|a, b\rangle \rightarrow |b, a\rangle$$

But CNOT only does:


$$|a, b\rangle \rightarrow |a, a \oplus b\rangle$$

So we need to **combine multiple CNOTs** to achieve a SWAP. Let's track what happens to a generic input:

$$|a, b\rangle \quad \text{with } a, b \in \{0, 1\}$$


- **First CNOT** (control: first qubit, target: second qubit):

$$|a, b\rangle \xrightarrow{\text{CNOT}} |a, a \oplus b\rangle$$




– **Second** CNOT (control: second qubit, target: first qubit):

$$|a, a \oplus b\rangle \xrightarrow{\text{CNOT}} |a \oplus (a \oplus b), a \oplus b\rangle = |b, a \oplus b\rangle$$




– **Third** CNOT (control: first qubit, target: second qubit):

$$|b, a \oplus b\rangle \xrightarrow{\text{CNOT}} |b, b \oplus (a \oplus b)\rangle = |b, a\rangle$$



In summary, the sequence of operations is:



QED

In general, the SWAP gate **does not create new correlations**; it only **re-orderes the information between qubits**. In other words, it only **changes where the information is stored**.

4.5.4 Controlled-Controlled-NOT (CCNOT) Gate (Toffoli)

The **Controlled-Controlled-NOT (CCNOT) Gate**, also called the **Toffoli Gate**, is a **three-qubit gate** composed of:

- Two **control qubits** that determine whether the gate will be applied.
- One **target qubit** that is flipped (NOT operation) if both control qubits are in the state $|1\rangle$.

It **generalizes the CNOT gate by adding an additional control qubit**, making it a crucial component in quantum computing for implementing more complex operations and algorithms.

📖 Action on Basis States

The CCNOT gate acts on the basis states as follows:

Input	Output
$ 000\rangle$	$ 000\rangle$
$ 001\rangle$	$ 001\rangle$
$ 010\rangle$	$ 010\rangle$
$ 011\rangle$	$ 011\rangle$
$ 100\rangle$	$ 100\rangle$
$ 101\rangle$	$ 101\rangle$
$ 110\rangle$	$ 111\rangle$
$ 111\rangle$	$ 110\rangle$

The target flips **only if both control qubits are $|1\rangle$** , demonstrating the conditional nature of the gate (last two rows of the table). For all other input combinations, the output remains unchanged.

✓✳ Matrix Representation

The matrix representation of the CCNOT gate in the computational basis is an 8×8 (since it operates on three qubits) unitary matrix given by:

$$\text{CCNOT} = \begin{bmatrix} 1 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 0 & 1 \\ 0 & 0 & 0 & 0 & 0 & 0 & 1 & 0 \end{bmatrix} \quad (49)$$

This matrix shows that the first six basis states are unchanged (diagonal entries of 1), while the **last two basis states are swapped** (off-diagonal entries of 1 in the last two rows and columns).

≡ Action on General States

For a general three-qubit state:

$$|\psi\rangle = \sum_{i,j,k \in \{0,1\}} \alpha_{ijk} |ijk\rangle$$

The CCNOT gate acts linearly on each component of the superposition and flips the target qubit (the third qubit) if and only if both control qubits are equal to $|1\rangle$. This can be expressed as:


$$\text{CCNOT} |\psi\rangle = \sum_{i,j,k \in \{0,1\}} \alpha_{ijk} |ij(k \oplus (i \cdot j))\rangle \quad (50)$$

Where $\oplus$ denotes the XOR operation, and $i \cdot j = 1$ if and only if $i = j = 1$, and 0 otherwise.

In simple terms, applying CCNOT affects only the c_6 and c_7 coefficients (corresponding to $|110\rangle$ and $|111\rangle$) by swapping them, while all other coefficients remain unchanged.

✂ Circuit Representation

In quantum circuit diagrams, the CCNOT gate is typically represented by a symbol with two control dots connected to a NOT gate (X gate) on the target qubit. The control dots indicate which qubits are the controls, and the NOT gate indicates the operation performed on the target qubit when both controls are active. It is similar to the CNOT gate but with an additional control dot, making it visually distinct and easy to identify in quantum circuits.



In summary, if both control qubits are $|1\rangle$, apply NOT to the target; otherwise do nothing.

⚙ Properties

- **Unitary**

$$\text{CCNOT}^\dagger \text{CCNOT} = I$$

- **Reversible**

$$\text{CCNOT}^{-1} = \text{CCNOT}^\dagger$$

- **Classical universal gate (can simulate AND)**. CCNOT gate is a **universal gate** for classical computation, meaning that **any classical**

logic gate can be constructed using CCNOT gates and single-qubit NOT gates. In particular, it can compute the AND operation in a reversible way:

$$|a, b, 0\rangle \xrightarrow{\text{CCNOT}} |a, b, 0 \oplus (a \cdot b)\rangle = |a, b, a \cdot b\rangle$$

Where a and b are the control qubits, and the target qubit is initialized to $|0\rangle$. After applying the CCNOT gate, the target qubit will be in the state $|1\rangle$ if and only if both a and b are $|1\rangle$, effectively computing the AND of the two control qubits.

Since AND and NOT are sufficient to express any Boolean function, the Toffoli gate can reproduce any classical computation.

- **Introduce multi-qubit interaction.** Multi-qubit interaction refers to operations in which the evolution of one qubit depends on the state of one or more other qubits. Unlike parallel gates, which act independently on each qubit, **interacting gates introduce conditional behavior and correlations between qubits.**

Typical examples include controlled gates such as CNOT and CCNOT, where the transformation applied to a target qubit depends on the value of one or more control qubits. These interactions are essential for creating entanglement and for implementing complex quantum algorithms.

- **Can create entanglement.** Similar to the CNOT gate, also the CCNOT gate can create entanglement between the control and target qubits. For example, if the control qubits are in a superposition state, applying the CCNOT gate can result in an entangled state between the control and target qubits.
- **Not decomposable into a single tensor product.** An interacting multi-qubit gate cannot be expressed as a tensor product of single-qubit operators. That is, in general:

$$U \neq U_A \otimes U_B$$

This means that the gate introduces correlations between qubits and cannot be reduced to independent operations.

In summary, the Toffoli gate performs a conditional operation based on two qubits, enabling multi-qubit logic and more complex correlations.

4.6 Quantum Circuit Representation

In the previous sections, we have been using visual representations of quantum gates and their effects on qubits. However, a quantum circuit can be expressed in a more formal way using a **single unitary matrix** that represents the entire operation of the circuit. This matrix acts on the global state of the system and is obtained by composing the individual gates according to the structure of the circuit. This is known as the **quantum circuit representation**.

Definition 1: Quantum Circuit Representation

A **quantum circuit** can be represented as a **unitary matrix** U that acts on the global state vector of the qubits. The overall operation of the circuit is obtained by composing the unitary matrices corresponding to each layer of gates in the circuit.

Mathematically, if a circuit consists of layers $G_1, G_2, \dots, G_n$ with corresponding unitary matrices $U_1, U_2, \dots, U_n$, then the overall unitary matrix U representing the circuit is given by:

$$U = U_n U_{n-1} \cdots U_2 U_1$$

Where the rightmost operator is applied first.

Each U_i is constructed by combining gates acting in parallel using tensor products, and by extending gates with identity operators on qubits where no operation is applied.

In simple terms, a **quantum circuit is just a structured way to build a single unitary matrix acting on the whole system**. So:

$$|\psi_{\text{out}}\rangle = U |\psi_{\text{in}}\rangle$$

Where $|\psi_{\text{in}}\rangle$ is the initial state of the qubits, $|\psi_{\text{out}}\rangle$ is the final state after applying the circuit, and U is the **product of all the gates in the circuit**.

⚠ The 3 Fundamental Rules of Quantum Circuit Representation

1. **Parallel composition.** Gates acting on different qubits are combined using the tensor product:

$$U = A \otimes B$$

2. **Sequential composition.** Gates applied in sequence are combined using matrix multiplication, evaluated from right to left:

$$U = U_n \cdots U_2 U_1$$

So the first gate applied is the rightmost one in the product.

3. **Identity extension.** When a gate does not act on a qubit, the identity operator must be used to extend it:

$$U = I \otimes A$$


This keeps dimensions consistent when combining gates that act on different subsets of qubits.

Example 4: Quantum Circuit Representation

Let's consider the following quantum circuit representation:

$$\underbrace{(H \otimes I \otimes I)}_4 \cdot \underbrace{(I \otimes \text{CNOT})}_3 \cdot \underbrace{(X \otimes I \otimes H)}_2 \cdot \underbrace{(\text{CNOT} \otimes I)}_1$$

First of all, the order of the gates is from right to left, so we start with the rightmost gate.



4.7 Entanglement

As discussed on page 91, we have already seen why entanglement exists and matters. In short, describing an n -qubit quantum state requires an exponential number of parameters, meaning that most multi-qubit states are entangled.

If qubits were independent (separable), we would only need $2n$ real numbers, since each qubit would require only 2 real parameters:

$$|v\rangle = a_0 |0\rangle + a_1 |1\rangle$$

Each qubit needs two real parameters, so for n qubits, we would need $2n$ real numbers. However, a general quantum state of n qubits is given by (see page 89):

$$|\psi\rangle = \sum_{k=0}^{2^n-1} c_k |k\rangle$$

This representation requires 2^n complex coefficients (subject to normalization and global phase constraints), corresponding to an exponential number of real degrees of freedom.

In conclusion, most multi-qubit states cannot be described as independent qubits. This phenomenon is called **entanglement** and is a fundamental feature of quantum mechanics with no classical analog.

Definition 2: Entanglement

A multi-qubit state is called **entangled** if it cannot be written as a tensor product of individual qubit states (i.e., it is not separable). Otherwise, it is called **separable** or **unentangled**. Entanglement can be viewed as a “failure of factorization”, where the state of the whole system cannot be factored into states of its parts.

An important consequence of entanglement is that we cannot assign a separate quantum state to each qubit independently.

✂ Analysis of a Real Example: Bell States

To better understand the concept of entanglement, it is useful to analyze a concrete example. In particular, we consider a class of two-qubit states known as **Bell states**, which provide the simplest and most important examples of entangled states. These states cannot be written as a tensor product of individual qubit states, and therefore explicitly demonstrate the impossibility of decomposing certain multi-qubit states into independent subsystems.

Definition 3: Bell States

The **Bell States** are a set of 4 two-qubit states that form an orthonormal basis of maximally entangled states. They are defined as:

$$\begin{aligned} |\Phi^+\rangle &= \frac{1}{\sqrt{2}} (|00\rangle + |11\rangle) & |\Phi^-\rangle &= \frac{1}{\sqrt{2}} (|00\rangle - |11\rangle) \\ |\Psi^+\rangle &= \frac{1}{\sqrt{2}} (|01\rangle + |10\rangle) & |\Psi^-\rangle &= \frac{1}{\sqrt{2}} (|01\rangle - |10\rangle) \end{aligned} \quad (51)$$

These states are called **maximally entangled** because each qubit, when considered individually, is in a completely mixed (maximally uncertain) state. In other words, Bell states are characterized by the fact that **each individual qubit is in a maximally mixed (completely random) state**, while the **joint state exhibits perfect correlations between the qubits**.

This means that when we measure a single qubit of a Bell state, the outcome is completely random. In other words, there is a 50% chance of getting a 0 and a 50% chance of getting a 1. Therefore, we cannot say that it is mostly a 0 or a 1. However, once we measure a single qubit, a paradox occurs: even though each qubit alone is random, together they are perfectly correlated. In fact, if we measure the first qubit and get $|0\rangle$, we know with certainty that the second qubit is also $|0\rangle$ (in the case of $|\Phi^+\rangle$ and $|\Phi^-\rangle$), or $|1\rangle$ (in the case of $|\Psi^+\rangle$ and $|\Psi^-\rangle$). Thus, we have **maximum uncertainty individually but maximum correlation jointly**.

Example 5: Proof of Entanglement in Bell States

After introducing the Bell states, we would like to **proof that decomposing them into independent qubits is impossible**. In other words, we want to show that:

$$|\Phi^+\rangle = \frac{1}{\sqrt{2}} (|00\rangle + |11\rangle)$$

Can be written as:

$$|\Phi^+\rangle = |v_A\rangle \otimes |v_B\rangle$$

Proof. Let's assume, for the sake of argument, that $|\Phi^+\rangle$ can be written as a tensor product of two single-qubit states:

$$|\Phi^+\rangle = |v_A\rangle \otimes |v_B\rangle$$

Where:

- $|v_A\rangle = a_0 |0\rangle + a_1 |1\rangle$ is the state of the first qubit.
- $|v_B\rangle = b_0 |0\rangle + b_1 |1\rangle$ is the state of the second qubit.

The tensor product of these two states is:

$$|v_A\rangle \otimes |v_B\rangle = a_0 b_0 |00\rangle + a_0 b_1 |01\rangle + a_1 b_0 |10\rangle + a_1 b_1 |11\rangle$$

For this to equal $|\Phi^+\rangle = \frac{1}{\sqrt{2}}(|00\rangle + |11\rangle)$, we must have:

$$a_0b_0 = \frac{1}{\sqrt{2}}, \quad a_1b_1 = \frac{1}{\sqrt{2}}, \quad a_0b_1 = 0, \quad a_1b_0 = 0$$

But here's the problem, if $a_0b_1 = 0$, then either $a_0 = 0$ or $b_1 = 0$:

✗ Case $a_0 = 0$, then $a_0b_0 = 0$, which **contradicts** $a_0b_0 = \frac{1}{\sqrt{2}}$ for $|00\rangle$.

✗ Case $b_1 = 0$, then $a_1b_1 = 0$, which **contradicts** $a_1b_1 = \frac{1}{\sqrt{2}}$ for $|11\rangle$.

Therefore, there is no way to choose a_0, a_1, b_0, b_1 such that the above equations hold simultaneously. This means that $|\Phi^+\rangle$ cannot be written as a tensor product of two single-qubit states, and thus it is an entangled state. All we can say is that these qubits are correlated and cannot be described independently. QED

❓ Entanglement: Intrinsic or Basis-Dependent?

Having established that Bell states are entangled by showing that they cannot be written as a tensor product of individual qubit states, a natural question arises: **is this property intrinsic to the state, or does it depend on the basis in which the state is expressed?** In other words, could a change of basis make an entangled state appear separable? The answer is no. **Entanglement** is not a property of the representation, but of the **structure of the state itself**.

In contrast to entanglement, **superposition depends on the basis we choose**, for example:

$$|0\rangle = \frac{1}{\sqrt{2}}(|+\rangle + |-\rangle)$$

This shows that the state $|0\rangle$ is a **superposition** of $|+\rangle$ and $|-\rangle$ in the **Hadamard basis**, but it is **not a superposition in the computational basis**, indeed:

$$|0\rangle = 1 \cdot |0\rangle + 0 \cdot |1\rangle$$

It is not a superposition because only one basis vector is present.¹

Differently, **entanglement** does **not** depend on basis, because it depends on **factorization**, not representation. So we can change basis, rewrite the state, but we **cannot make an entangled state separable**. This prevents a common misunderstanding: one might wonder whether a suitable change of basis could remove entanglement. This is not the case. Entanglement is preserved under local changes of basis, that is, transformations of the form $U_A \otimes U_B$ acting independently on each qubit. Therefore, **entanglement is an intrinsic property of the quantum state and does not depend on the particular representation of each subsystem**.

¹A state is a superposition in a given basis if it is written as a combination of multiple basis vectors with non-zero coefficients.

✂ From States to Operations

So far, we have analyzed entanglement as a property of quantum states, showing that certain states cannot be decomposed into independent subsystems. A natural question now arises: *how can such entangled states be generated in practice?* In other words, **which quantum operations are capable of transforming separable states into entangled ones?**

The answer lies in a special class of quantum gates, known as **entangling gates**, which introduce interactions between qubits and allow the creation of correlations that cannot be reduced to independent components.

Definition 4: Entangling Gates

A multi-qubit gate is called **entangling** (**Entangling Gates**) if it cannot be written as a tensor product of single-qubit gates. Equivalently, a gate is entangling if there exists at least one separable input state that it transforms into an entangled state.

Put simply, an **entangling gate is a gate that makes qubits interact and can create entanglement.**

⚠ Attention: Not every input becomes entangled. There exists at least one input that becomes entangled, but not all inputs necessarily do.

In simple terms, an entangling gate is one that can take two or more qubits that are initially uncorrelated (separable) and produce a state where the qubits become correlated in such a way that they cannot be described independently (entangled). For example, the CNOT gate is an entangling gate because it can create Bell states from separable inputs.

Example 6: CNOT as an Entangling Gate

Consider the separable state:

$$|+\rangle \otimes |0\rangle = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle) \otimes |0\rangle = \frac{1}{\sqrt{2}}(|00\rangle + |10\rangle)$$

This is a separable state, since it is written as a tensor product of two single-qubit states.

Now apply a CNOT gate (with the first qubit as control and the second as target, page 99):

$$\text{CNOT} \left(\frac{1}{\sqrt{2}}(|00\rangle + |10\rangle) \right) = \frac{1}{\sqrt{2}}(|00\rangle + |11\rangle)$$

The resulting state is the Bell state $|\Phi^+\rangle$, which is entangled. Therefore, the **CNOT gate is an entangling gate.**

Example 7: CNOT Does Not Always Create Entanglement

Not all inputs to an entangling gate produce entangled states. Consider the separable state:

$$|0\rangle \otimes |0\rangle = |00\rangle$$

Applying the CNOT gate:


$$\text{CNOT}(|00\rangle) = |00\rangle$$

The state remains separable.

This shows that an entangling gate does not necessarily produce entanglement for every input. However, it is called **entangling** because there exists at least one separable input state that it transforms into an entangled state.


Example 8: Bell-state generator

Exists a simple quantum circuit that produces **different Bell states depending on the input**. So, for the four input states $|00\rangle$, $|01\rangle$, $|10\rangle$, and $|11\rangle$, the circuit creates the four Bell states $|\Phi^+\rangle$, $|\Phi^-\rangle$, $|\Psi^+\rangle$, and $|\Psi^-\rangle$ respectively. This circuit consists of a Hadamard gate followed by a CNOT gate:




This circuit is a **Bell-state generator** because it can produce any of the four Bell states from the appropriate input.

- Input $|00\rangle$ produces $|\Phi^+\rangle$:




$$|\Phi^+\rangle = \frac{1}{\sqrt{2}} (|00\rangle + |11\rangle)$$

- Input $|01\rangle$ produces $|\Phi^-\rangle$:




$$|\Phi^-\rangle = \frac{1}{\sqrt{2}} (|00\rangle - |11\rangle)$$

- Input $|10\rangle$ produces $|\Psi^+\rangle$:



$$|\Psi^+\rangle = \frac{1}{\sqrt{2}} (|01\rangle + |10\rangle)$$

- Input $|11\rangle$ produces $|\Psi^-\rangle$:



$$|\Psi^-\rangle = \frac{1}{\sqrt{2}} (|01\rangle - |10\rangle)$$

Example 9: Bell States in the Hadamard Basis

In this exercise, we express the Bell state $|\Phi^+\rangle$ in the Hadamard basis instead of the computational basis.

Bell state $|\Phi^+\rangle$ in the Hadamard basis. Given:

$$|\Phi^+\rangle = \frac{1}{\sqrt{2}} (|00\rangle + |11\rangle)$$

We aim to re-express this state using the Hadamard basis $\{|+\rangle, |-\rangle\}$, where:

$$|+\rangle = \frac{1}{\sqrt{2}} (|0\rangle + |1\rangle) \quad |-\rangle = \frac{1}{\sqrt{2}} (|0\rangle - |1\rangle)$$

1. **Invert the definitions.** To convert from the computational basis to the Hadamard basis, we invert the above equations to express $|0\rangle$ and $|1\rangle$ in terms of $|+\rangle$ and $|-\rangle$:

$$|0\rangle = \frac{1}{\sqrt{2}} (|+\rangle + |-\rangle) \quad |1\rangle = \frac{1}{\sqrt{2}} (|+\rangle - |-\rangle)$$

2. **Substitute into $|00\rangle$ and $|11\rangle$.** We compute the tensor products using the expression above.

- Compute $|00\rangle$:

$$\begin{aligned} |00\rangle &= |0\rangle \otimes |0\rangle \\ &= \left(\frac{1}{\sqrt{2}} (|+\rangle + |-\rangle) \right) \otimes \left(\frac{1}{\sqrt{2}} (|+\rangle + |-\rangle) \right) \\ &= \frac{1}{2} (|++\rangle + |+-\rangle + |-+\rangle + |--\rangle) \end{aligned}$$

- Compute $|11\rangle$:

$$\begin{aligned} |11\rangle &= |1\rangle \otimes |1\rangle \\ &= \left(\frac{1}{\sqrt{2}} (|+\rangle - |-\rangle) \right) \otimes \left(\frac{1}{\sqrt{2}} (|+\rangle - |-\rangle) \right) \\ &= \frac{1}{2} (|++\rangle - |+-\rangle - |-+\rangle + |--\rangle) \end{aligned}$$

3. **Add the two to get $|\Phi^+\rangle$.** Now add the two results:

$$|\Phi^+\rangle = \frac{1}{\sqrt{2}} (|00\rangle + |11\rangle)$$

Substituting:

$$\begin{aligned} |\Phi^+\rangle &= \frac{1}{\sqrt{2}} \left[\frac{1}{2} (|++\rangle + |+-\rangle + |-+\rangle + |--\rangle) \right. \\ &\quad \left. + \frac{1}{2} (|++\rangle - |+-\rangle - |-+\rangle + |--\rangle) \right] \\ &= \frac{1}{\sqrt{2}} \cdot \frac{1}{2} (2|++\rangle + 0|+-\rangle + 0|-+\rangle + 2|--\rangle) \\ &= \frac{1}{\sqrt{2}} \cdot \frac{1}{2} (2|++\rangle + 2|--\rangle) \\ &= \frac{1}{\sqrt{2}} (|++\rangle + |--\rangle) \end{aligned}$$

Thus, in the Hadamard basis, we have:

$$|\Phi^+\rangle = \frac{1}{\sqrt{2}} (|++\rangle + |--\rangle)$$

Which is a Bell-like state expressed in the Hadamard basis instead of the computational basis. QED

4.8 Observables and Measurements

4.8.1 Observables: What Are We Measuring?

Let's start from the basics: *what is an observable?* In quantum mechanics, an **Observable** is a mathematical object representing a measurable physical quantity.

- For example, in classical physics, observables are physical quantities that we can measure, such as position, momentum, energy, etc. (e.g., the position of a particle, the energy of a system).
- In quantum mechanics, the state is no longer a point, but rather a vector (wavefunction) in a complex vector space (Hilbert space). Because of this, observables can no longer be ordinary functions of the state, but instead must be represented as **operators** that act on the state vector.

Definition 5: Observable

In quantum mechanics, an **Observable** is a **Hermitian operator** O associated with a measurable quantity of a quantum system:

$$O = O^\dagger$$

Where $O^\dagger$ denotes the Hermitian adjoint (conjugate transpose) of O .

With *conjugate transpose*, we mean that if O is represented as a matrix, then $O^\dagger$ is obtained by taking the **transpose** of the matrix and then taking the **complex conjugate of each element**. The condition $O = O^\dagger$ ensures that the eigenvalues of O are real, which is necessary for them to correspond to measurable quantities in quantum mechanics.

❓ Why does quantum mechanics specifically choose Hermitian operators for observables?

The answer is simple: **because measurements must produce physically meaningful outcomes**. Specifically, Hermitian operators guarantee: real eigenvalues and orthonormal eigenvectors.

1. **Real eigenvalues.** The eigenvalues of a Hermitian operator are always real numbers, which is **essential because measurement outcomes must be real values**. We cannot measure $3 + 2i$ as a physical quantity, but we can measure 3. Mathematically, if O is a Hermitian operator, then:

$$O |k\rangle = \lambda_k |k\rangle$$

Where λ_k is the possible measurement outcome (eigenvalue) corresponding to the eigenvector $|k\rangle$, and $|k\rangle$ is the state of the system after the measurement.

Remark

When we write:

$$O |k\rangle = \lambda_k |k\rangle$$

We are choosing $|k\rangle$ to be one of the eigenvectors of O , and λ_k is its corresponding eigenvalue. It is the definition of the eigenvector/eigenvalue relationship.

Suppose O is an operator, so a matrix. An eigenvector $|k\rangle$ of O is a special vector such that, when O acts on it, the result is the **same vector direction**, only multiplied by a number. That number is called the eigenvalue λ_k . So:

$$O |k\rangle = \lambda_k |k\rangle$$

Means applying the operator O to $|k\rangle$ does not change its direction; it only scales it by λ_k .

Example 10: Eigenvectors and Eigenvalues of the Pauli-Z Operator

For example, let's take the Pauli-Z operator:

$$Z = \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix}$$

And the state $|0\rangle$:

$$|0\rangle = \begin{bmatrix} 1 \\ 0 \end{bmatrix}$$

Applying Z to $|0\rangle$:

$$Z |0\rangle = \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix} \begin{bmatrix} 1 \\ 0 \end{bmatrix} = \begin{bmatrix} 1 \\ 0 \end{bmatrix} = 1 \cdot |0\rangle = \lambda_0 |0\rangle$$

Therefore, $|0\rangle$ is an eigenvector of Z with eigenvalue $\lambda_0 = 1$. Similarly, applying Z to $|1\rangle$:

$$Z |1\rangle = \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix} \begin{bmatrix} 0 \\ 1 \end{bmatrix} = \begin{bmatrix} 0 \\ -1 \end{bmatrix} = -1 \cdot |1\rangle = \lambda_1 |1\rangle$$

Therefore, $|1\rangle$ is an eigenvector of Z with eigenvalue $\lambda_1 = -1$.

Beyond the mathematical definition, $|0\rangle$ is a special state of the observable Z , measuring Z when the system is in $|0\rangle$ always gives the outcome $+1$. So, when we say that $|0\rangle$ and $|1\rangle$ are eigenvectors of Z , we are saying that these are the states in which the measurement of Z is **perfectly predictable**, yielding the eigenvalues $+1$ and -1 , respectively.

This is a fundamental aspect, because:

✓ If the **system is already in an eigenvector**: there is no uncertainty, and the measurement outcome is known with certainty.

✗ In contrast, if the **system is not in an eigenvector**: it is a combination of eigenvectors, and measurement becomes **probabilistic**. For example, suppose the qubit is in:

$$|+\rangle = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle)$$

This is **not** an eigenvector of Z , because applying Z :

$$\begin{aligned} Z|+\rangle &= \frac{1}{\sqrt{2}} \left(\begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix} \begin{bmatrix} 1 \\ 0 \end{bmatrix} + \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix} \begin{bmatrix} 0 \\ 1 \end{bmatrix} \right) \\ &= \frac{1}{\sqrt{2}} \left(\begin{bmatrix} 1 \\ 0 \end{bmatrix} + \begin{bmatrix} 0 \\ -1 \end{bmatrix} \right) \\ &= \frac{1}{\sqrt{2}}(|0\rangle - |1\rangle) \\ &= |-\rangle \end{aligned}$$

❓ **Why is $|+\rangle$ not an eigenvector of Z ?** If $|+\rangle$ were an eigenvector, we would have by definition:

$$Z|+\rangle = \lambda|+\rangle$$

For some eigenvalue λ . However, as we calculated, applying Z to $|+\rangle$ gives us $|-\rangle$, which is a different state. Therefore, there is no scalar λ such that $Z|+\rangle = \lambda|+\rangle$, confirming that $|+\rangle$ is not an eigenvector of Z . Physically, this means that if the system is in state $|+\rangle$, measuring Z does not yield a definite outcome; instead, it yields $+1$ with probability 0.5 and -1 with probability 0.5, reflecting the superposition of eigenstates.

In summary, if applying an observable O to a state $|\psi\rangle$ produces the same state multiplied by a scalar:

$$O|\psi\rangle = \lambda|\psi\rangle$$

Then $|\psi\rangle$ is an eigenvector of O , and λ is its eigenvalue. In this case, the state already has a definite value for that observable, so measuring O will return λ with certainty.

✓ **Physical consequence.** If the system is in an eigenvector: the **measurement is deterministic**, the **result is known in advance**, the **outcome is the corresponding eigenvalue**.

Why Hermitian operators have real eigenvalues. Let A be a Hermitian operator:

$$A = A^\dagger$$

Assume that $|x\rangle$ is an eigenvector of A with eigenvalue λ :

$$A|x\rangle = \lambda|x\rangle$$

Consider the quantity:

$$\langle x|A|x\rangle$$

Using the eigenvalue equation (i.e., $A|x\rangle = \lambda|x\rangle$) on the right:

$$\langle x|\underbrace{A|x\rangle}_{\lambda|x\rangle} = \langle x|(\lambda|x\rangle) = \lambda\langle x|x\rangle$$

This is possible because λ is just a scalar, so it can be moved outside bra-ket notation.² Now take the Hermitian conjugate of the eigenvalue equation:

$$A|x\rangle = \lambda|x\rangle \implies \langle x|A^\dagger = \bar{\lambda}\langle x|$$

Since A is Hermitian:

$$A^\dagger = A$$

Therefore:

$$\langle x|A = \bar{\lambda}\langle x|$$

Applying this on the left of $\langle x|A|x\rangle$:

$$\underbrace{\langle x|A}_{\bar{\lambda}\langle x|}|x\rangle = (\bar{\lambda}\langle x|)|x\rangle = \bar{\lambda}\langle x|x\rangle$$

Combining the two expressions:

$$\lambda\langle x|x\rangle = \bar{\lambda}\langle x|x\rangle$$

Since:

$$\langle x|x\rangle > 0$$

Because the inner product of a vector with itself is always positive (unless the vector is the zero vector, which cannot be an eigenvector), we can divide both sides by $\langle x|x\rangle$:

$$\lambda = \bar{\lambda}$$

Therefore, λ is real.

QED

²Remember that bras and kets can be represented using vectors and matrices, so the usual rules of linear algebra apply. In particular, since λ is a scalar, it can be factored out of an inner product:

$$\langle x|(\lambda|x\rangle) = \lambda\langle x|x\rangle$$

More generally, scalar multiplication commutes with matrix products. Therefore, for matrices A and B :

$$\lambda AB = A\lambda B = AB\lambda$$

Provided that the order of the matrices themselves is preserved.

2. **Orthonormal eigenvectors.** A vector is:

- **Orthogonal** if its inner product with another vector is zero (i.e., they are perpendicular in the vector space). For example, in a 2D space, the vectors $|0\rangle$ and $|1\rangle$ are orthogonal because:

$$\langle 0|1\rangle = \begin{bmatrix} 1 & 0 \end{bmatrix} \begin{bmatrix} 0 \\ 1 \end{bmatrix} = 0$$

- **Normalized** if its inner product with itself is equal to one (i.e., it has unit length). For example:

$$\langle 0|0\rangle = \begin{bmatrix} 1 & 0 \end{bmatrix} \begin{bmatrix} 1 \\ 0 \end{bmatrix} = 1$$

This property is crucial because quantum measurement requires a basis whose states are both perfectly distinguishable (orthogonal) and probabilistically consistent (normalized).

- ✗ **If eigenvectors were not orthogonal,** different measurement states could partially overlap:

$$\langle v_1|v_2\rangle \neq 0$$

In this case, the measurement process would not be able to distinguish the states perfectly, leading to ambiguity in the interpretation of measurement outcomes.

Example 11: Why Orthogonality Matters

Consider the two states:

$$|v_1\rangle = |0\rangle \quad |v_2\rangle = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle)$$

Their inner product is:

$$\langle v_1|v_2\rangle = \langle 0| \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle) = \frac{1}{\sqrt{2}}$$

Since:

$$\langle v_1|v_2\rangle \neq 0$$

the two states are not orthogonal. This means that the **states partially overlap**, and therefore a **measurement cannot distinguish them perfectly**. For example, if the system is in state $|v_2\rangle$, there is still a non-zero probability of confusing it with $|v_1\rangle$ during a measurement. Therefore, the measurement outcomes would be ambiguous, and we would not be able to assign a clear physical meaning to the measurement results.

- ✗ **If eigenvectors were not normalized:**

$$\langle v|v\rangle \neq 1$$

Then the Born rule (page 79) would not produce properly normalized probabilities, making the probabilistic interpretation of quantum mechanics inconsistent.

Example 12: Why Normalization Matters

Consider the state:

$$|v\rangle = \begin{pmatrix} 2 \\ 0 \end{pmatrix}$$

Its norm is:

$$\langle v|v\rangle = \begin{bmatrix} 2 & 0 \end{bmatrix} \begin{bmatrix} 2 \\ 0 \end{bmatrix} = 4$$

Therefore, the state is not normalized.

If we tried to interpret the amplitudes probabilistically using the Born rule, we would obtain:

$$p_0 = |2|^2 = 4$$

Which is **impossible**, since **probabilities must lie between 0 and 1**, and their total sum must equal 1.

To obtain a valid quantum state, we must normalize the vector:

$$|v_{\text{norm}}\rangle = \frac{1}{2} \begin{pmatrix} 2 \\ 0 \end{pmatrix} = \begin{pmatrix} 1 \\ 0 \end{pmatrix}$$

Therefore, without normalization, we would end up with an invalid quantum state that cannot be interpreted probabilistically, and the measurement outcomes would not correspond to any physical reality.

Why eigenvectors of Hermitian operators are orthogonal. Let A be Hermitian and let:

$$A|x\rangle = \lambda|x\rangle, \quad A|y\rangle = \mu|y\rangle$$

Where $\lambda \neq \mu$ are the eigenvalues corresponding to the eigenvectors $|x\rangle$ and $|y\rangle$, respectively. Consider the inner product:

$$\langle y|A|x\rangle$$

Because we want to show that $|x\rangle$ and $|y\rangle$ are orthogonal, we need to show that $\langle y|x\rangle = 0$. Using the eigenvalue equation on the right:

$$\langle y|A|x\rangle = \langle y|(\lambda|x\rangle) = \lambda\langle y|x\rangle$$

We moved λ outside the inner product because it is a scalar (see the footnote in the previous proof for more details on this step). Now use the Hermitian property on the left:

$$\underbrace{\langle y|A}_{\langle y|A^\dagger} = \mu\langle y|$$

Therefore:

$$\langle y| A |x\rangle = \mu \langle y|x\rangle$$

Combining the two expressions:

$$\lambda \langle y|x\rangle = \mu \langle y|x\rangle$$

Thus:

$$(\lambda - \mu) \langle y|x\rangle = 0$$

Since $\lambda \neq \mu$ by assumption, we must have:

$$\langle y|x\rangle = 0$$

Therefore, the eigenvectors are orthogonal.

QED

We can think of a **Hermitian operator** as a sort of “*machine*” that **decomposes the quantum state into measurable components** (eigenvectors) **and assigns a real value** (eigenvalue) **to each component**, which corresponds to the possible outcomes of a measurement. The orthonormality of the eigenvectors ensures that these outcomes are distinct and can be interpreted probabilistically in a consistent way. In summary, a Hermitian observable tells us:

- *What outcomes are possible when we measure a quantum system.*
- *With respect to which basis we are measuring the system.*
- *Into which states the system will collapse after the measurement.*

Spectral Theorem

So far, we know that an observable O is a Hermitian operator, it has eigenvectors $|k\rangle$, and each eigenvector has an eigenvalue λ_k . So if the system is in $|k\rangle$, measuring O returns λ_k with certainty. Now, a natural question arises: **what happens if the system is in an arbitrary state $|k\rangle$, not necessarily one of the eigenvectors?** To answer this question, the **Spectral Theorem** comes into play by showing that **every observable can be written as a sum of its eigenvectors and eigenvalues**.

Suppose the observable has a set of eigenvectors $|k\rangle$ with corresponding eigenvalues λ_k . Since the eigenvectors form an orthonormal basis, any quantum state $|v\rangle$ can be expressed as a linear combination of these eigenvectors (page 89):

$$|v\rangle = \sum_k c_k |k\rangle$$

Where c_k are complex coefficients. The **Spectral Theorem** states that the observable O can be expressed as:

$$O = \sum_k \lambda_k |k\rangle\langle k| \quad (52)$$

Where each term $\lambda_k |k\rangle\langle k|$ contains two pieces of information:

- **Projector** $|k\rangle\langle k|$ (page 76) onto the eigenvector $|k\rangle$, which extracts the component of the state along $|k\rangle$ during measurement. It is defined as:

$$|k\rangle\langle k| = |k\rangle \langle k|$$

- **Eigenvalue** λ_k , which assigns the measurement outcome associated with that component.

🔗 **Why the Spectral Theorem is important?** Suppose someone gives us an observable O without telling us its eigenvectors or eigenvalues:

$$O = \begin{bmatrix} 2 & 1 \\ 1 & 2 \end{bmatrix}$$

Without the Spectral Theorem, the physical meaning of the observable would not be immediately apparent. However, by applying the Spectral Theorem, we can decompose O into its eigenvectors and eigenvalues, allowing us to **understand the measurement process and predict the outcomes based on the state of the system**. For example, we can find the eigenvalues and eigenvectors of O :

- To find the eigenvalues, we solve the characteristic equation:

$$\begin{aligned} \det(O - \lambda I) &= 0 \\ \det\left(\begin{bmatrix} 2-\lambda & 1 \\ 1 & 2-\lambda \end{bmatrix}\right) &= 0 \\ (2-\lambda)(2-\lambda) - 1 \cdot 1 &= 0 \\ 4 - 4\lambda + \lambda^2 - 1 &= 0 \\ \lambda^2 - 4\lambda + 3 &= 0 \\ (\lambda - 3)(\lambda - 1) &= 0 \end{aligned}$$

Thus, the eigenvalues are $\lambda_1 = 3$ and $\lambda_2 = 1$.

- Eigenvectors can be found by solving $(O - \lambda I)|k\rangle = 0$ for each eigenvalue:
 - For $\lambda_1 = 3$:

$$\begin{aligned} (O - 3I)|v_1\rangle &= 0 \\ \left(\begin{bmatrix} 2-3 & 1 \\ 1 & 2-3 \end{bmatrix}\right)|v_1\rangle &= 0 \\ \left(\begin{bmatrix} -1 & 1 \\ 1 & -1 \end{bmatrix}\right)|v_1\rangle &= 0 \end{aligned}$$

Now to find the eigenvector, we need to solve the system of equations:

$$\begin{bmatrix} -1 & 1 \\ 1 & -1 \end{bmatrix} \begin{bmatrix} x \\ y \end{bmatrix} = \begin{bmatrix} 0 \\ 0 \end{bmatrix}$$

That is a homogeneous system of linear equations:

$$\begin{cases} -x + y = 0 \\ x - y = 0 \end{cases} = \begin{cases} y = x \\ x = y \end{cases}$$

So any vector of the form (x, x) is an eigenvector. We choose the simplest one $(1, 1)$, and then we normalize it:

$$\left\| \begin{bmatrix} 1 \\ 1 \end{bmatrix} \right\| = \sqrt{1^2 + 1^2} = \sqrt{2}$$

Therefore, the normalized eigenvector is:

$$|v_1\rangle = \frac{1}{\sqrt{2}} (|0\rangle + |1\rangle)$$

– For $\lambda_2 = 1$:

$$\begin{aligned} (O - 1I) |v_2\rangle &= 0 \\ \left(\begin{bmatrix} 2 & 1 \\ 1 & 2 \end{bmatrix} \right) |v_2\rangle &= 0 \\ \left(\begin{bmatrix} 1 & 1 \\ 1 & 1 \end{bmatrix} \right) |v_2\rangle &= 0 \end{aligned}$$

We need to solve the system of equations:

$$\begin{cases} x + y = 0 \\ x + y = 0 \end{cases} \Rightarrow x + y = 0 \Rightarrow y = -x \xrightarrow{\text{substitute from } \begin{bmatrix} x \\ y \end{bmatrix}} \begin{bmatrix} x \\ -x \end{bmatrix}$$

So any vector of the form $(x, -x)$ is an eigenvector. We choose the simplest one $(1, -1)$, and then we normalize it:

$$\left\| \begin{bmatrix} 1 \\ -1 \end{bmatrix} \right\| = \sqrt{1^2 + (-1)^2} = \sqrt{2}$$

Therefore, the normalized eigenvector is:

$$|v_2\rangle = \frac{1}{\sqrt{2}} (|0\rangle - |1\rangle)$$

Then we can express O in terms of its spectral decomposition:

$$O = 3 |v_1\rangle\langle v_1| + 1 |v_2\rangle\langle v_2|$$

From this decomposition, we can immediately read off the possible outcomes from the eigenvalues (3 and 1), the measurement basis from the eigenvectors $(|v_1\rangle$ and $|v_2\rangle)$, and the measurement operators from the projectors $(|v_1\rangle\langle v_1|$ and $|v_2\rangle\langle v_2|)$. It also allows us to calculate the probabilities of obtaining each outcome when measuring O on an arbitrary state $|\psi\rangle$ using the Born rule:

$$p_1 = |\langle v_1 | \psi \rangle|^2 \quad p_2 = |\langle v_2 | \psi \rangle|^2$$

Where p_1 and p_2 are the probabilities of obtaining the outcomes 3 and 1, respectively, when measuring the observable O on a state $|\psi\rangle$. And finally the expectation value of O in the state $|\psi\rangle$ can be calculated as:

$$\langle \psi | O | \psi \rangle = \sum_k \lambda_k p_k$$

In this example, this becomes:

$$\langle \psi | O | \psi \rangle = \sum_{k=1}^2 \lambda_k p_k = 3p_1 + 1p_2$$

In summary, the Spectral Theorem transforms an abstract Hermitian matrix into a complete description of a quantum measurement. It reveals:

- The **possible measurement outcomes** (eigenvalues),
- The **corresponding post-measurement states** (eigenvectors),
- The **projectors used to compute probabilities**,
- And the **expectation value** as a weighted average of the outcomes.

4.8.2 Measurement Operators and Projectors

In this section, we will explain **how measurement is actually performed mathematically**.

Measurement Operators

After introducing the Spectral Theorem, we know that any observable can be written as:

$$O = \sum_k \lambda_k |k\rangle\langle k|$$

Where:

- λ_k are the possible measurement outcomes (eigenvalues);
- $|k\rangle$ are the corresponding eigenvectors;
- $|k\rangle\langle k|$ are projection operators onto the eigenvectors.

At this point, a natural question arises: **what role do these projectors play in the measurement process?**

The answer is that each projector:

$$M_k = |k\rangle\langle k|$$

Is called a **Measurement Operator** (page 76). It represents the mathematical operation associated with the measurement outcome λ_k .

Definition 6: Measurement Operator

Given an observable (page 120):

$$O = \sum_k \lambda_k |k\rangle\langle k|$$

The **Measurement Operator** associated with the outcome λ_k is:

$$M_k = |k\rangle\langle k| = \begin{pmatrix} k_1 \\ k_2 \end{pmatrix} \begin{pmatrix} \overline{k_1} & \overline{k_2} \end{pmatrix} = \begin{pmatrix} k_1 \overline{k_1} & k_1 \overline{k_2} \\ k_2 \overline{k_1} & k_2 \overline{k_2} \end{pmatrix}$$

In other words, **each possible measurement outcome has an associated projector** that:

1. **Extracts the component** of the quantum state along the eigenvector $|k\rangle$;
2. **Determines the probability** of obtaining the corresponding eigenvalue λ_k ;
3. **Produces the post-measurement** state after collapse.

For this reason, a measurement operator can be thought of as a **detector** tuned to a specific eigenstate. If the detector corresponding to $|k\rangle$ “clicks”, then:

- The measurement outcome is λ_k ;
- The system collapses to the state $|k\rangle$.

For example, suppose an observable has two eigenstates $|0\rangle$ and $|1\rangle$. Then there are two measurement operators:

$$M_0 = |0\rangle\langle 0|, \quad M_1 = |1\rangle\langle 1|$$

We can imagine them as two detectors:

- Detector M_0 looks for the component of the state along $|0\rangle$.
- Detector M_1 looks for the component of the state along $|1\rangle$.

Suppose the state is:

$$|\psi\rangle = \alpha |0\rangle + \beta |1\rangle$$

This means that part of the state points along $|0\rangle$, and part of the state points along $|1\rangle$. The detector $M_0 = |0\rangle\langle 0|$ asks “*how much of the state is aligned with $|0\rangle$?*” and extracts $\alpha |0\rangle$. The detector $M_1 = |1\rangle\langle 1|$ asks “*how much of the state is aligned with $|1\rangle$?*” and extracts $\beta |1\rangle$.

Example 13: Example: Measurement Operators for Pauli-Z

The Pauli-Z observable can be written as:

$$Z = |0\rangle\langle 0| - |1\rangle\langle 1|$$

Therefore, the associated measurement operators are:

$$M_0 = |0\rangle\langle 0|, \quad M_1 = |1\rangle\langle 1|$$

These operators correspond to the two possible outcomes:

- +1, associated with the eigenstate $|0\rangle$;
- -1, associated with the eigenstate $|1\rangle$.

Suppose the system is in the state:

$$|\psi\rangle = \alpha |0\rangle + \beta |1\rangle$$

Applying the measurement operator M_0 :

$$M_0 |\psi\rangle = |0\rangle\langle 0| (\alpha |0\rangle + \beta |1\rangle) = \alpha |0\rangle$$

This means that the operator M_0 extracts only the component of the state aligned with $|0\rangle$ and removes the orthogonal component $|1\rangle$.

The probability of obtaining the corresponding outcome is:

$$p_0 = \langle \psi | M_0 | \psi \rangle = |\alpha|^2$$

Similarly:

$$p_1 = \langle \psi | M_1 | \psi \rangle = |\beta|^2$$

Therefore, **measurement operators** provide the complete mathematical description of the measurement process: they **isolate the relevant component** of the quantum state, **determine the probability** of each outcome, and **specify the state** after the measurement.

Completeness of the Basis

In the previous example, we defined two measurement operators M_0 and M_1 corresponding to the two eigenstates of the Pauli-Z observable. But what if we had an observable with more eigenstates? Or what if we had a different observable with a completely different set of eigenvectors? Therefore, **how do we know that the measurement operators we defined account for all possible outcomes of the measurement?**

The answer is that the eigenvectors of a Hermitian observable form a **complete orthonormal basis**. This means that any quantum state can be expressed as a linear combination of these eigenvectors:

$$|\psi\rangle = \sum_k c_k |k\rangle$$

Mathematically, this property is expressed by the **Completeness Relation**:

$$\sum_k |k\rangle\langle k| = I$$

Where I is the identity operator (page 45).

Definition 7: Completeness Relation

If $\{|k\rangle\}$ is a complete orthonormal basis, then:

$$\sum_k |k\rangle\langle k| = I \quad (53)$$

Since the measurement operators are defined as:

$$M_k = |k\rangle\langle k|$$

It follows that:

$$\sum_k M_k = I$$

This means that the **set of measurement operators is complete and accounts for all possible outcomes of the measurement.**

Deepening: When a set of vectors $\{|k\rangle\}$ is a complete orthonormal basis?

A set of vectors $\{|k\rangle\}$ is called a **Complete Orthonormal Basis** when it satisfies **three conditions**:

1. **Normalized**, each vector has length 1: $\langle k|k \rangle = 1$.
2. **Orthogonal**, different vectors are perpendicular: $\langle k|j \rangle = 0$ for $k \neq j$.
3. **Complete**, the vectors span the entire Hilbert space, meaning that every quantum state can be written as a linear combination of them. That is, for any state $|\psi\rangle$, there exist coefficients c_k such that:

$$|\psi\rangle = \sum_k c_k |k\rangle$$

Compactly, the *normalized* and *orthogonal* conditions are written as:

$$\langle k|j \rangle = \delta_{kj} \quad (54)$$

Where δ_{kj} is the **Kronecker delta**, which is 1 if $k = j$ and 0 otherwise:

$$\delta_{kj} = \begin{cases} 1 & k = j \\ 0 & k \neq j \end{cases} \quad (55)$$

And the *completeness* condition is expressed by the completeness relation:

$$\sum_k |k\rangle\langle k| = I$$

Example 14: Single-Qubit Computational Basis

For a single qubit, the computational basis consists of the vectors:

$$|0\rangle = \begin{bmatrix} 1 \\ 0 \end{bmatrix}, \quad |1\rangle = \begin{bmatrix} 0 \\ 1 \end{bmatrix}$$

These vectors are:

- Normalized: $\langle 0|0 \rangle = 1$ and $\langle 1|1 \rangle = 1$.
- Orthogonal: $\langle 0|1 \rangle = 0$.
- Complete: any single-qubit state can be expressed as a linear combination of $|0\rangle$ and $|1\rangle$.

$$|\psi\rangle = \alpha |0\rangle + \beta |1\rangle$$

This Equation 53 states that the **set of measurement operators is complete**: together, they **describe every possible outcome of the measurement**.

❓ Why is the completeness relation important? To understand why this relation is important, let us apply both sides to an arbitrary state:

$$|\psi\rangle = \sum_k c_k |k\rangle$$

Where c_k are the coefficients of $|\psi\rangle$ in the basis $\{|k\rangle\}$.

Now take the inner product with $\langle k|$ on both sides:

$$\langle k|\psi\rangle = \langle k|\left(\sum_j c_j |j\rangle\right)$$

Using linearity of the inner product:

$$\langle k|\psi\rangle = \sum_j c_j \langle k|j\rangle$$

Since the basis is orthonormal, $\langle k|j\rangle = \delta_{kj}$, so only the term where $j = k$ survives (Equation 54, page 133):

$$\langle k|j\rangle = \delta_{kj} = \begin{cases} 1 & k = j \\ 0 & k \neq j \end{cases}$$

Thanks to the Kronecker delta, all terms in the sum vanish except the one where $j = k$:

$$\langle k|\psi\rangle = c_k \langle k|k\rangle = c_k \cdot 1 = c_k$$

In other words, the bra $\langle k|$ acts as a coefficient extractor: it selects exactly the amount of $|\psi\rangle$ aligned with the basis vector $|k\rangle$.

Finally, apply the sum of all projectors to $|\psi\rangle$:

$$\left(\sum_k |k\rangle\langle k|\right) |\psi\rangle = \sum_k |k\rangle \langle k|\psi\rangle = \sum_k |k\rangle c_k = \sum_k c_k |k\rangle = |\psi\rangle$$

This shows that the **sum of all projectors reproduces the original state exactly**. In other words, **each projector $|k\rangle\langle k|$ extracts one component of the state, and when all these components are added together, the original state is reconstructed without losing any information.** Therefore:

$$\sum_k |k\rangle\langle k| = I$$

Example 15: Computational Basis

For a single qubit, the computational basis is:

$$|0\rangle, \quad |1\rangle$$

The corresponding projectors are:

$$|0\rangle\langle 0| = \begin{bmatrix} 1 & 0 \\ 0 & 0 \end{bmatrix}, \quad |1\rangle\langle 1| = \begin{bmatrix} 0 & 0 \\ 0 & 1 \end{bmatrix}$$

Their sum is:

$$|0\rangle\langle 0| + |1\rangle\langle 1| = \begin{bmatrix} 1 & 0 \\ 0 & 0 \end{bmatrix} + \begin{bmatrix} 0 & 0 \\ 0 & 1 \end{bmatrix} = \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} = I$$

The completeness relation also guarantees that the probabilities of all possible outcomes sum to one. If:

$$p_k = \langle \psi | M_k | \psi \rangle$$

Then:

$$\begin{aligned} \sum_k p_k &= \sum_k \langle \psi | M_k | \psi \rangle \\ &= \langle \psi | \left(\sum_k M_k \right) | \psi \rangle \\ &= \langle \psi | I | \psi \rangle \\ &= \langle \psi | \psi \rangle \\ &= 1 \end{aligned}$$

Therefore, the **completeness relation** ensures that:

- **All possible measurement outcomes** are included;
- **No probability is lost**;
- The **total probability** is always **equal to one**.

4.8.3 Expectation Value

In the previous sections, we have seen how to compute the probability of obtaining a certain measurement outcome when measuring an observable on a quantum state. However, in many cases, we are **interested in the average value of an observable over many measurements**, rather than the probability of specific outcomes. This average value is known as the **expectation value** of the observable.

Definition 8: Expectation Value

Let O be an observable represented by a Hermitian operator, and let $|\psi\rangle$ be a quantum state. The quantity:

$$\langle O \rangle = \langle \psi | O | \psi \rangle = \sum_k \lambda_k p_k \quad (56)$$

Is called the **Expectation Value** of the observable O in the state $|\psi\rangle$.

Physical Meaning. The expectation value $\langle O \rangle$ can be interpreted as the **average result obtained by measuring the observable O many times on identical copies of the state $|\psi\rangle$.**

1. Prepare many identical copies of the state $|\psi\rangle$.
2. Measure the observable O on each copy.
3. Record the outcomes.
4. Compute the arithmetic mean of the recorded outcomes.

As the number of experiments increases, the average converges to the expectation value $\langle \psi | O | \psi \rangle$.

⚠ Important Clarification

The expectation value is **not necessarily** one of the possible measurement outcomes. It is the **average (more precisely, the probability-weighted average)** of many outcomes, and can take values that are not eigenvalues of the observable. For example, if possible outcomes are $+1$ with probability 50% and -1 with probability 50%, then the expectation value is:

$$(+1) \cdot \frac{1}{2} + (-1) \cdot \frac{1}{2} = 0$$

Although the actual measurement never returns 0, the expectation value is 0 because it represents the average of many measurements. This means that half of the measurements return $+1$ and the other half return -1 , resulting in an average of 0.

The expectation value tells us the “center of mass” of the measurement distribution. **It summarizes the statistical behavior of the measurement in a single number.**

❓ **Why are we interested in the average value of an observable rather than in the probability of specific outcomes?** Because in many real situations we do not **care about** the result of a single measurement, but about the **overall behavior of the system**. Also, it proves a stable, experimentally meaningful quantity that summarizes the statistical behavior of an observable over many measurements, even when individual outcomes are random.

✂ **How can we compute the expectation value?**

To compute the expectation value $\langle O \rangle$ of an observable O in a state $|\psi\rangle$, we start from the Spectral Theorem (page 126):

$$O = \sum_k \lambda_k |k\rangle\langle k|$$

Substitute this into the expectation value formula (page 136):

$$\begin{aligned} \langle \psi | O | \psi \rangle &= \langle \psi | \left(\sum_k \lambda_k |k\rangle\langle k| \right) | \psi \rangle \\ &\downarrow \text{ use linearity of the inner product} \\ &= \sum_k \lambda_k \langle \psi | k \rangle \langle k | \psi \rangle \end{aligned}$$

Using the property of inner products (page 7):

$$\langle \psi | k \rangle = \overline{\langle k | \psi \rangle} \quad \implies \quad \overline{\langle k | \psi \rangle} \langle k | \psi \rangle = |\langle k | \psi \rangle|^2$$

Here, the Born rule (page 79) states that $|\langle k | \psi \rangle|^2$ is the probability of measuring the outcome λ_k when measuring O on the state $|\psi\rangle$. Therefore, we can rewrite the expectation value as:

$$p_k = |\langle k | \psi \rangle|^2 \quad \implies \quad \langle \psi | O | \psi \rangle = \sum_k \lambda_k p_k \quad (57)$$

This formula shows that the expectation value is the **weighted average** of the possible outcomes λ_k , where each outcome is weighted by its probability p_k . In other words, the **expectation value is the sum of all possible outcomes multiplied by their respective probabilities**, which is consistent with our interpretation of it as an average over many measurements.

4.8.4 Measuring $|+\rangle$ with the Pauli-Z Observable

After introducing observables, projectors, probabilities, and expectation values, it is useful to analyze a concrete example that combines all these concepts.

Consider the quantum state:

$$|+\rangle = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle)$$

And the Pauli-Z observable:

$$Z = \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix}$$

Calculate the possible measurement outcomes, their probabilities, the post-measurement states, and the expectation value of Z in the state $|+\rangle$.

From the spectral decomposition (page 126) of Z , we know that:

- The **eigenvalues** of Z are $+1$ and -1 :

$$\begin{aligned} \det(Z - \lambda I) &= 0 \\ \det\left(\begin{bmatrix} 1-\lambda & 0 \\ 0 & -1-\lambda \end{bmatrix}\right) &= 0 \\ (1-\lambda)(-1-\lambda) &= 0 \\ \lambda &= \pm 1 \end{aligned}$$

- The **first eigenvector** $|v_1\rangle$ is $|0\rangle$:

$$\begin{aligned} (Z - 1I)|v_1\rangle &= 0 \\ \begin{bmatrix} 1-1 & 0 \\ 0 & -1-1 \end{bmatrix} \begin{bmatrix} x \\ y \end{bmatrix} &= 0 \\ \begin{bmatrix} 0 & 0 \\ 0 & -2 \end{bmatrix} \begin{bmatrix} x \\ y \end{bmatrix} &= 0 \\ \begin{cases} 0 \cdot x + 0 \cdot y = 0 \\ 0 \cdot x - 2 \cdot y = 0 \end{cases} &\implies y = 0 \end{aligned}$$

So any vector of the form $\begin{pmatrix} x \\ y \end{pmatrix} \xrightarrow{y=0} \begin{bmatrix} x \\ 0 \end{bmatrix}$ is an eigenvector. We choose the simplest one $(1, 0)$, and then we normalize it:

$$\left\| \begin{bmatrix} 1 \\ 0 \end{bmatrix} \right\| = \sqrt{1^2 + 0^2} = 1$$

Therefore, the normalized eigenvector is:

$$|v_1\rangle = 1 \cdot \begin{bmatrix} 1 \\ 0 \end{bmatrix} = |0\rangle$$

- Similarly, the **second eigenvector** $|v_2\rangle$ is $|1\rangle$:

$$\begin{aligned}
 (Z + 1I) |v_2\rangle &= 0 \\
 \begin{bmatrix} 1+1 & 0 \\ 0 & -1+1 \end{bmatrix} \begin{bmatrix} x \\ y \end{bmatrix} &= 0 \\
 \begin{bmatrix} 2 & 0 \\ 0 & 0 \end{bmatrix} \begin{bmatrix} x \\ y \end{bmatrix} &= 0 \\
 \begin{cases} 2 \cdot x + 0 \cdot y = 0 \\ 0 \cdot x + 0 \cdot y = 0 \end{cases} &\implies x = 0
 \end{aligned}$$

So any vector of the form $\begin{pmatrix} x \\ y \end{pmatrix} \xrightarrow{x=0} \begin{bmatrix} 0 \\ y \end{bmatrix}$ is an eigenvector. We choose the simplest one $(0, 1)$, and then we normalize it:

$$\left\| \begin{bmatrix} 0 \\ 1 \end{bmatrix} \right\| = \sqrt{0^2 + 1^2} = 1$$

Therefore, the normalized eigenvector is:

$$|v_2\rangle = 1 \cdot \begin{bmatrix} 0 \\ 1 \end{bmatrix} = |1\rangle$$

Therefore:

- The possible **measurement outcomes** are **+1** and **-1**;
- The corresponding **eigenstates** are **$|0\rangle$** and **$|1\rangle$** ;
- The **measurement operators** are:

$$M_0 = |0\rangle \langle 0|, \quad M_1 = |1\rangle \langle 1|$$

≡ Measurement Probabilities

The state $|+\rangle$ is an equal superposition of $|0\rangle$ and $|1\rangle$:

$$|+\rangle = \frac{1}{\sqrt{2}} |0\rangle + \frac{1}{\sqrt{2}} |1\rangle$$

Therefore, the amplitudes are:

$$\alpha = \frac{1}{\sqrt{2}}, \quad \beta = \frac{1}{\sqrt{2}}$$

Using the Born rule:

$$p_0 = |\alpha|^2 = \frac{1}{2}, \quad p_1 = |\beta|^2 = \frac{1}{2}$$

Thus:

- There is a 50% probability of obtaining the outcome +1;
- There is a 50% probability of obtaining the outcome -1.

Post-Measurement States

If the measurement outcome is:

- $+1$, the state collapses to $|0\rangle$;
- -1 , the state collapses to $|1\rangle$.

Expectation Value

The expectation value of Z in the state $|+\rangle$ is:

$$\langle + | Z | + \rangle = (+1) \cdot \frac{1}{2} + (-1) \cdot \frac{1}{2} = 0$$

Remark

The expectation value is 0, but this does **not** mean that the measurement can return the value 0. The only possible outcomes are:

$$+1 \quad \text{and} \quad -1$$

The value 0 is simply the probability-weighted average of these outcomes over many repeated measurements.

What if the state to be measured is already an eigenstate of the observable?

Let's assume that now we want to calculate the measurement outcomes, probabilities, post-measurement states, and expectation value when the input state is $|0\rangle$ or $|1\rangle$ instead of $|+\rangle$. How we have seen, $|0\rangle$ and $|1\rangle$ are eigenvectors of Z with eigenvalues $+1$ and -1 , respectively. This means that they are already measurement states of the observable Z . Let's analyze what happens in these cases.

- **Measuring $|0\rangle$:** the measurement probabilities of $|0\rangle$ are:

$$|0\rangle = 1 \cdot |0\rangle + 0 \cdot |1\rangle$$

Therefore:

$$p_0 = |\alpha|^2 = 1, \quad p_1 = |\beta|^2 = 0$$

Using observable Z , there is a 100% probability of obtaining the outcome $+1$ and a 0% probability of obtaining the outcome -1 . Moreover, the (post-)measurement outcome is always $+1$, and the post-measurement state remains $|0\rangle$ because we have 100% probability of collapsing to $|0\rangle$ and 0% probability of collapsing to $|1\rangle$. Finally, the expectation value is:

$$\langle 0 | Z | 0 \rangle = (+1) \cdot 1 + (-1) \cdot 0 = +1$$

And indeed, the expectation value confirms that the measurement outcome is always $+1$.

- **Measuring $|1\rangle$:** the measurement probabilities of $|1\rangle$ are:

$$|1\rangle = 0 \cdot |0\rangle + 1 \cdot |1\rangle$$

Therefore:

$$p_0 = |\alpha|^2 = 0, \quad p_1 = |\beta|^2 = 1$$

Using observable Z , there is a 0% probability of obtaining the outcome $+1$ and a 100% probability of obtaining the outcome -1 . Moreover, the (post-)measurement outcome is always -1 , and the post-measurement state remains $|1\rangle$ because we have 0% probability of collapsing to $|0\rangle$ and 100% probability of collapsing to $|1\rangle$. Finally, the expectation value is:

$$\langle 1|Z|1\rangle = (+1) \cdot 0 + (-1) \cdot 1 = -1$$

And indeed, the expectation value confirms that the measurement outcome is always -1 .

In summary, **when a quantum state is already an eigenvector of the observable being measured:**

- The **measurement** outcome is **deterministic**;
- The **probability** of the corresponding eigenvalue is **1**;
- The **state does not change** after the measurement;
- The **expectation value** is exactly the associated **eigenvalue**.

In contrast, when the state is a superposition of eigenvectors (as in the case of $|+\rangle$), the measurement outcome is probabilistic and the expectation value becomes a weighted average of the possible outcomes.

4.8.5 Recovering Probabilities from Expectation Values

In the previous sections, we have seen that the expectation value of an observable is the weighted average of its possible measurement outcomes. But, is possible to go in the opposite direction? That is, **if we know the expectation value, can we determine the probabilities of the individual outcomes?** Let's explore how to get **Probabilities from the Expectation Value**.

Let's consider the Pauli-Z observable as an example.

$$Z = \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix}$$

With (proof at page 138):

- Eigenvalue $+1$ associated with the state $|0\rangle$;
- Eigenvalue -1 associated with the state $|1\rangle$.

Let:

- p_0 be the probability of measuring the state $|0\rangle$;
- p_1 be the probability of measuring the state $|1\rangle$.

Since Pauli-Z is a valid observable, the probabilities must satisfy:

$$p_0 + p_1 = 1$$

Therefore, the expectation value of Z is:

$$\langle Z \rangle = (+1)p_0 + (-1)p_1 = p_0 - p_1$$

Where $+1$ and -1 are the eigenvalues of Z corresponding to the states $|0\rangle$ and $|1\rangle$, respectively. Instead, p_0 and p_1 are the probabilities of obtaining those states upon measurement.

💡 Now, we are interested in the opposite direction: given the expectation value $m = \langle Z \rangle$ (we change the notation just to be general), can we determine p_0 and p_1 ? The answer is yes, and we can derive the formulas for p_0 and p_1 in terms of m (or $\langle Z \rangle$). We have two relationships:

$$\begin{aligned} p_0 + p_1 &= 1 \\ p_0 - p_1 &= m \end{aligned}$$

We can **solve this system of equations to express p_0 and p_1 in terms of m , and thus recover the probabilities from the expectation value.** Let's do that step by step.

Let's try to solve this system of equations to express p_0 and p_1 in terms of m :

$$\begin{aligned}
 \begin{cases} p_0 + p_1 = 1 \\ p_0 - p_1 = m \end{cases} &= \begin{cases} p_0 = 1 - p_1 \\ p_1 = -m + p_0 \end{cases} \\
 &= \begin{cases} p_0 = 1 - p_1 \\ p_1 = -m + (1 - p_1) \end{cases} \\
 &= \begin{cases} p_0 = 1 - p_1 \\ 2p_1 = -m + 1 \end{cases} \\
 &= \begin{cases} p_0 = 1 - p_1 \\ p_1 = \frac{1-m}{2} \end{cases} \\
 &= \begin{cases} p_0 = 1 - \frac{1-m}{2} \\ p_1 = \frac{1-m}{2} \end{cases} \\
 &= \begin{cases} p_0 = \frac{2-(1-m)}{2} \\ p_1 = \frac{1-m}{2} \end{cases} \\
 &= \begin{cases} p_0 = \frac{1+m}{2} \\ p_1 = \frac{1-m}{2} \end{cases}
 \end{aligned}$$

So, we have:

$$p_0 = \frac{1+m}{2} \quad \text{and} \quad p_1 = \frac{1-m}{2} \quad (58)$$

❓ Why is this important? This result shows that the expectation value of the Pauli-Z observable contains enough information to reconstruct the complete probability distribution of the measurement outcomes. In other words, by measuring only the average value $m = \langle Z \rangle$, we can determine:

- The probability p_0 of obtaining the state $|0\rangle$;
- The probability p_1 of obtaining the state $|1\rangle$.

⚠ Not always true in general

For a general observable with more than two outcomes, one expectation value is usually **not enough**. In general, **to determine n unknown probabilities, we need n independent equations**. Normalization provides one equation, so we typically need additional information such as: more expectation values, higher moments (e.g., $\langle O^2 \rangle$), or other constraints to fully determine the probability distribution.

However, if an observable has only two distinct outcomes a and b , then the same idea works. If:

- Outcome a occurs with probability p ,
- Outcome b occurs with probability $1 - p$,

Then the expectation value is:

$$\langle O \rangle = a \cdot p + b \cdot (1 - p) \xrightarrow{\text{solve for } p} p = \frac{\langle O \rangle - b}{a - b} \quad (59)$$

It finds **the probability of the first outcome** a , and the **probability of the second outcome** b can be found by normalization:

$$1 - p = 1 - \frac{\langle O \rangle - b}{a - b} = \frac{a - \langle O \rangle}{a - b} \quad (60)$$

For example, for the Pauli-Z observable, we have $a = +1$ and $b = -1$, so we can recover the probabilities as:

$$p_0 = P(+1) = \frac{\langle Z \rangle - (-1)}{(+1) - (-1)} = \frac{\langle Z \rangle + 1}{2}$$

$$p_1 = P(-1) = \frac{(+1) - \langle Z \rangle}{(+1) - (-1)} = \frac{1 - \langle Z \rangle}{2}$$

4.9 Heisenberg Representation of Quantum Circuits

Up to now, we have described quantum computation using the **Schrödinger representation**. In this approach, the **quantum state evolves over time**, while the observables remain fixed.

However, there is an alternative but completely equivalent description called the **Heisenberg representation**. In this approach, the **quantum state remains fixed**, while the observables evolve instead.

Both descriptions produce exactly the same physical predictions and measurement outcomes. They are just different mathematical viewpoints of the same underlying physics.

☐ Schrödinger Representation

In the **Schrödinger Representation**, a quantum gate U acts directly on the state:

$$|\psi_1\rangle = U |\psi_0\rangle \quad (61)$$

Where:

- $|\psi_0\rangle$ is the initial state;
- U is the unitary operator representing the quantum circuit;
- $|\psi_1\rangle$ is the final state.

The **observable does not change**. For example, if we measure in the computational basis, we use the Pauli-Z observable Z , which **remains the same before and after applying the circuit**. The expectation value after applying the circuit is:

$$\langle \psi_1 | Z | \psi_1 \rangle$$

In this case:

- The **state changes**;
- The **observable stays fixed**.

☐ Heisenberg Representation

In the **Heisenberg Representation**, the state remains unchanged $|\psi_0\rangle$. Instead, the **observable is transformed** according to:

$$Z \longrightarrow U^\dagger Z U \quad (62)$$

Where:

- $U^\dagger$ is the conjugate transpose of the gate U ;
- Z is the original observable;
- U is the gate itself.

The expectation value is then computed as:

$$\langle \psi_0 | U^\dagger Z U | \psi_0 \rangle$$

In this case:

- The **state stays fixed**;
- The **observable changes**.

❓ Why are the two representations equivalent?

Starting from the Schrödinger representation:

$$|\psi_1\rangle = U |\psi_0\rangle$$

The corresponding bra is:

$$\langle \psi_1 | = \langle \psi_0 | U^\dagger$$

Substituting into the expectation value:

$$\begin{aligned} \langle \psi_1 | Z | \psi_1 \rangle &= (\langle \psi_0 | U^\dagger) Z (U | \psi_0 \rangle) \\ &= \langle \psi_0 | U^\dagger Z U | \psi_0 \rangle \end{aligned}$$

Therefore (and this is the key point), the expectation value computed in the Schrödinger representation is exactly equal to the expectation value computed in the Heisenberg representation (see Equation 62):

$$\langle \psi_1 | Z | \psi_1 \rangle = \langle \psi_0 | U^\dagger Z U | \psi_0 \rangle \quad (63)$$

This proves that both representations yield exactly the same measurement result.

🔗 Physical Interpretation

The Schrödinger and Heisenberg representations are two different mathematical viewpoints of the same physical process.

In the **Schrödinger** representation:

- We imagine the quantum state moving through the circuit;
- Gates transform the state;
- Measurements are performed using fixed observables.

In the **Heisenberg** representation:

- We keep the quantum state fixed;
- Gates transform the observables;
- Measurements are performed using transformed observables.

✓ Why is the Heisenberg representation useful?

The Heisenberg representation is useful because it lets us answer a very important question: *what observable is this quantum circuit actually measuring?*

For example, in the Schrödinger representation, suppose we have an initial state $|\psi\rangle$, a quantum circuit H (the Hadamard gate, page 61), and we measure in the computational basis using the observable Z (page 52). *But what does this circuit actually measure?*

To find out, we can switch to the Heisenberg representation and compute the transformed observable:

$$H^\dagger Z H$$

This will give us the new observable that corresponds to the measurement performed by the circuit H . In this case, we find that:

$$H^\dagger Z H = \frac{1}{2} \left(\begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \right) = \frac{1}{2} \begin{bmatrix} 0 & 2 \\ 2 & 0 \end{bmatrix} = \begin{bmatrix} 0 & 1 \\ 1 & 0 \end{bmatrix} = X$$

This means that the circuit H actually measures the observable X (the Pauli- X gate, page 47), not Z . In other words, applying the Hadamard gate before measuring in the computational basis effectively changes our measurement from Z to X .

So, without the Heisenberg representation, we only know the sequence of gates. With the Heisenberg representation, we immediately understand: “*this circuit is actually measuring X !*” This is the real physical meaning of the circuit, and it is crucial for understanding how quantum algorithms work.

Example 16: Analogy with Arithmetic Expressions

Suppose someone gives us:

$$(3 + 5) \times 2 - 16$$

We could compute it step by step. Or we could simplify the whole expression to: 0. The Heisenberg representation does something similar:

- Instead of following every state transformation,
- It simplifies the entire circuit into an equivalent measurement.

Suppose a circuit contains many gates. In the **Schrödinger picture**, we must **track the state after each gate**. In the **Heisenberg picture**, we ask only: *what observable is measured at the end?* Sometimes the answer is a single operator such as X or Z . Sometimes it is a more complicated operator that involves multiple qubits. But in either case, we get a clear understanding of what the circuit does without having to track the state at every step.

4.10 Clifford Gates

4.10.1 Definition

In the previous section, we introduced the Heisenberg representation of quantum circuits. There, we saw that applying a Hadamard gate H and then measuring an observable Z is equivalent to first transforming the observable Z into X and then measuring X :

$$Z \xrightarrow{H} X$$

This naturally leads to an important question: *what kinds of gates transform simple observables into other simple observables?* A particularly important class of gates with this property is known as the **Clifford gates**.

Definition 9: Clifford Gate

A unitary gate U is called a **Clifford Gate** if, for every Pauli operator P (i.e., $P \in \{I, X, Y, Z\}$), the transformed operator

$$U^\dagger P U = P' \quad (64)$$

Is still a Pauli operator (possibly with an overall sign ± 1).

In other words, **Clifford gates map Pauli operators to other Pauli operators under conjugation.**

For a single qubit, the Pauli operators are:

$$I^3, \quad X, \quad Y, \quad Z.$$

Therefore, a single-qubit Clifford gate must transform each of these operators into another operator from the same set (up to sign).

For example:

$$Z \longrightarrow X$$

Is allowed, because X is still a Pauli operator. However:

$$Z \longrightarrow \frac{X + Y}{\sqrt{2}}$$

Is not allowed, because the **result is not a single Pauli operator**.

Multi-Qubit Extension

For n qubits, Pauli operators are formed by taking tensor products of single-qubit Pauli matrices. For two qubits, examples of Pauli operators include:

$$X \otimes I, \quad I \otimes Z, \quad Y \otimes X, \quad Z \otimes Z$$

³Technically, Wolfgang Pauli only defined X , Y , and Z as the Pauli operators because they are the non-trivial ones. However, we include the identity I in the set of Pauli operators for completeness.

For three qubits, examples include:

$$X \otimes I \otimes Z, \quad Y \otimes Y \otimes X$$

In general, an n -qubit Pauli operator has the form:

$$P = P_1 \otimes P_2 \otimes \cdots \otimes P_n$$

Where each P_i is one of the single-qubit Pauli operators $\{I, X, Y, Z\}$.

Example 17: Hadamard Gate is a Clifford Gate

The Hadamard gate H is:

$$H = \frac{1}{\sqrt{2}} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix}$$

Because H is both Hermitian and unitary, we have $H^\dagger = H$ and $H^{-1} = H$. Therefore, we can compute the conjugation of the Pauli operators by H :

$$HPH = P'$$

In practice, the Hadamard gate transforms the Pauli matrices as follows:

$$\begin{aligned} HXH &= \frac{1}{2} \left(\begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \begin{bmatrix} 0 & 1 \\ 1 & 0 \end{bmatrix} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \right) \\ &= \frac{1}{2} \left(\begin{bmatrix} 1 & 1 \\ -1 & 1 \end{bmatrix} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \right) \\ &= \frac{1}{2} \begin{bmatrix} 2 & 0 \\ 0 & -2 \end{bmatrix} \\ &= Z \end{aligned} \tag{65}$$

$$\begin{aligned} HZH &= \frac{1}{2} \left(\begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \right) \\ &= \frac{1}{2} \left(\begin{bmatrix} 1 & -1 \\ 1 & 1 \end{bmatrix} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \right) \\ &= \frac{1}{2} \begin{bmatrix} 0 & 2 \\ 2 & 0 \end{bmatrix} \\ &= X \end{aligned} \tag{66}$$

$$\begin{aligned} HYH &= \frac{1}{2} \left(\begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \begin{bmatrix} 0 & -i \\ i & 0 \end{bmatrix} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \right) \\ &= \frac{1}{2} \left(\begin{bmatrix} i & -i \\ -i & -i \end{bmatrix} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix} \right) \\ &= \frac{1}{2} \begin{bmatrix} 0 & 2i \\ -2i & 0 \end{bmatrix} \\ &= -Y \end{aligned} \tag{67}$$

Each result is still a Pauli operator (up to a sign), confirming that the Hadamard gate is indeed a Clifford gate.

Example 18: CNOT Gate is a Clifford Gate

The CNOT gate (page 99) is:

$$\text{CNOT} = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{bmatrix}$$

As with the Hadamard gate, we can verify that the CNOT gate is a Clifford gate by checking how it transforms the two-qubit Pauli operators. To do this, we compute the tensor products of the single-qubit Pauli operators with the identity (to create two-qubit Pauli operators) and then conjugate them by the CNOT gate (since the CNOT gate is hermitian, we have $\text{CNOT}^\dagger = \text{CNOT}$):

$$\begin{aligned} X \otimes I &= \begin{bmatrix} 0 \cdot \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} & 1 \cdot \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} \\ 1 \cdot \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} & 0 \cdot \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} \end{bmatrix} \\ &= \begin{bmatrix} 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \end{bmatrix} \\ \text{CNOT}(X \otimes I)\text{CNOT} &= \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{bmatrix} \begin{bmatrix} 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \end{bmatrix} \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{bmatrix} \\ &= \begin{bmatrix} 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 1 & 0 & 0 \\ 1 & 0 & 0 & 0 \end{bmatrix} \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{bmatrix} \\ &= \begin{bmatrix} 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \\ 1 & 0 & 0 & 0 \end{bmatrix} \\ &= X \otimes X \end{aligned} \tag{68}$$

For the Z operator, the CNOT gate does not change the first qubit, so we have $Z \otimes I$:

$$\begin{aligned} Z \otimes I &= \begin{bmatrix} 1 \cdot \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} & 0 \cdot \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} \\ 0 \cdot \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} & -1 \cdot \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} \end{bmatrix} \\ &= \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & -1 & 0 \\ 0 & 0 & 0 & -1 \end{bmatrix} \end{aligned}$$

$$\begin{aligned}
\text{CNOT}(Z \otimes I)\text{CNOT} &= \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{bmatrix} \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & -1 & 0 \\ 0 & 0 & 0 & -1 \end{bmatrix} \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{bmatrix} \\
&= \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & -1 \\ 0 & 0 & -1 & 0 \end{bmatrix} \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 0 & 1 \\ 0 & 0 & 1 & 0 \end{bmatrix} \\
&= \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & -1 & 0 \\ 0 & 0 & 0 & -1 \end{bmatrix} \\
&= Z \otimes I
\end{aligned} \tag{69}$$

Therefore, the CNOT gate transforms $X \otimes I$ into $X \otimes X$ and leaves $Z \otimes I$ unchanged. By performing similar calculations for all other two-qubit Pauli operators, we can confirm that the CNOT gate maps every two-qubit Pauli operator to another two-qubit Pauli operator (up to a sign):

- $\text{CNOT}(I \otimes X)\text{CNOT} = I \otimes X$
- $\text{CNOT}(I \otimes Z)\text{CNOT} = Z \otimes Z$

These results confirm that the CNOT gate is indeed a Clifford gate.

4.10.2 Non-Clifford Gates

While the Hadamard and CNOT gates are examples of Clifford gates, there are many other gates that do not have this property. The most important example of a non-Clifford gate is the T gate.

The **T Gate** (also called the $\pi/8$ gate) is a **single-qubit gate that applies a specific phase shift to the state $|1\rangle$, while leaving $|0\rangle$ unchanged**. Its matrix representation is:

$$T = \begin{bmatrix} 1 & 0 \\ 0 & e^{i\pi/4} \end{bmatrix} = \begin{bmatrix} 1 & 0 \\ 0 & \frac{1+i}{\sqrt{2}} \end{bmatrix} \quad (70)$$

This means:

$$T|0\rangle = |0\rangle \quad T|1\rangle = e^{i\pi/4}|1\rangle \quad (71)$$

On the Bloch sphere, the T gate corresponds to a rotation around the Z -axis by an angle of $\pi/4$ (or 45 degrees). In terms of the Pauli operators, the T gate transforms them as follows:

$$\begin{aligned} TXT^\dagger &= \frac{1}{\sqrt{2}}(X + Y) \\ TYT^\dagger &= \frac{1}{\sqrt{2}}(Y - X) \\ TZT^\dagger &= Z \end{aligned} \quad (72)$$

Since the T gate transforms the X and Y operators into linear combinations of X and Y (which are not single Pauli operators), the T gate is **not a Clifford gate**.

Deepening: The T Gate is the Square Root of the S Gate

The T gate is the square root of the Phase gate S (which is a Clifford gate) because applying T twice gives exactly S .

If we apply the T gate twice, we have:

$$T^2 = \begin{bmatrix} 1 & 0 \\ 0 & e^{i\pi/2} \end{bmatrix}$$

Where:

$$e^{i\pi/4} \cdot e^{i\pi/4} = \exp\left(\frac{i\pi}{4} + \frac{i\pi}{4}\right) = \exp\left(\frac{2i\pi}{4}\right) = \exp\left(\frac{i\pi}{2}\right) = e^{i\pi/2}$$

Now using Euler's formula, we can express $e^{i\pi/2}$ as:

$$\begin{aligned} e^{i\theta} &= \cos(\theta) + i \sin(\theta) \\ e^{i\pi/2} &= \cos\left(\frac{\pi}{2}\right) + i \sin\left(\frac{\pi}{2}\right) \\ &= 0 + i \cdot 1 \\ &= i \end{aligned}$$

Therefore, we have:

$$T^2 = \begin{bmatrix} 1 & 0 \\ 0 & i \end{bmatrix} = S$$

Finally, we can also express T as the square root of S :

$$T = \sqrt{S} = \begin{bmatrix} 1 & 0 \\ 0 & \sqrt{i} \end{bmatrix}$$

In summary, applying the T gate twice gives us the S gate, confirming that T is indeed the square root of S .

❓ Why are Non-Clifford Gates important?

The real question is: **why can some quantum circuits be simulated efficiently on a classical computer, while others cannot?** To answer this, we must compare two ways of describing a quantum state.

- The **full state vector representation**, where an n -qubit quantum state has the form (page 89):

$$|\psi\rangle = \sum_{k=0}^{2^n-1} c_k |k\rangle$$

This requires storing 2^n complex amplitudes (e.g., 1 qubit requires 2 amplitudes, 2 qubits require 4 amplitudes, etc.), which **grows exponentially** with the number of qubits.

- The **stabilizer representation**. Certain special states can be described much more compactly. Instead of storing all amplitudes, we store a small set of Pauli operators (stabilizers) that uniquely characterize the state. Only n independent stabilizers are needed for n qubits. For example, 10 qubits can be described by just 10 stabilizers, which is a huge reduction compared to the $2^{10} = 1024$ amplitudes needed in the full state vector representation. This representation **grows only linearly** with the number of qubits, making it much more efficient for certain states.

Clifford gates use the stabilizer representation, because transform Pauli operators into other Pauli operators. Therefore, we start with n stabilizers (n Pauli operators) that describe the initial state, and after applying Clifford gates, we still have n stabilizers that describe the new state. This allows to leave the state description compact and efficient.

❓ **What happens at a Non-Clifford Gate?** Consider the T gate. It transforms, for example, the X operator into a linear combination of X and Y :

$$TXT^\dagger = \frac{1}{\sqrt{2}}(X + Y)$$

The result is not a single Pauli operator, but a sum of two Pauli operators. After another Non-Clifford transformation, each term may split again. So **repeated Non-Clifford gates can cause the number of terms to double repeatedly, leading to exponential growth.**

✂ **Computational Consequence.** Classical simulation cost depends on how much information must be stored.

- Clifford circuits keep the description small.
- Non-Clifford circuits cause the description to grow rapidly.

Therefore, if a circuit contains only Clifford gates, a classical computer can efficiently simulate it. In contrast, if the circuit includes Non-Clifford gates such as T , simulation generally becomes exponentially more difficult.

☆ **So, why are Non-Clifford gates important?** If Clifford circuits are classically simulable, then they cannot provide full quantum computational power. To achieve universal quantum computation, we need gates that escape the stabilizer framework. The T gate does exactly this. By adding the T gate (or any other suitable non-Clifford gate) to the Clifford gate set, we obtain a universal set of quantum gates. This allows us to implement arbitrary quantum algorithms, including computations believed to be infeasible for classical computers.

4.10.3 Stabilizer States

As anticipated in the previous section, a **Stabilizer State** is a **quantum state that can be described** not by listing all of its amplitudes, but by **specifying which Pauli operators leave it unchanged**. This is one of the most elegant ideas in quantum computing and is the foundation of the stabilizer formalism used in quantum error correction and efficient simulation.

Definition 10: Stabilizer State

An n -qubit state $|\psi\rangle$ is a stabilizer state if there exists a Pauli operator P (or, more generally, a set of commuting Pauli operators) such that:

$$P|\psi\rangle = |\psi\rangle \quad (73)$$

This means:

- Applying P does not change the state $|\psi\rangle$.
- The state $|\psi\rangle$ is an eigenvector of P .
- The corresponding eigenvalue is $+1$.

The operator P is called a **Stabilizer** because it “*stabilizes*” the state $|\psi\rangle$.

≡ Meaning of “*stabilize*”. Suppose a transformation leaves an object unchanged. Some examples:

- Rotating a perfect sphere leaves it unchanged;
- Reflecting a symmetric figure may leave it unchanged;
- Applying certain Pauli operators may leave a quantum state unchanged.

In quantum mechanics, if the relation $P|\psi\rangle = |\psi\rangle$ holds, then P is a symmetry of the state $|\psi\rangle$, and we say that P stabilizes $|\psi\rangle$. This means that **the state $|\psi\rangle$ is invariant under the transformation represented by P** .

Example 19: $|0\rangle$ and $|1\rangle$

The Pauli-Z gate is:

$$Z = \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix}$$

Applying Z to $|0\rangle$:

$$Z|0\rangle = \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix} \begin{bmatrix} 1 \\ 0 \end{bmatrix} = \begin{bmatrix} 1 \\ 0 \end{bmatrix} = |0\rangle$$

Therefore, $|0\rangle$ is a stabilizer state and the Pauli-Z operator is one of its stabilizers.

By contrast, applying Z to $|1\rangle$:

$$Z|1\rangle = \begin{bmatrix} 1 & 0 \\ 0 & -1 \end{bmatrix} \begin{bmatrix} 0 \\ 1 \end{bmatrix} = \begin{bmatrix} 0 \\ -1 \end{bmatrix} = -|1\rangle$$

Shows that $|1\rangle$ is not stabilized by Z (since the eigenvalue is -1), and thus $|1\rangle$ is not a stabilizer state with respect to Z .

Example 20: $|+\rangle$

The state $|+\rangle$ is defined as:

$$|+\rangle = \frac{1}{\sqrt{2}}(|0\rangle + |1\rangle)$$

Applying the Pauli-X operator to $|+\rangle$:

$$X|+\rangle = \begin{bmatrix} 0 & 1 \\ 1 & 0 \end{bmatrix} \frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ 1 \end{bmatrix} = \frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ 1 \end{bmatrix} = |+\rangle$$

Therefore, $|+\rangle$ is a stabilizer state and the Pauli-X operator is one of its stabilizers.

Example 21: Bell State

Consider the Bell state (page 114):

$$|\Phi^+\rangle = \frac{1}{\sqrt{2}}(|00\rangle + |11\rangle)$$

Applying the operator $X \otimes X$ to $|\Phi^+\rangle$:

$$\begin{aligned} (X \otimes X) |\Phi^+\rangle &= \frac{1}{\sqrt{2}} (X|0\rangle \otimes X|0\rangle + X|1\rangle \otimes X|1\rangle) \\ &= \frac{1}{\sqrt{2}} (|11\rangle + |00\rangle) = |\Phi^+\rangle \end{aligned}$$

And also applying $Z \otimes Z$:

$$\begin{aligned} (Z \otimes Z) |\Phi^+\rangle &= \frac{1}{\sqrt{2}} (Z|0\rangle \otimes Z|0\rangle + Z|1\rangle \otimes Z|1\rangle) \\ &= \frac{1}{\sqrt{2}} (|00\rangle + |11\rangle) = |\Phi^+\rangle \end{aligned}$$

Therefore, $|\Phi^+\rangle$ is a stabilizer state and both $X \otimes X$ and $Z \otimes Z$ are stabilizers of $|\Phi^+\rangle$.

☰ Multiple Stabilizers

The Equation 73 defines a **stabilizer state with respect to a single Pauli operator** P . However, many quantum states are stabilized by multiple Pauli operators. In fact, for an n -qubit stabilizer state, we typically use n independent commuting stabilizers:

$$P_1, P_2, \dots, P_n$$

Each of these operators satisfies:

$$P_i |\psi\rangle = |\psi\rangle \quad \text{for } i = 1, 2, \dots, n \quad (74)$$

The **set of all such stabilizers forms a group** under multiplication, known as the **Stabilizer Group**.

✔ Why Stabilizers are powerful

A general n -qubit state requires 2^n complex amplitudes to be fully described. However, a stabilizer state can be completely characterized by its n independent stabilizers, which are much fewer in number. Furthermore, each stabilizer is describable with $O(n)$ symbols (since it is a tensor product of n Pauli operators), leading to an efficient representation of the state. Therefore, the description size grows only polynomially (i.e., $O(n)$) rather than exponentially.

For example, for 100 qubits, a full state-vector simulation requires 2^{100} amplitudes; in contrast a stabilizer formalism requires roughly 100 stabilizers. This is why large Clifford circuits can be simulated efficiently on classical computers.

In summary, instead of describing “*what are all amplitudes of the state?*”, we describe “*which symmetries does the state satisfy?*”. This is often dramatically more efficient.

4.11 Limits of Quantum Information

4.11.1 No-Cloning Principle

The **No-Cloning Theorem** states that it is **impossible to create an exact copy of an arbitrary unknown quantum state**. This is not a limitation of current technology, it is a fundamental result derived directly from the **linearity of quantum mechanics**.

❓ Why does it matter?

The no-cloning principle is critical because it prevents:

1. **Violations of quantum mechanics**: cloning would break the rules of **unitarity** and **linearity** of quantum evolution.
2. **No-signaling violation** (section 4.11.3 in depth, page 163): if cloning were possible, we could **instantly send information** across large distances, violating causality.
3. **Infinite data compression**: in theory, we could encode an arbitrarily long classical string into a quantum state and clone it infinitely to retrieve the data using quantum tomography.
4. **Quantum error correction becomes harder**: many classical redundancy techniques rely on copying data, which is not possible in quantum mechanics.

✅ Formal Proof

Let's try to define a hypothetical **cloning unitary operator** U . We assume:

$$U(|x\rangle \otimes |0\rangle) = |x\rangle \otimes |x\rangle$$

This says: *take any qubit $|x\rangle$ and a blank $|0\rangle$, and get two $|x\rangle$* . Now take two arbitrary qubits $|x\rangle$ and $|y\rangle$, and apply the same gate to both:

$$U|x\rangle|0\rangle = |x\rangle|x\rangle \quad U|y\rangle|0\rangle = |y\rangle|y\rangle$$

Since U is a **unitary operator**, it **preserves inner products** and the following statement should be true:

$$\langle x \otimes 0 | y \otimes 0 \rangle = \langle x \otimes x | y \otimes y \rangle$$

Let's compute both sides:

- Left side, before cloning:

$$\begin{aligned} \langle x \otimes 0 | y \otimes 0 \rangle &= \langle x | y \rangle \cdot \langle 0 | 0 \rangle \\ &= \langle x | y \rangle \cdot 1 \\ &= \langle x | y \rangle \end{aligned}$$

- Right side, after cloning:

$$\begin{aligned}\langle x \otimes x | y \otimes y \rangle &= \langle x | y \rangle \cdot \langle x | y \rangle \\ &= \langle x | y \rangle^2\end{aligned}$$

So now're claiming:

$$\langle x | y \rangle = \langle x | y \rangle^2$$

Let's analyze this equation:

- Let $\alpha = \langle x | y \rangle \in \mathbb{C}$
- Then $\alpha = \alpha^2 \Rightarrow \alpha - \alpha^2 = 0 \Rightarrow \alpha(\alpha - 1) = 0$

So this is only true if $\alpha = 0$ or $\alpha = 1$:

- The states are **identical**; same direction, same vector:

$$\langle x | y \rangle = 1$$

- The states are **orthogonal**; completely distinguishable:

$$\langle x | y \rangle = 0$$

Unfortunately, for **arbitrary quantum states**, the inner product is **almost always** somewhere between 0 and 1. Only in **special cases** (perfect alignment or perfect orthogonality) is it exactly 0 or 1. That's why we say:

$$\langle x | y \rangle \neq 0, 1 \text{ in general}$$

This is **exactly why the no-cloning proof works**, because it **fails for general** (non-orthogonal) **input states**, which are the rule rather than the exception.

⚠ Apparent Violation via CNOT

Let's explore a common misconception. We apply a CNOT gate with:

- Control qubit $v_A = a_0 |0\rangle + a_1 |1\rangle$
- Target qubit $v_B = |0\rangle$

Naively, one might write:

$$\text{CNOT}(v_A, v_B) = v_A \otimes (v_A \oplus 0) = v_A \otimes v_A$$

It **looks like we cloned** v_A ! But this is incorrect because:

- That informal rule $v_A \oplus v_B$ **only works for classical basis states** ($|0\rangle$ or $|1\rangle$).
- When v_A is in a **superposition**, this model breaks.

What really happens is:

1. Initial state:

$$v_A \otimes |0\rangle = a_0 |00\rangle + a_1 |10\rangle$$

2. Apply CNOT (flip second bit if control is 1):

$$\Rightarrow a_0 |00\rangle + a_1 |11\rangle$$

This is **not** a clone! It's an **entangled state**, we cannot factor it as $|\psi\rangle \otimes |\psi\rangle$. Compare with actual cloned state:

$$(a_0 |0\rangle + a_1 |1\rangle) \otimes (a_0 |0\rangle + a_1 |1\rangle) = a_0^2 |00\rangle + a_0 a_1 |01\rangle + a_0 a_1 |10\rangle + a_1^2 |11\rangle$$

They're **clearly different**: cloning would produce 4 terms, but CNOT produces only 2. Thus CNOT **does not** clone a general qubit. It **creates entanglement**, not copies.

4.11.2 No-Deleting Principle

The **No-Deleting Theorem** states that it is **impossible to delete an arbitrary unknown quantum state**. In other words, **there does not exist a unitary operator** U that can take a pair of identical qubits $|x\rangle \otimes |x\rangle$ and produce:

$$U(|x\rangle \otimes |x\rangle) = |0\rangle \otimes |x\rangle$$

This operation would “delete” the first copy of $|x\rangle$, replacing it with a standard $|0\rangle$, while leaving the second untouched.

❓ Why is deletion a problem?

If we could delete an arbitrary state, we could:

- Circumvent information preservation in quantum systems (which must be **unitary and reversible**).
- Violate **quantum linearity**, much like cloning would.
- Enable undesirable operations that break the **symmetry and reversibility** of quantum evolution.

✅ Formal Proof

Let’s assume that such a deleting unitary U exists. We define:

$$U(|x\rangle \otimes |x\rangle) = |0\rangle \otimes |x\rangle \quad U(|y\rangle \otimes |y\rangle) = |0\rangle \otimes |y\rangle$$

Take the inner product between both results:

- Left side, *before* deleting:

$$\langle x | \langle x | \cdot U^\dagger U \cdot | y \rangle | y \rangle$$

Because $U^\dagger U = I$, and inner products distribute:

$$= \langle x | y \rangle \cdot \langle x | y \rangle = \langle x | y \rangle^2$$

- Right side, *after* deleting:

$$\langle x | 0 \rangle \cdot \langle y | 0 \rangle = \langle x | y \rangle$$

So now we’re saying:

$$\langle x | y \rangle^2 = \langle x | y \rangle \quad \Rightarrow \quad \langle x | y \rangle \cdot (\langle x | y \rangle - 1) = 0$$

So the only possible solutions are:

$$\langle x | y \rangle = 0 \quad (\text{orthogonal}) \quad \text{or} \quad \langle x | y \rangle = 1 \quad (\text{identical})$$

But for **general quantum states**, $\langle x | y \rangle \notin \{0, 1\}$, so we’ve reached a **contradiction**. Therefore, **no such deletion operator** U **can exist for arbitrary stats**.

Physical Meaning

The no-deleting principle complements the **no-cloning principle**:

- We can't **make** copies of unknown quantum states (no-cloning)
- We can't **erase** arbitrary copies either (no-deleting)

These theorems emphasize that **quantum information is conserved**:

- It cannot be copied freely
- It cannot be erased freely
- It can only be **transferred** (e.g., through teleportation or interaction)

4.11.3 No-Signaling Principle

The **No-Signaling Theorem** asserts that: **no information can be transmitted faster than the speed of light, even using entangled quantum systems.**

Although **entanglement leads to instantaneous correlations** between distant qubits, it **does not allow communication** or information transfer without a classical channel.

This principle **preserves causality** and ensures that quantum mechanics remains compatible with **special relativity**.

✓ Explained Proof

To understand the **no-signal principle** in quantum mechanics, consider the classical scenario involving two observers, Alice and Bob, who share an **entangled pair** of qubits. Specifically, they share the Bell state:

$$|\Phi^+\rangle = \frac{1}{\sqrt{2}} (|00\rangle + |11\rangle)$$

Alice has qubit a , Bob has qubit b , and they are located far apart, even at opposite ends of the universe.

What happens when Alice measures? Suppose Alice chooses to **measure her qubit** in the computational basis.

- If she gets outcome $|0\rangle$, the join state **collapses** to $|00\rangle$
- If she gets $|1\rangle$, the state collapses to $|11\rangle$

In both cases, Bob's qubit becomes **perfectly correlated** with Alice's result. **So yes**, Alice's measurement causes the collapse of Bob's qubit; instantly, no matter the distance.

Can Bob detect this? Here's the crucial point: **Bob cannot tell whether Alice has measured her qubit.**

Why? Because from **Bob's perspective**, before doing anything, his own qubit is described by the **reduced density matrix**:

$$\rho_B = \frac{1}{2} |0\rangle \langle 0| + \frac{1}{2} |1\rangle \langle 1|$$

This is a **completely mixed state**. If Bob measures it, he gets:

- 50% chance of $|0\rangle$
- 50% chance of $|1\rangle$

Now suppose **Alice has already measured**, and the state is now $|00\rangle$.

- Bob's qubit is now **definitely** $|0\rangle$

- But Bob doesn't know that, and he has **no way to know**
- The only way for him to learn this is:
 1. **To measure** (and discover the value)
 2. Or **to be told** by Alice via classical communication

Why this preserves No-Signaling. Even though **Alice's measurement affects the state** of Bob's qubit, **it does not change what Bob sees statistically**, unless he receives a message from her. Therefore:

- Alice **cannot use entanglement** to send messages faster than light.
- Bob's observable outcomes are **indistinguishable** whether Alice measured or not.
- **Entanglement creates correlations**, not communication.

Summary of the story

- Entanglement causes **instant collapse of joint state** when one qubit is measured.
- But the **other party cannot detect** this collapse unless they **measure** or are **told**.
- No observable effect on Bob's side = **no information transfer** = no violation of causality.

🔍 Why it matters?

The no-signaling principle **guarantees**:

- ✓ **No faster-than-light communication**, preserving consistency with relativity
- ✓ **No “quantum telepathy”**, even in systems that exhibit entanglement
- ✓ Measurement outcomes are **random locally**, even when entanglement exists globally.

References

- [1] Cremonesi Paolo. Quantum computing. Slides from the HPC-E master's degree course on Politecnico di Milano, 2024.

Index

A

Azimuthal Angle	35
-----------------	----

B

Basis	16
Bell States	114
Bloch Sphere Representation of a Qubit	35
Born rule	79
Bra	9
Bra-Ket notation	74

C

Clifford Gate	148
Complete Orthonormal Basis	132
Completeness Relation	132
Controlled NOT (CNOT) Gate	99
Controlled-Controlled-NOT (CCNOT) Gate	108

E

Eigenstate	49
entangled	113
Entanglement	87
Entangling Gates	116
Expectation Value	136

G

Generic Controlled Gate (CU)	102
------------------------------	-----

H

Hadamard basis	61
Heisenberg Representation	145

I

Inner Product of Kets	74
-----------------------	----

K

Ket	9
Kronecker delta	133

M

Measurement	12
Measurement Operator	130

N

No-Cloning Theorem	30, 43, 158
No-Deleting Theorem	43, 161
No-Signaling Theorem	163

O

Observable	120
------------	-----

Orthonormal Basis	16
Outer Product of Kets	74
P	
Pauli Gates	46
Pauli matrices	47
Photon	12
Polarization	12
Polarizer	14
Probabilities from the Expectation Value	142
Projection Operator	76
Projector	76
Q	
Quantum Circuit	72
Quantum Gates	42
Quantum System	11
Qubit	15
R	
Relative Phase	34
S	
Schrödinger Representation	145
Single Qubit Gates: Hadamard Gate (S)	61
Single Qubit Gates: Identity Gate	45
Single Qubit Gates: Initialization	41
Single Qubit Gates: Logic Gates	38
Single Qubit Gates: Measurement	39
Single Qubit Gates: Pauli-X Gate	47
Single Qubit Gates: Pauli-Y Gate	56
Single Qubit Gates: Pauli-Z Gate	52
Single Qubit Gates: Phase Gate (S)	59
Single Qubit Gates: T Gate	152
Single-Qubit Gates	42
Spectral Theorem	126
Stabilizer	155
Stabilizer Group	157
Stabilizer State	155
State Space	32
Superposition	23
SWAP gate	105
T	
Tensor Product	84
Toffoli Gate	108
W	
When is a state entangled?	90
When is a state separable?	90