

AMENDMENT NO. 1 FEBRUARY 2018
TO
IS 16227 (Part 5) : 2014/IEC 61869-5 : 2011 INSTRUMENT TRANSFORMERS
PART 5 ADDITIONAL REQUIREMENTS FOR CAPACITORS VOLTAGE
TRANSFORMERS

This Amendment No. 1 is identical to Corrigendum 1 to IEC 61869-5 : 2011 issued by International Electrotechnical Commission.

C O R R I G E N D U M 1

6.502.2 Transients of ferro-resonance oscillations

Replace the existing formula by the following formula:

$$\hat{\varepsilon}_F = \frac{\hat{U}_{S(t=T_F)} - \frac{\sqrt{2} \times U_P}{k_r}}{\frac{\sqrt{2} \times U_P}{k_r}} = \frac{k_r \times \hat{U}_{S(t=T_F)} - \sqrt{2} \times U_P}{\sqrt{2} \times U_P}$$

Add the following new line at the end of the existing list:

t is the running time of the ferro-resonance oscillation test.

Table 508 – Test voltage for temperature rise test

Replace the existing Table 508 by the following table:

Table 508 — Test voltage for temperature rise test

Burden	Rated burden						Thermal limiting output from a secondary winding ^a	
Voltage factor & fault duration time	$F_V = 1,2$ continuous		$F_V = 1,5$ or $1,9$ 30 s		$F_V = 1,9$ 8 h		-	-
Configuration of test	Electro-magnetic unit	Complete capacitor voltage transformer	Electro-magnetic unit	Complete capacitor voltage transformer	Electro-magnetic unit	Complete capacitor voltage transformer	Electro-magnetic unit	Complete capacitor voltage transformer
Test voltage till temperature rise is below 1 K/h.	$U_S = \frac{12 \times U_{Pr}}{k_r}$	$U_P = 1,2 \times U_{Pr}$	$U_S = \frac{12 \times U_{Pr}}{k_r}$	$U_P = 1,2 \times U_{Pr}$	$U_S = \frac{12 \times U_{Pr}}{k_r}$	$U_P = 1,2 \times U_{Pr}$	$U_C = \frac{U_{Pr}}{K_C}$	$U_P = U_{Pr}$
Test voltage for fault duration time	—	—	$U_S = \frac{F_V \times U_{Pr}}{k_r}$	$U_P = F_V \times U_{Pr}$	$U_S = \frac{1,9 \times U_{Pr}}{k_r}$	$U_P = 1,9 \times U_{Pr}$	—	—

^aAdditional test if a thermal limiting output is specified.