

$$1. 1101101_2 - 1010101_2$$

$$a) C_b^2 = 2^8 - 1010101_2 = 10101011_2$$

b) suma

$$\begin{array}{r} 01101101_2 \\ + 10101011_2 \\ \hline 10011000_2 \end{array}$$

↑ signo (+)

c) Resultado: 11000_2

$$2. 3271762_8 - 2212345_8$$

$$a) C_b^8 = 8^8 - 2212345_8 = 75565433_8$$

b) suma:

$$\begin{array}{r} 03271762_8 \\ + 75565433_8 \\ \hline 1057415_8 \end{array}$$

↑ signo (+)

c) Resultado: 1057415_8

$$3. -1A3D27F_{16} - 64151423_8$$

e) Complemento resultado

$$a) \text{ Convertir } b \ 8 \rightarrow 16 = D0D313_{16}$$

$$b) C_a^{16} = 16^9 - 1A3D27F = FFE5C2D81_{16}$$

$$c) C_b^{16} = 16^9 - D0D313_{16} = FFF2F2CED_{16}$$

$$C_R^{16} = 16^9 - FD8B546E = F0274AB92_{16}$$

d) suma

$$\begin{array}{r} FE5C2D81_{16} \\ + FF2F2CED_{16} \\ \hline FD8B5A6E \end{array}$$

↓ signo Negativo (-)

f) Resultado - $F0274AB92_{16}$

$$4. 3052_6 - 455532_6$$

$$a) C'_6 = 6^7 - 455532_6 = 5100024_6$$

b) Suma

$$\begin{array}{r} 0 \quad 00 \quad 3052_6 \\ + 5 \quad 10 \quad 0024_6 \\ \hline 5 \quad 10 \quad 3120 \end{array}$$

↑ signo (-)

$$c) C'_6 = 6^7 - 103120_6 =$$

$$\begin{array}{r} \times 555 \quad 5550 \\ - \quad 10 \quad 3120 \\ \hline 5 \quad 45 \quad 2440 \end{array}$$

$$d) \text{Resultado} = -45 \quad 2440_6$$

$$5. 1111101_2 - 101_2$$

$$a) C'_2 = 2^8 - 101_2 = 1111 \quad 1011_2$$

$$\begin{array}{r} 0 \quad 111 \quad 1101_2 \\ + 1 \quad 111 \quad 1011_2 \\ \hline \cancel{0} \quad 111 \quad 1000 \end{array}$$

↑ signo +

$$c) \text{Resultado: } 1111000_2$$

$$6. 45_7 - 5612_7 = -5534_7 \rightarrow 65534_7$$

$$7. 14201_5 - 42214_5 = -23013_5 \rightarrow 423013_5$$

$$8. 22101_3 - 11222_3 = 10102_3$$