



$$\text{ADU} \leq 260 \text{ B (Modbus TCP)}$$

ADU (TCP):



$$\text{PDU} \leq 253 \text{ B}$$

PDU (FC03/04 response):



$$\text{MaxReadRegisters} = \left\lfloor \frac{\text{maxPDU} - \text{FC} - \text{byteCount}}{\text{bytes/register}} \right\rfloor = \left\lfloor \frac{253 - 1 - 1}{2} \right\rfloor = \left\lfloor \frac{251}{2} \right\rfloor =$$

125

the same budget, applied to bits instead of 16-bit registers and fixed at 2000 by §6.1/§6.2 rather than derived, bounds FC01/02 reads; §6.11/§6.12 subtract a 5-byte address/quantity/byteCount header instead of 2, giving 1968 coils and 123 registers for the write-multiple codes.