

Exp No: 4- 7-Segment Display using AT89C51

Objectives:

1. To interface a 7-segment display with the AT89C51.
2. To display decimal digits using a 7-segment display.
3. To understand output display interfacing.

Program:

ORG 000H

UP:MOV P2,#0C0H

ACALL DELAY

MOV P2,#0F9H

ACALL DELAY

MOV P2,#0A4H

ACALL DELAY

MOV P2,#0B0H

ACALL DELAY

MOV P2,#99H

ACALL DELAY

MOV P2,#92H

ACALL DELAY

MOV P2,#82H

ACALL DELAY

MOV P2,#0F8H

ACALL DELAY

MOV P2, #80H

ACALL DELAY

MOV P2, #90H

ACALL DELAY

DELAY: MOV R5, #10

H1: MOV R4, #180

H2: MOV R3, #255

H3: DJNZ R3, H3

DJNZ R4, H2

DJNZ R5, H1

RET

END

Output:

