

EXHAUSTIVE ACADEMIC REVIEW PROTOCOL

**ELECTRICAL INSTRUMENTATION: PHASE 1**

**Advanced Capacitive Transducer Systems**

*Grassroots Derivations, Orthogonal Topologies, and Engineering Physics*

Semester Preparation Masterclass

**Contents**

|          |                                                         |           |
|----------|---------------------------------------------------------|-----------|
| <b>1</b> | <b>Fundamentals of Capacitive Transduction</b>          | <b>3</b>  |
| <b>2</b> | <b>Variable Air Gap (Distance) Transducers</b>          | <b>4</b>  |
| 2.1      | Physical Architecture . . . . .                         | 4         |
| 2.2      | Grassroots Mathematical Derivation . . . . .            | 4         |
| 2.3      | Engineering Significance and Non-Linearity . . . . .    | 5         |
| <b>3</b> | <b>Variable Area (Translational) Transducers</b>        | <b>6</b>  |
| 3.1      | Physical Architecture . . . . .                         | 6         |
| 3.2      | Grassroots Mathematical Derivation . . . . .            | 6         |
| 3.3      | Engineering Significance of Perfect Linearity . . . . . | 7         |
| <b>4</b> | <b>Variable Area (Angular / Disc) Transducers</b>       | <b>8</b>  |
| 4.1      | Physical Architecture . . . . .                         | 8         |
| 4.2      | Grassroots Mathematical Derivation . . . . .            | 8         |
| 4.3      | Sensitivity Proportionality Proof . . . . .             | 9         |
| <b>5</b> | <b>Composite Dielectrics (Thickness Gauge)</b>          | <b>10</b> |
| 5.1      | Physical Architecture . . . . .                         | 10        |
| 5.2      | Derivation of the "K" Factor Equivalence . . . . .      | 10        |

|          |                                                     |           |
|----------|-----------------------------------------------------|-----------|
| <b>6</b> | <b>The Push-Pull (Differential) Fix</b>             | <b>12</b> |
| 6.1      | The Non-Linearity Crisis . . . . .                  | 12        |
| 6.2      | The Three-Plate Differential Architecture . . . . . | 12        |
| 6.3      | Mathematical Proof of Linearization . . . . .       | 12        |
| <b>7</b> | <b>Fringing Fields &amp; The Guard Electrode</b>    | <b>14</b> |
| 7.1      | The Fringing Field Crisis . . . . .                 | 14        |
| 7.2      | The Guard Ring Solution . . . . .                   | 14        |

# Fundamentals of Capacitive Transduction

---

A capacitive transducer is a passive electronic sensor that operates on the fundamental principles of electrostatics. It translates a physical measurand (such as displacement, pressure, level, or humidity) into a measurable change in electrical capacitance.

The absolute grassroots governing equation for an ideal parallel-plate capacitor is:

$$C = \frac{\epsilon_0 \epsilon_r A}{d} \quad (1)$$

Where:

- $C$  is the total capacitance in Farads (F).
- $\epsilon_0$  is the absolute permittivity of free space ( $8.854 \times 10^{-12}$  F/m).
- $\epsilon_r$  is the relative permittivity (dielectric constant) of the medium between the plates.
- $A$  is the effective overlapping geometric area of the plates ( $m^2$ ).
- $d$  is the absolute separation distance between the plates ( $m$ ).


To synthesize a viable transducer, an engineer must rigorously lock two of these three core variables ( $\epsilon_r, A, d$ ) as absolute constants, while allowing the physical measurand to dynamically modulate the third.

# Variable Air Gap (Distance) Transducers

---

## Physical Architecture

In this configuration, the overlapping area ( $A$ ) and the dielectric medium (air,  $\epsilon_r \approx 1$ ) are held rigidly constant. The physical input is a translational mechanical displacement ( $x$ ) that directly modulates the separation distance ( $d$ ) between the plates.



## Grassroots Mathematical Derivation

Let the initial resting separation gap be  $d$ . The static baseline capacitance is defined as:

$$C_0 = \frac{\epsilon A}{d} \quad (2)$$

When the moving electrode is subjected to a downward displacement of magnitude  $x$ , the separation gap dynamically compresses to  $(d - x)$ . The new instantaneous capacitance becomes:

$$C_x = \frac{\epsilon A}{d - x} \quad (3)$$

To analyze the linearity of this function, we mathematically factor out  $d$  from the denominator:

$$C_x = \frac{\epsilon A}{d \left(1 - \frac{x}{d}\right)} = C_0 \left(1 - \frac{x}{d}\right)^{-1} \quad (4)$$

Applying the Binomial Taylor Series Expansion (valid strictly under the assumption that the displacement is smaller than the gap,  $x < d$ ):

$$C_x = C_0 \left[ 1 + \left(\frac{x}{d}\right) + \left(\frac{x}{d}\right)^2 + \left(\frac{x}{d}\right)^3 + \dots \right] \quad (5)$$

## Engineering Significance and Non-Linearity

The mathematical presence of higher-order squared and cubed terms  $\left(\left(\frac{x}{d}\right)^2, \left(\frac{x}{d}\right)^3\right)$  serves as absolute proof that the transfer function of a variable distance capacitive transducer is **fiercely non-linear (hyperbolic)**.

This architecture can only be deployed for *microscopic* displacements where  $x \ll d$ . Under such restrictive boundary conditions, the higher-order terms mathematically decay to zero, allowing the engineer to utilize a localized linear approximation:

$$\Delta C \approx C_0 \left(\frac{x}{d}\right) \quad (6)$$

The base sensitivity ( $S$ ) for microscopic variations is:

$$S = \frac{dC}{dx} = \frac{\epsilon A}{d^2} \quad [\text{Farads/meter}] \quad (7)$$


Notice that sensitivity is inversely proportional to the square of the initial gap ( $d^2$ ).

# Variable Area (Translational) Transducers

---

## Physical Architecture

To circumvent the catastrophic non-linearity of the variable-gap design, engineers freeze the gap distance ( $d$ ) as an absolute constant. Instead, the physical input displacement ( $x$ ) slides one electrode laterally past the other, directly modulating the overlapping geometric area ( $A$ ).



## Grassroots Mathematical Derivation

Let both rectangular plates possess a constant longitudinal length  $L$  and a constant transverse width  $w$  (extending orthogonally into the Z-axis of the page). The initial, un-displaced overlapping area is  $A_0 = L \cdot w$ .

When the upper electrode is mechanically sheared laterally by a displacement vector  $x$ , the length of the actively overlapping region is physically reduced to  $(L - x)$ . The new dynamic overlapping area becomes:

$$A_x = w(L - x) \quad (8)$$

Substituting this dynamic area into the fundamental capacitance equation yields the system transfer function:

$$C_x = \frac{\epsilon \cdot w \cdot (L - x)}{d} = \frac{\epsilon w L}{d} - \frac{\epsilon w x}{d} \quad (9)$$

## Engineering Significance of Perfect Linearity

To analyze the sensitivity ( $S$ ) of this transducer, we extract the first mathematical derivative with respect to the input displacement  $x$ :

$$S = \frac{dC_x}{dx} = \frac{d}{dx} \left[ \frac{\epsilon w L}{d} - \frac{\epsilon w x}{d} \right] = -\frac{\epsilon w}{d} \quad [\text{Farads/meter}] \quad (10)$$


**Crucial Academic Conclusion:** The final expression for sensitivity ( $-\frac{\epsilon w}{d}$ ) is comprised entirely of absolute physical constants ( $\epsilon$ ,  $w$ ,  $d$ ). Because the input variable  $x$  has vanished entirely from the derivative, the slope of the capacitance-displacement curve is a pure, immutable constant. This proves mathematically that the variable-area transducer exhibits **perfect, flawless linearity** across its entire theoretical range of motion. No external electronic linearization networks are required.

# Variable Area (Angular / Disc) Transducers

---

## Physical Architecture

For rotational mechanics, the translational sliding plates are replaced with two identical semi-circular conductive discs. One disc (the Stator) is rigidly mounted to the chassis. The second disc (the Rotor) is concentrically affixed to the rotating measurement shaft, separated by a microscopic, rigidly maintained air gap  $d$ .



## Grassroots Mathematical Derivation

Let both semi-circular discs possess a maximum effective radius  $r$ . When the shaft undergoes an angular rotation, the overlapping geometry forms a sector of a circle. Let the angle of this overlapping sector be  $\theta$ , strictly measured in radians.

From standard geometric calculus, the absolute area of a circular sector is:

$$A(\theta) = \frac{1}{2}r^2\theta \quad (11)$$

Substituting this dynamic angular area directly into the electrostatic capacitance equation yields:

$$C(\theta) = \frac{\epsilon \left( \frac{1}{2}r^2\theta \right)}{d} = \frac{\epsilon \cdot r^2 \cdot \theta}{2d} \quad (12)$$



## Sensitivity Proportionality Proof

To extract the sensitivity ( $S$ ) of this angular transducer, we differentiate the capacitance with respect to the input angle  $\theta$ :

$$S = \frac{dC}{d\theta} = \frac{d}{d\theta} \left[ \frac{\epsilon \cdot r^2 \cdot \theta}{2d} \right] = \frac{\epsilon \cdot r^2}{2d} \quad [\text{Farads/radian}] \quad (13)$$


**Academic Conclusions required for Semester Exams:** By analyzing the final block for sensitivity  $S$ , we mathematically prove three distinct operational facts: 1. Because  $\theta$  has vanished via derivation, the sensitivity  $S$  is a pure constant, guaranteeing that the angular transducer is **perfectly linear**. 2. Sensitivity is **directly proportional to the square of the radius** ( $S \propto r^2$ ). Doubling the radius of the disc quadruples the signal output. 3. Sensitivity is **inversely proportional to the gap distance** ( $S \propto 1/d$ ).

# Composite Dielectrics (Thickness Gauge)

---

## Physical Architecture

This highly specific architecture is deployed in industrial manufacturing to continuously monitor the thickness of insulating sheets (glass, paper, plastic) rolling off a production line. The metallic electrodes are bolted in place with a massive, constant gap  $d$ . The solid material acts as a moving dielectric core.



## Derivation of the "K" Factor Equivalence

The transducer physically manifests as two discrete capacitors connected perfectly in **series**: 1. The remaining air gap capacitor:  $C_{air} = \frac{\epsilon_0 A}{d-t}$  2. The solid dielectric capacitor:  $C_{solid} = \frac{\epsilon_0 \epsilon_r A}{t}$

The total equivalent series capacitance  $C_{eq}$  is calculated via the product-over-sum rule:

$$C_{eq} = \frac{C_{air} \cdot C_{solid}}{C_{air} + C_{solid}} = \frac{\left(\frac{\epsilon_0 A}{d-t}\right) \left(\frac{\epsilon_0 \epsilon_r A}{t}\right)}{\frac{\epsilon_0 A}{d-t} + \frac{\epsilon_0 \epsilon_r A}{t}} \quad (14)$$

Multiply the numerator and denominator by  $(d-t)t$  to destroy the complex fractions:

$$C_{eq} = \frac{\epsilon_0 \epsilon_r A}{\epsilon_r (d-t) + t} = \frac{\epsilon_0 \epsilon_r A}{\epsilon_r d - t(\epsilon_r - 1)} \quad (15)$$

To normalize the equation, we mathematically extract the base capacitance of the completely empty air gap ( $C_0 = \frac{\epsilon_0 A}{d}$ ). We achieve this by factoring out  $\epsilon_r d$  from the denominator:

$$C_{eq} = \frac{\epsilon_0 \epsilon_r A}{\epsilon_r d \left[ 1 - \frac{(\epsilon_r - 1)t}{\epsilon_r d} \right]} = \frac{\frac{\epsilon_0 A}{d}}{1 - \left[ \frac{\epsilon_r - 1}{\epsilon_r} \right] t} \quad (16)$$

We define an absolute scalar constant,  $K$ , strictly as:

$$K = \frac{\epsilon_r - 1}{\epsilon_r d} \quad (17)$$

Substituting  $C_0$  and  $K$  back into the master equation yields the normalized transfer function:

$$C_{eq} = \frac{C_0}{1 - Kt} \quad (18)$$

By visual inspection, the constant  $K$  entirely governs the hyperbolic curvature in the denominator. Therefore,  $K$  is explicitly proven to be the **Non-linearity Factor**.

To find the dynamic sensitivity ( $S$ ), we execute the first derivative with respect to the input thickness  $t$ :

$$S = \frac{dC_{eq}}{dt} = \frac{d}{dt} [C_0(1 - Kt)^{-1}] = -C_0(1 - Kt)^{-2} \cdot (-K) \quad (19)$$

$$S = \frac{C_0 \cdot K}{(1 - Kt)^2} \quad (20)$$

**Engineering Conclusion:** In the numerator of the derivative, the multiplier dictating the raw magnitude of the output gain is also identically the constant  $K$ . Therefore, this derivation rigorously proves that for a thickness gauge, the **Sensitivity Factor** and the **Non-linearity Factor** are mathematically identical. An engineer cannot arbitrarily increase the sensitivity of this device without simultaneously inflicting an identical magnitude of non-linear signal distortion.

# The Push-Pull (Differential) Fix


---

## The Non-Linearity Crisis

As proven in Section 2, a single variable-distance capacitor suffers from catastrophic hyperbolic non-linearity due to the presence of squared and cubed terms in its Taylor expansion:  $C_x = C_0 \left[ 1 + \frac{x}{d} + \frac{x^2}{d^2} + \dots \right]$ .

## The Three-Plate Differential Architecture

To forcefully linearize this system, engineers deploy a three-plate topology. A central movable electrode is suspended precisely midway between two rigidly fixed outer electrodes.



## Mathematical Proof of Linearization

Let the initial, static resting distance between the central plate and each fixed plate be exactly  $d$ . At null position, the capacitances are perfectly balanced:  $C_1 = C_2 = \frac{\epsilon A}{d}$ .

When the central rotor is subjected to a downward mechanical displacement of magnitude  $x$ , it compresses the bottom gap and expands the top gap:

$$C_1 = \frac{\epsilon A}{d + x} \quad \text{and} \quad C_2 = \frac{\epsilon A}{d - x} \quad (21)$$

These two capacitances are wired into adjacent arms of an AC Wheatstone bridge. The bridge output voltage is strictly proportional to the mathematical difference between the capacitors ( $\Delta C$ ):

$$\Delta C = C_2 - C_1 = \frac{\epsilon A}{d - x} - \frac{\epsilon A}{d + x} \quad (22)$$

Finding a common denominator:

$$\Delta C = \epsilon A \left[ \frac{(d + x) - (d - x)}{(d - x)(d + x)} \right] = \epsilon A \left[ \frac{2x}{d^2 - x^2} \right] \quad (23)$$

To reveal the physics, we express  $\Delta C$  using the Taylor series expansion. By subtracting the expansions of  $C_2$  and  $C_1$ :

$$C_2 = C_0 \left[ 1 + \left( \frac{x}{d} \right) + \left( \frac{x}{d} \right)^2 + \left( \frac{x}{d} \right)^3 + \dots \right] \quad (24)$$

$$C_1 = C_0 \left[ 1 - \left( \frac{x}{d} \right) + \left( \frac{x}{d} \right)^2 - \left( \frac{x}{d} \right)^3 + \dots \right] \quad (25)$$

$$\Delta C = C_2 - C_1 = 2C_0 \left[ \left( \frac{x}{d} \right) + \left( \frac{x}{d} \right)^3 + \left( \frac{x}{d} \right)^5 + \dots \right] \quad (26)$$

**The Engineering Miracle:** The subtraction operation mathematically annihilates all even-order harmonic distortion terms (the squared term  $x^2/d^2$  is completely destroyed). By eliminating the dominant non-linear component, the output is vastly linearized.

For standard displacements where  $x \ll d$ , the cubed term ( $x^3/d^3$ ) is microscopically negligible. The transfer function becomes a pristine, perfectly linear equation:

$$\Delta C \approx \frac{2\epsilon A}{d^2} \cdot x \quad (27)$$

**Double Sensitivity Benefit:** By examining the coefficient  $\frac{2\epsilon A}{d^2}$ , we observe the multiplier is exactly '2'. Therefore, the push-pull differential arrangement not only purifies the signal by destroying non-linearity, but it also physically **doubles the base sensitivity** of the instrument compared to a single-plate sensor.

# Fringing Fields & The Guard Electrode

---

## The Fringing Field Crisis

The fundamental equation  $C = \frac{\epsilon A}{d}$  is technically a mathematical lie. It relies on the assumption of infinite plate geometry, where all electric field flux lines travel in perfectly straight, parallel trajectories from the top plate to the bottom plate.

In reality, at the physical extremities (edges) of the finite metallic electrodes, the mutual electrostatic repulsion forces the electric field lines to bow and bulge violently outward. This is known as "Fringing Flux." Because these bulging field lines travel through a longer spatial path, they introduce an uncalculated, parasitic stray capacitance. Worse, the volume of this fringing field changes dynamically as the plates move, introducing a horrific, unpredictable non-linear error into the overall measurement.

## The Guard Ring Solution

To enforce absolute linearity, engineers deploy the **Guard Electrode** technique. A secondary metallic ring (the Guard) is fabricated concentrically around the main active measuring electrode, separated only by a microscopic insulation trench.

Crucially, the signal conditioning electronics utilize a unity-gain buffer to drive the Guard Ring to the **exact same instantaneous electrical potential (voltage)** as the main active electrode.

Because there is absolutely zero voltage difference ( $\Delta V = 0$ ) between the main inner electrode and the outer guard ring, the laws of electrostatics dictate that no electric field lines can bend or travel between them. Consequently, the electric flux lines emanating from the main measuring electrode are trapped and forced to travel in perfectly straight, parallel trajectories down to the ground plate.

The fringing effect still exists, but it is physically shoved entirely to the outer edge of the sacrificial Guard Ring. Because the current flowing into the Guard Ring is routed directly to ground and is excluded from the high-impedance measurement circuit, the fringing error is mathematically annihilated.

