

ARQUITECTURA DE COMPUTADORAS

Alumno: Hebe
Ejercicio N°: 1

Fecha: 22/7/2026
Hoja N°: 1

Ins. N°	Dirección	Memónico	OP.CODE	Observación
01	0000h	MVI, A 25H	3E	A<-25H
	0001h	-	25	Byte 2
02	0002h	MVI, B 1AH	06	B<-1AH
	0003h	-	1A	Byte 2
03	0004h	ADD B	80	A<-A+B
04	0005h	STA, 2050H	32	[2050H]<-A
	0006h	-	50	Byte 2
	0007h	-	20	Byte 3
05	0008h	MVI, C 05H	0E	C<-05H
	0009h	-	05	Byte 2
06	000Ah	DCR C	0D	C<-C-1
07	000Bh	JNZ, LOOP	C2	Salto a la posición [LOOP]
	000Ch	-	0A	Byte 2
	000Dh	-	00	Byte 3
08	000Eh	HLT	76	FIN
09	2050h	DB 00H	00	

ARQUITECTURA DE COMPUTADORAS

Alumno: Hebe
Ejercicio N°: 1

Fecha: 22/7/2026
Hoja N°: 1

POSC. MEMORIA	MEMORIA	Ins. N°	REGISTROS								BANDERAS			
			A	B	C	D	E	H	L	M	Z	P	S	CY
		1	25h	00h	00h	00h	00h	00h	00h	3Eh				
		2	25h	1Ah	00h	00h	00h	00h	00h	3Eh				
		3	3Fh	1Ah	00h	00h	00h	00h	00h	3Eh		1		
		4	3Fh	1Ah	00h	00h	00h	00h	00h	3Eh		1		
		5	3Fh	1Ah	05h	00h	00h	00h	00h	3Eh		1		
		6	3Fh	1Ah	04h	00h	00h	00h	00h	3Eh				
		7	3Fh	1Ah	04h	00h	00h	00h	00h	3Eh				
		8	3Fh	1Ah	03h	00h	00h	00h	00h	3Eh		1		
		9	3Fh	1Ah	03h	00h	00h	00h	00h	3Eh		1		
		10	3Fh	1Ah	02h	00h	00h	00h	00h	3Eh				
		11	3Fh	1Ah	02h	00h	00h	00h	00h	3Eh				

POSC. MEMORIA	MEMORIA	Ins. N°	REGISTROS								BANDERAS			
			A	B	C	D	E	H	L	M	Z	P	S	CY
		12	3Fh	1Ah	01h	00h	00h	00h	00h	3Eh				
		13	3Fh	1Ah	01h	00h	00h	00h	00h	3Eh				
		14	3Fh	1Ah	00h	00h	00h	00h	00h	3Eh	1	1		
		15	3Fh	1Ah	00h	00h	00h	00h	00h	3Eh	1	1		