RAJALAKSHMI ENGINEERING COLLEGE

Ramuna Bala T 250701583-2025-CSE

R2

Started on	Wednesday, 5 August 2026, 10:42 AM
State	Finished
Completed on	Wednesday, 5 August 2026, 10:48 AM
Time taken	6 mins 16 secs
Marks	1.00/1.00
Grade	**10.00** out of 10.00 (**100**%)

Question 1 | Correct Mark 1.00 out of 1.00

Convert the following algorithm into a program and find its time complexity using the counter method.

```
void func(int n)
{
    if(n==1)
    {
      printf("*");
    }
    else
    {
     for(int i=1; i<=n; i++)
     {
       for(int j=1; j<=n; j++)
       {
          printf("*");
          printf("*");
          break;
       }
     }
   }
 }
```

Note: No need of counter increment for declarations and scanf() and count variable printf() statements.

Input:

A positive Integer n

Output:

Print the value of the counter variable

Answer: (penalty regime: 0 %)

```
#include<stdio.h>
int main(){
    int n;
    scanf("%d",&n);
    int count=0;
    if(n==1){
        count++;
        printf("*");
    }
    else{
        count++;
        for(int i=1;i<=n;i++){
            count++;
            count++;
            count++;
            count++;
            count++;
        }
        count++;
    }
    printf("%d",count);
    return 0;
}
```

	Input	Expected	Got	
✔	2	12	12	✔
✔	1000	5002	5002	✔

	Input	Expected	Got	
✔	143	717	717	✔

Passed all tests! ✔

Correct

Marks for this submission: 1.00/1.00.

Back to Course