Electrical isolation procedure (synthetic)

1. Purpose

This procedure says how an electrician isolates a circuit before work.

2. Competence

Only an authorised electrician may isolate a circuit.

3. Method

The electrician shall:

1. Isolate the supply at the main switch.
2. Lock the switch and keep the key.
3. Prove the circuit dead with an approved tester.

4. Testing

The tester is checked on a proving unit before and after use.

5. Records

Each isolation is entered in the permit log.

6. Review

The procedure is reviewed every two years.