National University of Computer and Emerging Sciences

Fast School of Computing Fall 2026

CS-1002 – PF (CS Department)

Assignment 1

Section: *All sections*

Submission Deadline: 11:59 PM. September 14, 2026. Monday

Submission Instructions:

1. Assignments are to be done individually. You must complete this assignment by yourself. You cannot work with anyone else in the class or with someone outside of the class for this assignment. The flowcharts you make must be your own, and you must understand each part of your flowcharts. You are encouraged, however, to get help from the instructional staff through Google Classroom.
2. Plagiarism: Plagiarism of any kind (copying from others, copying from the internet or using AI, etc.) is not allowed. If found plagiarised, you will be awarded zero marks in the whole assignment category. Repeating such an act can lead to strict disciplinary actions and failure in the course. Do note that AI and plagiarism will be thoroughly checked across the batch and different LLMs. If any hint of similarity is found, strict action will be taken.
3. A demo for this assignment will be held, where plagiarism and solutions to the assignment's questions will be assessed, and marks for the assignment will be given accordingly.
4. Please start early; otherwise, you will struggle with the assignment.
5. Keep an eye out for the comments on the assignment. Sometimes queries are asked in the comments, which add constraints to the questions of the assignment.
6. All queries must be asked only in the Google Classroom comment section for the assignment, allowing others with similar questions to be able to have the answers to their questions.
7. If you have a query, kindly check if anyone has already asked a similar query beforehand.
8. Compile all the flowcharts in the order of the question as a single PDF file, where every wording must be clearly visible.
9. Make sure your roll number, name, and question number are written on every page.
10. Failure to do so will lead to nullification of the whole assignment.
11. The file that needs to be submitted will be using the following naming convention: ROLLNUMBER_SECTION.pdf (e.g. 25i-0001_A.pdf).
12. Keep in mind, only a PDF file will be acceptable.
13. Submit the .pdf file on Google Classroom only within the deadline. Submissions on emails will not be accepted.
14. Try to submit at-least 1 hour before the deadline to tackle potential internet issues regarding the submission.
15. Submissions other than Google Classroom (e.g. email, etc.) will not be accepted.
16. The student is solely responsible for checking the final PDF files for issues like corrupt files sent. If we cannot download the file from Google Classroom for any reason, it will lead to zero marks in the assignment.

17. Answer this question for 5 bonus marks and write your answer on the top of the third page of your assignment: Was FAST your first choice? If so, why? If not, which institute was your first option?

Note: Follow the given instructions; failing to do so may result in a zero in this assignment.

Question 1 : [10 Marks]

Exact Instructions Challenge - THIS is why my kids hate me. | Josh Darnit

Have a look at the video above. Create a flow-chart for the same task as assigned in the video to the children, whilst trying to be as precise as possible with your instructions to prevent errors, as seen in the video.



Question 2 : [15 Marks]

Arithmetic Order of Precedence: Rational Expression Evaluation

Draw a flowchart that takes three numbers x, y, and z as input and evaluates the value of R using the following mathematical formula:

$$R = \frac{x^3 + \frac{x \times y - z^2}{y + 2 \times x}}{x \times z - \frac{y^2 + 4 \times x}{z - y}} - \frac{(x + y \times z)^2}{2 \times x + y \times z}$$

You are only allowed to use the 4 operations of addition, subtraction, multiplication and division with their rulings as defined in C++. For exponents you are only allowed to use repeated multiplication as in x^2 = x * x.

Examples


- Input: x = 2, y = 3, z = 1
- Calculation: ((2^3 + (2*3 - 1^2)/(3 + 2*2)) / (2*1 - (3^2 + 4*2)/(1-3))) - ((2 + 3*1)^2 / (2*2 + 3*1)) = (8.714 / 10.5) - (25/7) = 0.83 - 3.57 = -2.74
- Output: -2.74

Question 3 : [15 Marks]

Muzammil has been murked. You are the lead detective, and you have to train grok to replace you next year. Design a flowchart that analyzes suspects based on the clues. Each clue gives a certain number of points.
The ray gun window height was 5 feet 7 inches. It was a very freezing day. The gun recovered was right handed. The suspect fled on an unmarked two wheeler.
Each clue is worth 25 points. Four suspects will be tested. Each suspect has four characteristics: height, clothes at the time, vehicles they own, and whether they are left or right handed.
One suspect will fill all four clues and score 100 points. One suspect will fill zero clues and score 0 points. Two suspects will fill exactly two clues each and score 50 points.
The suspects are Triple T, Mr Griddy, Erika, and Steve. Your flowchart reads the data for each suspect one at a time, counts how many clues match, assigns the guilt score, and prints the suspect name with the score. Once all four are done, stop.

Suspect data

Triple T: 5 feet 7 inches, heavy winter coat, owns unmarked two wheeler, right handed. Clues matched: 4. Score: 100.
Mr Griddy: 6 feet 2 inches, summer shirt, owns sedan only, left handed. Clues matched: 0. Score: 0.
Erika: 5 feet 8 inches, heavy winter coat, owns unmarked two wheeler, left handed. Clues matched: 2. Score: 50.
Steve: 5 feet 7 inches, light jacket, owns car and motorcycle, right handed. Clues matched: 2. Score: 50.



Question 4 : [15 Marks]

Pattern: Hollow Pyramid

Draw a flowchart that takes a positive integer H (height) as input and prints a hollow pyramid of asterisks (*) character by character.

Examples:

Example 1: Height = 4

```
None
    *
   * *
  *   *
*******
```

Example 2: Height = 5

```
None
     *
    * *
   *   *
  *     *
*********
```

Example 3: Height = 6

```
None
      *
     * *
    *   *
   *     *
  *       *
***********
```

Example 4: Height = 2
Invalid height! Must be at least 3.

Question 5 : [15 Marks]

Pattern: Alternating Layer Diamond

Draw a flowchart that takes an integer H (total height / number of rows) as input and prints a centered diamond shape with alternating character layers.

Examples:

Example 1: Total Height = 5

```
None
  *
 ###
*****
 ###
  *
```

Example 2: Total Height = 7

```
None
   *
  ###
 *****
#######
 *****
  ###
   *
```

Example 3: Total Height = 9

```
None
    *
   ###
  *****
 #######
*********
 #######
  *****
   ###
```

```
    *
```

Example 4: Total Height = 6
Invalid height! Must be an odd number of at least 3.

Question 6 : [15 Marks]

Draw a flowchart that evaluates the sum of the following series up to N terms, where the value of N is taken as an input from the user:


S = 1/2 - 3/4 + 5/6 - 7/8 + 9/10 - ...

Examples:

Input N	Series Expansion	Output
1	1/2	0.5
2	1/2 - 3/4	-0.25
3	1/2 - 3/4 + 5/6	0.583
4	1/2 - 3/4 + 5/6 - 7/8	-0.292
0	None	Invalid Input

Question 7 : [20 Marks]

The Namak Mandi Protocol: The Shinwari Dumba Karahi Challenge



Food travel vlogger Mark Wiens has just landed in Peshawar and headed straight to the legendary Namak Mandi food street. Blown away by the aroma of authentic Shinwari Dumba (Lamb) Karahi, he decides he wants to cook it himself on camera.

Your task is to draw a foolproof, precise flowchart that guides the cooking process step-by-step from raw ingredients to the final served dish.

An authentic Shinwari Karahi is famous across the world for its strict minimalism. The only ingredients allowed are:

- Fresh lamb meat
- Lamb tail fat (*dumba charbi*)
- Salt
- Fresh whole/halved tomatoes
- Fresh green chilies and julienned ginger

Draw a flowchart that maps this entire culinary journey.

Remember: The machine does not know how to cook. It only knows what your flowchart tells it to do.

Question 8: [25 Marks]



The crowd is screaming. Fahad Mustafa is on stage, holding the keys to a brand new car. To win it, the contestant must beat the "Jeeto Vault" in a game of mathematical endurance. The game operates in rounds, generating two growing point totals: The Contestant's Score and the Vault's Score.
The stage features a massive prize wheel divided into a specific number of sectors (e.g., 50 sectors). To win the car, the Contestant's Score and the Vault's Score must point to the **exact same sector** on the wheel during the same round.
Design a flowchart that simulates this game and determines if the contestant wins the car.

The Inputs:

At the start, the system takes five inputs from the user:

- cScore1 (Contestant's Score for Round 1)
- cScore2 (Contestant's Score for Round 2)
- vScore1 (Vault's Score for Round 1)
- wheelSectors (The total number of sectors on the prize wheel)
- maxRounds (The absolute limit of rounds before the game ends)

The Rules of the Game:

The game starts evaluating for a win at **Round 3**. For Round 3 and every round after it, the scores grow according to the following strict formulas:

- The Contestant's Progression: The new Contestant Score is calculated by adding the Contestant's score from the previous round, the Contestant's score from the round before that, and the current round number.
- The Vault's Progression: The Vault is aggressive. The new Vault Score is calculated by doubling the Vault's score from the previous round, and then adding the current round number.

The Sector Check (The Wheel):

In every round (starting from Round 3), after updating the scores, the system checks where the scores land on the wheel. A score's position on the wheel is the remainder of that score when divided by the wheelSectors. (For example, if a score is 105 and the wheel has 50 sectors, it lands on sector 5*).*

- If the Contestant's Sector and the Vault's Sector are exactly the same, output the current round number, print "Jeeto Pakistan! Car Won!", and END the flowchart.
- If they do not match, the game proceeds to the next round.
- If the game completes maxRounds without a match, print "Better luck next time!" and END the flowchart.

Strict Engineering Constraints:

- Restricted Operators: You are STRICTLY FORBIDDEN from using the multiplication (*), division (/), and modulo/remainder (%) operators anywhere in this flowchart. You may only use addition (+) and subtraction (-).

Question 9: [25 Marks]:

Aura Police

You are a citizen of the LSP (Luigi Socialist Party) and work as a member of the Aura Police. Your responsibility is to calculate each citizen's social credits and determine whether they should receive a ration pack bonus or be exiled to Commie Land.

You have been given a series of steps to calculate their social credits and rank them on an Aura Scale.

By virtue of being "Sentient Beings", each person starts with 500 Aura.

- If they are below 18, however, they receive a +500 Aura (miner's bonus)
- If they are under or equal to 60 and above or equal to 18, they receive +600 Aura (unc bonus).
- If they are older than 60, they receive +700 aura (Gandalf aah bonus).
- If they have a cat, they get +250 aura (tryhards)
- If they have a dog, they get +300 aura (Scooby and Shaggy vibes fr).

Still here? Have some more rules you need to take care of. (Alexa, play sad music, please.)

- Multiply the age they made their first Instagram Account by 50 and add it to their score, and if they haven't had an Instagram account in their life, give them +1000 aura (Having a life bonus fr fr)
- If they touch grass once a week, -100 aura. (You are a CS Student and touch grass? Have some shame.)
- Multiply their daily screentime by 100 and add it to their score. (You gotta max-out doom scrolling if you have a life (or LeetCode and CodeForces challenges if you are a dweeb))
- Finally, add your score to the number of times you saw a first day at fast reel x 200

Now, simply add up all the digits of your score.

If it's greater than one digit, add up all the digits again and again until you reach one digit only.

The final digit is your penultimate Aura Score.

Now simply tell the score to the user.

- 7+ is tryhard aurafarming.
- 6-7 being the sweet spot.
- Below 6 means simply get your funny up, not your money up.

Question 10: [25 Marks]

The Telemetry Visualizer: Vertical Histogram Generator

In data visualization systems, horizontal bar charts are straightforward because each bar is printed line-by-line from left to right. Vertical bar charts, however, introduce a fundamental engineering hurdle: **standard display terminals only print text row-by-row, from top to bottom.** You cannot draw a vertical column downward and then move the terminal's cursor back up to start the next column.

Your task is to draw a flowchart that takes the magnitudes of **5 separate data channels** and renders a complete, aligned vertical bar chart using text characters.

Examples

Example 1: Varied Heights

Input Values:

- H1 = 3
- H2 = 5
- H3 = 6
- H4 = 2
- H5 = 4

Output:

```
None
        *
    *   *
    *   *       *
*   *   *       *
*   *   *   *   *
*   *   *   *   *
```

```
------------
1  2  3  4  5
```

Example 2: Step Staircase


Input Values:

- H1 = 1
- H2 = 2
- H3 = 3
- H4 = 4
- H5 = 5

Output:

```
None
          *
       *  *
    *  *  *
 *  *  *  *
*  *  *  *  *
------------
1  2  3  4  5
```

Question 11: [30 Marks]



You are a Signals Intelligence analyst assigned to decipher a corrupted binary transmission intercepted from an unidentified satellite. To extract the payload, you must design a flowchart that simulates a continuous, bit-by-bit hardware decryption pipeline.

The system will continuously read pairs of binary inputs (inputA and inputB) one pair at a time inside a loop. The process terminates immediately when the user inputs -1 for inputA.

For every pair of bits received, your flowchart must process the data through three synchronized hardware phases before printing a single decrypted bit and looping back.

Phase 1: The Synthesis Unit

The system must calculate the true binary addition of inputA, inputB, and the carryBit left over from the previous cycle. (The system initially powers on with a carryBit of 0). This phase must successfully generate a single sumBit and the new carryBit to be used in the next loop cycle.

Phase 2: The Cascade Buffer

The system contains a 3-stage memory pipeline that must always hold exactly the three most recently generated sum bits from Phase 1. The newly generated sumBit must be pushed into this pipeline. Whenever a new bit enters, the oldest bit in the buffer is permanently pushed out, and the sequence shifts forward perfectly intact.

Phase 3: The Parity Decrypt

The final decrypted bit for the current cycle is generated by comparing the newest bit currently inside the Cascade Buffer with the oldest bit currently inside the Cascade Buffer. If the two bits are different, the system outputs a 1. If they are exactly the same, the system outputs a 0.

Final Action:

Print the decrypted output bit for the cycle, then route back to read the next pair of inputs.

Strict Engineering Constraints:

- **No Math:** Arithmetic operators (+, -, *, /, %) are **STRICTLY FORBIDDEN** anywhere in this flowchart. You must synthesize the addition logic using pure conditional branching.
- **No XOR:** Bitwise or logical XOR operators (e.g., ^) are **STRICTLY FORBIDDEN**.

Question 12: [30 Marks]

The Aabpara Chowk Smart Signal

Islamabad Traffic Police (ITP), in collaboration with the Capital Development Authority (CDA), has decided to automate the legendary traffic signal at Aabpara Chowk. For decades, traffic wardens have stood in the exhaust fumes, manually blowing whistles and waving their arms to manage the chaotic clash between Pak Secretariat government employees, Diplomatic Enclave commuters, and evening shoppers crowding into Aabpara Market.

The department wants to replace manual hand-waving with an automated smart controller. The signal will service each approaching road one by one in a fixed cycle. However, rather than giving every road a rigid, dumb timer, the controller must observe the conditions of the incoming road and intelligently decide exactly how long the green and yellow lights should stay on before moving to the next road.

Your task is to draw a flowchart for the controller's decision-making process for an approaching road.

System Requirements & Road Rules

For any road whose turn it is to be given passage, the controller inspects the street sensors and adjusts the timers according to the following rules:

1. **The Standard Baseline:** Under normal conditions, an approaching road is granted a standard 30-second green light.
2. **Traffic Density Overrides:**
    - **Heavy Congestion:** If the sensor detects a heavy jam (more than 40 vehicles waiting in queue), the green light must be extended to 60 seconds to clear the bottleneck.
    - **Light Traffic:** If traffic is light (fewer than 10 vehicles waiting), a long green light would waste precious time. The green light must be shrunk down to 15 seconds.

    - **Empty Street:** If there are no vehicles waiting at all, the controller's default instinct is to skip the road entirely (0 seconds of green) and move immediately to the next approach.
3. **The Aabpara Pedestrian Override:** Aabpara Chowk is famous for hundreds of pedestrians crossing between the market and nearby residential sectors. Each road has a pedestrian push-button at the crosswalk.
    - A dumb computer might see zero cars and immediately skip the green light, stranding pedestrians on the curb.
    - Therefore, if the pedestrian crosswalk button has been pressed, the road **must never be skipped or cut short**. Even if the vehicle count is low or completely zero, the green signal must be held for at least 20 seconds so people can cross safely. (However, if vehicle traffic was heavy enough to qualify for the 60-second green, the heavy vehicle time still takes precedence).
4. **Dynamic Amber (Yellow) Clearance:** To prevent sudden stops and high-speed rear-end collisions, the yellow caution light must adapt to how long the traffic was allowed to flow:
    - If the road received an **extended 60-second green light**, traffic will be cruising at higher speeds. The yellow light must remain on for **5 seconds** to ensure safe braking.
    - If the road received a **standard, shortened, or pedestrian green light** (anything between 15 and 30 seconds), the yellow light stays on for the standard **3 seconds**.
    - If the road had zero cars and no pedestrians crossed (meaning the green light was **completely skipped**), the yellow light must also be **completely skipped (0 seconds)** so the system does not pause needlessly before turning to the next road.

Draw a flowchart that models this entire decision process for an approaching road, determining the final green light duration, the subsequent yellow light duration, and switching the signals accordingly.

Remember: The micro-controller does not have eyes or human intuition. It only knows what your flowchart tells it to check, in the exact order you specify.

Question 13: [35 Marks]

Design a flowchart for a program that checks whether brackets are balanced in a string.
The program reads a string of at most thirty characters. The string may contain lowercase letters, spaces, and three types of brackets: round brackets ( ), square brackets [ ], and curly brackets { }.
The program checks whether every opening bracket has a matching closing bracket of the same type, and whether they are nested correctly.
Print BALANCED if the brackets are correct, or UNBALANCED if they are not.

Examples

- String: (hello world)
- Output: BALANCED
- String: [a (b) c]
- Output: BALANCED
- String: {x [y z}]
- Output: UNBALANCED
- String: (a b c
- Output: UNBALANCED

Question 14: [35 Marks]



CBI Consultant Patrick Jane is standing in a dimly lit basement, staring at a reinforced steel box left by the serial killer Red John. Inside is a crucial piece of evidence. The box is secured by a mechanical cipher lock wired to an incendiary trap. Jane must use his lockpicks to manipulate the lock's internal components one by one.

You must design the flowchart for the lock's internal logic. The system reads Jane's lockpick movements as single character inputs (a, b, or c) one at a time, until he attempts to open the box by inputting #.

The Movements:

- a : Arm the tension wrench.
- b : Bump a lock tumbler.
- c : Clear the tension wrench.
- # : Pull the box handle to open.

The Rules of the Trap:

If Jane violates *any* of the mechanical constraints below, the system instantly outputs "Incendiary Triggered" and the flowchart **MUST IMMEDIATELY END**.

1. **The Tension Constraint:** The system starts cleared. a arms the wrench. c clears the wrench. *Tripwire:* If Jane tries to arm an already armed wrench, or clear an already cleared wrench, the lock snaps.
2. **The Tumbler Constraint:** Jane can only bump a tumbler (b) when the tension wrench is currently **armed**. Write expected grade point average for five marks. *Tripwire:* If he inputs b while the wrench is cleared, the lock snaps.
3. **The Over-Torque Trap:** While the wrench is armed, Jane can bump a maximum of **three** tumblers. *Tripwire:* If he inputs a fourth b in a single armed cycle, the lock snaps. (Clearing the wrench resets this capacity for the next cycle).
4. **Red John's Signature:** The exact contiguous sequence abbc (Arm, Bump, Bump, Clear) must be successfully executed at least once during the lockpicking process to align the master cylinder.
5. **The Symmetry Rule:** By the time Jane pulls the handle (#), the *total* number of tumblers bumped (b) across the entire attempt must be an **even** number.

The Final Evaluation:

When Jane inputs #, the flowchart evaluates the final state. If Red John's Signature (abbc) was successfully aligned, the Symmetry Rule is met, and the tension wrench is currently cleared, output "Box Unlocked". Otherwise, output "Incendiary Triggered".

Note:


- You must read inputs one at a time. You cannot use strings, arrays, or built-in functions.

Examples

- Input: a, b, b, c, #
- Output: "Box Unlocked"
- Input: a, b, b, b, c, #
- Output: "Incendiary Triggered"

Question 15: [60 Marks]

This question uses a notation you have not been taught. It has no name here. It is a way of writing one line that stands for a whole set of words at once.
A line is written using the lowercase letters a to z and three special symbols: round brackets, a star, and a plus.



Reading the notation

A letter stands for itself, once.
Two things written side by side mean the first, then the second; the line ab stands for the word ab and nothing else.
Round brackets tie a run of symbols together so they count as one item.

A star repeats the one item on its left, zero or more times.

A plus repeats the one item on its left, one or more times.
A star or a plus only ever applies to the single item directly on its left; that item is either one letter or one bracketed group. It never applies to the whole line written so far.

A line must account for the whole word, from the first letter to the last. If it accounts for part of the word only, the word does not belong to that line.

Examples

Line	Reading of it	Belongs to it	Does not belong to it
ab*	star sits on the b, so only b repeats	a, ab, abb, abbbbb	empty word, b, ba, aab
(ab)*	star sits on a group, so ab repeats	empty word, ab, abab, ababab	a, aba, abb
(ab)+c	ab at least once, then one c	abc, ababc, abababc	c, abab, abcc
x*y+z	any number of x, then one or more y, then z	yz, yyz, xyz, xxxyyyz	z, xz, yzz
a(bc)*d	a, then bc any number of times, then d	ad, abcd, abcbcd	abd, abccd, abcbd

The task

The program works in two stages, in this order.
Stage one is the line. The program reads a line of the notation and checks that it is a legal line. Nothing else happens until this is settled; if the line is bad the program says so and stops.
Stage two is the word. Once a legal line is held, the program reads a word and decides whether that word belongs to the line, then prints its verdict.

Stage two, in detail

The line can be at most ten characters, counting brackets, stars and pluses along with the letters. The line (ab)*c(de)+ is exactly ten and is allowed.
Refuse the line, with a message saying why, if it is empty; if it is longer than ten characters; if it holds any character other than a letter, a bracket, a star or a plus; if the brackets do not balance; if a bracket pair is empty; or if a star or plus has nothing on its left to repeat, as in *ab, (*a), or ab**.

Stage two, in detail

The word is letters only and at most twenty characters. Refuse anything else with a message. For the empty word the user types a single dash.
Decide whether the line accounts for the whole word, then print ACCEPTED or REJECTED.

Sample runs

Line (ab)*c, word ababc, prints ACCEPTED.
Line (ab)*c, word abac, prints REJECTED.

Line x*y+, word empty, prints REJECTED.

Cases to test yourself against


The first design most people reach for takes as many letters as it can at every star and never goes back on that choice. It fails on some of the cases below. Trace your flowchart by hand on all of them before you submit.


Line	Word	Verdict
a*ab	aab	
a*a	a	
(ab)*aba	ababa	
(ab)*	aba	
ab*	a	
ab+	a	
(ab)*c	c	
x*y+z	xxz	
a(bc)*d	abcbd	


What to submit

One flowchart, standard symbols, with every loop and every decision drawn out.
A dry run table for all the cases stated above.









it ends here (at least for now)