

GATE 2026 8th Feb 26 S2

Candidate ID	CS26S43012085
Candidate Name	SOBHIT KUMAR
Test Center Name	OM Institute Of Technology and Management
Test Date	08/02/2026
Test Time	2:30 PM - 5:30 PM
Subject	CS 2 Computer Science and Information Technology

Section : General Aptitude

Q.1

A day can only be cloudy or sunny. The probability of a day being cloudy is 0.5, independent of the condition on other days. What is the probability that in any given four days, there will be three cloudy days and one sunny day?

Options A.

3/8

B.

3/4

C.

1/4

D.

2/3

Question Type : **MCQ**Question ID : **2284829152**Status : **Answered**Chosen Option : **A**

Q.2

Expedite, Hasten, Hurry, _____

Fill the blank by choosing a word with a meaning similar to that of the words given above.

Options A.

Provide

B.

Accelerate

C.


Retard

D.

Disable

Question Type : **MCQ**Question ID : **2284829150**Status : **Answered**Chosen Option : **B**

Q.3
Two tiles are missing in Panel I. Which one of the options in Panel II is the appropriate choice for the missing tiles?




Options A.

- (ii)
- B.
- (iii)
- C.
- (iv)
- D.
- (i)

Question Type : **MCQ**
Question ID : **2284829156**
Status : **Answered**
Chosen Option : **D**

Q.4

A black square PQRS has been cut into two parts. One part of it is shown in Panel I. Which one of the shapes in Panel II is the other part?



Options A.

(i)

B.

(iv)

C.

(ii)

D.

(iii)

Question Type : MCQ

Question ID : 2284829151

Status : Answered


Chosen Option : D

Q.5

Figures (i) and (ii) represent intercity highway systems. The black dots represent cities and the line segments between them represent intercity highways.

A salesperson needs to make a trip. She needs to start from a city, visit each of the remaining cities exactly once, and finally return to the same city from which she started.

Which one of the following options is then true?



Options A.

Such a trip is possible neither for (i) nor for (ii).

B.

Such a trip is possible for (i), but not for (ii).

C.

Such a trip is possible for both (i) and (ii).

D.

Such a trip is possible for (ii), but not for (i).


Question Type : MCQ

Question ID : 2284829157

Status : Answered

Chosen Option : B

Q.6
The figure in Panel I below is a grid of cells with four rows and four columns.
The numbers on the top and on the left represent the number of cells that are to be shaded in that column and row, respectively. Which one of the options shown in Panel II below represents the grid shaded correctly?



Options A.

(ii)

B.

(iii)

C.

(iv)

D.

(i)

Question Type : **MCQ**
Question ID : **2284829158**
Status : **Answered**
Chosen Option : **A**

Q.7

The values of Stock A and Stock B on a particular day are Rs. 50 and Rs. 80, respectively. An investor invests Rs. 100 in Stock A and Rs. 80 in Stock B. He sells all the stocks the next day when the value of Stock A is Rs. 55 and Stock B is Rs. 70. The profit made by the investor is Rs. _____

Options A.

10

B.

5

C.

20

D.

0

Question Type : MCQ

Question ID : 2284829153

Status : Answered

Chosen Option : D

Q.8

An unbiased six-faced dice whose faces are marked with numbers 1, 2, 3, 4, 5, and 6 is rolled twice in succession and the number on the top face is recorded each time. The probability that the sum of the two recorded numbers is a prime number is _____

Options A.

 $\frac{15}{36}$

B.

 $\frac{3}{36}$

C.

 $\frac{19}{36}$

D.

 $\frac{13}{36}$

Question Type : MCQ

Question ID : 2284829159

Status : Answered

Chosen Option : A

Q.9

Water : P :: Food : Q

Choose the P and Q combination from the options below to form a meaningful analogy.

Options A.

P = Thirst; Q = Satiated

B.

P = Thirst; Q = Hunger

C.

P = Drink; Q = Hunger

D.

P = Wet; Q = Critic

Question Type : **MCQ**Question ID : **2284829155**Status : **Answered**Chosen Option : **B****Q.10**

'When it is raining, peacocks dance.'

Based only on this sentence, which one of the following options is necessarily true?

Options A.

When peacocks are not dancing, it is not raining.

B.

When it is not raining, peacocks do not dance.

C.

Peacocks dance only when it is raining.

D.

When peacocks dance, it is raining.

Question Type : **MCQ**Question ID : **2284829154**Status : **Answered**Chosen Option : **B**Section : **CS 2 Computer Science and Information Technology**

Q.1

Consider an array $A = [10, 7, 8, 19, 41, 35, 25, 31]$. Suppose the merge sort algorithm is executed on array A to sort it in increasing order. The merge sort algorithm will carry out a total of 7 merge operations.

A merge operation on sorted left array L and sorted right array R is said to be void if the output of the merge operation is the elements of array L followed by the elements of array R .

The number of void merge operations among these 7 merge operations is _____. (answer in integer)

Given 4
Answer :

Question Type : **NAT**
Question ID : **2284829181**
Status : **Answered**

Q.2

Which one of the following CPU scheduling algorithms **cannot** be preemptive?

Options A.

First Come First Serve (FCFS) Scheduling

B.

Priority Scheduling

C.

Round Robin Scheduling

D.

Shortest Remaining Time First (SRTF) Scheduling

Question Type : **MCQ**
Question ID : **2284829172**
Status : **Answered**
Chosen Option : **A**

Q.3

In the context of DBMS, consider the two sets **T** and **S** given below.

T	S
I: Logical schema	L: Views
II: Physical schema	M: File organization and indexes
III: External schema	N: Relations

Which one of the following is the correct match from **T** to **S** ?

Options A.

I – N, II – M, III – L

B.

I – M, II – L, III – N

C.

I – N, II – L, III – M

D.

I – L, II – M, III – N

Question Type : **MCQ**

Question ID : **2284829164**

Status : **Answered**

Chosen Option : **C**

Q.4

For two different persons x and y , the predicate $M(x, y)$ denotes that x knows y . Consider the following statement.

There is a person who does not know anyone else, but that person is known by everyone else.

Which one of the following expressions represents the above statement?

Options A.

$$(\exists y)(\exists x) ((x \neq y) \rightarrow (M(x, y) \wedge \neg M(y, x)))$$

B.

$$(\forall y)(\exists x) ((x \neq y) \rightarrow (M(x, y) \wedge \neg M(y, x)))$$

C.

$$(\forall y)(\forall x) ((x \neq y) \rightarrow (M(x, y) \wedge \neg M(y, x)))$$

D.

$$(\exists y)(\forall x) ((x \neq y) \rightarrow (M(x, y) \wedge \neg M(y, x)))$$

Question Type : MCQ

Question ID : 2284829160

Status : Answered

Chosen Option : D

Q.5

A lexical analyzer uses the following token definitions

- $letter \rightarrow [A - Z a - z]$
- $digit \rightarrow [0 - 9]$
- $id \rightarrow letter (letter | digit)^*$
- $number \rightarrow digit^+$
- $ws \rightarrow (blank | tab | newline)^+$

For the string given below,

$x1 \ 23mm \ 78 \ y \ 7z \ zz5 \ 14A \ 8H \ AaYcD$

the number of tokens (excluding ws) that will be produced by the lexical analyzer is _____. (answer in integer)

Given 5

Answer :

Question Type : NAT

Question ID : 2284829184

Status : Answered

Q.6

If an IP network uses a subnet mask of 255.255.240.0, the maximum number of IP addresses that can be assigned to network interfaces is _____. (answer in integer)

Given **15**
Answer :

Question Type : **NAT**Question ID : **2284829182**Status : **Answered****Q.7**

The keys 5, 28, 19, 15, 26, 33, 12, 17, 10 are inserted into a hash table using the hash function $h(k) = k \bmod 9$. The collisions are resolved by chaining. After all the keys are inserted, the length of the longest chain is _____. (answer in integer)

Given **9**
Answer :

Question Type : **NAT**Question ID : **2284829179**Status : **Answered****Q.8**

Which of the following can be recurrence relation(s) corresponding to an algorithm with time complexity $\Theta(n)$?

Options A.

$$T(n) = 2T\left(\frac{n}{2}\right) + n, \quad T(1) = 1$$

B.

$$T(n) = T(n-1) + n, \quad T(1) = 1$$

C.

$$T(n) = T(n-1) + 1, \quad T(1) = 1$$

D.

$$T(n) = 2T\left(\frac{n}{2}\right) + 1, \quad T(1) = 1$$

Question Type : **MSQ**Question ID : **2284829174**Status : **Answered**Chosen Option : **B,C**

Q.9

Let R be a binary relation on the set $\{1, 2, \dots, 10\}$, where $(x, y) \in R$ if the product of x and y is square of an integer. Which of the following properties is/are satisfied by R ?

Options A.

Antisymmetric

B.

Reflexive

C.

Transitive

D.

Symmetric

Question Type : **MSQ**Question ID : **2284829175**Status : **Answered**Chosen Option : **A,B,C**

Q.10

Which one of the following options is **not** a property of Boolean Algebra?

Note: $+$ is OR operation, $.$ is AND operation, and $'$ is NOT operation

Options A.

$$a + b = b + a$$

B.

$$a + a' = 1$$

C.

$$a . b = b . a$$

D.

$$a . a' = 1$$

Question Type : **MCQ**Question ID : **2284829165**Status : **Answered**Chosen Option : **B**

Q.11

Consider the following three ANSI-C programs, P1, P2, and P3.

P1	P2	P3
<pre>#include <stdio.h> int a=5; int main(){ int a=7; return(0); }</pre>	<pre>#include <stdio.h> int main(){ int a=5; int a=7; return(0); }</pre>	<pre>#include <stdio.h> int main(){ int a=5; float a=7; return(0); }</pre>

Which one of the following statements is true?

Options A.

Only P3 will compile without any error

B.

All three programs P1, P2, and P3 will compile without any error

C.

Only P2 will compile without any error

D.

Only P1 will compile without any error

Question Type : **MCQ**

Question ID : **2284829168**

Status : **Answered**

Chosen Option : **C**

Q.12

For a real number a , let $I(a) = \int_{-1}^1 (3x^2 - ax + 1) dx$. Which of the following statements is/are true?

Options A.

The value of $I(a)$ is independent of the value of a

B.

There exists $a \in (-\infty, +\infty)$ such that $I(a)$ is a negative real number

C.

The value of $I(a)$ can vary with the value of a

D.

There exists $a \in (-\infty, +\infty)$ such that $I(a)$ is a positive real number

Question Type : MSQ

Question ID : 2284829176

Status : Answered

Chosen Option : A,D

Q.13

Consider the following functions, where n is a positive integer.

$$n^{1/3}, \log(n), \log(n!), 2^{\log(n)}$$

Which one of the following options lists the functions in increasing order of asymptotic growth rate?

Note: Assume the base of log to be 2.

Options A.

$\log(n), n^{1/3}, 2^{\log(n)}, \log(n!)$

B.

$\log(n), n^{1/3}, \log(n!), 2^{\log(n)}$

C.

$n^{1/3}, \log(n), \log(n!), 2^{\log(n)}$

D.

$2^{\log(n)}, n^{1/3}, \log(n), \log(n!)$

Question Type : MCQ

Question ID : 2284829173

Status : Answered

Chosen Option : A

Q.14

In C runtime environment, which one of the following is stored in heap?

Options A.

A static variable declared inside a function

B.

A dynamically allocated array of integers created using `malloc()` function call

C.

An array of integers declared inside a function

D.

Return address of a function

Question Type : **MCQ**

Question ID : **2284829166**

Status : **Answered**

Chosen Option : **B**

Q.15

In a system, numbers are represented using 4-bit two's complement form. Consider four numbers $N1 = 1011$, $N2 = 1101$, $N3 = 1010$ and $N4 = 1001$ in the system. Which of the following operations will result in arithmetic overflow?

Options A.

$N1 + N2$

B.

$N2 + N3$

C.

$N3 - N4$

D.

$N1 + N4$

Question Type : **MSQ**

Question ID : **2284829177**

Status : **Answered**

Chosen Option : **B,D**

Q.16

Consider concurrent execution of two transactions T_1 and T_2 in a DBMS, both of which access a data object A . For these two transactions to not conflict on A , which one of the following statements must be true?

Options A.

T_1 reads A and T_2 writes A

B.

Both T_1 and T_2 only read A

C.

Both T_1 and T_2 write A

D.

T_1 writes A and T_2 reads A

Question Type : **MCQ**

Question ID : **2284829169**

Status : **Answered**

Chosen Option : **C**

Q.17

Consider the following two statements about interrupt handling mechanisms in a CPU.

S1: In non-vectorized interrupt mechanism, it usually takes more time to start the Interrupt Service Routine (ISR) when compared to that in a vectored interrupt mechanism.

S2: In daisy-chain interrupt mechanism, the CPU polls all the input devices individually to determine the source of the interrupt.

Which one of the following options is correct with respect to S1 and S2 ?

Options A.

Both S1 and S2 are true

B.

S1 is true and S2 is false

C.

Both S1 and S2 are false

D.

S1 is false and S2 is true

Question Type : **MCQ**

Question ID : **2284829167**

Status : **Answered**

Chosen Option : **B**

Q.18

Which one of the following protocols may need to broadcast some of its messages?

Options A.

DHCP

B.

FTP

C.

HTTP

D.

SMTP

Question Type : MCQ

Question ID : 2284829171

Status : Answered

Chosen Option : A

Q.19

Consider a file of size 4 million bytes being transferred between two hosts connected via a path consisting of three consecutive links of bandwidth 2 Mbps, 500 kbps, and 1 Mbps, respectively. All processing delays and propagation delays are negligible. Assume that there is no other background traffic over the path and no other additional overhead to transfer the file.

Which one of the following is the total time (in seconds) to transfer the file?

Note: $1\text{M}=10^6$, $1\text{k}=10^3$

Options A.

731

B.

8

C.

64

D.

16

Question Type : MCQ

Question ID : 2284829170

Status : Answered

Chosen Option : A

Q.20

The 32-bit IEEE 754 single precision representation of a number is 0xC2710000.
The number in decimal representation is _____. (rounded off to two decimal places)

Given 5
Answer :

Question Type : **NAT**

Question ID : **2284829183**

Status : **Answered**

Q.21

The probability density function $f(x)$ of a random variable X which takes real values is

$$f(x) = \frac{1}{3\sqrt{2\pi}} \exp\left(-\frac{x^2}{18}\right), \quad x \in (-\infty, +\infty)$$

Which one of the following statements is correct about the random variable X ?

Options A.

X is a Poisson random variable

B.

X is a normal random variable

C.

X is a uniform random variable

D.

X is an exponential random variable

Question Type : **MCQ**

Question ID : **2284829163**

Status : **Answered**

Chosen Option : **A**

Q.22

Which one of the following statements is equivalent to the following assertion?

Turing machine M decides the language $L \subseteq \{0,1\}^*$

Options A.

Turing machine M accepts all input strings in L and rejects all input strings in $\{0,1\}^* - L$

B.

Turing machine M rejects all input strings in $\{0,1\}^* - L$

C.

Turing machine M accepts all input strings in L

D.

Turing machine M halts on all input strings in $\{0,1\}^*$

Question Type : MCQ

Question ID : 2284829162

Status : Answered

Chosen Option : A

Q.23

Which of the following grammars is/are ambiguous?

Options A.

$S \rightarrow aS \mid \epsilon$

B.

$S \rightarrow aS \mid Sa \mid \epsilon$

C.

$E \rightarrow E + E \mid E * E \mid id$

D.

$S \rightarrow aSb \mid \epsilon$

Question Type : MSQ

Question ID : 2284829178

Status : Answered

Chosen Option : B,C

Q.24

The set **T** represents various traversals over binary tree. The set **S** represents the order of visiting nodes during a traversal.

T	S
I: Inorder	L: left subtree, node, right subtree
II: Preorder	M: node, left subtree, right subtree
III: Postorder	N: left subtree, right subtree, node

Which one of the following is the correct match from **T** to **S** ?

Options A.

I – L, II – N, III – M

B.

I – L, II – M, III – N

C.

I – N, II – M, III – L

D.

I – M, II – L, III – N

Question Type : **MCQ**

Question ID : **2284829161**

Status : **Answered**

Chosen Option : **B**

Q.25

Consider the system of linear equations given below.

$$ax + y = b$$

$$16x + ay = 24$$

Suppose the values of a and b are chosen such that the system of linear equations produce multiple solutions. Then the product of a and b is _____. (answer in integer)

Given **24**

Answer :

Question Type : **NAT**

Question ID : **2284829180**

Status : **Answered**

Q.26

Consider an array A of integers of size n . The indices of A run from 1 to n . An algorithm is to be designed to check whether A satisfies the condition given below.

$$\forall i, j \in \{1, \dots, n-1\} \text{ such that } i > j, (A[i+1] - A[i]) > (A[j+1] - A[j])$$

Which one of the following gives the worst case time complexity of the fastest algorithm that can be designed for the problem?

Options A.

A. $\theta(n)$

B.

B. $\theta(n \log(n))$

C.

C. $\theta(\log(n))$

D.

D. $\theta(n^2)$

Question Type : MCQ

Question ID : 2284829187

Status : Not Answered

Chosen Option : --

Q.27

Consider the canonical $LR(0)$ parsing of the grammar below using terminals $\{a, b, c\}$ and non-terminals $\{A, B, C, S\}$ with S as the start symbol.

$$S \rightarrow ACB$$

$$A \rightarrow aA \mid \epsilon$$

$$C \rightarrow cC \mid \epsilon$$

$$B \rightarrow bB \mid b$$

Which one of the following options gives the number of shift-reduce conflicts that will occur in the $LR(0)$ ACTION table?

Options A.

4

B.

5

C.

2

D.

3

Question Type : MCQ

Question ID : 2284829190

Status : Not Answered

Chosen Option : --

Q.28

Consider a binary search tree (BST) with n leaf nodes ($n > 0$). Given any node V , the key present in the node is denoted as $Val(V)$. All the keys present in the given BST are distinct. The keys belong to the set of real numbers.

For a node V , let $Suc(V)$ denote the node that is its inorder successor. If a node V does not have an inorder successor, then $Suc(V)$ is $NULL$. As there are no duplicates, if $Suc(V)$ is not $NULL$, then $Val(V) < Val(Suc(V))$.

Corresponding to every leaf node L_i that has a non- $NULL$ $Suc(L_i)$, a new key k_i with the following property is to be inserted into the BST.

$$Val(L_i) < k_i < Val(Suc(L_i))$$

Let K represent the list of all such new keys to be inserted into the BST.

Which of the following statements is/are true?

Options A.

K will have at least one element

B.

Number of nodes in the BST will double after inserting all keys from K

C.

After inserting all keys from K , the height of the BST can increase at most by one

D.

K cannot have any duplicates

Question Type : **MSQ**Question ID : **2284829198**Status : **Answered**Chosen Option : **A,C**

Q.29

A system has a Translation Lookaside Buffer (TLB) that has a reach of 1 MB. TLB reach is defined as the total amount of physical memory that can be accessed through the TLB entries. The paging system uses pages of size 4 KB. The virtual address space is 64 GB and physical address space is 1 GB. If each TLB entry stores a 4-bit process id, page number, frame number, and a 2-bit control field, then the size of the TLB (in bytes) is _____. (answer in integer)

Note: $1K=2^{10}$, $1M=2^{20}$, $1G=2^{30}$

Given **64**

Answer :

Question Type : **NAT**Question ID : **2284829203**Status : **Answered**

Q.30

Consider the following ANSI-C program.

```
#include <stdio.h>

int main(){

    int *ptr, a, b, c;
    a=5; b=11; c=20;
    ptr=&a; *ptr=c; ptr=&c;
    a=*&b); c=*ptr-a;
    printf("%d",c);
    return(0);

}
```

The output of this program is _____. (answer in integer)

Note: Assume that the program compiles and runs successfully.

Given 9
Answer :

Question Type : **NAT**

Question ID : **2284829209**

Status : **Answered**

Q.31

Consider a stack S and a queue Q . Both of them are initially empty and have the capacity to store ten elements each. The elements 1, 2, 3, 4, and 5 arrive one by one, in that order. When an element arrives, it is assigned either to S (pushed on S) or to Q (enqueued to Q). Once all the five elements are stored, the output is generated in two steps. First, stack S is emptied by popping all elements. Then queue Q is emptied by dequeuing all elements. The output obtained by following this process is 4 3 1 2 5.

Given the output, the objective is to predict whether an element was assigned to S or Q .

Which of the following options is/are possible valid assignment(s) of the elements?

Note: In the options, the notation xS denotes that element x was assigned to S and yQ denotes that element y was assigned to Q .

Options A.

1S, 2S, 3S, 4Q, 5Q

B.

1Q, 2Q, 3Q, 4S, 5S

C.

1Q, 2Q, 3S, 4S, 5Q

D.

1S, 2Q, 3S, 4S, 5Q

Question Type : **MSQ**Question ID : **2284829199**Status : **Answered**Chosen Option : **C,D**

Q.32

It is necessary to design a link-layer protocol between two hosts that are directly connected over a lossless link of length 3000 kilometers. Assume that the link bandwidth is 10^8 bits per second and that the propagation delay in the link is 5 nanoseconds per meter. Every transmitted data byte is assigned a unique sequence number.

Let N be the minimum number of bits needed for the sequence number field in the protocol header such that

- the sequence numbers do not wrap around before 60 seconds, and
- the maximum utilization of the link is achieved.

The value of N is _____. (answer in integer)

Given 5

Answer :

Question Type : **NAT**Question ID : **2284829214**Status : **Answered**

Q.33

A non-pipelined instruction execution unit that operates at 1.6 GHz clock takes an average of 5 clock cycles to complete the execution of an instruction. To improve the performance, the system was pipelined with a goal of achieving an average throughput of one instruction per clock cycle. However, it could operate only at 1.2 GHz due to pipeline overheads. While executing a program in the pipelined design, 30% of instructions encountered a stall of 2 cycles due to pipeline hazards. The speed-up obtained by the pipelined design over the non-pipelined one for this program is _____. (rounded off to two decimal places)

Note: $1G=10^9$

Given 68

Answer :

Question Type : **NAT**

Question ID : **2284829206**

Status : **Answered**

Q.34

In the context of schema normalization in relational DBMS, consider a set F of functional dependencies. The set of all functional dependencies implied by F is called the closure of F. To compute the closure of F, Armstrong's Axioms can be applied. Consider X, Y, and Z as sets of attributes over a relational schema. The three rules of Armstrong's Axioms are described as follows.

Reflexivity: If $Y \subseteq X$, then $X \rightarrow Y$

Augmentation: If $X \rightarrow Y$, then $XZ \rightarrow YZ$ for any Z

Transitivity: If $X \rightarrow Y$ and $Y \rightarrow Z$, then $X \rightarrow Z$

The additional rule of Union is defined as follows.

Union: If $X \rightarrow Y$ and $X \rightarrow Z$, then $X \rightarrow YZ$

It can be proved that the additional rule of Union is also implied by the three rules of Armstrong's Axioms. Listed below are four combinations of these three rules. Which one of these combinations is both necessary and sufficient for the proof ?

Options A.

Transitivity

B.

Reflexivity and Augmentation

C.

Augmentation and Transitivity

D.

Reflexivity, Augmentation, and Transitivity

Question Type : **MCQ**

Question ID : **2284829191**


Status : **Answered**

Chosen Option : **C**

Q.35

Consider the digital circuit shown below with two input lines A and B, two select lines S0 and S1, and an output line Y. The blocks Q and M represent active high 2:4 decoder and 4-to-1 multiplexer, respectively. Out of 16 possible input combinations, the number of combinations that produce Y=1 is _____.
(answer in integer)

Note: One input combination is an instance of [A B S1 S0].



Given 5
Answer :

Question Type : **NAT**

Question ID : **2284829208**

Status : **Answered**

Q.36

An index in a DBMS is said to be dense if an index entry appears for every search-key value in the indexed file. Otherwise it is called a sparse index. Consider the following two statements.

S1: A hash index must be a dense index

S2: A B^+ tree index can be a sparse index

Which one of the following options is correct?

Options A.

Both S1 and S2 are false

B.

Both S1 and S2 are true

C.

S1 is true and S2 is false

D.

S1 is false and S2 is true

Question Type : **MCQ**

Question ID : **2284829195**

Status : **Answered**

Chosen Option : **D**

Q.37

Consider a table T , where the elements $T[i][j]$, $0 \leq i, j \leq n$, represent the cost of the optimal solutions of different subproblems of a problem that is being solved using a dynamic programming algorithm. The recursive formulation to compute the table entries is as follows:

$$T[0][k] = T[k][0] = 1 \quad \text{for } k = 0, 1, 2, \dots, n$$

$$T[i][j] = 2T[i-1][j] + 3T[i][j-1] \quad \text{for } 1 \leq i, j \leq n$$

Consider the following two algorithms to compute entries of T . Assume that for both the algorithms, for all $0 \leq i, j \leq n$, $T[i][j]$ has been initialized to 1.

Algorithm B_1 : For $i = 1, 2, \dots, n$

For $j = 1, 2, \dots, n$

$$T[i][j] = 2T[i-1][j] + 3T[i][j-1]$$

Algorithm B_2 : For $s = 2, 3, \dots, 2n$

For $i = 1, 2, \dots, n$

For $j = 1, 2, \dots, n$

If $(i + j == s)$

$$T[i][j] = 2T[i-1][j] + 3T[i][j-1]$$

Algorithm B_k , $k \in \{1, 2\}$ is said to be correct if and only if it calculates the correct values of $T[i][j]$, for all $0 \leq i, j \leq n$, (as per the recursive formulation) at the end of the execution of the algorithm B_k .

Which one of the following statements is true?

Options A.

Both algorithms B_1 and B_2 are correct

B.

Algorithm B_2 is correct, but algorithm B_1 is incorrect

C.

Algorithm B_1 is correct, but algorithm B_2 is incorrect

D.

Both algorithms B_1 and B_2 are incorrect

Question Type : MCQ

Question ID : 2284829188

Status : Not Answered

Chosen Option : --

Q.38

Consider a system with 1 MB physical memory and a word length of 1 byte. The system uses a direct mapped cache, with block numbers starting from 0. The word with physical address 0xA2C28 is mapped to the cache block number 176₁₀. The maximum possible size of the cache (in KB) for this configuration is _____. (answer in integer)

Note: 1K=2¹⁰ and 1M=2²⁰

Given 16

Answer :

Question Type : **NAT**

Question ID : **2284829205**

Status : **Answered**

Q.39

Consider a complete graph K_n with n vertices ($n > 4$). Note that multiple spanning trees can be constructed over K_n . Each of these spanning trees is represented as a set of edges. The Jaccard coefficient between any two sets is defined as the ratio of the size of the intersection of the two sets to the size of the union of the two sets.

Which one of the following options gives the lowest possible value for the Jaccard coefficient between any two spanning trees of K_n ?

Options A.

0

B.

$$\frac{1}{n-1}$$

C.

$$\frac{1}{n}$$

D.

$$\frac{1}{2n-3}$$

Question Type : **MCQ**

Question ID : **2284829185**

Status : **Not Answered**

Chosen Option : --

Q.40

Consider a new TCP connection between a sender and a receiver. The receiver advertised window is constant at 48 KB, the maximum segment size (MSS) is 2 KB, and the slow start threshold for TCP congestion control is 16 KB. Assume that there are no timeouts or duplicate acknowledgements. The number of rounds of transmission required for the congestion control algorithm of the TCP connection to reach the congestion avoidance phase is _____. (answer in integer)

Note: $1K=2^{10}$

Given 5

Answer :

Question Type : **NAT**

Question ID : **2284829207**

Status : **Answered**

Q.41

To keep track of free blocks in a file system, one of the two approaches is generally used – using bitmaps (bit vectors) or using linked lists. Consider that the linked list approach is used to keep track of free blocks in a file system. Assume that the disk size is 16 GB, block size is 2 KB, and block numbers used are 32-bit long. A single pointer of size 4 bytes is used in each block of the list to point to the next block of the list. The number of blocks required to hold the free disk block numbers is _____. (answer in integer)

Note: $1K=2^{10}$ and $1G=2^{30}$

Given 5


Answer :

Question Type : **NAT**


Question ID : **2284829202**

Status : **Answered**

Q.42 Consider the following two finite automata D_1 and D_2 .



D_1



D_2

Which of the following statements is/are true?

Options A.

$$L(D_1) \cap L(D_2) = \{\epsilon\}$$

B.

$(L(D_1) \cup L(D_2))^*$ consists of all strings in $\{0,1\}^*$ whose length is divisible by 3

C.

$L(D_1)$ is a proper subset of $L(D_2)$

D.

$$L(D_1) = L(D_2)$$

Question Type : **MSQ**

Question ID : **2284829196**

Status : **Answered**

Chosen Option : **A,C,D**

Q.43

Consider a system with a processor and a 4 KB direct mapped cache with block size of 16 bytes. The system has a 16 MB physical memory. Four words P, Q, R, and S are accessed by the processor in the same order 10 times. That is, there are a total of 40 memory references in the sequence P, Q, R, S, P, Q, R, S,...

Assume that the cache memory is initially empty. The physical addresses of the words are given below (1 word = 1 byte).

P: 0x845B32, Q: 0x845B26, R: 0x845B36, S: 0x846B32

Which of the following statements is/are true?

Note: $1K=2^{10}$ and $1M=2^{20}$

Options A.

Every access to R results in a cache hit

B.

Every access to Q results in a cache miss

C.

Except the first access to S, all subsequent accesses to S result in cache hits

D.

Every access to P results in a cache miss

Question Type : **MSQ**

Question ID : **2284829201**

Status : **Answered**

Chosen Option : **B,C**

Q.44

Let G be a weighted directed acyclic graph with m edges and n vertices. Given G and a source vertex s in G , which one of the following options gives the worst case time complexity of the fastest algorithm to find the lengths of shortest paths from s to all vertices that are reachable from s in G ?

Options A.

$\Theta(n^3)$

B.

$\Theta(m + n \log(n))$

C.

$\Theta(nm)$

D.

$\Theta(m + n)$

Question Type : MCQ

Question ID : 2284829186

Status : Not Answered

Chosen Option : --

Q.45

Consider the following 4-variable Boolean function

$$F(A, B, C, D) = \Sigma m(0, 1, 2, 3, 8, 9, 10, 11)$$

Consider A as MSB, D as LSB. Which one of the following options represents the minimal sum of products form for the above function?

Note: $+$ is OR operation, $.$ is AND operation, $'$ is NOT operation

Options A.

$A' + B' + C' + D'$

B.

B'

C.

A'

D.

$A'.B' + A.B$

Question Type : MCQ

Question ID : 2284829189

Status : Not Answered

Chosen Option : --

Q.46

Consider contiguous allocation of physical memory to processes using variable partitioning scheme. Suppose there are 8 holes in the memory of sizes 20 KB, 4 KB, 25 KB, 18 KB, 7 KB, 9 KB, 15 KB, and 12 KB. Assume that no two holes are adjacent. Two processes P1 of size 16 KB and P2 of size 9 KB arrive in that order, and they are allocated memory using the best-fit technique. After allocating space to P1 and P2, the number of holes of size less than 8 KB is _____. (answer in integer)

Note: $1K=2^{10}$

Given 5

Answer :


Question Type : NAT

Question ID : 2284829204

Status : Answered

Q.47

Consider the control flow graph given below.



Which one of the following options is the set of live variables at the exit point of each basic block?

Options A.

B1: $\emptyset$, B2: {d, e}, B3: {a, c, f}, B4: $\emptyset$

B.

B1: {a, b, c, e, f}, B2: {d, e}, B3: {c, e, f}, B4: $\emptyset$

C.

B1: {a, b, c, e, f}, B2: {d, e}, B3: {b, c, e, f}, B4: $\emptyset$

D.

B1: $\emptyset$, B2: {d, e, f}, B3: {a, b, c, e, f}, B4: $\emptyset$

Question Type : MCQ

Question ID : 2284829194

Status : Not Answered

Chosen Option : --

Q.48

Consider a processor that has 16 general purpose registers and it uses 2-byte instruction format for all its instructions. Variable-sized opcodes are permitted. There are three different types of instructions; M-type, R-type, and C-type. Each M-type instruction has 2 register operands and a 6-bit immediate operand. Each R-type instruction has 3 register operands. Each C-type instruction has a register operand and a 6-bit offset value. If there are 2 unique M-type opcodes and 7 unique R-type opcodes, which one of the following options gives the maximum number of unique opcodes possible for C-type instructions?

Options A.

4

B.

16

C.

8

D.

64

Question Type : **MCQ**Question ID : **2284829193**Status : **Not Answered**

Chosen Option : --

Q.49

Consider three processes P1, P2, and P3 running identical code, as shown in the pseudocode below. A and B are two binary semaphores initialized to 1 and 0, respectively. X is a shared variable initialized to 0. Each line in the pseudocode is executed atomically.

Pseudocode of P1, P2, and P3

```
Wait(A);
Print(*);
X = X+1;
If (X == 2)
{
    Print($);
    Signal(B);
}
Signal(A);
Wait(B);
Print(#);
Signal(B);
```

Assume that any of the three processes can start to execute first and context switching can happen between these processes at any arbitrary time and in any arbitrary order.

Which of the following patterns is/are possible to be generated as an outcome of the execution of these three processes?

Options A.

****\$*##**

B.

****\$####**

C.

****\$##*#**

D.

*****\$###**

Question Type : **MSQ**

Question ID : **2284829200**

Status : **Answered**

Chosen Option : **B,D**

Q.50

Consider a function $f: (0,1) \rightarrow \{0,1\}$ defined as follows.

For a real number $r \in (0,1)$, $f(r) = 1$ if the second digit after the decimal point in r is one of the four digits 2, 3, 6 and 7. Otherwise, $f(r)$ is equal to 0.

The number of points in $(0,1)$ at which f is discontinuous is _____. (answer in integer)

Given **2**

Answer :

Question Type : **NAT**Question ID : **2284829213**Status : **Answered****Q.51**

Suppose an unbiased coin is tossed 6 times. Each coin toss is independent of all previous coin tosses. Let E_1 be the event that among the second, fourth, and sixth coin tosses, there are at least two heads. Let E_2 be the event that among the first, second, third, and fifth coin tosses, there are equal number of heads and tails.

The conditional probability $P(E_1|E_2)$ is equal to _____. (rounded off to one decimal place)

Given **0.2**

Answer :

Question Type : **NAT**Question ID : **2284829212**Status : **Answered**

Q.52

Consider the following ANSI-C function.

```
int func(int start, int end){
    int length=end+1-start;
    if((length<1)|| (start<0)|| (end<0)){ return(0); }
    if(length%3==0){
        return(func(start+1, end));
    } else if(length%3==1){
        return(1+func(start, end-1));
    } else {
        return(func(start+2, end));
    }
}
```

The maximum possible value that can be returned from this function is _____. (answer in integer)

Note: Ignore syntax errors (if any) in the function.

Given 5

Answer :

Question Type : **NAT**

Question ID : **2284829210**

Status : **Answered**

Q.53

Consider the transmission of data bits 110001011 over a link that uses Cyclic Redundancy Check (CRC) code for error detection. If the generator bit pattern is given to be 1001, which one of the following options shows the remainder bit pattern appended to the data bits before transmission?

Options A.

000

B.

011

C.

100

D.

101

Question Type : **MCQ**

Question ID : **2284829192**

Status : **Not Answered**

Chosen Option : --

Q.54

Let $\Sigma = \{a, b, c, d\}$ and let $L = \{a^i b^j c^k d^\ell \mid i, j, k, \ell \geq 0\}$.

Which of the following constraints ensure(s) that the language L is context-free?

Options A.

$$i = k \text{ and } j = \ell$$

B.

$$i = \ell \text{ and } j = k$$

C.

$$i + k = j + \ell$$

D.

$$i + j = k + \ell$$

Question Type : **MSQ**Question ID : **2284829197**Status : **Answered**Chosen Option : **C,D**

Q.55

The determinant of a 4×4 matrix A is 3. The value of the determinant of $2A$ is _____ . (answer in integer)

Given 9

Answer :

Question Type : **NAT**Question ID : **2284829211**Status : **Answered**