


Etiqueta + 8 entradas + 8 saídas para LED. Monte sempre todos os CIs:
a posição de cada byte na cadeia depende disso. Entrada ou saída sem uso fica livre.




Entradas: SIN165 > U2 > U1 > SOUT165 (para o Mega).
O Mega lê nesta ordem: U1 (etiqueta), U2 (IN0-7).
Botão ou chave: entre INN e GND. Apertado/ligado = 0 (pull-up de 10k).

Saídas: SIN595 > U3 > SOUT595 (para o próximo slot).
LED: anodo em LEDn, catodo no GND (1k: uns 3 mA por LED).
Quem acende os LEDs é o Mega, com o estado que vem do jogo:
nenhum LED é ligado direto a um botão.

Pinout diagram of the 74HC595 shift register. The chip is shown with pins 1 through 16. Pin 16 is VCC (+5V), pin 8 is GND, and pin 14 is SER (U3). Pins 11 and 10 are SCK and SRCLR (both +5V). Pins 12 and 13 are RCLK and OE (both GND). Pins 15 through 9 are QA through QH, which are connected to OUT0 through SOUT595. Pin 2 is GND.

Four circuit diagrams are shown, each representing a different capacitor value connected to a +5V supply and ground (GND). Each diagram consists of a vertical line with a red arrow pointing up to +5V and a green arrow pointing down to GND. A capacitor is connected in parallel across this line. The capacitors are labeled C1, C2, C3, and C4, with values 100nF, 100nF, 100nF, and 10uF respectively.



KSP Cockpit

Sheet: /
File: modulo_pequeno.kicad_sch

Title: Módulo pequeno do painel

Size: A3	Date: 2026-09-26	Rev: 1
KiCad E.D.A. kicad-cli 7.0.11+dfsg-1build4		Id: 1/1