


Base Shield V2



Arduino Uno is the most popular Arduino board so far, how ever it is sometimes frustrating w hen your project requires a lot of sensors or Leds and your jumper wires are in a mess. The purpose of creating the Base Shield is to help you get rid of bread board and jumper wires. With the rich grove connectors on the base board, you can add all the grove modules to the Arduino Uno conveniently! The pinout of Base Shield V2 is the same as Arduino Uno R3, how ever Arduino Uno is not the board one that the Base Shield V2 is compatible w ith plenty of boards.

Get One Now

Version

Product Version	Changes	Released Date
Base Shield V1.2	Initial	Oct 2011
Base Shield V1.3	Change the Grove connector layout and quantity	Aug 2012
Base Shield V2.0	Change the Grove connector layout and quantity, as well as a power sw itch to enable both 3.3V and 5V.	Mar 2014

Compatible Boards

The Base Shield is tested and fully compatible w ith follow ing boards:


- Arduino Uno(all revisions)/Seeeduino(V4&V4.2)
- Arduino Mega/Seeeduino Mega
- Arduino Zero(M0)/Seeeduino Lorawan
- Arduino Leonardo/Seeeduino Lite
- Arduino 101
- Arduino Due 3.3V
- Intel Edison 5V
- Linkit One

!!!Note

The boards are not listed above mean that it might have chance to w ork w ith the platform board how ever requires extra w ork such as jump wires or rew riting the

code. If you are interested in digging more, welcome to contact techsupport@seeed.cc.

Hardware Overview







- **1-Analog Ports:** include 4 analog ports, A0, A1, A2 and A3.
- **2-Digital Ports:** include 7 digital ports, D2, D3, D4, D5, D6, D7 and D8.
- **3-UART Port:** 1 UART port.
- **4-I2C Ports:** 4 I2C ports.
- **5-Power Switch:** when using Arduino UNO with Base Shield v2, please turn the switch to 5v position; While using Seeeduino Arch with Base Shield v2, please turn the switch to 3.3v.
- **6-Reset Button:** reset the arduino board.
- **7-PWR LED:** The Green LED turns on when power on.
- **8-P1, P2:** please solder the pads, P1 and P2 if use Base Shield v2 with Seeeduino V3.
- **Dimension:** 2.1 * 2.7 inch


Getting Started

Hardware

- Step 1. Prepare the below stuffs:

Seeeduino V4.2	Base Shield	Grove - Buzzer	Grove - Button
			
Get ONE Now	Get ONE Now	Get ONE Now	Get ONE Now

- Step 2. Connect Grove - Buzzer to port D3 of Base Shield.
- Step 3. Connect Grove - Button to port D2 of Base Shield.
- Step 4. Plug Base Shield into Seeeduino.
- Step 5. Connect Seeeduino to PC through a USB cable.



Software

- Step 1. Copy below code to Arduino IDE and upload to Seeeduino.

```
const int button = 2;      // connect a button
const int buzzer = 3;      // connect a buzzer
void setup()
{
  pinMode(button, INPUT); //set button as an INPUT device
  pinMode(buzzer, OUTPUT); //set LED as an OUTPUT device
}
void loop()
{
  int btn = digitalRead(button); //read the status of the button
  digitalWrite(buzzer, btn);
  delay(10);
}
```

- Step 2. Press the button and we will hear the buzzer.

FAQ

Please click [here](#) to see all Base Shield V2 FAQs.

Resources

- [PDF] [Download Wiki PDF](#)
- [Eagle] [Base Shield V2 SCH](#)

- [\[Eagle\]](#) Base Shiled V2 PCB
- [\[PDF\]](#) Base Shiled V2 SCH
- [\[PDF\]](#) Base Shiled V2 PCB