PHKI / HSLU / SIMON BALMER

JUST ONE MORE MOMENT

WIRING OVERVIEW

REV 02 / 28 OCT 2026

01 / TOUCH DISPLAY 2

JUST ONE MORE
MOMENT_
remaining: ...

P2 / 5 V
P6 / GND

POWER: P2 / P6
VIDEO + TOUCH: DSI / FFC

05 / LOGITECH C270

USB / VISUAL CONTEXT

03 / TOGGLE SWITCH 1

P15 / GPIO22
P20 / GND
GPIO / GND

04 / TOGGLE SWITCH 2

P16 / GPIO23
P25 / GND
GPIO / GND

Switch functions: to document

02 / ILLUMINATED ARCADE BUTTON

+TIME

COM / P9
NO / P11 / GPIO17
LED+ P13 / GPIO27
LED- / P14

33 mm / WHITE LED

GPIO / TOP VIEW

2 4 6 8 10 12 14 16 18 20 22 24 26 28 30 32 34 36 38 40
1 3 5 7 9 11 13 15 17 19 21 23 25 27 29 31 33 35 37 39

J8 / PIN 1

USB

RASPBERRY PI 5 / 8 GB

CAM/DISP

USB-C

DSI / FFC

D1
BAND / K

06 / WS2812B / 12 LEDs

+V
DIN
01 02 03 04 05 06 07 08 09 10 11 12
GND

DIN -> PIXEL 01 -> ... -> PIXEL 12

P19 / GPIO10 -> DIN
Common ground with my Pi.

OFFICIAL
27 W
USB-C PSU

PI 5 V / PIN TBD

PI GND / PIN TBD

READ THE DRAWING

- 5 V supply
- GND / common return
- GPIO signal (3.3 V)

Pxx = physical header pin.
Crossings do not join wires.
Component views are not to scale.

D1 / DIODE IN THE 5 V LEAD

PI 5 V — STRIP +V

A K

Cathode band faces the strip.
DIN connects directly to GPIO10.
Diode model: still to record.

MY CONNECTION NOTES

NeoPixel supply pins: still open.
Display power: P2 + P6.
DSI socket: CAM/DISP 0/1 TBD.
Switch functions: to document.
Power off before changing wires.
USB/DSI port positions: illustrative.