

Software Development Fundamentals Lab – I [24B15CS111]

Lab 3

NOTE: All students must submit the programs (code with running output) of this assignment in doc format to their respective faculty of Lab. as per the file naming convention Enrollment No._Assignment No.

C172.1	Develop programs/logic for data types, expressions and conditional structure.
--------	---

1. Write a C program to print a block F using the hash (#), where the F has a height of seven characters and width of five and six characters.

Expected Output:

```
#####  
#  
#  
#####  
#  
#  
#
```

2. Write a C program to compute the perimeter and area of a rectangle with a height of 7 inches and width of 5 inches.

Expected Output:

Perimeter of the rectangle = 24 inches

Area of the rectangle = 35 square inches

3. Write a C program that accepts an employee's ID, total worked hours in a month and the amount he received per hour. Print the ID and salary (with two decimal places) of the employee for a particular month.

Test Data :

Input the Employees ID(Max. 10 chars): 0342

Input the working hrs: 8

Salary amount/hr: 15000

Expected Output:
Employees ID = 0342
Salary = U\$ 120000.00

4. Write a C program to read an amount (integer value) and break the amount into the smallest possible number of bank notes.

Test Data :

Input the amount: 375

Expected Output:

There are:

3 Note(s) of 100.00

1 Note(s) of 50.00

1 Note(s) of 20.00

0 Note(s) of 10.00

1 Note(s) of 5.00

0 Note(s) of 2.00

0 Note(s) of 1.00

5. Write a C program to convert a given integer (in days) to years, months and days, assuming that all months have 30 days and all years have 365 days.

Test Data :

Input no. of days: 2535

Expected Output:

6 Year(s)

11 Month(s)

15 Day(s)

6. Write a C program to check if two numbers in a pair are in ascending order or descending order.

Test Data :

Input a pair of numbers (for example 10,2 : 2,10):

Input first number of the pair: 10

Expected Output:

Input second number of the pair: 2

The pair is in descending order!