

PAKISTAN NAVY ENGINEERING COLLEGE, NATIONAL UNIVERSITY OF SCIENCES
AND TECHNOLOGY, KARACHI

PNEC NUST



Electromagnetic Field Theory

Complex Engineering Problem (CEP)

Name: Sonia Azhar Siddiqui

CMS-ID: EE-1667

Class: EE-B2

Semester: 4

Department: Electrical Engineering

Instructor: Muhammad Mustaqim

DEPARTMENT OF ELECTRONICS & POWER ENGINEERING

Electromagnetic Field Analysis for Multi-layer PCB

Problem Statement

You are an electrical engineer working on the design of a multi-layered printed circuit board (PCB) for high-frequency applications. The PCB consists of three dielectric layers with different relative permittivities, sandwiched between two large conducting planes that serve as ground and power planes. A signal trace runs through the middle layer, carrying a time-varying current that generates an electric field within the structure.

Dielectric Layers

- **Top Dielectric Layer:**
 - Thickness: $d_1 = 0.5$ mm
 - Relative Permittivity: $\epsilon_{r1} = 4.5$
- **Middle Dielectric Layer:**
 - Thickness: $d_2 = 1.0$ mm
 - Relative Permittivity: $\epsilon_{r2} = 3.0$
- **Bottom Dielectric Layer:**
 - Thickness: $d_3 = 0.5$ mm
 - Relative Permittivity: $\epsilon_{r3} = 6.0$

1. Electric Field Distribution

Using Maxwell's equations and electromagnetic boundary conditions, the electric field distribution can be analyzed as follows:

Let the electric field in each layer be $E_1(z)$, $E_2(z)$, and $E_3(z)$ for the top, middle, and bottom layers respectively.

Boundary Conditions:

- The tangential component of E is continuous across boundaries.
- The normal component of $D = \epsilon E$ is also continuous.

Using these, and assuming symmetry due to the signal trace at the center of the middle layer, the fields can be modeled by solving

Poisson's equation in each dielectric region and applying boundary conditions at the interfaces.

2. Effect of Layer Properties

Relative permittivity (ϵ_r) and thickness influence field distribution:

- Higher ϵ_r causes the electric field to be more concentrated in that region.
- Thicker layers increase the contribution of that layer's permittivity to overall field distribution.

Implications:

- Higher ϵ_r improves signal confinement but increases capacitance and affects impedance.
- Uneven layers may cause field distortion leading to crosstalk or EMI.

3. Capacitance per Unit Length

Capacitance per unit length (C') is modeled as a series combination of individual capacitances:

$$C' = \epsilon_0 * (\epsilon_{r1}/d1 + \epsilon_{r2}/d2 + \epsilon_{r3}/d3)$$

Substituting values:

$$C' = 8.854e-12 * (4.5/0.0005 + 3.0/0.001 + 6.0/0.0005) = 8.854e-12 * 27000 = 2.39e-7 \text{ F/m}$$

Characteristic Impedance:

$$Z_0 = 1 / (v * C') \text{ where } v = c / \sqrt{\epsilon_{\text{eff}}}$$

$$\text{Approximate } \epsilon_{\text{eff}} \approx (\epsilon_{r1}*d1 + \epsilon_{r2}*d2 + \epsilon_{r3}*d3) / (d1 + d2 + d3) = 3.75$$

$$v = 3e8 / \sqrt{3.75} \approx 1.55e8 \text{ m/s}$$

$$Z_0 = 1 / (1.55e8 * 2.39e-7) \approx 27.1 \text{ ohms}$$

4. Impact of Imperfect Conductors

Assuming perfect conductors simplifies the model by enforcing $E = 0$ at the boundaries.

However, in real applications:

- Finite conductivity causes surface resistance and power loss.
- Skin effect at high frequency further alters current distribution.
- Boundary conditions are modified due to surface currents and penetration depth.

These effects slightly degrade signal integrity and must be modeled using full-wave solvers or numerical techniques.