

1.1.4 Boolean Algebra

بولىن الجبرا جارج بول (George Boole) نے بنايا۔

CS XI

Chapter 1: Computer Systems

Lecture 04 of 20

1.1.4 Boolean Algebra

LEARN IT

Boolean algebra was developed by the English mathematician **George Boole**. It is a kind of algebra that deals with only two values: **TRUE (1)** and **FALSE (0)**. It is the foundation of digital electronics and computer programming — every `if` condition in a program is a small piece of Boolean algebra.

Concept	Description	Example
Variables	Letters that hold the value 0 or 1.	A, B, C, X, Y
Operations	Actions performed on variables.	AND, OR, NOT
Expressions	Combinations of variables and operations.	A AND B, $Y = A + B$

Some simple rules (laws) follow directly from the meaning of AND, OR and NOT. They are useful when you check or simplify answers:

OR rules	AND rules	NOT rules
$A + 0 = A$	$A \cdot 1 = A$	$(A')' = A$
$A + 1 = 1$	$A \cdot 0 = 0$	$A + A' = 1$
$A + A = A$	$A \cdot A = A$	$A \cdot A' = 0$

WORKED EXAMPLE

Using a law: Simplify $Y = A'B + AB$.

Step 1: Both terms contain B, so take B out: $Y = B(A' + A)$.

Step 2: $A' + A = 1$ (a variable OR its opposite is always 1).

Step 3: $Y = B \cdot 1 = B$.

COMMON MISTAKE

In Boolean algebra "+" means OR, not addition. So $1 + 1 = 1$ (TRUE OR TRUE is TRUE), not 2. There is no value bigger than 1.

اردو میں سمجھیں

بولین الجبرا جارج بول (George Boole) نے بنایا۔ اس میں صرف دو قیمتیں ہوتی ہیں: درست (1) اور غلط (0)۔ متغیرات (Variables) جیسے A اور B صرف 0 یا 1 رکھتے ہیں، آپریشنز AND، OR اور NOT ہیں، اور ان کے ملاپ سے ایکسپریشن (Expression) بنتا ہے۔

CHECK YOURSELF

1. Who developed Boolean algebra?

2. In Boolean algebra, what is $1 + 1$?

Answers: 1. George Boole. 2. 1 (because + means OR).

Next lecture: 1.1.5 Boolean Operations