

1.1.5 Boolean Operations

AND آپریشن تب ہی 1 دیتا ہے جب تمام ان پٹ 1 ہوں (دو تالوں والا دروازہ)۔

CS XI

Chapter 1: Computer Systems

Lecture 05 of 20

1.1.5 Boolean Operations

LEARN IT

There are three basic Boolean operations. Every other operation can be made from them.

- 1. AND operation ($\cdot$)** — gives output 1 **only when ALL inputs are 1**. Expression: $Y = A \cdot B$ (often written just AB).
- 2. OR operation ($+$)** — gives output 1 **when ANY input is 1**. Expression: $Y = A + B$.
- 3. NOT operation (' or $\bar{}$)** — **inverts** (flips) the input. If the input is 1 the output is 0, and if the input is 0 the output is 1. It is a **unary** operation, meaning it works on only one operand. Expression: $Y = A'$ (also written as A with a bar on top, $\bar{A}$).

Operation	Real-life analogy
AND	A door with two locks. The door opens only when both locks are unlocked.
OR	A room with two doors. You can enter if either door is open.
NOT	A room light switch. When the switch is ON the room is lit; when it is OFF the room is dark — the state is the opposite of "dark".

WORKED EXAMPLE

Evaluate each expression for $A = 1, B = 0$.

- $A \cdot B = 1 \cdot 0 = 0$ (not all inputs are 1).
- $A + B = 1 + 0 = 1$ (at least one input is 1).
- $B' = 0' = 1$ (NOT flips 0 to 1).
- $A \cdot B' = 1 \cdot 1 = 1$.

REMEMBER IT

AND is "strict" — everyone must agree (all 1s). OR is "easy-going" — one 1 is enough. NOT is "the rebel" — it always says the opposite.

اردو میں سمجھیں

AND آپریشن تب ہی 1 دیتا ہے جب تمام ان پٹ 1 ہوں (دو تالوں والا دروازہ)۔ OR آپریشن تب 1 دیتا ہے جب کوئی ایک ان پٹ بھی 1 ہو (دو دروازوں والا کمرہ)۔ NOT آپریشن ان پٹ کو الٹ دیتا ہے اور صرف ایک ان پٹ پر کام کرتا ہے، اس لیے اسے یونری (Unary) کہتے ہیں۔

CHECK YOURSELF

1. What symbol is used for the OR operation?
2. Why is NOT called a unary operation?
3. Find $A + B'$ when $A = 0$, $B = 1$.

Answers: 1. "+". 2. Because it works on only one operand (one input). 3. $B' = 0$, so $0 + 0 = 0$.

Next lecture: 1.1.6 Truth Tables