

# Lecture 07

## Final Revision and Mock Paper

Final revision lecture — 1 topics with explanations, worked examples, Urdu notes, practice questions and a full answer key.

BIEK Computer Science XI · Bilingual support: English + اردو

بی آئی ای کے کمپیوٹر سائنس — گیارہویں جماعت

01 book lectures in this pack

★ Golden topics, Urdu notes, review and answer key

XI

# How to use this BIEK Computer Science lecture

Each PDF is a classroom lecture from the BIEK / Sindh Computer Science textbooks (New Sindh Curriculum, STBB Grade XI–XII). Read *Learn it*, study the SVG diagram, try the worked example on paper, then answer *Check yourself* before looking at the answers. **Extra board practice** (MCQs, short and long questions) is added after the book content — it is not in the textbook. Career-only extras that were not in the book lecture list have been removed. Math is rendered with MathJax. ★ Golden topics are high-yield in board exams. The green box repeats the idea in Urdu.

ہر لیکچر بی آئی ای کے / سندھ نصاب کی کتاب کے درس کے مطابق ہے۔ سبق پڑھیں، مثال حل کریں، پھر چیک یورسیلف کے سوالات کے جواب اپنے نوٹ بک میں لکھیں۔ کتاب کے بعد اضافی بورڈ پریکٹس ہے۔ ★ گولڈن ٹاپکس امتحان میں زیادہ پوچھے جاتے ہیں۔

# One-page recaps and a mock paper

Use these pages in the last week before the exam. Read one recap, close the booklet, and say it aloud. Then sit the mock paper in 2 hours 30 minutes with no notes.

امتحان سے ایک ہفتہ پہلے یہ خلاصے زبانی دہرائیں، پھر ماک پیپر بغیر نوٹس کے حل کریں۔

## Chapter 1 recap — Computer Systems

- Discrete = counted (stairs). Continuous = measured (ramp). Digital systems use bits 0 and 1; they are reliable, accurate, easy to design and programmable.
- Analog signal = smooth sine wave. Digital signal = square wave HIGH/LOW. Digital data resists noise.
- AND · output 1 only if all inputs 1. OR + output 1 if any input 1. NOT ' inverts. NAND = NOT-AND, NOR = NOT-OR (universal). XOR 1 when inputs differ. XNOR 1 when inputs same.
- Truth table rows =  $2^n$ . SOP = sum of minterms where output is 1. POS = product of maxterms where output is 0.
- K-map: group 1, 2, 4, 8 adjacent 1s (power of 2, wrap-around allowed). Each group drops the variables that change.
- SDLC: requirement → design → implementation → testing → deployment → maintenance. Waterfall = sequential; Agile = short sprints and feedback.
- OSI 7: Physical, Data Link, Network, Transport, Session, Presentation, Application. Mnemonic: Please Do Not Throw Sausage Pizza Away. TCP/IP 4: Network Access, Internet, Transport, Application.

## Chapter 2 recap — Computational Thinking & Algorithm

- CT pillars: decomposition, pattern recognition, abstraction, algorithms.
- Algorithm = finite, ordered, unambiguous steps. Pseudocode = structured English, not a programming language.
- Bubble Sort: compare neighbours, swap if out of order; largest "bubbles" to the end each pass.  $O(n^2)$ .
- Selection Sort: find the minimum in the unsorted part and swap it to the front.  $O(n^2)$ .
- Linear Search: check one by one. Works on unsorted data.  $O(n)$ .
- Binary Search: list MUST be sorted. Repeatedly test the middle.  $O(\log n)$ . Trace with low / mid / high.
- Judge an algorithm on correctness, efficiency (time and space) and clarity. Prefer binary search on large sorted lists; linear search on small or unsorted lists.

## Chapter 3 recap — Programming Fundamentals

---

- Python: high-level, interpreted. Variables are names; types int, float, str, bool, list, dict. `input()` returns str.
- Arithmetic `+` `-` `*` `/` `//` `%` `**`. Relational. Logical `and` `or` `not`. Bitwise `&` `|` `^` `~` `<<` `>>`.
- Selection: `if` / `if-else` / `if-elif-else` / nested. Test from the top; first True wins.
- `for` = known count + range. `while` = unknown count; always update the condition. `break` leaves; `continue` skips one.
- Libraries: `import math` / `random` / `datetime`. Third-party via `pip`: NumPy, Pandas, Matplotlib.
- Syntax = will not run. Runtime = crash + traceback. Logical = runs, wrong answer.

## Chapter 4 recap — Data and Analysis

---

- Data = raw facts. Information = processed data used for decisions. Database = organised related data. DBMS = software that manages it (reduces redundancy, improves security, sharing, integrity).
- Table / relation; row / record / tuple; column / field / attribute. Primary key uniquely identifies a row. Foreign key refers to another table's primary key.
- ER model: entity (rectangle), attribute (oval), relationship (diamond), cardinality 1:1, 1:M, M:N.
- Referential integrity: you cannot orphan a child row. Cascade Update / Cascade Delete copy or remove matching child rows.
- Access objects: tables, forms, queries, reports. Queries filter with criteria, wildcards (`*`, `?`), AND/OR. Totals: Count, Sum, Avg, Group By. Charts visualise the result.

## Chapter 5 recap — Application and Impacts of Computing

---

- IoT = connected devices. Six parts: sensor, actuator, connectivity, processing, cloud, UI. AI = machines that learn and decide. Analytics = collect → store → clean → analyse → visualise.
- Together: IoT (eyes) → Analytics (sort) → AI (brain) → actuator (action).
- Sources: primary (firsthand), secondary (explained by others), tertiary (summaries). No author / date / references → do not trust.
- Assistive tech: mobility, sensory, communication, cognitive. Goal: equal access, independence, inclusion.

## Chapter 6 recap — Digital Literacy

---

- Digital literacy = find, evaluate, create and share information with digital tools, safely.
- Qualitative = words/descriptions. Quantitative = numbers. Strategies: interview, survey, prototype, observation, simulation.

- Primary data you collect; secondary data already exists. Good survey questions are clear, single-idea, unbiased.
- Present with spreadsheets (formulas such as `=AVERAGE()` ), slides, infographics and reports. Cite sources. Follow the 12-step inquiry project from question to artefact.

## Mock paper — Computer Science XI

---

Time: 2 hours 30 minutes | Total: 75 marks | Answer all questions. Calculators allowed.  
Write Python with correct indentation.

### Section A — Multiple choice (15 × 1 = 15)

1. Which quantity is discrete?
  - a. Room temperature
  - b. Number of desks
  - c. Car speed
  - d. Time of day
2. NAND is called universal because:
  - a. it has two inputs
  - b. any gate can be built from it
  - c. its output is always 1
  - d. it is faster than AND
3. The Boolean expression for XOR is:
  - a.  $A \cdot B$
  - b.  $A + B$
  - c.  $A \oplus B$
  - d.  $(A \cdot B)'$
4. OSI layer that chooses the best path (IP addresses) is:
  - a. Transport
  - b. Network
  - c. Data Link
  - d. Session
5. Which SDLC model delivers working software in short sprints?
  - a. Waterfall
  - b. Agile
  - c. Spiral only
  - d. Big Bang
6. Binary Search requires the list to be:
  - a. unsorted
  - b. sorted
  - c. all unique and unsorted
  - d. of even length
7. Worst-case time of Bubble Sort is:
  - a.  $O(n)$
  - b.  $O(\log n)$
  - c.  $O(n^2)$
  - d.  $O(1)$
8. `input()` in Python returns a:
  - a. int
  - b. str
  - c. float
  - d. bool
9. `17 // 5` equals:
  - a. 3.4
  - b. 3
  - c. 2
  - d. 3.0

- .0. A program that runs but prints the wrong total has a:
  - a. syntax error
  - b. runtime error
  - c. logical error
  - d. hardware fault
- .1. A field that uniquely identifies each record is a:
  - a. foreign key
  - b. primary key
  - c. composite description
  - d. query
- .2. An actuator in IoT:
  - a. collects temperature
  - b. opens a water valve
  - c. stores cloud files
  - d. draws a chart
- .3. Wikipedia is a:
  - a. primary source
  - b. secondary source
  - c. tertiary source
  - d. sensor
- .4. Marks out of 100 are:
  - a. qualitative data
  - b. quantitative data
  - c. tertiary data
  - d. metadata only
- .5. Which Access object is best for printing a formatted class list?
  - a. Table
  - b. Form
  - c. Query
  - d. Report

## Section B — Short questions (10 × 3 = 30)

1. Differentiate analog and digital signals with one example of each.
2. Draw the symbol and truth table of a 2-input NOR gate.
3. List the four pillars of computational thinking in one sentence each.
4. Why can you not use Binary Search on an unsorted attendance list?
5. Write a Python `if-elif-else` that prints Pass if marks  $\geq 40$ , else Fail.
6. Define primary key and foreign key.
7. Name the six components of IoT.
8. Classify: (a) a photograph you took, (b) a textbook, (c) an encyclopedia.
9. Give two good and two bad survey questions about mobile-phone use in college.
- .0. State three advantages of a DBMS over paper files.

## Section C — Long questions (3 × 10 = 30). Attempt any three.

1. Simplify  $F(A,B,C) = \Sigma(1,3,5,7)$  using a 3-variable K-map. Show the grouping and the final expression. Draw the logic diagram.

2. Dry-run Bubble Sort on the list [5, 1, 4, 2]. Show every pass. Then search for 4 using Binary Search on the sorted result, with a low/mid/high table.
3. Write a complete Python program that reads n subject marks, prints the average, and prints "A" if average  $\geq 80$ , "B" if  $\geq 70$ , "C" if  $\geq 60$ , else "D". Include a sample run of four marks: 80, 70, 90, 60.
4. Design an ER diagram and relational schema for a school library (Student, Book, Issue). Mark keys. Write one Access/SQL query that lists all books issued to roll number 101.
5. Explain how IoT, Data Analytics and AI work together on a Sindh farm. Then discuss two positive and two negative impacts of computing on education in Pakistan.

## Mock paper — answers

### Section A

- |      |      |      |       |       |
|------|------|------|-------|-------|
| 1. b | 4. b | 7. c | 10. c | 13. c |
| 2. b | 5. b | 8. b | 11. b | 14. b |
| 3. c | 6. b | 9. b | 12. b | 15. d |

### Section B

1. Analog: continuous, sine wave, e.g. human voice. Digital: two levels 0/1, square wave, e.g. computer data. Digital resists noise.
2. NOR symbol: OR-gate shape with a bubble on the output.  $Y = (A+B)'$ . Truth: 00→1, 01→0, 10→0, 11→0.
3. Decomposition = split a problem. Pattern recognition = reuse similarities. Abstraction = ignore extra detail. Algorithms = write ordered steps.
4. Binary Search repeatedly halves a sorted range. If the list is unsorted, the middle value does not tell you which half to keep, so the method is invalid.
5. `m = int(input("Marks: "))` then `if m ≥ 40: print("Pass") else print("Fail")`.
6. Primary key: unique identifier of a row (e.g. StudentID). Foreign key: a field that refers to the primary key of another table (e.g. StudentID in Issuance).
7. Sensors, actuators, connectivity, data processing, cloud computing, user interface.
8. (a) primary (b) secondary (c) tertiary.
9. Good: "How many hours per day do you use a phone for study?" / "Which apps do you use for class notes?" Bad: "Don't you agree phones are destroying students?" (leading) / "Do you like phones and also use laptops?" (double-barrelled).
10. Less redundancy, easier search and update, better security and multi-user access, integrity constraints. (Any three.)

### Section C — outline

1. K-map 1s at m1, m3, m5, m7 form one group of 4 covering B=1 (or C=1 depending on labelling — with standard ABC order the 1s are all cells where C=1).  $F = C$ . Diagram: a single wire C to output (or a buffer). Show the map with the group circled.

2. Pass 1: [1,4,2,5]; Pass 2: [1,2,4,5]; Pass 3: already sorted. Sorted [1,2,4,5]. Search 4: low=0 high=3 mid=1 (2<4) → low=2; mid=2 (4=4) found at index 2.
3. Read n, loop n times adding `float(input())`, avg = total/n, then if-elif for A/B/C/D. Sample: total 300, avg 75.0, grade B.
4. Entities Student(StudentID PK, Name, Class), Book(BookID PK, Title, Author), Issue(IssueID PK, StudentID FK, BookID FK, Date). Query: `SELECT Book.Title FROM Issue INNER JOIN Book ON Issue.BookID = Book.BookID WHERE StudentID = 101;`
5. Soil sensor (IoT) → cloud spreadsheet of moisture (Analytics) → model decides "too dry" (AI) → pump (actuator). Education +: LMS, remote classes. Education -: screen addiction, urban/rural device gap.