

1.1.5 Boolean Operations

AND آپریشن تب ہی 1 دیتا ہے جب تمام ان پٹ 1 ہوں (دو تالوں والا دروازہ)۔

CS XI

Chapter 1: Computer Systems

Lecture 05 of 20

1.1.5 Boolean Operations

LEARN IT

There are three basic Boolean operations. Every other operation can be made from them.

1. AND operation ($\cdot$) — gives output 1 **only when ALL inputs are 1**. Expression: $Y = A \cdot B$ (often written just AB).

2. OR operation ($+$) — gives output 1 **when ANY input is 1**. Expression: $Y = A + B$.

3. NOT operation (' or $\bar{}$) — **inverts** (flips) the input. If the input is 1 the output is 0, and if the input is 0 the output is 1. It is a **unary** operation, meaning it works on only one operand. Expression: $Y = A'$ (also written as A with a bar on top, $\bar{A}$).

Operation	Real-life analogy
AND	A door with two locks. The door opens only when both locks are unlocked.
OR	A room with two doors. You can enter if either door is open.
NOT	A room light switch. When the switch is ON the room is lit; when it is OFF the room is dark — the state is the opposite of "dark".

WORKED EXAMPLE

Evaluate each expression for $A = 1$, $B = 0$.

- (a) $A \cdot B = 1 \cdot 0 = 0$ (not all inputs are 1).
- (b) $A + B = 1 + 0 = 1$ (at least one input is 1).
- (c) $B' = 0' = 1$ (NOT flips 0 to 1).
- (d) $A \cdot B' = 1 \cdot 1 = 1$.

REMEMBER IT

AND is "strict" — everyone must agree (all 1s). OR is "easy-going" — one 1 is enough. NOT is "the rebel" — it always says the opposite.

اردو میں سمجھیں

AND آپریشن تب ہی 1 دیتا ہے جب تمام ان پٹ 1 ہوں (دو تالوں والا دروازہ)۔ OR آپریشن تب 1 دیتا ہے جب کوئی ایک ان پٹ بھی 1 ہو (دو دروازوں والا کمرہ)۔ NOT آپریشن ان پٹ کو الٹ دیتا ہے اور صرف ایک ان پٹ پر کام کرتا ہے، اس لیے اسے یونری (Unary) کہتے ہیں۔

CHECK YOURSELF

- 1. What symbol is used for the OR operation?
- 2. Why is NOT called a unary operation?
- 3. Find $A + B'$ when $A = 0$, $B = 1$.

Answers: 1. "+". 2. Because it works on only one operand (one input). 3. $B' = 0$, so $0 + 0 = 0$.

Next lecture: 1.1.6 Truth Tables