Sherlotronics 12 V Relay Board 7 A

12–16 V AC/DC relay board with LED · 7 A contact

STOCK CODE

14SHRELAY

Small relay board for switching sirens, strobes, lights or isolating fence outputs.



7 A	10 A	AC/DC	24 mo
@ 250 VAC	@ 30 VDC	10–16 V coil	warranty

WHY CUSTOMERS CHOOSE IT

- **N/O and N/C** potential-free contacts
- Full-bridge rectifier — AC or DC coil
- LED indication
- Tiny 35 × 30 mm board

BEST FOR

- ✔ Switching a 240 V light from an alarm or receiver
- ✔ Driving sirens/strobes needing more current
- ✔ Converting N/C to N/O
- ✔ Isolating electric fence outputs from transmitters

NOT FOR

- ✖ Loads above 7 A AC / 10 A DC
- ✖ 24 V coil supplies

KEY SPECS

Coil voltage	**10 – 16 V AC/DC**
Contacts	**7 A @ 250 VAC · 10 A @ 30 VDC**
Size / weight	**35 × 30 × 16 mm · 17 g**
Operating temp	**−3 to +60 °C**

FAMILY — PICK THE RIGHT ONE

RELAY	Single relay — **this unit**
DOUBLERELAY	**12 V DC double-pole relay board**

COUNTER QUICK ANSWERS

Switch a flood light? Yes, up to 7 A at 240 VAC.

AC or DC? Coil works on either, 10–16 V.

Warranty? 24 months.

Source: Sherlotronics Relay Boards datasheet.