

84 8

Mo Tu We Th Fr Sa Su

Sales 4 - 2. 22V 12V - 5 no new time

400W
RV, 24V

Memo No. _____
Date / /

479.92

3) Desktop - 200W.

minimum 150w

KV TV

L7 PABX - 20W 8 to 5pm.

Mylaminator = 350 - 400W

*N) AC (2400 - 6000W)

07 Server = 390W

- 420W

- 800W

- 1200W

* Servers

* Routers

* Switches - 26W

* Firewalls

Sitting Customer Data


1. Name

2. Location

3. Problem - solar, inverter charger [System needed]

4. Location. Contact - phone number, e-mail.





Mo	We	Th	Fr	Sa	Su
----	----	----	----	----	----

Q - 3

195,086.34

0736083819

Memo No. 241 bal.
Date / /

7 Toaster - 600W Blender - 600-800

E. Kettle - ¹⁸⁰⁰2250W - 3kW, 15 mins [Use 1hr, 252

* F. Jugs 1800 - 2250W

Cooker

A

1532.50

Small water booster pump

0.5HP → 1HP

550W

750W.

1HP = 0.75kW.

or 375W.

Max of 2hrs

B7 CCTV, NVR

~~30W~~ - 60W

- 24hrs

- 70-80% usage.

C7 Electric fence energizer - 30W

- 24hrs

- 80%

Instant shower

4500W -
5000W

600g

Cutting machine

3600 - 5500W
ene



600

Mo Tu We Th Fr Sa Su

Memo No. _____

Date / /

C7 Tube light

2 feet - 9W / 10W

4 feet - 18 / 20W

Sitting room, Kitchen, Dining, Pantry, Corridor, Bedroom,
stairs, study room, balcony, washrooms, garage

Outdoor / security lights

Gate lights

Wall lights

Fence / perimeter lights

Garden lights =

12hrs

100%

7W

* Floodlights = 30W - 100W. Recommend

all-in one solar light

Bedroom lights = 2hrs, 100% or 80%

LOAD SEPARATION ✓



Mo	Tu	We	Th	Fr	Sa	Su
----	----	----	----	----	----	----

TRAINING

Memo No.

Date _____

Solar Design tool.

Ay <u>TV</u> + Size - 32"	40"/43"	4 ⁹ 8 "	50/55"	65"	75"
29-40W	60-68W	130W	145W	160W	160W

→ Usage hours = ? 4 hours

- * TV Decoder - Zuber
- Statimes
- DSTV

* GoTV ✓

! → Usage 2 hrs.

12 hrs = 100% ✓✓

802

Microwave - 600 W
1 hr - 30%

$$\frac{200 \text{ km}}{10 \text{ h}}$$

B7 Home theatre - 70W.

or subwoofer

5 hrs.

or radio

100? $\frac{1}{2}$

Changeover
15,000 l

с7. Wi-fi Router / TP link. - 20W

12 hrs

low

Long tube $\rightarrow 9W, 18W$

~~250-300 km~~
~~12-15 k~~
~~delivery~~
~~long~~
~~distance.~~

~~Def.~~

$FX = 100\%$

$Fridge = 50\%$



Mo	Tu	We	Th	Fr	Sa	Su
----	----	----	----	----	----	----

Memo No. _____

Date / /

1) Livoitek. (DC) Voltage. (Watts) Maximum Solar Input

1KW

12V

560W (680W)

3KW

24V

1680W.

5KW

48V

4000W.

2) Foxpowers.

3.6KW.

24V

4000W

5.6KW.

48V.

6000W.

$$4 \times 200ah = 5.12 KWh.$$

$$8 \times 200ah = 10.24 KWh.$$

* BMS - Battery Management System.

30% for Lithium.

Selling Solar Power Solutions.


* Identifying Customer needs;

- Cold Calling.

- Email

- Physical Visit.

* Create / take a load profile & usage pattern.



Livoltex.	(DC)	(Watts)
	Voltage	Maximum Solar Input
1KW	12V	560W(680W)
3KW	24V	1680W.
5KW	48V	4000W.

2) Foxpowers.

3.6KW.	24V	4000W
5.6KW.	48V.	6000W.

$$4 \times 200ah = 5.12KWh.$$

$$8 \times 200ah = 10.24KWh.$$

70-9

* BMS - Battery Management System.
30% for Lithium.

Selling Solar Power Solutions.

* Identifying Customer needs;

- Cold Calling.

- Email

- Physical Visit.

* Create / take a load profile & usage pattern.



0715267160/0713042419

Memo No. _____

Date _____ / _____ / _____

Memo No. _____

Date _____ / _____ / _____

TRAINING

Mo	Tu	We	Th	Fr	Sa	Su

Solar Design tool.

A7 TV + Size - 32"	40"/43"	48"	50/55"	65"	75"
29-40W	60-68W	130W	145W	160W	160W

anya Good Neighbours

Kinganyu.

-1✓

Usage hours = ?

5hrs

TV Recorder - Zuker

80%



Mo	Tu	We	Th	Fr	Sa	Su
----	----	----	----	----	----	----

NRLA - Valve Regulated

Lead Acid

Memo No. _____

Date _____

Inverter Voltages

i) 12VDC. Voltage Direct current (VDC).

ii) 24VDC

iii) 36VDC.

iv) 48VDC.

* Sun hours always use 5 hours.

* Solar Panels commonly available in stock: 24VDC, 48VDC, 340W, 415W, 550W, 565W, 580W.
 415W Flagson, 550W TW Solar, 565W JA Solar, 580W

Types of Inverters.

1. Off-grid Inverters - Inbuilt No solar charge controller
2. Hybrid Inverters - Inbuilt solar charge controller (MPPT).

Solar charge controller - Regulates charging for batteries.

ii) Regulates LVD for batteries in a purely DC setup.

* 12VDC - 1 batteries. Odd/even number of batteries.

* 24VDC - A multiple of 2 batteries.

* 48VDC - A multiples of 4 batteries.

direct
indirect
system.

0.5 hr 500
Blender 600W
Dispenser 500W 12 hr 30%

DCS

0.5 80%
Iron box 1100W

Microwave 800W 0.5 hrs 80



Tuata

Mo Tu We Th Fr Sa Su

Memo No. _____
Date / /

➤ Motorized gate - 50W

- 1 hr

- 70?

E) Door access - 10W }
Electric Bell - 10W } 100?

LIGHTING

A) Indoor lights.

Chandelier - 30W / 40W

Wall brackets - 7W

Normal bulbs - 7W *

Spot lights / gypsum lights - 3W

Panel lights - Round 6W (homes)

Square - 14W (offices)

B) Snake lights

1 meter = 1W



Tuata

Mo Tu We Th Fr Sa Su

Memo No.
Date

⇒ Motorized gate - 50W

- 1 hr

- 70?

⇒ Door access - 10W }
Electric Bell - 10W } 100?

LIGHTING

A) Indoor lights.

Chandelier - 30W / 40W

Wall brackets - 7W

Normal bulbs - 7W *

Spot lights / gypsum lights - 3W

Panel lights - Round 6W (homes)

Square - 14W (offices)

B) Snake lights

1 meter = 1W



Mo	Tu	We	Th	Fr	Sa	Su
----	----	----	----	----	----	----

Memo No. _____

Date / /

D7 Laptops - 65W - 100%

- 2 hours

Office too
E7 Desktop - 150 - 200WHouse printer
F7 Small printer - 50W

G7 Iron box - 1100W

- 1 hour

A7 Water dispenser - 500W

- 12 hrs = 30%

Highly rated

200

KITCHEN

B7 Fridge - standard fridge

- 115W

- 24hrs

Duty cycle - 30-50%

Side by side fridge

- 170W

- 24hrs

Duty cycle = 30 - 50%

100%

50%

C7 Deep freezer - 175W 30% 24HRS

San
King
West

OFFICE APPLIANCES

10
60

Appliances

A) Printer - Centralized
• ~~Printer~~ Standalone 1250-2100 W
Copier

• Desk printers - 350 W.

• Ink-jet printer - 50 W (epson)

8 hrs 20% / 30

B) Paper shredder - 450 W

C) Microwave - ^{high} 1200 W ~~1000~~ 1250.

- 10 mins 1 hr 50%

D) Fridge - 115 W, 24 hrs, 50%

E) Dispenser - 500 W - 420

F) CCTV - 60 W

G) Door Access Control - 10 W

H) Wifi router - 20 W

I) Laptops - 45 / 65 W

Washing Machine (wash & spin) - 600 W.