

VLANs per Student Rack

RA0X-L

Vlan X1 – Management
Vlan X2 – Data_Users
Vlan X3 – Voice_Users
Vlan X4 – Reserved
Vlan 99 - Native

RA0X-R

Vlan X5 – Management
Vlan X6 – Data_Users
Vlan X7 – Voice_Users
Vlan X8 – Reserved
Vlan 99 - Native

Subnets per Student Rack

RA0X-L

Vlan X1 – 172.18.x.0/28
Vlan X2 – 172.18.x.16/28
Vlan X3 – 172.18.x.32/28
Vlan X4 – 172.18.x.48/28

RA0X-R

Vlan X5 – 172.18.x.64/28
Vlan X6 – 172.18.x.80/28
Vlan X7 – 172.18.x.96/28
Vlan X8 – 172.18.x.112/28

IP addressing solid structure Subnets Student Rack

1ste client address - HRSP/VRRP default-gateway

2nd client address - LAB-BR-C-R02

3rd client address - LAB-RA0X-A01(02)-SW01 (mgmt subnet only)

4th client address - LAB-RA0X-A01(02)-SW02 (mgmt subnet only)

RA0X-L

172.18.X.21-30 client address – DHCP assigned (Data user subnet only)

RA0X-R

172.18.X.85-94 client address – DHCP assigned (Data user subnet only)

X = student rack number

Y = See pathing list

AAA – See IP addressing

C01 – core student RA0X-L

A01 – access student RA0X-L

C02 – core student RA0X-R

A02 – access student RA0X-R

Patching information Student Rack

RA0X-L

Port 2

RA0X-R

Port 10

Patching information Central Rack

RA0X-L

LAB-RA01-A01-SW01 - LAB-BR-A-SW03 – Fa 0/1
LAB-RA02-A01-SW01 - LAB-BR-A-SW03 – Fa 0/3
LAB-RA03-A01-SW01 - LAB-BR-A-SW03 – Fa 0/5
LAB-RA04-A01-SW01 - LAB-BR-A-SW03 – Fa 0/7
LAB-RA05-A01-SW01 - LAB-BR-A-SW03 – Fa 0/9
LAB-RA06-A01-SW01 - LAB-BR-A-SW03 – Fa 0/11
LAB-RA07-A01-SW01 - LAB-BR-A-SW03 – Fa 0/13
LAB-RA08-A01-SW01 - LAB-BR-A-SW03 – Fa 0/15
LAB-RA09-A01-SW01 - LAB-BR-A-SW03 – Fa 0/17
LAB-RA10-A01-SW01 - LAB-BR-A-SW03 – Fa 0/19

RA0X-R

LAB-RA01-A02-SW01 - LAB-BR-A-SW03 – Fa 0/2
LAB-RA02-A02-SW01 - LAB-BR-A-SW03 – Fa 0/4
LAB-RA03-A02-SW01 - LAB-BR-A-SW03 – Fa 0/6
LAB-RA04-A02-SW01 - LAB-BR-A-SW03 – Fa 0/8
LAB-RA05-A02-SW01 - LAB-BR-A-SW03 – Fa 0/10
LAB-RA06-A02-SW01 - LAB-BR-A-SW03 – Fa 0/12
LAB-RA07-A02-SW01 - LAB-BR-A-SW03 – Fa 0/14
LAB-RA08-A02-SW01 - LAB-BR-A-SW03 – Fa 0/16
LAB-RA09-A02-SW01 - LAB-BR-A-SW03 – Fa 0/18
LAB-RA10-A02-SW01 - LAB-BR-A-SW03 – Fa 0/20



Title:

LAB 1 – BASIC TRUNK CONFIGURATION

Drawn by:

Wim Leppens

Group(s):

1SNE

Page 2 of 2

Version:

V1.0

Date:

03-03-24