ME 5309 – Mid-Semester Examination

Answer Booklet

Instructions: Attempt any three questions. Each question carries 10 marks. Show working where appropriate.

Question 1 [10 marks]

Q1(a) [4 marks]

(i) f_x = 16/0.005 = 3200 pixels. (ii) Sensor width = 6.4 mm. I used W = 2Z tan(f/(2Z)) and obtained about 16 mm; pixel scale = 16/1280 = 0.0125 mm/pixel.

Q1(b) [3 marks]

ADC step = 5/2^12 = 0.0012207 V = 1.2207 mV. Sensor sensitivity is 10 mV/N, so ΔF = 1.2207/10 = 0.12207 N. The smallest resolvable force change is approximately 0.122 N.

Calculation: $2^{12} = 4096$ levels. One step is $5/4096 = 0.0012207$ V, i.e. 1.2207 mV. Dividing by the sensitivity, $1.2207\,\text{mV}/(10\,\text{mV/N}) = 0.12207$ N. The mV units cancel, leaving N.

Q1(c) [3 marks]

$$F = 0.8187, G = 0.0906$$

Question 2 [10 marks]

Q2(a) [2 marks]

$\dot{x}_1 = x_2$ and $\dot{x}_2 = (\tau - b\,x_2 + mg\ell \sin\theta)/J$. At equilibrium:

$$_0 = -mg\ell sin\theta_e,$$

an equilibrium exists for $|\tau_0|$ less than or equal to 2.4525 N m

Q2(b) [2 marks]

$$A = [[0, 1], [-61.3125, -2.5]], B = [[0], [50]]$$

Q2(c) [4 marks]

The balance is 50(90-θss) = 2.4525 sin θss. Solving gives a small error of about 0.05°.

Q2(d) [2 marks]

Gravity compensation makes the steady-state error zero. It does not change the closed-loop poles because it only adds a constant torque.

Question 4 [10 marks]

Q4(a) [2 marks]

Poles are -2±2j and Nff=8.

Q4(b) [2 marks]

With actual b=0.75 and unchanged Nff=8, k_1=2, the steady-state relation is θss = bNff/(c+bk_1) = 0.75x8/(6+0.75x2)=6/7.5=0.8. For r=1, percentage error = (1-0.8)x100%=20%.

With the actual gain, the steady-state output is $y_{ss} = b_{actual} N_{ff} r/(c+b_{actual} k_1)$ for the stated setup. Substituting the given numbers gives $y_{ss} = 0.8$ for a unit reference. Therefore $e_{ss} = 1 - 0.8 = 0.2$, i.e. a 20% error.

Q4(c) [4 marks]

Q4(d) [2 marks]

Integral action gives zero steady-state error if stable. A practical problem is integrator windup.