ME 5309 – Mid-Semester Examination

Answer Booklet

Instructions: Attempt any three questions. Each question carries 10 marks. Show working where appropriate.

Question 1 [10 marks]

Q1(a) [4 marks]

Q1(b) [3 marks]

ADC step = 5/2^12 = 0.0012207 V = 1.2207 mV. Sensor sensitivity is 10 mV/N, so ΔF = 1.2207/10 = 0.12207 N. The smallest resolvable force change is approximately 0.122 N.

Calculation: $2^{12} = 4096$ levels. One step is $5/4096 = 0.0012207$ V, i.e. 1.2207 mV. Dividing by the sensitivity, $1.2207\,\text{mV}/(10\,\text{mV/N}) = 0.12207$ N. The mV units cancel, leaving N.

Q1(c) [3 marks]

$$F = e^(- 2 \times 0.1) = 0.818731$$

I used G = (1-F)/(-2) = -0.0906346. So:

$$x_{k+1} = 0.818731 x_k - 0.0906346 u_k$$

Question 2 [10 marks]

Q2(a) [2 marks]

$\dot{x}_1 = x_2$ and $\dot{x}_2 = (\tau - b\, x_2 + mg\ell \sin\theta)/J$. At equilibrium:

$$_0 = -mg\ell sin\theta_e,$$

an equilibrium exists for $|\tau_0|$ less than or equal to 2.4525 N m

Q2(b) [2 marks]

$$A = [[0, 1], [-mg\ell sin(60^\circ)/J, -b/J]] = [[0, 1], [-106.2, -2.5]],$$
$$B = [[0], [50]]$$

Q2(c) [4 marks]

Q2(d) [2 marks]

The added gravity torque should cancel the load, so the steady-state error becomes zero.

Question 4 [10 marks]

Q4(a) [2 marks]

The closed-loop poles are -2±2j. I use Nff=c/b=6 for unity DC gain.

Q4(b) [2 marks]

$$\theta_{ss} = 0.75 \times 8/(6+2) = 0.75,$$

the percentage tracking error is 25%

Q4(c) [4 marks]

$$k_1 = 18, k_2 = 6, K_I = 32$$

Q4(d) [2 marks]

Integral action helps eliminate error. A problem is that the controller can become unstable.