

Second Chance implementation

Version 1 : FIFO-like algorithm

➔ use the accessed bit supported by most hardware

Data structure

linked list of pages with two pointers head and tail

Code

- on hit, set the corresponding page's accessed bit to 1
- on miss
 1. while head's accessed bit is 1, set head's accessed bit to 0 and move it to tail
 2. else head's accessed bit is 0, swap the head and move the new page to tail

● Good performances but requires moving pages on every miss

Second Chance implementation

Version 2 : Clock algorithm

➔ use the accessed bit supported by most hardware

Data structure

circular linked list of pages (clock) with one pointer (hand)

Code

- on hit, set the corresponding page's accessed bit to 1
- on miss
 1. while hand's accessed bit is 1, set hand's accessed bit to 0 and move to next page
 2. else if hand's accessed bit is 0, swap the hand's page with the new page and an move next page

● Better performances than fifo-like second chance (no rotation on miss)