

NATEF TASK SHEET --- SECTION A6 B.1, 5 (P-1)

SC2: CHARGE BATTERY: FILLING UP THE BATTERY!

Student: _____ Date: _____ Period: _____
VIN: _____ Year: _____ Make: _____ Model: _____

OBJECTIVE: Student will check a battery's state of charge, charge the battery in or out of a vehicle, recheck the state of charge, and make recommendations.

MATERIALS:1. **EYE PROTECTION**
2. Volt meter
3. Battery Charger
4. Vehicle or Battery (see instructor)

CAUTION: **EXPLOSION HAZARD!**

PROCEDURE: **WEAR EYE PROTECTION!** Watch power point SC2.
Use fender covers, seat covers, and floor mats. Verify state of charge.
Record state of charge below. Hook up positive clamp on charger to battery positive post. Hook negative lead on battery charger to good ground on engine block. Set battery charger settings according to directions on charger. Set timer for appropriate time charging.

LAST, PLUG CHARGER INTO 110 VOLT AC OUTLET!

After Charging:

Unplug charger first, then disconnect clamps on battery.

Record voltage after charging. DID IT GO UP? _____

CHECK BATTERY STATE OF CHARGE BEFORE CHARGING,
FILL IN ALL THE INFORMATION BLANKS, BELOW:

1. Voltage reading before charging:	Volts DC	Percent Full
2. Battery Eye appearance:	(GREEN, BLACK, OR YELLOW)	
3. Voltage reading after charging:	Volts DC	Percent Full

YOUR RECOMMENDATION: _____

Does the battery still need more charging?

INSTRUCTORS EVALUATION

LEVEL OF SKILL ATTAINED	Initial	OVERALL SKILL EVALUATION	Points
DEMONSTRATES MASTERY (5)		DOCUMENTATION COMPLETENESS (1)	
PERFORMS SATISFACTORILY (4)		SAFETY COMPLIANCE (1)	
CAPABLE, NEEDS PRACTICE (3)		WORK PROFESSIONALISM (3)	
ASSISTED IN PERFORMING (2)		LEVEL OF SKILL ATTAINED (1-5)	
EXPOSURE, OBSERVATION (1)		TOTAL SCORE	
INSTRUCTOR'S SIGNATURE:			

SC2/BATTCHARGE/07-05-07/VDB