

MMET 410 – Lab 6

Instructions

- Do Task 1,2,3 and 4.
- Answer all the questions by yourself.
- For task 4 the format will be the same as previous labs.
 1. Program Screenshot
 2. Program Description
 3. Input/Output Addresses
- Due date is tomorrow midnight.

Task 4

- Procedure: Push **start** button -> turn on **stacker** -> **15** parts are loaded -> turn off the **stacker** and start **conveyor** -> arrive at **B position**-> **conveyor** stop -> **painter** on for **12.5s** -> **conveyor** start -> arrive at **C position**->stop **conveyor** / **reset** CTU -> turn on **stacker again** -> Repeat...
- Total 7 rungs: 5 outputs + 1 CTU counter + 1 TON timer
- 5 Inputs: **Start: IN-0** , **Stop: IN-1** **Photoelectric_Sensor : IN-2**, **Proximity_sensor@B: IN-4**, **Proximity_sensor@C: IN-5**
- 5 Outputs: **System: OUT-0**, **Stacker: OUT-1**, **conveyor: OUT-2**, **painter: OUT-3**, **Reset for CTU**
- Push **stop** button, stop every step of the system