

(Case 1)

(10% 每個答案2分)

Example of **input and **output**:**

```
s111111  
input divisor 1 :3  
input divisor 2 :5  
input divisor 3 :7  
input remainder 1: 2  
input remainder 2: 3  
input remainder 3: 2  
magic numbers are 70,21,15,105  
answer=23
```

(Case 2) #不互質加重複

(10% 每個答案2分)

Example of **input and **output**:**

```
s111111  
input divisor 1 :12  
input divisor 2 :8  
input divisor 3 :8  
input remainder 1: 7  
input remainder 2: 3  
input remainder 3: 3  
magic numbers are null,null,null,24  
answer=19
```

(Case 3) #考 a b互質 a c互質 bc不互質

(10% 每個答案2分)

Example of **input** and **output**:

```
s111111  
input divisor 1 :9  
input divisor 2 :35  
input divisor 3 :25  
input remainder 1: 6  
input remainder 2: 18  
input remainder 3: 23  
magic numbers are null,null,null,1575  
answer=123
```

(Case 4) #考0

(5% 每個答案1分)

Example of **input** and **output**:

```
s111111  
input divisor 1 :0  
input divisor 2 :5  
input divisor 3 :7  
input remainder 1: 0  
input remainder 2: 3  
input remainder 3: 2  
magic numbers are null,null,null,null  
answer=null
```

(Case 5) #一個負數

(5% 每個答案1分)

Example of input and output:

```
s111111  
input divisor 1 :3  
input divisor 2 :5  
input divisor 3 :7  
input remainder 1: -1  
input remainder 2: 3  
input remainder 3: 2  
magic numbers are 70,21,15,105  
answer=null
```

(Hidden Case 6) #考一題有magic numbers的

(15% 每個答案3分)

Example of input and output:

```
s111111  
input divisor 1 :13  
input divisor 2 :17  
input divisor 3 :61  
input remainder 1: 5  
input remainder 2: 3  
input remainder 3: 4  
magic numbers are 4148,11102,11713,13481  
answer=6531
```

(Hidden Case 7) #考ab互質 bc互質 ac不互質

(15% 每個答案3分)

Example of input and output:

```
s111111
input divisor 1 :15
input divisor 2 :7
input divisor 3 :9
input remainder 1: 3
input remainder 2: 4
input remainder 3: 6
magic numbers are null,null,null,315
answer=123
```

(Hidden Case 8) #無解

(15% 每個答案3分)

Example of input and output:

```
s111111
input divisor 1 :3
input divisor 2 :6
input divisor 3 :9
input remainder 1: 0
input remainder 2: 0
input remainder 3: 2
magic numbers are null,null,null,18
answer=null
```

(Hidden Case 9) #一個較大的質數

(15% 每個答案3分)

Example of **input and **output**:**

```
s1111111
input divisor 1 :65537
input divisor 2 :5
input divisor 3 :7
input remainder 1: 123
input remainder 2: 3
input remainder 3: 2
magic numbers are 131075,1835036,327685,2293795
answer=1638548
```

BONUS

輸出學號(5%)

(Bonus Case 1) (5% , 全對才給分)

Example of **input and **output**:**

```
s1111111
input divisor 1 :1000
input divisor 2 :2000
input divisor 3 :1500
input remainder 1: 654
input remainder 2: 54
input remainder 3: 654
magic numbers are null,null,null,6000
answer=null
```

(Hidden Bonus Case 2)

#常見的 $\text{lcm} = a * b / \text{gcd}(a,b)$ 會爆，改變排列組合不會

(5%，全對才給分)

Example of **input** and **output**:

```
s1111111
input divisor 1 : 40000
input divisor 2 : 50000
input divisor 3 : 2000
input remainder 1: 16789
input remainder 2: 6789
input remainder 3: 789
magic numbers null,null,null,200000
answer=56789
```

滿分115

Hidden Bonus Case 2(5%) 處理第四個magic number，可能要想一下喔，改變排列組合，套常用公式會比較好找

(Hidden Case 6~9) (15% 每個答案3分)

繳交請勿上傳壓縮檔，請大家繳交，s111111.asm s111111.png(s111111是你的學號不是要用s111111)，若你繳交的.asm不只一份或者有特殊情形，請寫一份s111111_README.pdf給我們

若未依照我們說明者繳交格式，扣10分，再麻煩大家配合，非常感謝

請依照這份檔案格式輸出，否則會有扣分情況

繳交程式碼副檔名非.asm的直接給0分

當題輸入未能停止也視為當題功能異常 當題判0

功能異常者給0(若有學號給5)，執行未過也給0儘管有截圖也一樣

抄襲判定成立雙方(抄襲者和被抄襲者)給0

整份作業最低扣至0分

若有問題可以寄信給我

s1121415@mail.yzu.edu.tw 陳泳諳助教

