



Lecture 3: Stability

Chen, Jiahao
SIST 1D#206



Poles and Zeros

- Pole, zero, and gain defined by Douglas:

$$G(s) = \frac{s + 5}{(s + 1)(s + 3)}$$

Poles are values of s that cause $G(s) \rightarrow \infty$

$$s = -1 \quad \text{and} \quad s = -3$$

Zeros are values of s that cause $G(s) \rightarrow 0$

$$s = -5$$

Gain is the value of $G(s)$ under steady state conditions

$$G(0) = \frac{0 + 5}{(0 + 1)(0 + 3)} = \frac{5}{3}$$

Poles and Zeros

- ❑ Pole due to input -> forced response
- ❑ Pole due to transfer function -> natural response
- ❑ Zero and pole both contribute to the amplitudes of the response
- ❑ Recall the solution of the state space model:

$$\begin{aligned}\mathbf{x}(t) &= e^{\mathbf{A}t}\mathbf{x}(0) + \int_0^t e^{\mathbf{A}(t-\tau)}\mathbf{B}\mathbf{u}(\tau)d\tau \\ &= \underbrace{\Phi(t)\mathbf{x}(0)}_{\text{zero-input response (natural response)}} + \underbrace{\int_0^t \Phi(t-\tau)\mathbf{B}\mathbf{u}(\tau)d\tau}_{\text{Zero-state response (forced response) as convolution integral}}\end{aligned}$$

zero-input response
(natural response)

Zero-state response
(forced response)
as convolution integral





FIGURE 4.1 a. System showing input and output; b. pole-zero plot of the system; c. evolution of a system response. Follow blue arrows to see the evolution of the response component generated by the pole or zero.

Evaluating Response Using Poles

PROBLEM: Given the system of Figure 4.3, write the output, $c(t)$, in general terms. Specify the forced and natural parts of the solution.

SOLUTION: By inspection, each system pole generates an exponential as part of the natural response. The input's pole generates the forced response. Thus,

$$C(s) \equiv \underbrace{\frac{K_1}{s}}_{\text{Forced response}} + \underbrace{\frac{K_2}{s+2} + \frac{K_3}{s+4} + \frac{K_4}{s+5}}_{\text{Natural response}} \quad (4.3)$$

Taking the inverse Laplace transform, we get

$$c(t) \equiv \underbrace{K_1}_{\text{Forced response}} + \underbrace{K_2 e^{-2t} + K_3 e^{-4t} + K_4 e^{-5t}}_{\text{Natural response}} \quad (4.4)$$




FIGURE 4.3 System for Example 4.1

PROBLEM: A system has a transfer function, $G(s) = \frac{10(s+4)(s+6)}{(s+1)(s+7)(s+8)(s+10)}$.

Write, by inspection, the output, $c(t)$, in general terms if the input is a unit step.

ANSWER: $c(t) \equiv A + Be^{-t} + Ce^{-7t} + De^{-8t} + Ee^{-10t}$



Typical Systems (excited with test signal)

- Step response of the first order system (with no zero)
 - Forced and natural response:

$$c(t) = c_f(t) + c_n(t) = 1 - e^{-at}$$




FIGURE 4.4 a. First-order system; b. pole plot




FIGURE 4.5 First-order system response to a unit step

Second order system

□ Step response of the second order system (with no zero) depends on pole locations on the pzmap:

- How about right plane pole?




FIGURE 4.8 Second-order step response components generated by complex poles




FIGURE 4.7 Second-order systems, pole plots, and step responses

- ❑ Natural frequency ω_n defines the time scale of the time response plot
 - In s-plane, it defines the length of the pole location vector
- ❑ Damping ratio ζ defines the shape of the time response plot
 - In s-plane, it defines the angle of the pole location vector

$$G(s) = \frac{\omega_n^2}{s^2 + 2\zeta\omega_n s + \omega_n^2}$$

Finding ζ and ω_n For a Second-Order System

PROBLEM: Given the transfer function of Eq. (4.23), find ζ and ω_n .

$$G(s) = \frac{36}{s^2 + 4.2s + 36} \quad (4.23)$$

SOLUTION: Comparing Eq. (4.23) to (4.22), $\omega_n^2 = 36$, from which $\omega_n = 6$. Also, $2\zeta\omega_n = 4.2$. Substituting the value of ω_n , $\zeta = 0.35$.




FIGURE 4.11 Second-order response as a function of damping ratio

- Time domain performance metrics are defined in terms of the underdamped response of a second order system with $\zeta \in (0,1)$

$$C(s) = \frac{\omega_n^2}{s(s^2 + 2\zeta\omega_n s + \omega_n^2)} = \frac{K_1}{s} + \frac{K_2 s + K_3}{s^2 + 2\zeta\omega_n s + \omega_n^2}$$

$$C(s) = \frac{1}{s} - \frac{(s + \zeta\omega_n) + \frac{\zeta}{\sqrt{1-\zeta^2}}\omega_n\sqrt{1-\zeta^2}}{(s + \zeta\omega_n)^2 + \omega_n^2(1-\zeta^2)}$$

$$\begin{aligned} c(t) &= 1 - e^{-\zeta\omega_n t} \left(\cos \omega_n \sqrt{1-\zeta^2} t + \frac{\zeta}{\sqrt{1-\zeta^2}} \sin \omega_n \sqrt{1-\zeta^2} t \right) \\ &= 1 - \frac{1}{\sqrt{1-\zeta^2}} e^{-\zeta\omega_n t} \cos(\omega_n \sqrt{1-\zeta^2} t - \phi) \end{aligned}$$

where $\phi = \tan^{-1}(\zeta/\sqrt{1-\zeta^2})$.




FIGURE 4.14 Second-order underdamped response specifications

Finding T_p , %OS, T_s , and T_r from a Transfer Function

PROBLEM: Given the transfer function

$$G(s) = \frac{100}{s^2 + 15s + 100} \quad (4.43)$$

find T_p , %OS, T_s , and T_r .

SOLUTION: ω_n and ζ are calculated as 10 and 0.75, respectively. Now substitute ζ and ω_n into Eqs. (4.34), (4.38), and (4.42) and find, respectively, that $T_p = 0.475$ second, %OS = 2.838, and $T_s = 0.533$ second. Using the table in Figure 4.16, the normalized rise time is approximately 2.3 seconds. Dividing by ω_n yields $T_r = 0.23$ second. This problem demonstrates that we can find T_p , %OS, T_s , and T_r without the tedious task of taking an inverse Laplace transform, plotting the output response, and taking measurements from the plot.

$$T_p = \frac{\pi}{\omega_n \sqrt{1 - \zeta^2}} \quad (4.34)$$

$$\%OS = e^{-(\zeta\pi/\sqrt{1-\zeta^2})} \times 100 \quad (4.38)$$

$$T_s = \frac{4}{\zeta\omega_n} \quad (4.42)$$




FIGURE 4.16 Normalized rise time versus damping ratio for a second-order underdamped response

Percent overshoot, %OS. The amount that the waveform overshoots the steady-state value (or final value) at the peak time, expressed as a percentage of the steady state value.

Time domain performance metrics in s-domain

□ Peak time and settling time are related to :

- damped frequency of oscillation, ω_d
- and exponential damping frequency σ_d

$$T_p = \frac{\pi}{\omega_n \sqrt{1 - \zeta^2}} = \frac{\pi}{\omega_d}$$

$$T_s = \frac{4}{\zeta \omega_n} = \frac{\pi}{\sigma_d}$$




FIGURE 4.17 Pole plot for an underdamped second-order system




FIGURE 4.18 Lines of constant peak time, T_p , settling time, T_s , and percent overshoot, $\%OS$. Note: $T_{s2} < T_{s1}$; $T_{p2} < T_{p1}$; $\%OS_1 < \%OS_2$.

Example responses




FIGURE 4.19 Step responses of second-order underdamped systems as poles move: **a.** with constant real part; **b.** with constant imaginary part; **c.** with constant damping ratio

Finding T_p , %OS, and T_s from Pole Location




FIGURE 4.20 Pole plot for Example 4.6

PROBLEM: Given the pole plot shown in Figure 4.20, find ζ , ω_n , T_p , %OS, and T_s .

SOLUTION: The damping ratio is given by $\zeta = \cos \theta = \cos[\arctan(7/3)] = 0.394$. The natural frequency, ω_n , is the radial distance from the origin to the pole, or $\omega_n = \sqrt{7^2 + 3^2} = 7.616$. The peak time is

$$T_p = \frac{\pi}{\omega_d} = \frac{\pi}{7} = 0.449 \text{ second} \quad (4.46)$$

The percent overshoot is

$$\%OS = e^{-(\zeta\pi/\sqrt{1-\zeta^2})} \times 100 = 26\% \quad (4.47)$$

The approximate settling time is

$$T_s = \frac{4}{\sigma_d} = \frac{4}{3} = 1.333 \text{ seconds} \quad (4.48)$$




Stability

(in terms of total response due to bounded input)



Bounded input bounded output (BIBO) stability




- ❑ A system is **stable** if every bounded input yields a bounded output.
- ❑ A system is **unstable** if any bounded input yields an unbounded output.
- ❑ **Marginal stability** means that the system is stable for some bounded inputs and unstable for others.
 - Poles of multiplicity greater than 1 on the imaginary axis lead to the sum of responses of the form $At^n \cos(\omega t + \phi)$, where $n = 1, 2, 3 \dots$ where the amplitude approaches infinity as time approaches infinity.



Increase gain from 3 to 7



(a)



(b)

FIGURE 6.1 Closed-loop poles and response: **a.** stable system; **b.** unstable system



Stability

(in terms of Routh-Hurwitz Criterion)

- Not easy to find **closed loop poles** given **open loop poles**, e.g.





FIGURE 6.2 Common cause of problems in finding closed-loop poles: **a.** original system; **b.** equivalent system

- We can quickly learn the number of poles in the right half s -plane and $j\omega$ -axis by writing down a table of coefficients, called Routh table.

TABLE 6.1 Initial layout for Routh table

s^4	a_4	a_2	a_0
s^3	a_3	a_1	0
s^2			
s^1			
s^0			

Routh Table

Basic Routh table example




FIGURE 6.3 Equivalent closed-loop transfer function


TABLE 6.2 Completed Routh table

s^4	a_4	a_2	a_0
s^3	a_3	a_1	0
s^2	$-\frac{\begin{vmatrix} a_4 & a_2 \\ a_3 & a_1 \end{vmatrix}}{a_3} = b_1$	$-\frac{\begin{vmatrix} a_4 & a_0 \\ a_3 & 0 \end{vmatrix}}{a_3} = b_2$	$-\frac{\begin{vmatrix} a_4 & 0 \\ a_3 & 0 \end{vmatrix}}{a_3} = 0$
s^1	$-\frac{\begin{vmatrix} a_3 & a_1 \\ b_1 & b_2 \end{vmatrix}}{b_1} = c_1$	$-\frac{\begin{vmatrix} a_3 & 0 \\ b_1 & 0 \end{vmatrix}}{b_1} = 0$	$-\frac{\begin{vmatrix} a_3 & 0 \\ b_1 & 0 \end{vmatrix}}{b_1} = 0$
s^0	$-\frac{\begin{vmatrix} b_1 & b_2 \\ c_1 & 0 \end{vmatrix}}{c_1} = d_1$	$-\frac{\begin{vmatrix} b_1 & 0 \\ c_1 & 0 \end{vmatrix}}{c_1} = 0$	$-\frac{\begin{vmatrix} b_1 & 0 \\ c_1 & 0 \end{vmatrix}}{c_1} = 0$

Creating a Routh Table

PROBLEM: Make the Routh table for the system shown in Figure 6.4(a).

FIGURE 6.4 a. Feedback system for Example 6.1; b. equivalent closed-loop system



Routh-Hurwitz Criterion



- Simply stated, the **Routh-Hurwitz criterion** declares that the number of roots of the polynomial that are in the right half-plane is equal to the number of sign changes in the first column of Routh table

PROBLEM: Make a Routh table and tell how many roots of the following polynomial are in the right half-plane and in the left half-plane.

$$P(s) = 3s^7 + 9s^6 + 6s^5 + 4s^4 + 7s^3 + 8s^2 + 2s + 6$$

ANSWER:

<https://routhhurwitz.streamlit.app/>

Routh-Hurwitz Table Generator

Polynomial

Enter polynomial coefficients separated by commas

6,2,8,7,4,6,9,3

$$3s^7 + 9s^6 + 6s^5 + 4s^4 + 7s^3 + 8s^2 + 2s + 6$$

Go

Routh-Hurwitz Table

s^7	3	6	7	2
s^6	9	4	8	6
s^5	$\frac{14}{3}$	$\frac{13}{3}$	0	0
s^4	$-\frac{61}{14}$	8	6	0
s^3	$\frac{787}{61}$	$\frac{392}{61}$	0	0
s^2	$\frac{8004}{787}$	6	0	0
s	$-\frac{1581}{1334}$	0	0	0
1	6	0	0	0



- ❑ If the first element of a row is zero, division by zero would be required to form the next row. To avoid this phenomenon, an epsilon, ϵ , is assigned to replace the zero in the first column. The value ϵ is then allowed to approach zero from either the positive or the negative side, after which the signs of the entries in the first column can be determined.

---known as **epsilon method**.

TryIt 6.1

Use the following MATLAB statement to find the poles of the closed-loop transfer function in Eq. (6.1).

```
roots([1 2 3 6 5 3])
```

Stability via Epsilon Method

PROBLEM: Determine the stability of the closed-loop transfer function

$$T(s) = \frac{10}{s^5 + 2s^4 + 3s^3 + 6s^2 + 5s + 3} \tag{6.2}$$

SOLUTION: The solution is shown in Table 6.4. We form the Routh table by using the denominator of Eq. (6.2). Begin by assembling the Routh table down to the row where a zero appears *only* in the first column (the s^3 row). Next replace the zero by a small number, ϵ , and complete the table. To begin the interpretation, we must first assume a sign, positive or negative, for the quantity ϵ . Table 6.5 shows the first column of Table 6.4 along with the resulting signs for choices of ϵ positive and ϵ negative.

TABLE 6.4 Completed Routh table for Example 6.2

s^5	1	3	5
s^4	2	6	3
s^3	$\cancel{0} \ \epsilon$	$\frac{7}{2}$	0
s^2	$\frac{6\epsilon - 7}{\epsilon}$	3	0
s^1	$\frac{42\epsilon - 49 - 6\epsilon^2}{12\epsilon - 14}$	0	0
s^0	3	0	0

TABLE 6.5 Determining signs in first column of a Routh table with zero as first element in a row

Label	First column	$\epsilon = +$	$\epsilon = -$
s^5	1	+	+
s^4	2	+	+
s^3	$\cancel{0} \ \epsilon$	+	-
s^2	$\frac{6\epsilon - 7}{\epsilon}$	-	+
s^1	$\frac{42\epsilon - 49 - 6\epsilon^2}{12\epsilon - 14}$	+	+
s^0	3	+	+

Routh Table with Zero Only in the First Column (2)



- Alternatively, there is a reverse coefficient method that is suited to be numerically implemented.
 - It is valid because we only care about the location of the poles (left or right half plane)
 - Let $s = 1/d$

$$\left(\frac{1}{d}\right)^n + a_{n-1} \left(\frac{1}{d}\right)^{n-1} + \cdots + a_1 \left(\frac{1}{d}\right) + a_0 = 0$$

Stability via Reverse Coefficients

PROBLEM: Determine the stability of the closed-loop transfer function

$$T(s) = \frac{10}{s^5 + 2s^4 + 3s^3 + 6s^2 + 5s + 3} \quad (6.6)$$

SOLUTION: First write a polynomial that has the reciprocal roots of the denominator of Eq. (6.6). From our discussion, this polynomial is formed by writing the denominator of Eq. (6.6) in reverse order. Hence,

$$D(s) = 3s^5 + 5s^4 + 6s^3 + 3s^2 + 2s + 1 \quad (6.7)$$

We form the Routh table as shown in Table 6.6 using Eq. (6.7). Since there are two sign changes, the system is unstable and has two right-half-plane poles. This is the same as the result obtained in Example 6.2. Notice that Table 6.6 does not have a zero in the first column.

TABLE 6.6 Routh table for Example 6.3

s^5	3	6	2
s^4	5	3	1
s^3	4.2	1.4	
s^2	1.33	1	
s^1	-1.75		
s^0	1		

```
G =
      10
-----
s^5 + 2 s^4 + 3 s^3 + 6 s^2 + 5 s + 3

Continuous-time transfer function.
Model Properties

RH_Table =

    1.0000    3.0000    5.0000    0
    2.0000    6.0000    3.0000    0
         0    3.5000         0    0
    -Inf      NaN      NaN    0
      NaN      NaN      NaN    0
      NaN      NaN      NaN    0

*You have 0 right-half poles and 5 left-half poles

RH_Table =

    3.0000    6.0000    2.0000    0
    5.0000    3.0000    1.0000    0
    4.2000    1.4000         0    0
    1.3333    1.0000         0    0
   -1.7500         0         0    0
    1.0000         0         0    0

*Upon changes made to the RH Table, you now have 2
>> roots([1,2,3,6,5,3])

ans =

    0.3429 + 1.5083i
    0.3429 - 1.5083i
   -1.6681 + 0.0000i
   -0.5088 + 0.7020i
   -0.5088 - 0.7020i
```

<https://jp.mathworks.com/matlabcentral/fileexchange/72884-routh-hurwitz-stability-criteria-table-generator-all-cases>

Routh Table with Entire Row being Zero


Stability via Routh Table with Row of Zeros

PROBLEM: Determine the number of right-half-plane poles in the closed-loop transfer function

$$T(s) = \frac{10}{s^5 + 7s^4 + 6s^3 + 42s^2 + 8s + 56} \quad (6.8)$$

- When there is an even polynomial that is a factor of the original polynomial, an entire row consists of zeros will result in Routh table. We can write down an auxiliary polynomial and take derivative w.r.t. s to continue with the Routh table

---known as **auxiliary polynomial method**.



A: Real and symmetrical about the origin ———
 B: Imaginary and symmetrical about the origin ———
 C: Quadrantal and symmetrical about the origin - - - -

FIGURE 6.5 Root positions to generate even polynomials: A, B, C, or any combination

SOLUTION: Start by forming the Routh table for the denominator of Eq. (6.8) (see Table 6.7). At the second row we multiply through by $1/7$ for convenience. We stop at the third row, since the entire row consists of zeros, and use the following procedure. First we return to the row immediately above the row of zeros and form an auxiliary polynomial, using the entries in that row as coefficients. The polynomial will start with the power of s in the label column and continue by skipping every other power of s . Thus, the polynomial formed for this example is

$$P(s) = s^4 + 6s^2 + 8 \quad (6.9)$$

Next we differentiate the polynomial with respect to s and obtain

$$\frac{dP(s)}{ds} = 4s^3 + 12s + 0 \quad (6.10)$$

Finally, we use the coefficients of Eq. (6.10) to replace the row of zeros. Again, for convenience, the third row is multiplied by $1/4$ after replacing the zeros.

The remainder of the table is formed in a straightforward manner by following the standard form shown in Table 6.2. Table 6.7 shows that all entries in the first column are positive. Hence, there are no right-half-plane poles.

TABLE 6.7 Routh table for Example 6.4

s^5	1	6	8
s^4	1	6	8
s^3	0	0	0
s^2	3	8	0
s^1	$\frac{1}{3}$	0	0
s^0	8	0	0

Routh Table with Entire Row being Zero

PROBLEM: Use the Routh-Hurwitz criterion to find how many poles of the following closed-loop system, $T(s)$, are in the rhp, in the lhp, and on the $j\omega$ -axis:

$$T(s) = \frac{s^3 + 7s^2 - 21s + 10}{s^6 + s^5 - 6s^4 + 0s^3 - s^2 - s + 6}$$

ANSWER:

```
>> routh_hurwitz
Enter highest power in numerator: 3
Enter coefficients, starting with the highest power: 1
Enter coefficients, starting with the highest power: 7
Enter coefficients, starting with the highest power: -21
Enter coefficients, starting with the highest power: 10
Enter highest power in denominator: 6
Enter coefficients, starting with the highest power: 1
Enter coefficients, starting with the highest power: 1
Enter coefficients, starting with the highest power: -6
Enter coefficients, starting with the highest power: 0
Enter coefficients, starting with the highest power: -1
Enter coefficients, starting with the highest power: -1
Enter coefficients, starting with the highest power: 6
Are you entering an open loop or closed loop TF? If closed loop type "C"
```

G =

$$\frac{s^3 + 7s^2 - 21s + 10}{s^6 + s^5 - 6s^4 - s^2 - s + 6}$$

Continuous-time transfer function.

[Model Properties](#)

RH_Table =

1	-6	-1	6
1	0	-1	0
-6	0	6	0
0	0	0	0
NaN	NaN	NaN	0
NaN	NaN	NaN	0
NaN	NaN	NaN	0

*You have 1 right-half poles and 5 left-half poles. Thus, you have an u


RH_Table =

1	-6	-1	6
1	0	-1	0
-6	0	6	0
-18	6	0	0
-2	6	0	0
-48	0	0	0
6	0	0	0

*Upon changes made to the RH Table, you now have 2 right-half poles and

Standard Routh-Hurwitz

PROBLEM: Find the number of poles in the left half-plane, the right half-plane, and on the $j\omega$ -axis for the system of Figure 6.6.



SOLUTION: First, find the closed-loop transfer function as

$$T(s) = \frac{200}{s^4 + 6s^3 + 11s^2 + 6s + 200} \quad (6.14)$$

The Routh table for the denominator of Eq. (6.14) is shown as Table 6.10. For clarity, we leave most zero cells blank. At the s^1 row there is a negative coefficient; thus, there are two sign changes. The system is unstable, since it has two right-half-plane poles and two left-half-plane poles. The system cannot have $j\omega$ poles since a row of zeros did not appear in the Routh table.

TABLE 6.10 Routh table for Example 6.6

s^4	1	11	200
s^3	6 1	6 1	
s^2	10 1	200 20	
s^1	-19		
s^0	20		

Routh-Hurwitz with Zero in First Column

PROBLEM: Find the number of poles in the left half-plane, the right half-plane, and on the $j\omega$ -axis for the system of Figure 6.7.




FIGURE 6.7 Feedback control system for Example 6.7

SOLUTION: The closed-loop transfer function is

$$T(s) = \frac{1}{2s^5 + 3s^4 + 2s^3 + 3s^2 + 2s + 1} \quad (6.15)$$

Form the Routh table shown as Table 6.11, using the denominator of Eq. (6.15). A zero appears in the first column of the s^3 row. Since the entire row is not zero, simply replace

TABLE 6.11 Routh table for Example 6.7


s^5	2	2	2
s^4	3	3	1
s^3	0 ϵ	$\frac{4}{3}$	
s^2	$\frac{3\epsilon - 4}{\epsilon}$	1	
s^1	$\frac{12\epsilon - 16 - 3\epsilon^2}{9\epsilon - 12}$		
s^0	1		

More Examples

Stability Design via Routh-Hurwitz

PROBLEM: Find the range of gain, K , for the system of Figure 6.10 that will cause the system to be stable, unstable, and marginally stable. Assume $K > 0$.

FIGURE 6.10 Feedback control system for Example 6.9



SOLUTION: First find the closed-loop transfer function as

$$T(s) = \frac{K}{s^3 + 18s^2 + 77s + K} \quad (6.20)$$


Next form the Routh table shown as Table 6.15.

TABLE 6.15 Routh table for Example 6.9

s^3	1	77
s^2	18	K
s^1	$\frac{1386 - K}{18}$	
s^0	K	

Routh-Hurwitz with Row of Zeros

PROBLEM: Find the number of poles in the left half-plane, the right half-plane, and on the $j\omega$ -axis for the system of Figure 6.8. Draw conclusions about the stability of the closed-loop system.



SOLUTION: The closed-loop transfer function for the system of Figure 6.8 is

$$T(s) = \frac{128}{s^8 + 3s^7 + 10s^6 + 24s^5 + 48s^4 + 96s^3 + 128s^2 + 192s + 128} \quad (6.17)$$

Using the denominator, form the Routh table shown as Table 6.13. A row of zeros appears in the s^5 row. Thus, the closed-loop transfer function denominator must have an even polynomial as a factor. Return to the s^6 row and form the even polynomial:

$$P(s) = s^6 + 8s^4 + 32s^2 + 64 \quad (6.18)$$

TABLE 6.13 Routh table for Example 6.8

s^8	1	10	48	128	128
s^7	3	24	96	192	64
s^6	2	16	64	128	64
s^5	0	0	0	0	0
s^4	8	64	64	24	
s^3	3	8			
s^2	1	5			
s^1	3	8			
s^0	3				

$$\frac{dP(s)}{ds} = 6s^5 + 32s^3 + 64s + 0$$

Factoring via Routh-Hurwitz

PROBLEM: Factor the polynomial

$$s^4 + 3s^3 + 30s^2 + 30s + 200 \quad (6.23)$$

SOLUTION: Form the Routh table of Table 6.17. We find that the s^1 row is a row of zeros. Now form the even polynomial at the s^2 row:

$$P(s) = s^2 + 10 \quad (6.24)$$

TABLE 6.17 Routh table for Example 6.10

s^4	1	30	200
s^3	3 1	30 10	
s^2	20 1	200 10	
s^1	0 2	0 0	
s^0	10		

This polynomial is differentiated with respect to s in order to complete the Routh table. However, since this polynomial is a factor of the original polynomial in Eq. (6.23), dividing Eq. (6.23) by (6.24) yields $(s^2 + 3s + 20)$ as the other factor. Hence,

$$\begin{aligned} s^4 + 3s^3 + 30s^2 + 30s + 200 &= (s^2 + 10)(s^2 + 3s + 20) \\ &= (s + j3.1623)(s - j3.1623) \\ &\quad \times (s + 1.5 + j4.213)(s + 1.5 - j4.213) \end{aligned} \quad (6.25)$$

Stability in State Space

PROBLEM: Given the system

$$\dot{\mathbf{x}} = \begin{bmatrix} 0 & 3 & 1 \\ 2 & 8 & 1 \\ -10 & -5 & -2 \end{bmatrix} \mathbf{x} + \begin{bmatrix} 10 \\ 0 \\ 0 \end{bmatrix} u \quad (6.33a)$$

$$y = [1 \quad 0 \quad 0] \mathbf{x} \quad (6.33b)$$

find out how many poles are in the left half-plane, in the right half-plane, and on the $j\omega$ -axis.

SOLUTION: First form $(s\mathbf{I} - \mathbf{A})$:

$$(s\mathbf{I} - \mathbf{A}) = \begin{bmatrix} s & 0 & 0 \\ 0 & s & 0 \\ 0 & 0 & s \end{bmatrix} - \begin{bmatrix} 0 & 3 & 1 \\ 2 & 8 & 1 \\ -10 & -5 & -2 \end{bmatrix} = \begin{bmatrix} s & -3 & -1 \\ -2 & s-8 & -1 \\ 10 & 5 & s+2 \end{bmatrix} \quad (6.34)$$

Now find the $\det(s\mathbf{I} - \mathbf{A})$:

$$\det(s\mathbf{I} - \mathbf{A}) = s^3 - 6s^2 - 7s - 52 \quad (6.35)$$

Using this polynomial, form the Routh table of Table 6.18.

TABLE 6.18 Routh table for Example 6.11

s^3	1	-7
s^2	6 -3	52 -26
s^1	$\frac{47}{3}$ -1	0 0
s^0	-26	

Steady State Error (for stable system)




FIGURE 7.2 Steady-state error: **a.** step input; **b.** ramp input

Steady state error

□ Final value theorem

$$E(s) = R(s)[1 - T(s)]$$

$$e(\infty) = \lim_{s \rightarrow 0} sR(s)[1 - T(s)]$$

PROBLEM: Find the steady-state error for the system of Figure 7.3(a) if $T(s) = 5/(s^2 + 7s + 10)$ and the input is a unit step.

SOLUTION: From the problem statement, $R(s) = 1/s$ and $T(s) = 5/(s^2 + 7s + 10)$. Substituting into Eq. (7.4) yields

$$E(s) = \frac{s^2 + 7s + 5}{s(s^2 + 7s + 10)} \quad (7.7)$$

Since $T(s)$ is stable and, subsequently, $E(s)$ does not have right-half-plane poles or $j\omega$ poles other than at the origin, we can apply the final value theorem. Substituting Eq. (7.7) into Eq. (7.5) gives $e(\infty) = 1/2$.

¹The final value theorem is derived from the Laplace transform of the derivative. Thus,

$$\mathcal{L}[\dot{f}(t)] = \int_{0-}^{\infty} \dot{f}(t)e^{-st} dt = sF(s) - f(0-)$$

As $s \rightarrow 0$,

$$\int_{0-}^{\infty} \dot{f}(t) dt = f(\infty) - f(0-) = \lim_{s \rightarrow 0} sF(s) - f(0-)$$

or

$$f(\infty) = \lim_{s \rightarrow 0} sF(s)$$

For finite steady-state errors, the final value theorem is valid only if $F(s)$ has poles only in the left half-plane and, at most, one pole at the origin. However, correct results that yield steady-state errors that are infinite can be obtained if

- The steady state performance is evaluated in terms of forward path transfer function

Step Input. Using Eq. (7.11) with $R(s) = 1/s$, we find

$$e(\infty) = e_{\text{step}}(\infty) = \lim_{s \rightarrow 0} \frac{s(1/s)}{1 + G(s)} = \frac{1}{1 + \lim_{s \rightarrow 0} G(s)}$$

$$G(s) \equiv \frac{K(s + z_1)(s + z_2) \cdots}{s^n(s + p_1)(s + p_2) \cdots}$$

If there are no integrations, then $n = 0$.

Ramp Input. Using Eq. (7.11), with $R(s) = 1/s^2$, we obtain

$$e(\infty) = e_{\text{ramp}}(\infty) = \lim_{s \rightarrow 0} \frac{s(1/s^2)}{1 + G(s)} = \lim_{s \rightarrow 0} \frac{1}{s + sG(s)} = \frac{1}{\lim_{s \rightarrow 0} sG(s)}$$

$$\lim_{s \rightarrow 0} G(s) = \frac{z_1 z_2 \cdots}{p_1 p_2 \cdots} K$$

Parabolic Input. Using Eq. (7.11), with $R(s) = 1/s^3$, we obtain

$$e(\infty) = e_{\text{parabola}}(\infty) = \lim_{s \rightarrow 0} \frac{s(1/s^3)}{1 + G(s)} = \lim_{s \rightarrow 0} \frac{1}{s^2 + s^2 G(s)} = \frac{1}{\lim_{s \rightarrow 0} s^2 G(s)}$$

Steady State Error Specifications

- ❑ **System type:** the number of integrators in the forward path
 - Three error constants are defined for each system type.




FIGURE 7.8 Feedback control system for defining system type

TABLE 7.2 Relationships between input, system type, static error constants, and steady-state errors

Input	Steady-state error formula	Type 0 $\frac{K(s+z_1)(s+z_2) \dots}{s^0(s+p_1)(s+p_2) \dots}$	Type 1 $\frac{K(s+z_1)(s+z_2) \dots}{s^1(s+p_1)(s+p_2) \dots}$	Type 2 $\frac{K(s+z_1)(s+z_2) \dots}{s^2(s+p_1)(s+p_2) \dots}$
		Static error constant Error	Static error constant Error	Static error constant Error
Step, $u(t)$	$\frac{1}{1 + \lim_{s \rightarrow 0} G(s)} = \frac{1}{1 + K_p}$	$K_p = \text{Constant}$ $\frac{1}{1 + K_p}$	$K_p = \infty$ 0	$K_p = \infty$ 0
Ramp, $tu(t)$	$\frac{1}{\lim_{s \rightarrow 0} sG(s)} = \frac{1}{K_v}$	$K_v = 0$ ∞	$K_v = \text{Constant}$ $\frac{1}{K_v}$	$K_v = \infty$ 0
Parabola, $\frac{1}{2}t^2u(t)$	$\frac{1}{\lim_{s \rightarrow 0} s^2G(s)} = \frac{1}{K_a}$	$K_a = 0$ ∞	$K_a = 0$ ∞	$K_a = \text{Constant}$ $\frac{1}{K_a}$

Interpreting the Steady-State Error Specification

PROBLEM: What information is contained in the specification $K_p = 1000$?



Gain Design to Meet a Steady-State Error Specification




FIGURE 7.10 Feedback control system for Example 7.6

PROBLEM: Given the control system in Figure 7.10, find the value of K so that there is 10% error in the steady state.

SOLUTION: Since the system is Type 1, the error stated in the problem must apply to a ramp input; only a ramp yields a finite error in a Type 1 system. Thus,

$$e(\infty) = \frac{1}{K_v} = 0.1 \quad (7.55)$$

Therefore,

$$K_v = 10 = \lim_{s \rightarrow 0} sG(s) = \frac{K \times 5}{6 \times 7 \times 8} \quad (7.56)$$

which yields

$$K = 672 \quad (7.57)$$

Applying the Routh-Hurwitz criterion, we see that the system is stable at this gain.

Although this gain meets the criteria for steady-state error and stability, it may not yield a desirable transient response. In Chapter 9 we will design feedback control systems to meet all three specifications.

- The transfer function from input to error is:

$$E(s) = \frac{1}{1 + G_1(s)G_2(s)} R(s) - \frac{G_2(s)}{1 + G_1(s)G_2(s)} D(s)$$




FIGURE 7.11 Feedback control system showing disturbance

$$\begin{aligned} e(\infty) &= \lim_{s \rightarrow 0} sE(s) = \lim_{s \rightarrow 0} \frac{s}{1 + G_1(s)G_2(s)} R(s) - \lim_{s \rightarrow 0} \frac{sG_2(s)}{1 + G_1(s)G_2(s)} D(s) \\ &= e_R(\infty) + e_D(\infty) \end{aligned}$$

Steady State Error Due to Disturbance



PROBLEM: Find the steady-state error component due to a step disturbance for the system of Figure 7.13.




FIGURE 7.13 Feedback control system for Example 7.7



Stability

(in terms of **Root Locus**
for higher order **control systems**)

- The zeros of $T(s)$ consist of the zeros of $G(s)$ and the poles of $H(s)$. The poles of $T(s)$ are not immediately known without factoring the denominator, and they are a function of K . Since the system's transient response and stability are dependent upon the poles of $T(s)$, we have no knowledge of the system's performance unless we factor the denominator for specific values of K .





FIGURE 8.1 a. Closed-loop system; b. equivalent transfer function

- $s + a$ is a complex number and can be represented by a vector drawn from the zero of the function to the point s in the complex plane

$$M = \frac{\prod \text{zero lengths}}{\prod \text{pole lengths}} = \frac{\prod_{i=1}^m |(s + z_i)|}{\prod_{j=1}^n |(s + p_j)|}$$

$$\begin{aligned} \theta &= \sum \text{zero angles} - \sum \text{pole angles} \\ &= \sum_{i=1}^m \angle(s + z_i) - \sum_{j=1}^n \angle(s + p_j) \end{aligned}$$

FIGURE 8.2 Vector representation of complex numbers: **a.** $s = \sigma + j\omega$; **b.** $(s + a)$; **c.** alternate representation of $(s + a)$; **d.** $(s + 7)|_{s \rightarrow 5+j2}$



Vector Representation of Complex Numbers



Evaluation of a Complex Function via Vectors

PROBLEM: Given

$$F(s) = \frac{(s + 1)}{s(s + 2)} \quad (8.7)$$

find $F(s)$ at the point $s = -3 + j4$.

SOLUTION: The problem is graphically depicted in Figure 8.3, where each vector, $(s + \alpha)$, of the function is shown terminating on the selected point $s = -3 + j4$. The vector originating at the zero at -1 is

$$\sqrt{20} \angle 116.6^\circ \quad (8.8)$$

The vector originating at the pole at the origin is

$$5 \angle 126.9^\circ \quad (8.9)$$

The vector originating at the pole at -2 is

$$\sqrt{17} \angle 104.0^\circ \quad (8.10)$$

Substituting Eqs. (8.8) through (8.10) into Eqs. (8.5) and (8.6) yields

$$M \angle \theta = \frac{\sqrt{20}}{5\sqrt{17}} \angle 116.6^\circ - 126.9^\circ - 104.0^\circ = 0.217 \angle -114.3^\circ \quad (8.11)$$

as the result for evaluating $F(s)$ at the point $-3 + j4$.




FIGURE 8.3 Vector representation of Eq. (8.7)

- ❑ Root locus focuses on a simple feedback control system with a proportional gain K .
 - There is variant of root locus method that can deal with problem with more than one parameter.
- ❑ The root locus can be used to analyze closed loop system in terms of information about the forward path transfer function $G(s) = C(s)P(s)$




FIGURE 8.1 a. Closed-loop system; b. equivalent transfer function



- ❑ The root locus begins at the finite and infinite poles of $G(s)H(s)$ and ends at the finite and infinite zeros of $G(s)H(s)$.