

3

inputs:

Road Factors:

- $R - 0 \rightarrow \text{road bad}, 1 \rightarrow \text{road good}$
- $F - 0 \rightarrow \text{below } 60 \text{ km/h}, 1 \rightarrow \text{above } 60 \text{ km/h}$

Driver Factors:

- $V - 0 \rightarrow \text{not speeding}, 1 \rightarrow \text{speeding}$
- $T - 0 \rightarrow \text{signals not used}, 1 \rightarrow \text{signals used}$

outputs:

- $E = 1$

- exactly three 1 in inputs

- $R = 0, T = 1, V = 0, F = 0$

- $E = 0$:

- all inputs 0
- $E = X$:
 - even 1s in Driver Factors or Road Factors

- $T = 1$:

- * minimum req is $T = 1$. So it must be true for all cases.
- $T = 1$ and $R = 0, F = 1, V = 0$
- all inputs 1
- = $R = 1, F = 0, V = 0, T = 1$

- $T = X$:

- $T = 1$ and exactly three 1s (2 more 1s other than T)

- $T = 0$:

- all other cases

					RF \ VT					<u><u>E</u></u>
0	0	0	0	0	00	01	11	10		

R	F	V	T	E	T
0	0	0	0	0	0
0	0	0	1	1	0
0	0	1	0	X	0
0	0	1	1	X	0
0	1	0	0	X	0
0	1	0	1	0	1
0	1	1	0	0	0
0	1	1	1	1	X
1	0	0	0	X	0
1	0	0	1	0	1
1	0	1	0	0	0
1	0	1	1	1	X
1	1	0	0	X	0
1	1	0	1	1	X
1	1	1	0	1	0
1	1	1	1	X	1

00		1	X	X
01	X		1	
11	X	1	X	1
10	X		1	

$\rightarrow R'F'T$
 $+$
 VT
 $+$
 RF

I

		00	01	11	10
RF \ VT	00				
	01		1	X	
	11		1	X	
	10		X	1	

$\rightarrow FT$
 $+$
 RT

