

Quiz: defining data

This quiz has 5 questions. The passing grade is 4.

[Back](#)[Next](#)

Started on	Wednesday, January 15, 2025, 1:48 PM
State	Finished
Completed on	Wednesday, January 15, 2025, 2:01 PM
Time taken	12 mins 48 secs
Grade	0.00 out of 5.00 (0%)

Question **1**

Incorrect

0.00 points out of 1.00

Which statement in the list is invalid (syntactically incorrect)?

Select one:

- ☐ A. MVC Fld1,=50C'**'
- ☐ B. MVC DOB,=C'20010101'
- ☒ C. AH 3,=H'100' ✕
- ☐ D. AH 3,=0H'100'
- ☐ E. AH 3,=1H'100'

The invalid statement is:

AH 3,=0H'100'

Literals can have the same attributes as DEFINE CONSTANT, **except an explicit length of zero.**

The correct answer is:

AH 3,=0H'100'

Question **2**

Incorrect

0.00 points out of 1.00

[Back](#)[Next](#)

Which of these is not a valid Assembler statement? (Select 2)

Select one or more:

- ☐ A. `DC 300C'ABC'`
- ☐ B. `DC H'100000'`
- ☐ C. `DC 100H'1000'`
- ☒ D. `DC CL1'HELLO WORLD!'` ✕
- ☐ E. `DC CL300'ABC'`

The invalid statements are:

`DC H'100000'`

This statement is invalid because the maximum positive number a halfword can contain is 32767.

`DC CL300'ABC'`

This statement is invalid because the maximum length for character fields is 256.

These statements are correct:

`DC 300C'ABC'`

This generates the characters 'ABC' repeated 300 times.

`DC 100H'1000'`

This generates a halfword containing decimal 1000, repeated 100 times.

`DC CL1'HELLO WORLD!'`

This generates a 1-character field containing the character 'H'.

The correct answers are:

`DC H'100000'`

,

`DC CL300'ABC'`

Question 3

Incorrect

0.00 points out of 1.00

Back

Next

Which of these fields is 2 bytes in length? (Select 3)

Select one or more:

- ☐ A. DC C'ABCD'
- ☐ B. DC X'ABCD'
- ☒ C. DC C'**' ✓
- ☐ D. DC CL10'**'
- ☐ E. DC B'1 0000 0000'

The correct answers are:

DC C''**

As defined, the field is two bytes in length.

DC X'ABCD'

This is also two bytes. One has X'AB', the other X'CD'.

DC B'1 0000 0000'

The unit of memory is a byte, so this is padded with B'0' on the left. The first byte is **B'0000 0001'**, the second is **B'0000 0000'**.

The incorrect answers are:

DC C'ABCD'

The size of this field is 4 characters.

DC CL10''**

The size of this is, as specified, 10 characters (two asterisks padded on the right with spaces).

The correct answers are:

DC C''**

,

DC X'ABCD'

,

DC B'1 0000 0000'

[Back](#)[Next](#)**Question 4**

Incorrect

0.00 points out of 1.00

This statement:

DC FL4'100'

reserves 4 bytes on a multiple-of-4 address (a fullword boundary)

Select one:

☒ True ✖

☐ False

The Assembler does not enforce a storage boundary when the definition contains an explicit length.

The correct answer is 'False'.

Question 5

Incorrect

0.00 points out of 1.00

Fields defined with DEFINE CONSTANT (DC) are true constants and can't be changed during program execution

Select one:

☒ True ✖

☐ False

In spite of the Assembler instruction's name, fields defined with DC can be changed during program execution.

The correct answer is 'False'.