

2.7

RATHERI $Q = 120 \text{ Ah}$

LADDNING? $Q = 120 \cdot 3600 = 4.32 \cdot 10^5 \text{ C}$

ENERGI $W = Pt = UIt = 12 \cdot 1 \cdot 120 \cdot 3600 =$
 $= \underline{5.184 \cdot 10^6} \text{ J}$

LAMPORNA DRAR 150 W

$$\begin{aligned} W_{\text{KVAR}} &= W_{\text{FART}} - W_{\text{FÄRRUKAD}} = \\ &= 5.18 \cdot 10^6 - 150 \cdot 8 \cdot 3600 = \\ &= 860 \cdot 10^3 \text{ J} \end{aligned}$$

SVAR: a) 5.18 MJ
b) 0.86 MJ