A seventeen-variable candidate equation

Positive integer unknowns; degree 32; a 99-operation evaluator.

The only unknowns are the seventeen distinct positive integers

$$J, F, \alpha, f, g, T, X, Y, \xi, \eta, \zeta, \upsilon, \gamma, \epsilon, Z, D, V \in \mathbb{Z}_{>0}.$$

Their ASCII names in the circuit are respectively `J, F, alpha, f, g, T, X, Y, xi, eta, zeta, upsilon, gamma, epsilon, Z, D, V`. Each name denotes one unknown.

The four fixed integers are `beta`, `K`, `mu`, and `omega`, defined below. The single equation is

$$\boxed{\texttt{hCU} = 0.}$$

Here `hCU` is the last gate of the complete circuit on the next page. Every `h`-name denotes an integer polynomial abbreviation, not an additional unknown. All arithmetic in the circuit is over the integers.

The four fixed integers. Every index, set, sum, product and floor below defines a constant, not another unknown. Put

$$\rho = 2^{47}, \quad B = \rho^{2011}, \quad \beta = B - 1,$$
$$G_m(x) = \sum_{j=0}^{m-1} x^j, \quad \Lambda = \rho^{1005}.$$

$$\begin{aligned}\mu &= \beta - G_{951}(\rho) \\ &\quad - \rho^{960} G_{26}(\rho) - \rho^{1004}, \\ \omega &= \beta + 8G_{917}(\rho) - 4 + (2^{45} - 4)\Lambda \\ &\quad + \rho^{960} G_9(\rho) + \rho^{987} G_8(\rho) + \rho^{1004}, \\ K &= \rho^{18} + \rho^{1004} + \rho^{2020} \\ &\quad + 2\Lambda\Phi(1/\rho),\end{aligned}$$

where

$$\begin{aligned}\chi_i &= 1 + 2^{10}(1 + w_i + 2^8 n_i \\ &\quad + 2^{17} p_i + 2^{25} s_i) \quad (0 \le i \le 941),\end{aligned}$$
$$\pi(0) = 0, \quad \pi(i) = 1 + \sum_{j=1}^{941} \left\lfloor \frac{2^{44} - 1 + \chi_j - \chi_i}{2^{44}} \right\rfloor \quad (1 \le i \le 941).$$

$$\begin{aligned}\Phi(x) = \sum_{i=0}^{941} &\chi_i x^{\pi(i)} \\ &+ 2^{10} x^{969}(x^9 + 2^{17}) G_8(2x) \\ &+ 2^{18} x^{942}(x^{18} + 2^{17}) G_9(2x).\end{aligned}$$

The rational intermediate in K cancels exactly; all four results are positive integers.

The 942 indexed fixed tiles. Use the actions u_j, v_j, d_j decoded below. For $d = 0, 1$, let

$$h(q,b) = 2q + b + 2, \quad \mathcal{S}_d = \{u_j : d_j = d,\ 0 \le j < 430\},$$
$$r_{d,q} = 205 - 199d + |\mathcal{S}_d \cap \{0, \dots, q-1\}|.$$

An interval ending at -1 is empty. The table defines t_i for $0 \le i \le 941$; all index ranges are fixed:

index i	tile $t_i = (w_i, n_i, p_i, s_i)$
0	$(2, 435, 3, 1)$
$j+1$ $(j = 2q + b < 430)$	$((1 - d_j) r_{0,u_j}, h(q,b), d_j r_{1,u_j}, v_j)$
$433 - 2a + b$ $(a, b = 0, 1)$	$(0, 432a + b, 0, 432a + b)$
$\substack{423+2r_{d,q}+b \\ q \in \mathcal{S}_d,\ d,b=0,1}$	$(d r_{d,q}, b, (1-d) r_{d,q}, h(q,b))$
$923 + 2a + b$ $(a, b = 0, 1)$	$(0, 432a + b, 0, 438)$
927	$(2, 434, 2, 0)$
928	$(3, 436, 4, 4)$
929	$(4, 436, 4, 0)$
$496 + t$ $(t = 434, 435, 436)$	$(1, 438, 1, t)$
$933 + 3a + b$ $(a, b = 0, 1, 2)$	$(a^2, 437, b, 437)$

A closed decoder for the 430 actions. Put $D_b(A,k) = \lfloor A/b^k \rfloor \bmod b$, where $a \bmod b = a - b\lfloor a/b \rfloor$. For $0 \le q < 215$, $b = 0, 1$, $j = 2q + b$:

$$\mathcal{N} = \mathcal{A} \bmod 2^{636}, \quad \mathcal{T} = \lfloor \mathcal{A}/2^{636} \rfloor,$$
$$\nu_j = D_2(\mathcal{N}, j), \quad \kappa_j = (\sigma_j + 2)^{1-\nu_j} \quad (0 \le j < 430),$$
$$\sigma_j = \sum_{k=0}^{j-1} \nu_k, \quad \Pi_j = \prod_{k=0}^{j-1} \kappa_k \quad (0 \le j \le 430),$$
$$m_q = D_2(\mathcal{N}, 430 + q), \quad \tau_q = \sum_{k=0}^{q-1} m_k,$$
$$F_q = 14 + m_q(D_{16}(\lfloor \mathcal{T}/\Pi_{430} \rfloor, \tau_q) - 14),$$
$$u_j = (\sigma_{j+1} - (\lfloor \mathcal{T}/\Pi_j \rfloor \bmod \kappa_j)) \bmod 216,$$
$$v_j = D_2(F_q, 2b), \quad d_j = D_2(F_q, 2b+1).$$

Empty sums/products are 0/1. Here $(v_0, d_0, u_0) = (1, 1, 1)$; the constructor tile uses this actual first target, including its state renaming.

The integer $\mathcal{A}$ in base 10. Its complete decimal expansion is the concatenation of these lines:

```
12889260410359561746736540743515845134244260640012702033212621
95398074180784058571518488282119861023093355389406939414042892
97455773992193784795705001618777025966369137954859764532832722
75411843410809038713502633204617333246733616940964578272360901
56186216508504953649192752154519268024509952082950238865468307
22999632482769253980274091217460707829023970817244790340704449
09085581271192071656170732004937337082171141082486384269072884
72778087419663417942892520175630649792329265834490253035577533
96449689808375788457488971017043689875433162972390177936123032
89025657757489526342497438772045714099661532481123050235898973
27443609903800541199351405985754278307227777584454508422717998
33411356440933534607489268032843 7
```

The fixed integer $\mathcal{A}$ above is written in base 10. This is a research candidate. Exact polynomial calculations certify degree 32 and the substitution identities. A historical guarded Lean author run compiled witness transport and an intuitionistic PRA equivalence to a translated consistency sentence; independent audit and paired replay remain pending. No minimality claim is made.

Complete 99-operation circuit

Each line defines one gate. The only inputs are the 17 positive integers and the four fixed integers on the first page. The final gate `hCU` is a sum of 8 squares; setting it to zero is the displayed equation. Gate names are local abbreviations and are distinct from all input names.

```
1.  hA = J * beta
2.  hB = 1 + hA
3.  hC = hB * hB
4.  hD = hB * hC
5.  hE = Y * hC
6.  hF = hB - F
7.  hG = hF - alpha
8.  hH = X * Y
9.  hI = eta + zeta
10.  hJ = Y * hI
11.  hK = eta + hJ
12.  hL = hK * hK
13.  hM = hH + Y
14.  hN = 4 * hM
15.  hO = 3 + hN
16.  hP = hM * hM
17.  hQ = hO + hP
18.  hR = hM * hK
19.  hS = X + hR
20.  hT = hH * hJ
21.  hU = hD * hA
22.  hV = K * hB
23.  hW = X + hV
24.  hX = hG * hW
25.  hY = F * hB
26.  hZ = hX - hY
27.  hAA = hT + hI
28.  hAB = hAA + xi
29.  hAC = hI * hZ
30.  hAD = hAB - hAC
31.  hAE = hU * hAD
32.  hAF = Y * hA
33.  hAG = hZ * hD
34.  hAH = hAE + hAF
35.  hAI = hAH - hAG
36.  hAJ = Z * Z
37.  hAK = hU * hU
38.  hAL = hT * hAA
39.  hAM = 1 + hAL
40.  hAN = hAK * hAM
41.  hAO = hAJ - hAN
42.  hAP = hF * hA
43.  hAQ = alpha + hAP
44.  hAR = hC - 1
45.  hAS = hAQ * hAR
46.  hAT = omega * hB
47.  hAU = mu + hAT
48.  hAV = J * hAU
49.  hAW = hAS + hAV
50.  hAX = hI - epsilon
51.  hAY = hAX - 1
52.  hAZ = hE * gamma
53.  hBA = hH * hB
54.  hBB = hAZ + hBA
55.  hBC = hBB - hAY
56.  hBD = hE * hS
57.  hBE = hO * hBC
58.  hBF = hBD + hBE
59.  hBG = D * D
60.  hBH = hE * hE
61.  hBI = hQ * hL
62.  hBJ = 1 + hBI
63.  hBK = hBH * hBJ
64.  hBL = hBG - hBK
65.  hBM = f * f
66.  hBN = hBM - 1
67.  hBO = hQ * hBN
68.  hBP = hL * g
69.  hBQ = hBP * hBP
70.  hBR = hBQ - hBO
71.  hBS = T * hK
72.  hBT = hBS - epsilon
73.  hBU = hBM * hBT
74.  hBV = hBU - hK
75.  hBW = upsilon * upsilon
76.  hBX = V * V
77.  hBY = hBW - hBX
78.  hBZ = hBO * hBY
79.  hCA = hBW - hBZ
80.  hCB = hCA - 1
81.  hCC = epsilon - hAW
82.  hCD = Z - hAI
83.  hCE = D - hBF
84.  hCF = V - hBV
85.  hCG = hAO * hAO
86.  hCH = hBL * hBL
87.  hCI = hCB * hCB
88.  hCJ = hBR * hBR
89.  hCK = hCC * hCC
90.  hCL = hCD * hCD
91.  hCM = hCE * hCE
92.  hCN = hCF * hCF
93.  hCO = hCG + hCH
94.  hCP = hCO + hCI
95.  hCQ = hCP + hCJ
96.  hCR = hCQ + hCK
97.  hCS = hCR + hCL
98.  hCT = hCS + hCM
99.  hCU = hCT + hCN
```