

RGB LED Effects

RGB LED Effects

- 1. RGB LED Effects Overview
- 2. Core Concepts
 - 2.1 WS2812B Protocol Key Points
 - 2.2 Adafruit NeoPixel Library
 - 2.3 Linear Interpolation (Lerp)
- 3. Hardware Dependencies
- 4. Project Architecture and Flow
- 5. Source Code
 - 5.1 Header Files and Global Variables
 - 5.2 `setup()` — Initialize NeoPixel
 - 5.3 `loop()` — Color Loop
 - 5.4 `fadeToColor()` — Linear Interpolation Fade
- 6. Operation Flow
 - 6.1 Build and Flash
 - 6.2 Normal Phenomena
 - 6.3 Verification Methods
- 7. Common Problems

1. RGB LED Effects Overview

WS2812B is a single-wire cascadable addressable RGB LED that can control color and brightness through a single data line. This experiment drives the on-board WS2812B (GPIO48), smoothly transitioning between 7 rainbow colors in a loop. The Adafruit NeoPixel library encapsulates the underlying RMT timing, and calling `setPixelColor` + `show` updates the color.

Typical Application Scenarios:

Application Type	Example
Consumer Electronics	Ambient lights, gaming peripherals RGB, chassis lighting effects
Industrial Indicators	Device status lights (Green=Normal, Red=Fault, Yellow=Standby)
Commercial Display	LED strips, pixel matrix screens, advertising light boxes
Smart Home	Panel backlight, scene lighting, notification reminder lights

2. Core Concepts

2.1 WS2812B Protocol Key Points

- **Single-wire NZR zero-code:** Each LED requires 24 bits of data (G→R→B, 8 bits each)
- **Communication Rate:** 800kHz (`NEO_KHZ800`), each bit is approximately 1.25µs
- **Data Encoding:** 1 code = High 0.8µs + Low 0.45µs; 0 code = High 0.4µs + Low 0.85µs
- **Cascade Method:** Each LED consumes the first 24 bits, and the remaining signal is reshaped and forwarded to the next one
- **Color Order:** GRB (Green-Red-Blue), different from common RGB order

ESP32 generates precise pulse timing through the RMT (Remote Control) peripheral without bit-banging to occupy the CPU.

2.2 Adafruit NeoPixel Library

```
Adafruit_NeoPixel pixels(LED_NUM, PIN, NEO_GRB + NEO_KHZ800);

pixels.setPixelColor(0, pixels.Color(R, G, B)); // write frame buffer
pixels.show();                                // Send via RMT serial
pixels.setBrightness(100);                     // Global brightness 0~255
```

`setPixelColor` only writes to the RAM buffer, and `show()` actually sends data to the LED. When batch updating multiple LEDs, call `setPixelColor` individually first, then call `show()` only once at the end.

2.3 Linear Interpolation (Lerp)

Smooth transition between two colors, interpolating RGB three channels separately:

```
r = r1 + (r2 - r1) × i / steps
g = g1 + (g2 - g1) × i / steps
b = b1 + (b2 - b1) × i / steps

where i ranges from 0 to steps, and i/steps is the interpolation ratio (0.0 ~ 1.0)
```

3. Hardware Dependencies

Pin	Peripheral	Configuration	Description
GPIO48	WS2812B	Data Output	Single-wire NZR protocol, 800kHz

Requires installing the **Adafruit NeoPixel** library: Arduino IDE → Library Manager → Search "Adafruit NeoPixel" → Install.

4. Project Architecture and Flow

```

setup()
├ Serial.begin(115200)           // Serial debug
├ pixels.begin()                 // Initialize RMT peripheral
├ pixels.setBrightness(100)      // Global brightness 100/255
└ pixels.clear() + show()       // Turn off all LEDs

loop()
├ fadeToColor(current, target, 100 steps, 20ms) // Fade for 2 seconds
├ current_index advances
└ target_index = (target + 1) % 7              // Loop to next color

fadeToColor(from, to, steps, delay)
└ for i=0..steps:
    └ r = r1 + (r2-r1)*i/steps // RGB three channel interpolation
    └ setPixelColor(0, r, g, b) // write frame buffer
    └ show()                    // Send data
    └ delay(20ms)

```

5. Source Code

Complete source code: [Source Code](#) → [Arduino](#) → [1.Basic Peripherals](#) → [9.RGB](#) → [9.RGB.ino](#)

5.1 Header Files and Global Variables

When constructing the `Adafruit_NeoPixel` object, specify the LED count, pin, and color format. Predefine 7 rainbow colors for loop switching.

```

#include <Adafruit_NeoPixel.h>

#define BLINK_GPIO  48
#define LED_NUM     1
#define FADE_STEPS  100
#define FADE_DELAY   20

Adafruit_NeoPixel pixels(LED_NUM, BLINK_GPIO, NEO_GRB + NEO_KHZ800);

const uint32_t colors[] = {
  pixels.Color(255, 0, 0),           // Red
  pixels.Color(255, 128, 0),         // Orange
  pixels.Color(255, 255, 0),         // Yellow
  pixels.Color(0, 255, 0),           // Green
  pixels.Color(0, 255, 255),         // Cyan
  pixels.Color(0, 0, 255),           // Blue
  pixels.Color(128, 0, 255),         // Purple
};
#define COLOR_COUNT (sizeof(colors) / sizeof(uint32_t))

int current_index = 0;
int target_index  = 1;

```

`COLOR_COUNT` calculates the array length at compile time. Adding colors only requires modifying the `colors[]` array, and the loop automatically adapts.

5.2 `setup()` — Initialize NeoPixel

`setBrightness(100)` proportionally dims all colors to approximately 39%, protecting eyes and reducing power consumption.

```
void setup() {
  Serial.begin(115200);
  pixels.begin();
  pixels.setBrightness(100);
  pixels.clear();
  pixels.show();
}
```

`clear()` writes all zeros to the frame buffer, and `show()` sends the all-zero data out, ensuring the LED is off at power-on.

5.3 `loop()` — Color Loop

Each transition to the next color uses `fadeToColor` for smooth transition. Index modulo arithmetic automatically loops.

```
void loop() {
  Serial.print(" -> ");
  Serial.println(color_names[target_index]);

  fadeToColor(colors[current_index], colors[target_index], FADE_STEPS, FADE_DELAY);

  current_index = target_index;
  target_index = (target_index + 1) % COLOR_COUNT; // Loop back to 0 at end
}
```

5.4 `fadeToColor()` — Linear Interpolation Fade

Extract RGB three channels from the merged `uint32_t` color, interpolate each independently, then merge and write back to the frame buffer.

```
void fadeToColor(uint32_t from, uint32_t to, int steps, int stepDelay) {
  uint8_t r1 = (from >> 16) & 0xFF; // Extract R component
  uint8_t g1 = (from >> 8) & 0xFF; // Extract G component
  uint8_t b1 = from & 0xFF; // Extract B component

  uint8_t r2 = (to >> 16) & 0xFF;
  uint8_t g2 = (to >> 8) & 0xFF;
  uint8_t b2 = to & 0xFF;

  for (int i = 0; i <= steps; i++) {
    uint8_t r = r1 + (r2 - r1) * i / steps; // Linear interpolate R
```

```

uint8_t g = g1 + (g2 - g1) * i / steps;    // Linear interpolate G
uint8_t b = b1 + (b2 - b1) * i / steps;    // Linear interpolate B

pixels.setPixelColor(0, pixels.Color(r, g, b));
pixels.show();
delay(stepDelay);
}
}

```

`(r2 - r1) * i` multiplies first then divides to avoid integer division truncating to zero early. When extracting colors, `>>16 & 0xFF` corresponds to the high byte (G) of the GRB byte order, not the standard RGB order.

6. Operation Flow

6.1 Build and Flash

Arduino Flash Process: See `Arduino` → `1. Before Development` → `2. Build and Flash`.

Install library: **Arduino IDE** → **Sketch** → **Include Library** → **Manage Libraries** → **Search "Adafruit NeoPixel"** → **Install**

Verify/Compile Ctrl+R

Upload Ctrl+U

Configure and Upload

Upload Using Programmer Ctrl+Shift+U

Export Compiled Binary Alt+Ctrl+S

Optimize for Debugging

Show Sketch Folder Alt+Ctrl+K

Include Library

Add File...

Manage Libraries...

Ctrl+Shift+I

Add .ZIP Library...

Contributed libraries

Adafruit NeoPixel

Async TCP

Audio

ESP Async WebServer


ESP32SPISlave

libraries

NimBLE-Arduino

PubSubClient


TM16xx LEDs and Buttons




6.2 Normal Phenomena

After power-on, the LED smoothly transitions in a loop between the seven rainbow colors, with each transition taking approximately 2 seconds.

```
RGB Gradient Started!  
Current: Red  
-> Orange  
-> Yellow  
-> Green  
-> Cyan  
-> Blue  
-> Purple  
-> Red  
-> Orange  
-> Yellow  
-> Green  
-> Cyan  
-> Blue  
-> Purple  
-> Red
```





6.3 Verification Methods

Operation	Expected Result
Power on and observe	Red→Orange→Yellow→Green→Cyan→Blue→Purple→Red, looping endlessly
Change <code>FADE_STEPS</code> to 20	Transition speeds up, step effect becomes obvious
Change <code>FADE_DELAY</code> to 50	Transition slows down, smoother effect

7. Common Problems

Phenomenon	Cause	Solution
LED does not light up	NeoPixel library not installed or GPIO error	Install Adafruit NeoPixel in Library Manager, confirm GPIO48
Color display incorrect (red turns green)	Color order reversed	<code>NEO_GRB</code> is WS2812's color order, do not use <code>NEO_RGB</code>
Compilation error: cannot find <code>Adafruit_NeoPixel.h</code>	Library not installed	Search and install in Library Manager

Phenomenon	Cause	Solution
Fade looks choppy	<code>steps</code> too small or <code>stepDelay</code> too large	Increase <code>FADE_STEPS</code> or decrease <code>FADE_DELAY</code>