

Robot Speed Control

Robot Speed Control


[Function Description](#)
[Experiment Steps](#)
[Code Implementation](#)
[Experiment Result](#)
[Notes](#)

Function Description

In this section, we learn how to control the driving speed of the robot.

Experiment Steps

Before flashing, make sure `LASTBIT.hex` has been flashed, otherwise an error will occur and the module cannot be imported.




1. Before flashing, toggle the switch to the OFF position, and connect the computer to the micro:bit main board with a microUSB data cable. **Note: use the Microbit interface, not the Charging port of the expansion board.**
2. Open the Mu software and directly copy the program source code we provide. The operation steps are as follows. You can also enter the code yourself in the editor window. Note! All letters and symbols should be entered in English input mode, use the Tab key for indentation, and the last line should end with a blank program.
Click the `New` button in the toolbar at the top left corner, and a file titled untitled will appear.



3. Copy the content of the `Code Implementation` section provided below into the current file. You will notice a small red dot after the title bar, indicating that the code content has been modified but is in an unsaved state.

Whether you save or not does not affect code checking and flashing.


4. At this point, you can click `Check` to check whether there are any problems with the code format.



5. At this point, if you have already connected the MICROBIT to the PC computer following the steps above and flashed `LASTBIT.hex`, the next step is to download the current program to the Microbit.

Click the `Flash` tool in the toolbar to start flashing!

While flashing, the orange-yellow indicator light near the micro:bit main board will blink frequently. When the editor prompts `Copied code onto micro:bit.`, the flashing is complete, and the indicator light will stop blinking afterwards.



6. Unplug the Microusb data cable and toggle the switch to the ON position.

Code Implementation

```
from microbit import *
from lastbit import LASTBIT

Lastbit = LASTBIT()
# robot speed control
speed = 80

while True:
    # A+B Stop!
    if button_a.was_pressed() and button_b.was_pressed():
```

```

    speed=0
    display.show(speed)
    sleep(300)
    display.clear()
# A button: increase speed
if button_a.is_pressed():
    speed += 20
    if speed > 255:
        speed = 255
    # display speed
    display.show(speed)
    sleep(300)
    display.clear()
# B button: decrease speed
if button_b.is_pressed():
    speed -= 20
    if speed < 0:
        speed = 0
    # display speed
    display.show(speed)
    sleep(300)
    display.clear()
# Lastbit.car_control('FORWARD', speed)
Lastbit.set_motor(speed,speed)
sleep(50)

```

display.show(): a display function provided by Microbit, used here to display the speed value.

was_pressed(): used to detect button trigger events.

is_pressed(): used to check whether the button is currently pressed.

Experiment Result

The car will drive forward. Pressing button A will increase the car's speed, pressing button B will decrease the car's speed, and pressing both A and B will stop the car. Meanwhile, the modified speed value will be displayed on the dot matrix screen, with a minimum value of 0 and a maximum value of 255.

Notes

Make sure the car battery is sufficiently charged, otherwise there may be problems such as inability to control or insufficient motor torque.