LAB 5: ANGULAR VELOCITY CONTROL FOR DC MOTOR

```
%--------------------------------------
% Fill in your student Name and ID.
Students.Name = '';
Students.ID = '';
%--------------------------------------
```

0. Objectives


In this lab, we will design an angular velocity state-feedback controller to track a desired reference signal. First, we will run an open-loop experiment to get an understanding about the normal system dynamics. Second, we will design a theoretical state-feedback controller based on a DC Motor model. Finally, we will tune the gains of the controller on the Virtual Motor to account for modeling uncertainties and sensor noise.

To initiate a connection with the virtual motor, run the following:

```
Motor = VirtualMotor();
```

1. A State-Space Representation of DC Motor

A DC motor is a device that converts armature current into mechanical torque. A schematic of a DC motor is shown in the following



We can model the DC motor using the armature current i and the angular speed ω. The dynamics of the DC motor are given by the following two coupled differential equations:

$$J\frac{d\omega}{dt} + b\omega = K_t i$$

$$L\frac{di}{dt} + Ri = v - K_e\omega$$

where the parameters are defined as follow

```
Param.Kt = 0.034; % Torque proportionality constant (Kg m2 /s2/A) (N.m/A)
Param.Ke = 0.034; % Back electromotive proportionality constant (V/rad/s)
Param.L = 0.018; % Electric inductance (H)
Param.R = 8.4; % Terminal resistance (Ohm)
Param.J = 2e-05; % Rotor moment of inertia (kg.m2)
Param.b = 1e-06; % Rotor viscous friction constant (Kg.m2/s) (N.m.s)
```

From these differential equations we can represent the DC Motor model by the following state-space representation

$$\frac{d}{dt}x(t) = \begin{bmatrix} -\frac{b}{J} & \frac{K_t}{J} \\ -\frac{K_e}{L} & -\frac{R}{L} \end{bmatrix} x(t) + \begin{bmatrix} 0 \\ \frac{1}{L} \end{bmatrix} v(t)$$

where $v(t)$ is the voltage and the state vector contains the angular velocity $\omega(t)$ and the current $i(t)$

$$x(t) = \begin{bmatrix} \omega(t) \\ i(t) \end{bmatrix}$$

Note that if we think of the angular velocity $\omega(t)$ as the output of this system, then $C = [1 \quad 0]$ and

$$\omega(t) = Cx(t)$$

In this case, the transfer function from the voltage $v(t)$ to the angular velocity $\omega(t)$ is given by

$$G_o(s) = C(sI - A)^{-1}B$$

The state-space representation of the DC Motor can be written as

```
A = [ ...
    -Param.b / Param.J, Param.Kt / Param.J; ...
    -Param.Ke / Param.L, -Param.R / Param.L];
B = [ ...
    0; ...
    1 / Param.L];
C = [1, 0];
D = 0;
Go = ss(A, B, C, D);
tf(Go)
```

```
ans =


        9.444e04
  --------------------
  s^2 + 466.7 s + 3234
```

```
Continuous-time transfer function.
```

2. Desired specifications

The objective of this lab is to track a reference signal ω_{ref} while satisfying the following requirements:

- Overshoot less than 20%.
- 5%-settling time less than 0.25 seconds.
- Steady state gain of $1 \pm 5\%$.


The Reference angular velocity is defined by the following:

$$\omega_{ref}(t) = \begin{cases} 25, & 0 \leqslant t < 5 \\ 75, & t \geqslant 5 \end{cases}$$

In **MATLAB** we define ω_{ref} by:


```
T = 10; % Simulation duration
dt = 0.01; % Simulation step time
t = (0:dt:T)'; % Time array
TStart = 5; % Step start
wRef = zeros(size(t));
wRef(t < TStart) = 25; % rad/s
wRef(t >= TStart) = 75; % rad/s

figure;
clf;
plot(t, wRef, 'LineWidth', 2.0)
legend('Reference angular velocity (rad/s)');
xlim([0, T])
ylim([0, 100])
title(sprintf('Student ID %s - Reference angular velocity', Students.ID));
grid on
```



3. Open-loop Experiment

The state-space open-loop system is presented below.



The gain N_o is used to compensate for the open-loop DC gain, such as the total gain from ω_{ref} to ω is one.

Question 1 (2 marks)

Complete the following code to run the DC Motor in open-loop in such a way that the angular velocity $\omega(t)$ follows the desired angular velocity signal ω_{ref}

```
% Determine a pre compensator N_o

N_o


% Run the experiment
Motor.reset();
% [Answer here] fill the value of the voltage v

v = 0;

Motor.input(v);
Motor.off();

Motor.save(Students, 'Lab05.Q1');
```

```
N_o =

    0.0342
```

```
% Get results of driving Virtual DC Motor
v = Motor.voltage(Motor.time <= T);
i = Motor.current(Motor.time <= T);
w = Motor.velocity(Motor.time <= T);

% Plot results
figure;
clf;


% [Answer here] Superpose the angular velocity w and the reference wRef

legend('Angular velocity (rad/s)', ...
    'Reference angular velocity (rad/s)', ...
    'location', 'best');
xlim([TStart - 1, T])
ylim([0, 100])
title(sprintf('Student ID %s - Open-loop tracking experiment', Students.ID));
grid on
```


Question 2 (0.5 marks)

Based on the plot above, determine if all the requirements are satisfied. Justify your answer.

Answer here

4. Closed-Loop Simulation Experiment

The closed-loop system is presented in the following figure.




The full-state feedback control law is defined as follow

$$v(t) = N_c \omega_{ref} - Kx(t)$$

where gain K is a 1 by 2 matrix and the gain N_c is forward gain that will ensure achieving ω_{ref} at steady state.

Actually, this diagram is equivalent to an open-loop diagram but with a different state transition matrix $A_{cl} = A - BK$



Doing a state feedback with gain K is equivalent to changing the system dynamics from A to $A - BK$. Recall that the eigenvalues of a state transition matrix A are the poles of the system.

We want to choose K to specify the new poles of the closed-loop system $A - BK$ in a way that satisfies the desired specifications

- Overshoot less than 20%.
- 5%-settling time less than 0.25 seconds.

Then we will choose N_c similarly to the open-loop section to satisfy the steady state requirements:

- Steady state gain of 1 $\pm$ 5%.

Question 3 (2 marks)

Calculate the desired poles that satisfies the specifications (Use formula sheet for transient response of 2nd order system in myCourses if needed). And find the gain K that place the poles of $A - BK$ at the desired poles (Use **`place`**).

```
K
```

Question 4 (1 mark)

- The closed-loop transfer function is

$$G_c(s) = C(sI - (A - BK))^{-1}B$$

1. What is the value of the DC gain of the closed-loop system.
2. What is the value N_c needed to compensate for the DC gain of the closed-loop system.

```
dcGainCL
```

```
Nc
```

Question 5 (1 mark)

Complete the following to simulate angular velocity control with state feedback that tracks the desired ω_{ref}.

```
% [Answer here] Define the closed-loop system using ss

Gc


% [Answer here] Simulate the output angular velocity using lsim

wSim


% We also simulate the voltage for visualization
vSim = -lsim(ss(Gc.A, Gc.B, eye(2), Gc.D), Nc*wRef, t) * K' + Nc * wRef;

figure;
clf;

subplot(2, 1, 1)
% [Answer here] Superpose the simulated angular velocity wSim with the
% angular velocity reference

legend('Simulated angular velocity (rad/s)', ...
    'Reference angular velocity (rad/s)', ...
    'location', 'best');
xlim([TStart-1, T])
ylim([0, 100])
grid on
title(sprintf('Student ID %s - Closed-loop tracking Simulation', Students.ID));

subplot(2, 1, 2)
% [Answer here] Plot the simulated voltage input

legend('voltage (V)', 'location', 'best');
xlim([TStart-1, T])
grid on
```

3.2. Closed-loop Experiment

In order to control the virtual DC Motor, we need to take into account the sampling time δt. For this, we generate a discrete control law that achieves the desired poles.

```
Go_d = c2d(Go, dt, 'zoh'); % get the equivalent discrete open-loop system
Kd = place(Go_d.A, Go_d.B, [exp(p1d*dt), exp(p2d*dt)]);
Nd = 1 / (Go_d.C * (eye(2) - Go_d.A + Go_d.B * Kd)^(-1) * Go_d.B);
```

The gains K_d and N_d are the discrete equivalent of the gains K and N_c. we will use these gains (K_d and N_d) instead to control the virtual DC Motor.

Observe that now in closed-loop the value of the voltage (the control law) changes every time depending on the new value of $x(t)$, or in other words $\omega(t)$ and $i(t)$. To do this we will create a **for** loop that will loop over the time signal t. At every instant: # we will wait for the Motor time to sync with our time signal, using the **wait** command. # we will read new values of $\omega(t)$ and $i(t)$. # we will generate the new voltage to send. # we will send the voltage using **input** command.

Question 6 (2 marks)

Complete the following to test the state feedback controller for tracking the desired ω_{ref}. Observe that the control starts at time $t \geqslant T_{Start}$.

```
% Run the experiment
Motor.reset();
for n = 1:length(t)
    Motor.wait(t(n));
    w_ = Motor.velocity_final; % the final reading of velocity by sensor
    i_ = Motor.current_final; % the final reading of current by sensor

    if t(n) < TStart % We only run
        v_ = wRef(n) / dcGainOL;
    else
        % [Answer here] Write the state feedback controller equation

        v_ = 0;

    end
    Motor.input(v_);
end
Motor.off();
Motor.save(Students, 'Lab05.Q6');
```

```
% Get results of Virtual DC Motor
v = Motor.voltage(Motor.time <= T);
i = Motor.current(Motor.time <= T);
w = Motor.velocity(Motor.time <= T);

% Plot results
figure;
clf;

subplot(3, 1, 1)
title(sprintf('Student ID %s - Closed-loop tracking experiment', Students.ID));
% [Answer here] Superpose angular velocity and the velocity reference

legend('Angular velocity (rad/s)', ...
    'Simulated Angular velocity (rad/s)', ...
    'Reference angular velocity (rad/s)', ...
    'location', 'best');
xlim([TStart - 1, T])
grid on

subplot(3, 1, 2)
% [Answer here] Plot current

legend('Current (A)', 'location', 'best');
xlim([TStart - 1, T])
grid on

subplot(3, 1, 3)
% [Answer here] Plot voltage

legend('Voltage (V)', 'location', 'best');
xlim([TStart - 1, T])
grid on
```

Question 7 (0.5 marks)

Based on the plot above, determine if all the requirements are satisfied. Justify your answer.

```
% Answer here
```

Question 8 (1 mark)

Can you tune the value of the gain N_d and K_d to get the required performance.

When you finish tuning, plot the final graph and fill up your final performances.

```
NdTuned = Nd;
KdTuned = [Kd(1), Kd(2)];

Motor.reset();
% [Answer here] Run the experiment use
for n = 1:length(t)

end
Motor.off();

Motor.save(Students, 'Lab05.Q8');

% Get results of Virtual DC Motor
v = Motor.voltage(Motor.time <= T);
i = Motor.current(Motor.time <= T);
w = Motor.velocity(Motor.time <= T);
```

```
% Plot new results
figure;
clf;

subplot(3, 1, 1)
title(sprintf('Student ID %s - Closed-loop tracking experiment (Tweaking); N = %04.2f; K=[%04.2f,%04.2f]', ...
    Students.ID, NdTuned, KdTuned));
% [Answer here] Superpose the angular velocity and the velocity reference

legend('Angular velocity (rad/s)', ...
    'Simulated Angular velocity (rad/s)', ...
    'Reference angular velocity (rad/s)', ...
    'location', 'best');
xlim([TStart - 1, T])
grid on

subplot(3, 1, 2)
% [Answer here] Plot current

legend('Current (A)', 'location', 'best');
xlim([TStart - 1, T])
grid on

subplot(3, 1, 3)
% [Answer here] Plot voltage

legend('Voltage (V)', 'location', 'best');
xlim([TStart - 1, T])
grid on
```

```
% [Answer here] Final performance obtained:

settlingTime % in seconds
overshoot % as a percentage [0 - 100]
steadyStateError % as a percentage [0 - 100]

if settlingTime <= 0.25 && ...
        overshoot <= 20 && ...
        steadyStateError <= 1
    disp('All requirements are satisfied')
else
    disp('Not all requirements are satisfied')
end
```