TUGAS ULANGAN TENGAH SEMESTER

MATA KULIAH:

BASIS DATA



Dosen Pengampu:

Ranny Meilisa, S.Kom.,M.Pd.T

Dibuat Oleh:

Teguh Tegar Aulia (20230801124)

TEKNIK INFORMATIKA

UNIVERSITAS ESA UNGGUL

2024

1. Suatu nilai otomatis merupakan suatu field yang diisi secara otomatis oleh sistem. Biasanya paling banyak digunakan pada *Primary Key*. Tipe data kolom yang akan diset nilai autoincrement adalah **int.**

   Perintahnya :

   Auto_Increment

   Contoh :

   Mysql>Create Table Mahasiswa (
   ID int(5) not null primary key auto_increment,
   NIM char(8) not null,
   Nama_Mhs varchar(50),
   Jurusan varchar(200),
   Fakultas varchar(30));

   Lakukan perintah tersebut kemudian tampilkan hasilnya dalam bentuk gambar (screenshoot)

   JAWABAN:



```
Microsoft Windows [Version 10.0.22631.4317]
(c) Microsoft Corporation. All rights reserved.

C:\Users\HP>cd\xampp\mysql\bin

C:\xampp\mysql\bin>mysql -u root -p
Enter password:
Welcome to the MariaDB monitor.  Commands end with ; or \g.
Your MariaDB connection id is 8
Server version: 10.4.32-MariaDB mariadb.org binary distribution

Copyright (c) 2000, 2018, Oracle, MariaDB Corporation Ab and others.

Type 'help;' or '\h' for help. Type '\c' to clear the current input statement.

MariaDB [(none)]> show databases;
+--------------------+
| Database           |
+--------------------+
| information_schema |
| mysql              |
| orderentry         |
| penjualan_barang   |
| performance_schema |
| pertemuan_4        |
| phpmyadmin         |
| praktikum          |
| test               |
+--------------------+
9 rows in set (0.030 sec)

MariaDB [(none)]> create database Dealer_Pagani;
Query OK, 1 row affected (0.001 sec)

MariaDB [(none)]> use Dealer_Pagani;
Database changed
MariaDB [Dealer_Pagani]> create table Mobil (
    -> id_mobil int auto_increment primary key,
    -> nama_mobil varchar(50) not null,
    -> tahun_produksi year,
    -> harga bigint,
    -> warna varchar(30));
Query OK, 0 rows affected (0.015 sec)

MariaDB [Dealer_Pagani]> insert into Mobil (nama_mobil, tahun_produksi, harga, w
arna) values
    -> ('Pagani Huayra', 2023, 70000000000, 'Merah'),
    -> ('Pagani Zonda', 2022, 55000000000, 'Hitam'),
    -> ('Pagani Utopia', 2023, 70000000000, 'Biru'),
    -> ('Pagani Huayra Roadster', 2022, 90000000000, 'Putih'),
    -> ('Pagani Imola', 2023, 130000000000, 'Silver');
Query OK, 5 rows affected (0.053 sec)
Records: 5  Duplicates: 0  Warnings: 0

MariaDB [Dealer_Pagani]> select * from Mobil;
+----------+----------------------+---------------+--------------+--------+
| id_mobil | nama_mobil           | tahun_produksi | harga        | warna  |
+----------+----------------------+---------------+--------------+--------+
|        1 | Pagani Huayra        |          2023 |  70000000000 | Merah  |
|        2 | Pagani Zonda         |          2022 |  55000000000 | Hitam  |
|        3 | Pagani Utopia        |          2023 |  70000000000 | Biru   |
|        4 | Pagani Huayra Roadster |          2022 |  90000000000 | Putih  |
|        5 | Pagani Imola         |          2023 | 130000000000 | Silver |
+----------+----------------------+---------------+--------------+--------+
5 rows in set (0.000 sec)

MariaDB [Dealer_Pagani]>
```

2. Buatlah sebuah database baru dengan nama Penjualan_Barang

   JAWABAN:

```
MariaDB [(none)]> create database penjualan_barang_uts;
Query OK, 1 row affected (0.001 sec)
```

3. Gunakan database Penjualan_Barang kemudian buatlah table hasil dari diagram relationship penjualan barang

   JAWABAN:

```
Microsoft Windows [Version 10.0.22631.4317]
(c) Microsoft Corporation. All rights reserved.

C:\Users\HP>cd\xampp\mysql\bin

C:\xampp\mysql\bin>mysql -u root -p
Enter password:
Welcome to the MariaDB monitor.  Commands end with ; or \g.
Your MariaDB connection id is 10
Server version: 10.4.32-MariaDB mariadb.org binary distribution

Copyright (c) 2000, 2018, Oracle, MariaDB Corporation Ab and others.

Type 'help;' or '\h' for help. Type '\c' to clear the current input
statement.

MariaDB [(none)]> show databases;
+--------------------+
| Database           |
+--------------------+
| dealer_pagani      |
| information_schema |
| mysql              |
| orderentry         |
| penjualan_barang   |
| performance_schema |
| pertemuan_4        |
| phpmyadmin         |
| praktikum          |
| test               |
+--------------------+
10 rows in set (0.001 sec)

MariaDB [(none)]> create database penjualan_barang_uts;
Query OK, 1 row affected (0.001 sec)

MariaDB [(none)]> use penjualan_barang_uts;
Database changed
MariaDB [penjualan_barang_uts]> create table barang (
    ->     id_barang int auto_increment primary key,
```

```
    ->     nama_barang varchar(100) not null,
    ->     kategori varchar(50),
    ->     harga bigint,
    ->     stok int
    -> );
Query OK, 0 rows affected (0.007 sec)

MariaDB [penjualan_barang_uts]> create table transaksi (
    ->     id_transaksi int auto_increment primary key,
    ->     id_barang int,
    ->     jumlah int,
    ->     total_harga bigint,
    ->     tanggal_transaksi date,
    ->     foreign key (id_barang) references barang(id_barang)
    -> );
Query OK, 0 rows affected (0.016 sec)

MariaDB [penjualan_barang_uts]> create table pelanggan (
    ->     id_pelanggan int auto_increment primary key,
    ->     nama_pelanggan varchar(100),
    ->     alamat varchar(200),
    ->     telepon varchar(20)
    -> );
Query OK, 0 rows affected (0.005 sec)

MariaDB [penjualan_barang_uts]> create table supplier (
    ->     id_supplier int auto_increment primary key,
    ->     nama_supplier varchar(100),
    ->     alamat varchar(200),
    ->     telepon varchar(20)
    -> );
Query OK, 0 rows affected (0.015 sec)

MariaDB [penjualan_barang_uts]> create table pembelian (
    ->     id_pembelian int auto_increment primary key,
    ->     id_supplier int,
    ->     id_barang int,
    ->     jumlah int,
    ->     harga_pembelian bigint,
    ->     tanggal_pembelian date,
    ->     foreign key (id_supplier) references supplier(id_supplier),
    ->     foreign key (id_barang) references barang(id_barang)
    -> );
Query OK, 0 rows affected (0.015 sec)

MariaDB [penjualan_barang_uts]>
```

```
Microsoft Windows [Version 10.0.22631.4317]
(c) Microsoft Corporation. All rights reserved.

C:\Users\HP>cd\xampp\mysql\bin

C:\xampp\mysql\bin>mysql -u root -p
Enter password:
Welcome to the MariaDB monitor.  Commands end with ; or \g.
Your MariaDB connection id is 10
Server version: 10.4.32-MariaDB mariadb.org binary distribution

Copyright (c) 2000, 2018, Oracle, MariaDB Corporation Ab and others.

Type 'help;' or '\h' for help. Type '\c' to clear the current input statement.

MariaDB [(none)]> show databases;
+--------------------+
| Database           |
+--------------------+
| dealer_pagani      |
| information_schema |
| mysql              |
| orderentry         |
| penjualan_barang   |
| performance_schema |
| pertemuan_4        |
| phpmyadmin         |
| praktikum          |
| test               |
+--------------------+
10 rows in set (0.001 sec)

MariaDB [(none)]> create database penjualan_barang_uts;
Query OK, 1 row affected (0.001 sec)

MariaDB [(none)]> use penjualan_barang_uts;
Database changed
MariaDB [penjualan_barang_uts]> create table barang (
    ->     id_barang int auto_increment primary key,
    ->     nama_barang varchar(100) not null,
    ->     kategori varchar(50),
    ->     harga bigint,
    ->     stok int
    -> );
Query OK, 0 rows affected (0.007 sec)

MariaDB [penjualan_barang_uts]> create table transaksi (
    ->     id_transaksi int auto_increment primary key,
    ->     id_barang int,
    ->     jumlah int,
    ->     total_harga bigint,
    ->     tanggal_transaksi date,
    ->     foreign key (id_barang) references barang(id_barang)
    -> );
Query OK, 0 rows affected (0.016 sec)

MariaDB [penjualan_barang_uts]> create table pelanggan (
    ->     id_pelanggan int auto_increment primary key,
    ->     nama_pelanggan varchar(100),
    ->     alamat varchar(200),
    ->     telepon varchar(20)
    -> );
Query OK, 0 rows affected (0.005 sec)

MariaDB [penjualan_barang_uts]> create table supplier (
    ->     id_supplier int auto_increment primary key,
    ->     nama_supplier varchar(100),
    ->     alamat varchar(200),
    ->     telepon varchar(20)
    -> );
Query OK, 0 rows affected (0.015 sec)

MariaDB [penjualan_barang_uts]> create table pembelian (
    ->     id_pembelian int auto_increment primary key,
    ->     id_supplier int,
    ->     id_barang int,
    ->     jumlah int,
    ->     harga_pembelian bigint,
    ->     tanggal_pembelian date,
    ->     foreign key (id_supplier) references supplier(id_supplier),
    ->     foreign key (id_barang) references barang(id_barang)
    -> );
Query OK, 0 rows affected (0.015 sec)

MariaDB [penjualan_barang_uts]>
```

Table Diagram Relationship

