

```

import numpy as np
from PyLTSpice import RawRead
import matplotlib.pyplot as plt

raw = RawRead("./ngspice/NMOS.raw", dialect="ngspice")

par_names = raw.get_trace_names()

par_prefix = par_names[1].split('[')[0]

short_names = {}
for name in par_names:
    short_name = name.split('[', 1)[1].split(']', 1)[0] if '[' in name and ']' in name else name
    short_names[short_name] = name

var1 = raw.get_trace(short_names["id"]).get_wave()
var2 = raw.get_trace(short_names["vds"]).get_wave()
var3 = raw.get_trace(short_names["vgs"]).get_wave()
sweep = raw.get_trace(short_names["v(v-sweep)"]).get_wave()

v_sweep = np.array(list(dict.fromkeys(sweep)))

var1 = np.reshape(var1, (len(v_sweep), -1), order='F')
var2 = np.reshape(var2, (len(v_sweep), -1), order='F')
var3 = np.reshape(var3, (len(v_sweep), -1), order='F')
vgs = var3[0, :]

plt.figure(figsize=(7, 5))
plt.plot(var2, var1 * 1000)
plt.legend([f"VGS = {v:.2f} V" for v in vgs])

plt.xlabel("Vds (V)")
plt.ylabel("Id (mA)")
plt.grid(True)

plt.tight_layout()
plt.show()

```




Figure 1: Drain current I_D versus drain-source voltage V_{DS} for different V_{GS} values.

```
#target curve
target_vgs = 0.8
idx = np.argmin(np.abs(vgs - target_vgs))

plt.figure(figsize=(7, 5))
plt.plot(var2[:, idx], var1[:, idx] * 1000)
plt.legend([f"VGS = {vgs[idx]:.2f} V"])

plt.xlabel("Vds (V)")
plt.ylabel("Id (mA)")
plt.grid(True)

plt.tight_layout()
plt.show()
```




Figure 2: Drain current I_D versus drain-source voltage V_{DS} for $V_{GS} = 0.8$.

```
var1 = raw.get_trace(short_names["gm"]).get_wave()
var2 = raw.get_trace(short_names["vgs"]).get_wave()
var3 = raw.get_trace(short_names["vds"]).get_wave()
sweep = raw.get_trace(short_names["v(v-sweep)"]).get_wave()

v_sweep = np.array(list(dict.fromkeys(sweep)))

var1 = np.reshape(var1, (len(v_sweep), -1), order='F')
var2 = np.reshape(var2, (len(v_sweep), -1), order='F')
var3 = np.reshape(var3, (len(v_sweep), -1), order='F')
vds = var3.T[0, :]

#target curve
target_vds = 1.8
idx = np.argmin(np.abs(vds - target_vds))

plt.figure(figsize=(5, 3))
plt.plot(var2.T[:, idx], var1.T[:, idx] * 1000)
plt.legend([f"VDS = {vds[idx]:.2f} V"])

plt.xlabel("Vgs (V)")
plt.ylabel("gm (m)")
```

```

plt.grid(True)

plt.tight_layout()
plt.show()

var1 = raw.get_trace(short_names["gds"]).get_wave()
var1 = np.reshape(var1, (len(v_sweep), -1), order='F')

plt.figure(figsize=(5, 3))
plt.plot(var2.T[:, idx], var1.T[:, idx] * 1000)
plt.legend([f"VDS = {vds[idx]:.2f} V"])

plt.xlabel("Vgs (V)")
plt.ylabel("gds (m)")
plt.grid(True)

plt.tight_layout()
plt.show()

```




Figure 3: Variation of g_m and g_{ds} versus V_{GS} for $V_{DS} = 1V$.

```

var1 = raw.get_trace(short_names["gds"]).get_wave()
var1 = np.reshape(var1, (len(v_sweep), -1), order='F')
var2 = raw.get_trace(short_names["id"]).get_wave()
var2 = np.reshape(var2, (len(v_sweep), -1), order='F')

#target curve
target_vds = 1.8
idx = np.argmin(np.abs(vds - target_vds))

plt.figure(figsize=(7, 5))
plt.plot(var2.T[:, idx] * 1000, var1.T[:, idx] * 1000)
plt.legend([f"VDS = {vds[idx]:.2f} V"])

```

```
plt.xlabel("Id (mA)")
plt.ylabel("gds (m)")
plt.grid(True)

plt.tight_layout()
plt.show()
```




Figure 4: Variation of g_{ds} versus Drain current I_d for $V_{DS} = 1.8V$.

```
from scipy.interpolate import PchipInterpolator

var1 = raw.get_trace(short_names["gm"]).get_wave()
var2 = raw.get_trace(short_names["vgs"]).get_wave()
var3 = raw.get_trace(short_names["vds"]).get_wave()
var4 = raw.get_trace(short_names["gds"]).get_wave()
sweep = raw.get_trace(short_names["v(v-sweep)"]).get_wave()

v_sweep = np.array(list(dict.fromkeys(sweep)))

var1 = np.reshape(var1, (len(v_sweep), -1), order='F')
var2 = np.reshape(var2, (len(v_sweep), -1), order='F')
var3 = np.reshape(var3, (len(v_sweep), -1), order='F')
var4 = np.reshape(var4, (len(v_sweep), -1), order='F')
```

```

vds = var3.T[0, :]

#target curve
target_vds = 1.8
idx = np.argmin(np.abs(vds - target_vds))

x = var2.T[:, idx]
y = var1.T[:, idx]/var4.T[:, idx]

x_smooth = np.linspace(x.min(), x.max(), 100)
interp = PchipInterpolator(x, y)
y_smooth = interp(x_smooth)

plt.figure(figsize=(7, 5))
plt.plot(x_smooth, y_smooth)
plt.legend([f"VDS = {vds[idx]:.2f} V"])

plt.xlabel("Vgs (V)")
plt.ylabel("gm/gds")
plt.grid(True)

plt.tight_layout()
plt.show()

```




Figure 5: Intrinsic small-signal low-frequency gain of NMOS with $W/L = 100\mu/1.5\mu$.

```
raw = RawRead("./ngspice/NMOS_sc.raw", dialect="ngspice")

par_names = raw.get_trace_names()

par_prefix = par_names[1].split(' ')[0]

short_names = {}
for name in par_names:
    short_name = name.split('[', 1)[1].split(']', 1)[0] if '[' in name and ']' in name else name
    short_names[short_name] = name

var1 = raw.get_trace(short_names["gm"]).get_wave()
var2 = raw.get_trace(short_names["vgs"]).get_wave()
var3 = raw.get_trace(short_names["vds"]).get_wave()
var4 = raw.get_trace(short_names["gds"]).get_wave()
var5 = raw.get_trace(short_names["id"]).get_wave()
sweep = raw.get_trace(short_names["v(v-sweep)"]).get_wave()

v_sweep = np.array(list(dict.fromkeys(sweep)))

var1 = np.reshape(var1, (len(v_sweep), -1), order='F')
```

```

var2 = np.reshape(var2, (len(v_sweep), -1), order='F')
var3 = np.reshape(var3, (len(v_sweep), -1), order='F')
var4 = np.reshape(var4, (len(v_sweep), -1), order='F')
var5 = np.reshape(var5, (len(v_sweep), -1), order='F')

vds = var3.T[0, :]

#target curve
target_vds = 1.8
idx = np.argmin(np.abs(vds - target_vds))

plt.figure(figsize=(5, 3))
plt.plot(var2.T[:, idx], var1.T[:, idx] * 1000)
plt.legend([f"VDS = {vds[idx]:.2f} V"])
plt.xlabel("Vgs (V)")
plt.ylabel("gm (m)")
plt.grid(True)
plt.tight_layout()
plt.show()

plt.figure(figsize=(5, 3))
plt.plot(var2.T[:, idx], var4.T[:, idx] * 1000)
plt.legend([f"VDS = {vds[idx]:.2f} V"])
plt.xlabel("Vgs (V)")
plt.ylabel("gds (m)")
plt.grid(True)
plt.tight_layout()
plt.show()

plt.figure(figsize=(5, 3))
plt.plot(var2.T[:, idx], var1.T[:, idx]/var4.T[:, idx])
plt.legend([f"VDS = {vds[idx]:.2f} V"])
plt.xlabel("Vgs (V)")
plt.ylabel("gm/gds")
plt.grid(True)
plt.tight_layout()
plt.show()

plt.figure(figsize=(5, 3))
plt.plot(var5.T[:, idx]*1000, var4.T[:, idx]*1000)
plt.legend([f"VDS = {vds[idx]:.2f} V"])
plt.xlabel("Id (mA)")
plt.ylabel("gds (m)")
plt.grid(True)
plt.tight_layout()

```



```
plt.show()
```




Figure 6: Variation of small-signal parameters versus V_{GS} for short-channel NMOS where $W = 10\mu m$ and $L = 0.15\mu m$.