

SPECIFICATION**Introduction**

The 1 speed CBX99100 Fan Off Delay Control Board is an electronic fan control board which provides, in one device, control of a line voltage fan motor. The primary purpose is to control the fan motor used in air-conditioning & heating systems. The control board is powered by a 24VAC input and will accept a 24VAC fan signal from the thermostat.

Features

The control board has no fan ON delay and a 90 second fixed post fan OFF delay during which the relay will be energized for another 90 seconds after the thermostat fan signal (G) is turned off. Spade terminals are used for R, C and G connections to the thermostat and an X terminal for the transformer's hot 24VAC input. The board and its 24vac output to the thermostat are protected by an in line 5A replaceable Blade type minifuse (ATM).

. Fan connections are quick connects located on the relay.

Electrical specification

- Nominal Input: 24 VAC
- Operating Input Range: 18-30VAC
- Fan Outputs: 12 FLA (30 LRA) at 240 VAC

PCB Dimension: 2.5" x 2.5"

Terminals

Line voltage connections are .250" x 0.032" quick connect terminals on top of the relay.

Quick connect terminals are provided for T and C inputs from the transformer.

Quick connect terminals are provided for a thermostat.

- 24VAC Hot (R) (fused)
- 24VAC Neutral (C) (same terminal for transformer common input)
- Fan Output (G)

Wiring Diagram and Component Layout



