

Logic Circuits

Tutorial 3 (Boolean Algebra & Logic Gates, Simplification)

Deadline: 2079/10/9

1) Simplify the following expressions using Boolean Algebra:

i) $((AB^1+ABC)^1+A(B+(AB)^1))^1$

ii) $A^1C(ABD)^1+A^1B(CD)^1+AB^1C$

2) Define minterm and maxterm. Write all the minterms and maxterms for 4-variables.

3) Express the following Boolean functions in Sum of Minterms and Product of Maxterms:

i) $F(A,B,C)=A^1B+C^1$

ii) $F(A,B,C,D)=D(A^1+B)+B^1D$

4) Simplify:

i) $Xyz+x^1y+xyz^1$

Ans: y

ii) $x+yz+x^1(y^1+z^1)$

Ans: 1

iii) $(x+y)(x^1+z)(y+z^1)$

Ans: $(x+y)(x^1+z)$

iv) $(BC^1+A^1D)(AB^1+CD^1)$

Ans: 0

v) $ABC^1D^1+A^1BC^1D^1+BC^1D$

Ans: BC^1

5) Simplify the following Boolean functions in to minimum number of literals in SOP and POS form using Boolean algebra:

i) $ABC+AB^1(A^1C^1)^1$

Ans: AB^1+AC , $A(B^1+C)$

ii) $(AB+C)(B+C^1D)$

Ans: $(AB+BC)$, $B(A+C)$

iii) $x^1+x(x+y^1)(y+z^1)$

Ans: x^1+y+z^1 , (x^1+y+z^1)

Also draw the logic diagram for the above results.

6) Convert $F(A,B,C)=AB+BC+AC^1$ into standard SOP form

7) Convert $F(A,B,C)=(A+B)(A+C)(B+C^1)$ into standard POS form.

[Hint: Standard SOP=Sum of Minterms &

Standard POS= Product of Maxterms]

8) Using K-map, simplify the following Boolean functions in SOP and POS form:

i) $F(A,B,C,D)=\sum(5,7,9,12,13,14,15)$ with don't care $d(A,B,C,D)=\sum(3,6,8)$.

ii) $F(A,B,C,D)=\sum(0,6,8,13,14)$ with don't care $d(A,B,C,D)=\sum(2,4,10)$.

iii) $F(A,B,C,D)=\sum(2,3,7,10,11,14)$ with don't care $d(A,B,C,D)=\sum(1,5,15)$.

iv) $F(A,B,C,D)=\sum(1,4,5,6,12,14,15)$ with don't care $d(A,B,C,D)=\sum(10,11)$.

