

Memory Management

Design and implement a memory management module for our Operating System Simulator `oss`.

Implement and compare LRU and FIFO page replacement algorithms, both with dirty-bit optimization.

When a page-fault occurs, it will be necessary to swap in that page. If there are no empty frames, your algorithm will select the victim frame based on the algorithm for that module (FIFO or LRU).

Each frame should also have an additional dirty bit, which is set on writing to the frame. This bit is necessary to consider dirty bit optimization when determining how much time these operations take. The dirty bit will be implemented as a part of the page table.

Operating System Simulator

This will be your main program and serve as the master process. You will start the operating system simulator (call the executable `oss`) as one main process who will fork multiple children at random times. The randomness will be simulated by a logical clock that will be updated by `oss` as well as user processes. Thus, the logical clock resides in shared memory and is accessed as a critical resource using a semaphore. You should have two unsigned integers for the clock; one will show the time in seconds and the other will show the time in nanoseconds, offset from the beginning of a second.

In the beginning, `oss` will allocate shared memory for system data structures, including page table. You can create fixed sized arrays for page tables, assuming that each process will have a requirement of less than 32K memory, with each page being 1K. The page table should also have a delimiter indicating its size so that your programs do not access memory beyond the page table limit. The page table should have all the required fields that may be implemented by bits or character data types.

Assume that your system has a total memory of 256K. You will require a frame table, with data required such as reference byte and dirty bit. Use a bit vector to keep track of the unallocated frames.

After the resources have been set up, `fork` a user process at random times (between 1 and 500 milliseconds of your logical clock). Make sure that you never have more than 18 user processes in the system. If you already have 18 processes, do not create any more until some process terminates. 18 processes is a hard limit and you should implement it using a `#define` macro. Thus, if a user specifies an actual number of processes as 30, your hard limit will still limit it to no more than 18 processes at any time in the system. Your user processes execute concurrently and there is no scheduling performed. They run in a loop constantly till they have to terminate.

`oss` will monitor all memory references from user processes and if the reference results in a page fault, the process will be *suspended* till the page has been brought in. Implement the memory references through a semaphore for each process. Effectively, if there is no page fault, `oss` just increments the clock by 10 nanoseconds and sends a signal on the corresponding semaphore. In case of page fault, `oss` queues the request to the device. Each request for disk read/write takes about 14ms to be fulfilled. In case of page fault, the request is queued for the device and the process is suspended as no signal is sent on the semaphore. The request at the head of the queue is *fulfilled* once the clock has advanced by disk read/write time since the time the request was found at the head of the queue. The fulfillment of request is indicated by showing the page in memory in the page table. `oss` should periodically check if all the processes are queued for device and if so, advance the clock to fulfill the request at the head. We need to do this to resolve any possible deadlock in case memory is low and all processes end up waiting.

While a page is referenced, `oss` performs other tasks on the page table as well such as updating the page reference, setting up dirty bit, checking if the memory reference is valid and whether the process has appropriate permissions on the frame, and so on.

When a process terminates, **oss** should log its termination in the log file and also indicate its effective memory access time. **oss** should also print its memory map every second showing the allocation of frames. You can display unallocated frames by a period and allocated frame by a +.

For example at least something like...

```
Master: P2 requesting read of address 25237 at time xxx:xxx
Master: Address 25237 in frame 13, giving data to P2 at time xxx:xxx
Master: P5 requesting write of address 12345 at time xxx:xxx
Master: Address 12345 in frame 203, writing data to frame at time xxx:xxx
Master: P2 requesting write of address 03456 at time xxx:xxx
Master: Address 12345 is not in a frame, pagefault
Master: Clearing frame 107 and swapping in p2 page 3
Master: Dirty bit of frame 107 set, adding additional time to the clock
Master: Indicating to P2 that write has happened to address 03456
```

Current memory layout at time xxx:xxx is:

	Occupied	RefByte	DirtyBit
Frame 0: No	0	0	
Frame 1: Yes	13	1	
Frame 2: Yes	1	0	
Frame 3: Yes	120	1	

where **Occupied** indicates if we have a page in that frame, the **refByte** is the value of our reference bits in the frame and the dirty bit indicates if the frame has been written to.

User Processes

Each user process generates memory references to one of its locations. This will be done by generating an actual byte address, from 0 to the limit of the process memory. In addition, the user process will generate a random number to indicate whether the memory reference is a read from memory or write into memory. This information is also conveyed to **oss**. The user process will **wait** on its semaphore that will be signaled by **oss**. **oss** checks the page reference by extracting the page number from the address, increments the clock as specified above, and sends a signal on the semaphore if the page is valid.

At random times, say every 1000 ± 100 memory references, the user process will check whether it should terminate. If so, all its memory should be returned to **oss** and **oss** should be informed of its termination.

The statistics of interest are:

- Number of memory accesses per second
- Number of page faults per memory access
- Average memory access speed

Make sure that you have signal handling to terminate all processes, if needed. In case of abnormal termination, make sure to remove shared memory and semaphores.

I suggest you implement these requirements in the following order:

1. Get a makefile that compiles two source files, have master allocate shared memory, use it, then deallocate it. Make sure to check all possible error returns.
2. Get Master to fork off and exec one child and have that child attach to shared memory and check the clock and verify it has correct resource limit. Then test having child and master communicate through message queues. Set up PCB and frame table/page tables

3. Have child request a read/write of a memory address and have master always grant it and log it.
4. Set up more than one process going through your system, still granting all requests.
5. Now start filling out your page table and frame table; if a frame is full, just empty it (indicating in the process that you took it from that it is gone) and granting request.
6. Implement a wait queue for I/O delay on needing to swap a process out.
7. Do not forget that swapping out a process with a dirty bit should take more time on your device

Deliverables

Handin an electronic copy of all the sources, **README**, **Makefile(s)**, and results. Create your programs in a directory called *username.6* where *username* is your login name on hoare. Once you are done with everything, *remove the executables and object files*, and issue the following commands:

```
chmod 700 username.6
```

```
cp -p -r username.6 /home/hauschild/cs4760/assignment5
```

Do not forget **Makefile** (with suffix rules), version control, and **README** for the assignment. If you do not use version control, you will lose 10 points. Omission of a **Makefile** (with suffix rules) will result in a loss of another 10 points, while **README** will cost you 5 points.