2.3: Introduction to Sensors and Actuators

1. Introduction

Welcome to this module on **Sensors and Actuators**! In the exciting world of electronics and prototyping, sensors and actuators are the fundamental components that allow electronic systems to interact with the physical world. Think of sensors as the ‘eyes’ and ‘ears’ of a system, gathering information about the environment, and actuators as the ‘muscles’ and ‘mouths’, performing actions based on that information. This module will introduce you to the basic concepts of sensors and actuators, explore common types, and provide practical examples of their applications.

2. What are Sensors?

A **sensor** is a device that detects and responds to some type of input from the physical environment. The input could be light, heat, motion, moisture, pressure, or any one of a great number of other environmental phenomena. The output is generally an electrical signal that is proportional to the measured input. This electrical signal can then be processed by a microcontroller or other electronic circuit.

2.1. Key Characteristics of Sensors

When working with sensors, it’s important to understand some key characteristics:

- **Accuracy:** How close the sensor’s reading is to the true value.
- **Precision:** The repeatability of the sensor’s measurements under the same conditions.
- **Resolution:** The smallest change in the input that the sensor can detect.
- **Range:** The minimum and maximum values that the sensor can measure.

- **Sensitivity:** The ratio of the change in electrical output to the change in physical input.

2.2. Common Types of Sensors

Let's explore some common types of sensors:

2.2.1. Light Sensors (Photoresistors/LDRs)

A **photoresistor**, also known as a Light Dependent Resistor (LDR), is a passive component that decreases resistance with respect to receiving luminosity (light) on the component's sensitive surface. The resistance of an LDR decreases as the intensity of incident light increases.

Example: An LDR can be used in automatic street lights. When it's dark, the LDR's resistance is high, allowing more current to flow to a transistor that switches on the light. When it's bright, the resistance is low, turning off the light.

2.2.2. Temperature Sensors (Thermistor, LM35)

Temperature sensors measure heat or cold. Common types include thermistors and integrated circuit (IC) sensors like the LM35.

- **Thermistor:** A type of resistor whose resistance is strongly dependent on temperature, more so than in standard resistors. They are widely used as inrush current limiters, temperature sensors, self-resetting overcurrent protectors, and self-regulating heating elements.
- **LM35:** A precision integrated-circuit temperature sensor, whose output voltage is linearly proportional to the Celsius (Centigrade) temperature. It does not require any external calibration or trimming to provide typical accuracies of $\pm 1/4^\circ C$ at room temperature and $\pm 3/4^\circ C$ over a full -55 to $+150^\circ C$ temperature range.

Example: An LM35 can be used in a simple thermostat. The output voltage of the LM35 can be read by a microcontroller, which then turns a heater or cooler on/off based on a set temperature.

2.2.3. Distance Sensors (Ultrasonic, Infrared)

Distance sensors measure the distance to an object. Common types include ultrasonic and infrared (IR) sensors.

- **Ultrasonic Sensor (HC-SR04):** These sensors measure distance by emitting a sound wave at a frequency too high for humans to hear. It then waits for the sound wave to be reflected back. The time taken for the sound to return is used to calculate the distance to the object. The formula for distance is:

$$\text{Distance} = \frac{\text{Time} \times \text{Speed of Sound}}{2}$$

  The division by 2 is because the sound travels to the object and back.

- **Infrared (IR) Sensor:** These sensors work by emitting an infrared light beam and detecting the reflection of that beam. The amount of reflected light can be used to determine the distance to an object. They are generally less accurate than ultrasonic sensors for distance measurement but can be useful for proximity detection.

Example: An ultrasonic sensor is commonly used in robotics for obstacle avoidance. The robot can detect objects in its path and change direction to avoid collisions.

3. What are Actuators?

An **actuator** is a component of a machine that is responsible for moving or controlling a mechanism or system. It takes energy, usually created by air, electric current, or liquid, and converts that into some kind of motion. In electronic systems, actuators typically convert electrical signals into physical motion.

3.1. Common Types of Actuators

Let's look at some common types of actuators:

3.1.1. Motors (DC Motors)

A **DC motor** is an electric machine that converts electrical energy into mechanical energy. DC motors take electrical power through direct current and convert this energy into mechanical rotation. They are widely used in applications requiring variable speed and torque.

Example: DC motors are used in robotic wheels, fans, and many other devices where continuous rotation is needed.

3.1.2. Servos (Servo Motors)

A **servo motor** is a rotary actuator or linear actuator that allows for precise control of angular or linear position, velocity, and acceleration. It consists of a suitable motor coupled to a sensor for position feedback. Servo motors are commonly used in applications where precise angular movement is required.

Example: Servo motors are extensively used in robotics for controlling robotic arms, in remote-controlled airplanes for controlling flaps, and in various automation tasks.

3.1.3. Solenoids

A **solenoid** is a type of electromagnet, the purpose of which is to generate a controlled magnetic field. If the purpose of the solenoid is to convert electric current into linear motion, then the solenoid is an actuator. They are often used for opening and closing valves, locking mechanisms, and other on/off type actions.

Example: Solenoids are used in automatic door locks, car starter motors, and pneumatic or hydraulic valves.

4. Sensors vs. Actuators: A Comparison

Here's a table summarizing the key differences between sensors and actuators:

Feature	Sensors	Actuators
Function	Detects physical phenomena	Converts energy into physical motion
Input	Physical phenomena (light, temp, dist)	Electrical signal
Output	Electrical signal	Physical motion (rotation, linear, etc.)
Role	Input device (eyes/ears)	Output device (muscles/mouths)
Examples	LDR, Thermistor, Ultrasonic Sensor	DC Motor, Servo Motor, Solenoid

5. Practice Problems

1. **Problem:** You want to design a system that automatically turns on a garden light when it gets dark. Which type of sensor would be most suitable for this application, and why? **Solution:** A photoresistor (LDR) would be most suitable. Its resistance changes with light intensity, allowing the system to detect darkness and activate the light.

2. **Problem:** A robot needs to navigate a maze and avoid bumping into walls. Which type of sensor would be best for detecting obstacles, and how does it work? **Solution:** An ultrasonic distance sensor (e.g., HC-SR04) would be best. It emits sound waves and calculates the distance to an object based on the time it takes for the sound to return, enabling the robot to detect walls and avoid collisions.

3. **Problem:** You are building a robotic arm that needs to precisely control the angle of its joints. Which type of actuator would you use for this purpose? **Solution:** A servo motor would be ideal. Servo motors provide precise control over angular position, making them perfect for controlling the joints of a robotic arm.

6. Conclusion

Sensors and actuators are indispensable components in modern electronic systems, enabling them to perceive and interact with their environment. Understanding their fundamental principles and common types is crucial for anyone venturing into electronics and prototyping. As you continue your journey, you'll find these components at the heart of countless innovative projects.

7. References

[1] Wikipedia. (n.d.). *Photoresistor*. Retrieved from https://en.wikipedia.org/wiki/Photoresistor [2] Texas Instruments. (n.d.). *LM35 Precision Centigrade Temperature Sensors*. Retrieved from https://www.ti.com/lit/ds/symlink/lm35.pdf [3] Wikipedia. (n.d.). *Ultrasonic sensor*. Retrieved from https://en.wikipedia.org/wiki/Ultrasonic_sensor [4] Wikipedia. (n.d.). *Actuator*. Retrieved from https://en.wikipedia.org/wiki/Actuator [5] Wikipedia. (n.d.). *DC motor*. Retrieved from https://en.wikipedia.org/wiki/DC_motor [6] Wikipedia.

(n.d.). *Servomotor*. Retrieved from https://en.wikipedia.org/wiki/Servomotor [7] Wikipedia. (n.d.). *Solenoid*. Retrieved from https://en.wikipedia.org/wiki/Solenoid