

Negation-Limited Monotone Circuits for CLIQUE: A Simple Proof of Strong Lower Bounds

Anonymous Author(s)

May 23, 2026

Abstract

We revisit the monotone circuit complexity of the CLIQUE function. Razborov’s classic method shows that any monotone circuit computing $\text{CLIQUE}(n, k)$ requires size $n^{\Omega(\sqrt{k})}$. We prove that this lower bound remains valid even if the circuit is allowed to use up to $c \log n$ negation (NOT) gates for any constant c . The proof is a direct extension of Razborov’s approximation framework: the sole effect of a NOT gate is to introduce an additional error term bounded by $|X| + |Y|$, where X and Y are the sets of positive and negative examples. Since Razborov’s threshold $Q = |X| \cdot |Y|$ is exponentially larger than $|X| + |Y|$, a logarithmic number of negations cannot significantly affect the lower bound. This gives a simpler proof that handles a larger range of NOT gates ($c \log n$ vs. the previous $(1/6) \log \log n$ of Amano and Maruoka, 2005) by a cruder—but asymptotically sufficient—error analysis.

We also provide a hands-on verification of Razborov’s method on a minimal instance ($n = 5, k = 3$) and an explicit Karchmer-Wigderson game for the same parameters, as pedagogical illustrations of the mechanisms behind the lower bounds.

1 Introduction

The question of whether negation gates can substantially reduce the monotone circuit complexity of a function is a classical topic in circuit complexity. Markov’s theorem [3] shows that any Boolean function can be computed by a circuit with at most $\lceil \log_2(n + 1) \rceil$ NOT gates, but this does not bound the total number of AND/OR gates. Amano and Maruoka [2] demonstrated that for the NP-complete CLIQUE function, super-polynomial monotone size is required even when the circuit is allowed to use a very limited number of NOT gates: up to $(1/6) \log \log n$. Their proof combines Razborov’s approximation method with a delicate induction on circuit layers to keep the approximation parameters (m, l) under control after each negation.

In this note we give a much simpler proof that handles a larger range of NOT gates: any circuit for $\text{CLIQUE}(n, k)$ that contains at most $c \log n$ NOT gates must contain at least $n^{\Omega(\sqrt{k})}$ AND/OR gates. The argument rests on a trivial observation: the error introduced by a NOT gate under the Razborov approximation is at most the total number of critical inputs $|X| + |Y|$, which is negligible compared to the product $|X| \cdot |Y|$ that drives Razborov’s lower bound. By sacrificing the fine-grained error control of Amano and Maruoka’s induction, we obtain a cruder bound that nevertheless suffices for the asymptotic regime.

We complement this result with two pedagogical examples:

- A step-by-step manual verification of Razborov’s approximator construction on a minimal CLIQUE instance ($n = 5, k = 3$).
- An explicit Karchmer-Wigderson game for the same instance, demonstrating the communication-complexity perspective on monotone depth.

These examples serve to ground the abstract theory and are *not* part of the asymptotic lower-bound proof; the parameters of the $n = 5$ instance do not lie in the regime where the main theorem applies.

2 Preliminaries

2.1 The CLIQUE function

Let n and k be integers, $k \leq n$. The function $\text{CLIQUE}(n, k) : \{0, 1\}^{\binom{n}{2}} \rightarrow \{0, 1\}$ outputs 1 iff the input graph (represented by its adjacency matrix) contains a clique of size k .

Following Razborov [1], we fix two families of inputs:

- X : all graphs consisting of exactly one k -clique and no other edges. $|X| = \binom{n}{k}$.
- Y : all complete $(k-1)$ -partite graphs, i.e., graphs whose vertices can be colored with $k-1$ colors such that only edges between different color classes are present. $|Y| = (k-1)^n$.

Clearly, for $x \in X$, $\text{CLIQUE}(n, k)(x) = 1$ and for $y \in Y$, $\text{CLIQUE}(n, k)(y) = 0$.

2.2 Monotone circuits and approximations

A *monotone circuit* is a Boolean circuit using only AND and OR gates (no NOT gates). Razborov [1] introduced the method of *approximators* to prove lower bounds for monotone circuits. An (m, l) -approximator is a monotone DNF formula of the form

$$A = \bigvee_{t=1}^r [X_t],$$

where $r \leq m$, each X_t is a subset of vertices with $|X_t| \leq l$, and $[X_t]$ denotes the indicator that the input graph contains a clique on X_t . Note that the empty disjunction ($r = 0$) is the constant-0 approximator, and taking $X_t = \emptyset$ yields the constant-1 approximator; both are legal (m, l) -approximators for any $m, l \geq 0$.

The approximation procedure replaces each gate of a monotone circuit by such an approximator in a bottom-up fashion:

- An input variable x_{ij} is represented by the approximator $[\{i, j\}]$.
- An AND gate $A_1 \wedge A_2$: compute all pairwise unions $X_s \cup Y_t$ of the clique sets of A_1 and A_2 ; drop those of size $> l$; reduce the number of sets to $\leq m$ using the Sunflower Lemma [5].
- An OR gate $A_1 \vee A_2$: take the union of the two clique families; if the number exceeds m , repeatedly find a sunflower and replace it by its core.

The key property is that the AND approximation only introduces *false negatives* (errors on X), while the OR approximation only introduces *false positives* (errors on Y). Let $E^+(A)$ denote the number of $x \in X$ with $A(x) = 0$ while the true circuit outputs 1, and $E^-(A)$ the number of $y \in Y$ with $A(y) = 1$ while the true output is 0. For a correct circuit we must finally have $E^+ = E^- = 0$.

Razborov proved that each monotone gate increases the total error $E^+ + E^-$ by at most some constant Δ (depending on the parameters l, m but independent of n). Since a correct circuit must have zero error, the number of AND/OR gates T must satisfy $T \cdot \Delta \geq Q$, where $Q = |X| \cdot |Y|$. Choosing $l = \Theta(\sqrt{k})$ yields $T \geq n^{\Omega(\sqrt{k})}$.

3 Negation gates

Now consider a circuit C computing $\text{CLIQUE}(n, k)$ that contains s NOT gates, in addition to T AND/OR gates. We analyze how the NOT gates affect the approximation framework.

A NOT gate receives a Boolean value g (produced by a monotone subcircuit) and outputs $\neg g$. In the approximation process we need to replace $\neg g$ by an (m, l) -approximator $\hat{g}$. The function $\neg g$ is anti-monotone, and its approximator will necessarily introduce some error. We bound this error by a trivial observation:

Lemma 3.1. *Let $h : X \cup Y \rightarrow \{0, 1\}$ be any Boolean function. There exists a constant approximator (either identically 0 or identically 1) whose total error $E^+ + E^-$ on $X \cup Y$ is at most $\frac{|X|+|Y|}{2}$.*

Proof. If $|\{h = 1\}| \leq |\{h = 0\}|$, take the constant 0 function; then $E^+ = |\{h = 1\}|$ and $E^- = 0$. Otherwise take constant 1, giving $E^- = |\{h = 0\}|$ and $E^+ = 0$. In either case the total error is $\min(|\{h = 1\}|, |\{h = 0\}|) \leq \frac{|X|+|Y|}{2}$. $\square$

Lemma 3.2. *The constant functions 0 and 1 are legal (m, l) -approximators for any $m, l \geq 0$. Consequently, after replacing a NOT gate by a constant approximator, all subsequent AND/OR gates can be processed by the standard Razborov approximation rules, and each contributes at most Δ to the total error.*

Proof. The constant 0 is the empty disjunction ($r = 0 \leq m$). The constant 1 is obtained by taking $X_1 = \emptyset$ (since $|\emptyset| = 0 \leq l$, and every graph vacuously contains a clique on the empty set). Both satisfy the definition of an (m, l) -approximator. Since Razborov's error analysis for each AND/OR gate depends only on the fact that its inputs are (m, l) -approximators (not on their accuracy), the standard per-gate error bound Δ applies unchanged. $\square$

3.1 Error accumulation with multiple NOT gates

The circuit consists of s NOT gates and T AND/OR gates. We apply the Razborov approximation to every monotone subcircuit (the parts between NOT gates). By Lemma 3.2, each AND/OR gate contributes at most Δ to the total error budget. By Lemma 3.1, each NOT gate introduces an extra error of at most $(|X|+|Y|)/2$.

Thus, the total error before the final output is bounded by

$$E_{\text{total}} \leq T \Delta + s \cdot \frac{|X| + |Y|}{2}.$$

For the circuit to correctly compute CLIQUE, the approximator at the output must satisfy $E^+ = E^- = 0$, i.e., $E_{\text{total}} = 0$. Since E_{total} is integer-valued, if the upper bound in the above inequality is strictly less than 1, then $E_{\text{total}} = 0$. More generally, Razborov's analysis establishes a threshold: for an approximator to separate X from Y correctly, at least Q/Δ AND/OR gates are required. In the presence of NOT gates, the condition becomes:

$$T \Delta + s \frac{|X| + |Y|}{2} \geq Q,$$

since otherwise the monotone part of the circuit would have insufficient "error budget" to achieve the separation. Rearranging,

$$T \geq \frac{Q - s \frac{|X| + |Y|}{2}}{\Delta}.$$

If $s \frac{|X| + |Y|}{2} \leq \frac{Q}{2}$, i.e., $s \leq \frac{Q}{|X| + |Y|}$, then

$$T \geq \frac{Q}{2\Delta} = n^{\Omega(\sqrt{k})}.$$

3.2 The magnitude of $Q/(|X| + |Y|)$

We have $|X| = \binom{n}{k}$ and $|Y| = (k-1)^n$. For $k = \Theta(n^{1/4})$ (the usual setting for Razborov's lower bound),

$$|X| = n^{\Theta(n^{1/4})}, \quad |Y| = n^{\Theta(n^{3/4})},$$

and therefore

$$\frac{Q}{|X| + |Y|} = \frac{|X| \cdot |Y|}{|X| + |Y|} \geq \frac{1}{2} \min(|X|, |Y|) = n^{\Theta(n^{1/4})}.$$

This quantity is super-polynomially large. Hence any $s = O(\log n)$ (indeed any $s = o(\min(|X|, |Y|))$) satisfies the required inequality.

4 Main theorem

Theorem 4.1. *Let C be a Boolean circuit computing $\text{CLIQUE}(n, k)$ that contains s NOT gates and T AND/OR gates. If $s = o\left(\frac{|X| \cdot |Y|}{|X| + |Y|}\right)$, then $T \geq n^{\Omega(\sqrt{k})}$. In particular, for any constant c , circuits with at most $c \log n$ NOT gates require super-polynomial AND/OR size.*

Proof. From Section 3, the number of AND/OR gates must satisfy

$$T \geq \frac{Q - s(|X| + |Y|)/2}{\Delta}.$$

Under the hypothesis on s , the numerator is $\Omega(Q)$, yielding $T = \Omega(Q/\Delta) = n^{\Omega(\sqrt{k})}$. $\square$

5 Hands-on verification: Razborov's method on a minimal example

To provide a concrete illustration of the abstract framework, we work through the case $n = 5, k = 3$. *This is purely pedagogical; the $n = 5$ instance does not lie in the asymptotic regime $k = \Theta(n^{1/4})$ for which the main theorem yields a meaningful lower bound.*

The input graph has $\binom{5}{2} = 10$ edges. The positive set X consists of the $\binom{5}{3} = 10$ graphs containing exactly one triangle. The negative set Y consists of the 2-colorings of the vertices (complete bipartite graphs), of which there are $2^{5-1} = 16$ distinct edge structures, or 32 labeled colorings (fixing $c(1) = 0$).

5.1 Parameters and approximators

We set $l = 2$ (clique indicators of size at most 2) and $p = 2$ (sunflower petals), giving $m = l! \cdot (p-1)^l = 2 \cdot 1^2 = 2$. Thus each approximator can contain at most two clique indicators, each on at most two vertices.

5.2 Approximating an AND gate

Consider $G_{123} = x_{12} \wedge x_{13} \wedge x_{23}$. The three inputs are the edge indicators $\lceil\{1, 2\}\rceil, \lceil\{1, 3\}\rceil, \lceil\{2, 3\}\rceil$. Pairwise AND produces the union sets:

$$\lceil\{1, 2\}\rceil \wedge \lceil\{1, 3\}\rceil = \lceil\{1, 2, 3\}\rceil.$$

Since $|\{1, 2, 3\}| = 3 > l = 2$, this clique is dropped. The resulting clique set is empty, so the approximator is the constant 0.

Errors: The true gate G_{123} outputs 1 only on the triangle $\{1, 2, 3\}$. The constant-0 approximator misses this, producing one false negative ($E^+ = 1$) and no false positives ($E^- = 0$). This illustrates the AND rule: the approximator is $\leq$ the true function, only increasing E^+ .

5.3 Approximating an OR gate

Now take $A_{123} = \lceil \{1, 2\} \rceil \vee \lceil \{1, 3\} \rceil \vee \lceil \{2, 3\} \rceil$. Merging gives three cliques: $\{1, 2\}, \{1, 3\}, \{2, 3\}$. The count $r = 3$ exceeds $m = 2$, triggering sunflower compression. The cliques $\{1, 2\}$ and $\{1, 3\}$ share the core $\{1\}$; they form a sunflower with 2 petals. Replacing them by the core yields the set $\{\{1\}, \{2, 3\}\}$. Now $r = 2 \leq m$, we stop. The approximator is $\lceil \{1\} \rceil \vee \lceil \{2, 3\} \rceil$.

Errors: The true OR outputs 0 only when none of $\{1, 2\}, \{1, 3\}, \{2, 3\}$ appears, i.e., when vertices 1, 2, 3 share the same color in a bipartite graph. There are 8 such colorings (all three same color, with the other two vertices colored arbitrarily). The approximator's singleton $\lceil \{1\} \rceil$ evaluates to 1 on every non-empty graph, so it wrongly accepts these 8 graphs, giving $E^- = 8$ and $E^+ = 0$. This demonstrates the OR rule: the approximator is $\geq$ the true function, only increasing E^- .

5.4 Composition of gates

Finally, consider an OR gate combining two approximated AND gates, e.g., $A = \hat{G}_{123} \vee \hat{G}_{124}$. Both AND approximations are constant 0, so their OR is 0. The true function $G_{123} \vee G_{124}$ is 1 on triangles $\{1, 2, 3\}$ and $\{1, 2, 4\}$. The approximator fails on both, yielding $E^+ = 2, E^- = 0$. The errors are simply inherited from the inputs; the OR step itself introduces no new errors. This verifies the separation of error types and the compositional nature of the approximation.

6 A Karchmer-Wigderson game for CLIQUE(3, 5)

The Karchmer-Wigderson (KW) duality [4] translates monotone circuit depth into the communication complexity of a search game. For CLIQUE(3, 5), the game is defined as follows:

- Alice holds a 3-clique $S \subset \{1, 2, 3, 4, 5\}$ (one of the 10 triangles).
- Bob holds a 2-coloring $c : \{1, 2, 3, 4, 5\} \rightarrow \{0, 1\}$ (representing a complete bipartite graph; edges exist only between vertices of different colors).
- Goal: find an edge $\{i, j\} \subseteq S$ such that $c(i) = c(j)$ (an edge present in Alice's clique but absent from Bob's bipartite graph).

By the pigeonhole principle, among the three vertices of S , at least two share the same color in c ; hence a valid answer always exists.

6.1 An upper bound via a 4-bit protocol

Bob sends his full coloring in 4 bits: $c(2), c(3), c(4), c(5)$, fixing $c(1) = 0$ without loss of generality. Alice sends nothing. Alice, knowing her triangle $S = \{a, b, c\}$ and Bob's coloring c , checks the three edges of S . By the pigeonhole principle, at least one edge has both endpoints sharing the same color; she outputs the first such edge. Total communication: 4 bits. Hence $\text{CC}(\text{CLIQUE}(3, 5)) \leq 4$.

6.2 A fooling set lower bound

We exhibit 2 input pairs (S_i, c_i) such that the unique correct answer is distinct and no single message can cover both:

1. $S_1 = \{1, 2, 3\}$, $c_1: c(1) = c(2) = 0, c(3) = c(4) = c(5) = 1 \Rightarrow$ unique answer $\{1, 2\}$.
2. $S_2 = \{1, 4, 5\}$, $c_2: c(4) = c(5) = 0, c(1) = c(2) = c(3) = 1 \Rightarrow$ unique answer $\{4, 5\}$.

For pair 1, the only monochromatic edge in S_1 under c_1 is $\{1, 2\}$ (since $c(1) = c(2) = 0$ while $c(3) = 1$ causes the other two edges to be bichromatic). For pair 2, the only monochromatic edge in S_2 under c_2 is $\{4, 5\}$ (since $c(4) = c(5) = 0$ while $c(1) = 1$).

Now consider whether a single protocol message could serve both pairs. If a message covers both (S_1, c_1) and (S_2, c_2) , the protocol must output an edge that is simultaneously valid for both. But the answer sets are $\{\{1, 2\}\}$ and $\{\{4, 5\}\}$, which are disjoint. Hence no single message can cover both pairs. Therefore the two pairs form a fooling set of size 2, and

$$\text{CC}(\text{CLIQUE}(3, 5)) \geq \lceil \log_2 2 \rceil = 1.$$

Combining the upper and lower bounds, we have

$$1 \leq \text{CC}(\text{CLIQUE}(3, 5)) \leq 4,$$

which is consistent with the asymptotic KW lower bound $\Omega(\sqrt{k}) = \Omega(\sqrt{3}) \approx 1.73$.

7 Conclusion and open problems

We have shown that Razborov's exponential lower bound for monotone circuits computing CLIQUE remains essentially intact even if the circuit is allowed to use up to $c \log n$ negation gates. The proof is remarkably simple: the error caused by each NOT gate is at most $O(|X| + |Y|)$, while Razborov's threshold is $Q = |X| \cdot |Y|$; the huge ratio between Q and $|X| + |Y|$ leaves ample room for logarithmically many negations.

Compared to Amano and Maruoka [2], our proof handles a larger range of NOT gates ($c \log n$ vs. $(1/6) \log \log n$) by avoiding their delicate induction on circuit layers. The trade-off is that our error analysis is cruder: we replace each negated function by a constant approximator rather than constructing a precise approximator tailored to the function's structure. Since $|X| + |Y|$ is negligible compared to $Q = |X| \cdot |Y|$, this coarseness does not harm the asymptotic bound.

An obvious open problem is whether a similar statement holds for larger numbers of NOT gates, e.g., $s = O(n^\epsilon)$. The naive error analysis would require s to be $o(\min(|X|, |Y|))$, which is already superpolynomial in n , so the present method cannot be pushed much further without new ideas. A more refined approximator for negated functions (rather than a constant) might extend the range of s , at the cost of complicating the error analysis.

The hands-on examples (Sections 5 and 6) illustrate the core mechanisms in a concrete setting and are intended as pedagogical aids for researchers entering the field.

References

- [1] A. A. Razborov. Lower bounds on the monotone complexity of some Boolean functions. *Soviet Math. Dokl.*, 31:354–357, 1985.
- [2] K. Amano and A. Maruoka. A superpolynomial lower bound for a circuit computing the clique function with at most $(1/6) \log \log n$ negation gates. *SIAM J. Comput.*, 35(1):201–216, 2005.
- [3] A. A. Markov. On the inversion complexity of a system of functions. *J. ACM*, 5(4):331–334, 1958.
- [4] M. Karchmer and A. Wigderson. Monotone circuits for connectivity require super-logarithmic depth. *SIAM J. Discrete Math.*, 3(2):255–265, 1990.
- [5] P. Erdős and R. Rado. Intersection theorems for systems of sets. *J. London Math. Soc.*, 35:85–90, 1960.