


Industrial Data Logger GUI Configuration Manual



1. Selecting the COM Port

This should be the first step before in using the Data Logger UI.

1. Plugin the hardware and check for the COM Port number in **Computer->System Properties->Device Manager->Ports**
2. Select the COM Port number in the UI App as shown below and Click Open.





2. UI Settings

2.1. MODBUS

2.1.1. Com Port Settings

This is the UART settings for Modbus Communication. Refer the screenshot below.

UI Settings | Log Settings | Time settings | System Log

IOBUS ☐ ADC ☐ Digital Input

DBUS | ADC | Digital Input

Com.Port Settings | MODBUS Settings

Baude Rate: 9600

Data Bit: 8 bit

Parity: None

Stop Bit: 1 bit

Slave Restart Time:

CRC: ☐ Enable ☒ Disable

1. Select **Baud Rate** from the list.
2. Select **Data Bit** from the list.
3. Select **Parity** from the list.
4. Select **Stop Bit** from the list.
5. Ignore **Slave Restart Time** for now.
6. Select **CRC Disable**
7. Click on Apply.

2.1.2. Modbus Settings

This is Modbus Slave information to log the Modbus data.



UI Settings | Log Settings | Time settings | System Log | IP Settings | Protocol Settings | Com.Port Settings | Change Password | Factory Default Settings | Debug

MODBUS ☐ ADC ☐ Digital Input Apply Read

MODBUS ☐ ADC ☐ Digital Input

Com.Port Settings | MODBUS Settings

S.No	Slave ID	Start Address	Type	Length	Log
1	1	0001	Coil	5	<input checked="" type="checkbox"/>
2	2	0010	Input Register	4	<input type="checkbox"/>
3	3	0020	Holding Register	5	<input type="checkbox"/>
4	4	0030	Coil	3	<input checked="" type="checkbox"/>
5					<input type="checkbox"/>
6					<input type="checkbox"/>
7					<input type="checkbox"/>
8					<input type="checkbox"/>
9					<input type="checkbox"/>
10					<input type="checkbox"/>
11					<input type="checkbox"/>
12					<input type="checkbox"/>
13					<input type="checkbox"/>
14					<input type="checkbox"/>
15					<input type="checkbox"/>

* Max 32 Slave Address Apply Read

1. **Slave ID:** This is the Modbus Slave ID. Maximum 32 Slave info can be accessed.
2. **Start Address:** This is the starting address of the slave from where data needs to be read.
3. **Type:** Mention the register type. It could be Coil/Input Register/Holding Register.
4. **Length:** Number of data to read. Ex: 5 indicates registers are read from address 0001 to 0005, a total of $5 \times 2 = 10$ bytes as each data is 2 bytes wide.
5. **Log:** If tick is enabled, the slave data pertaining to that slave id will be logger, if tick is not enabled, slave data is not logged.
6. Click Apply will write these configuration settings in the memory.
7. Clicking on Read will display the configuration that is already saved.

2.2. ADC

2.2.1. ADC Channel Settings

These Settings will configure ADC as either current channel (4-20mA) or 0-10V ADC Channel.

1. **Tick enabled** on **Enable/Disable** on a particular channel number will log that ADC channel data. **Tick Disabled** on **Enable/Disable** will not log the channel data.
2. Selecting **4-20mA** will configure the adc as a current channel, leaving adc in **0-10V** will configure adc as a normal adc channel.
3. Click Apply will write these configuration settings in the memory.



4. Clicking on Read will display the configuration that is already saved.

	Channel	Resolution	Enable/Disable	Mode
	1	16 bit	<input checked="" type="checkbox"/>	4-20mA ▼
	2	16 bit	<input type="checkbox"/>	0-10V ▼
▶	3	16 bit	<input checked="" type="checkbox"/>	4-20mA ▼
	4	16 bit	<input type="checkbox"/>	0-10V ▼
	5	10 bit	<input type="checkbox"/>	0-10V ▼
	6	10 bit	<input type="checkbox"/>	0-10V ▼
	7	10 bit	<input type="checkbox"/>	0-10V ▼
	8	10 bit	<input type="checkbox"/>	0-10V ▼

2.3. Digital Input

This Setting will indicate which digital input needs to be logged.

1. **Tick enabled** on **Enable/Disable** on a particular channel number will log that Digital Input channel data. **Tick Disabled** on **Enable/Disable** will not log the digital input channel data.
2. Click Apply will write these configuration settings in the memory.
3. Clicking on Read will display the configuration that is already saved.

Monitor
UI Settings
Log Settings
Time settings
System Log
IP Settings
Protocol Settings
Com.Port Settings
Change Password
Factory D

☐ MODBUS
 ☐ ADC
 ☐ Digital Input

MODBUS
ADC
Digital Input

	Channel	Enable/Disable
	1	<input checked="" type="checkbox"/>
	2	<input checked="" type="checkbox"/>
	3	<input type="checkbox"/>
	4	<input checked="" type="checkbox"/>
	5	<input type="checkbox"/>
	6	<input type="checkbox"/>
	7	<input checked="" type="checkbox"/>
▶	8	<input type="checkbox"/>



3. Log Settings

These settings will indicate how often logging of data needs to happen for Modbus/ADC/Digital Input.

1. **MODBUS Polling Interval:** Every polling interval of time Modbus Channel data is logged to a file. Value should be in seconds (between 1- 86400).
2. **ADC Polling Interval:** Every polling interval of time ADC Channel data is logged to a file. Value should be in seconds (between 1- 86400).
3. **Digital Input Polling:** Acts like a Master Control. Selecting enable will enable the data logging for selected channels in Modbus Setting Tab. Selecting Disable here will Disable the data logging for the digital input channels even if the channels are selected for logging in Modbus Setting Tab.
4. Click Apply will write these configuration settings in the memory.
5. Clicking on Read will display the configuration that is already saved.

Monitor UI Settings **Log Settings** Time settings System Log IP Settings Proto

MODBUS Polling Interval: 15 (sec)

ADC Polling Interval: 10 (sec)

Digital Input Polling: Enable

Apply Read

3.1. FTP Uploading Time

This setting is for uploading Modbus/ADC/Digital Input data to the server if enabled to log.

1. **MODBUS Polling Interval:** Every polling interval of time Modbus Channel data is logged to a server. Value should be in seconds (between 1- 86400).
2. **ADC Polling Interval:** Every polling interval of time ADC Channel data is logged to a server. Value should be in seconds (between 1- 86400).
3. **Digital Input Polling:** Acts like a Master Control. Selecting enable will enable the data logging for selected channels in Modbus Setting Tab. Selecting Disable here will Disable the data logging for the digital input channels even if the channels are selected for logging in Modbus Setting Tab.



4. Click Apply will write these configuration settings in the memory.
5. Clicking on Read will display the configuration that is already saved.

FTP Uploading Time _____

MODBUS Polling Interval:	<input type="text"/>	(sec)
ADC Polling Interval:	<input type="text"/>	(sec)
Digital Input Polling:	<input type="text"/>	(sec)
<input type="button" value="Apply"/>		<input type="button" value="Read"/>

4. Time Settings

4.1. Local Time

This setting is for Setting/getting time from local machine.

1. **Current Time:** Time in hour, minute and seconds.
2. **Date:** Select from the drop down menu
3. Click Save will write these time settings in the memory.
4. Clicking on Read will display the current time.

Monitor	UI Settings	Log Settings	Time settings	System Log	IP Settings	Prot
---------	-------------	--------------	---------------	------------	-------------	------

Local Time

Current Time: h: m: s:

Date:



4.2. SNTP

This setting is for Synchronizing the time from the local machine with the time from NTP serve.

1. **Enable SNTP Client:** Time in hour, minute and seconds.
2. **SNTP Time Polling:** Synchronization time which tells how often the time from local machine needs to be in sync with the NTP server.
3. **SNTP Server:** Server URL or its IP address. Ex: public NTP server IP is 198.168.0.160
4. **SNTP Path:** Path for the SNTP server.
5. Click Save will write these time settings in the memory.
6. Clicking on Read will display the current time.

SNTP

Enable SNTP Client: ☒ Enable ☐ Disable

SNTP Time Polling: (min)

SNTP Server:

SNTP Path:

5. System Log

This setting will enable or disable the system log for the list shown.

1. Presence of tick for an item in the list will enable logging system data for that item.
2. Absence of tick for an item in the list will disable logging system data for that item.
3. Click Apply will write these configuration settings in the memory.
4. Clicking on Read will display the configuration that is already saved.



UI Settings	Log Settings	Time settings	System Log
-------------	--------------	---------------	------------

- ☒ WiFi
- ☐ Ethernet
- ☐ GSM/GPRS
- ☒ SD Card
- ☐ Power ON/OFF
- ☐ FTP Server
- ☐ Cloud Push
- ☐ MODBUS
- ☐ SNTP

Save

Read

6. IP Settings

6.1. Primary Connection

This setting will choose the connection for the server.

1. **Primary Connection:** Choose the primary connection from the drop down menu; settings are enabled for the selected primary connection.
2. Click Save will save these settings in the memory.
3. Clicking on Read will display the configuration that is already saved.

Primary Connection: GSM/GPRS ▼

Save

Read



6.2. GPRS Settings

UI Settings	Log Settings	Time settings	System Log	IP Settings	Protocol Settings	Com.Port
-------------	--------------	---------------	------------	-------------	-------------------	----------

Primary Connection: GSM/GPRS ▼

Save Read

GPRS Settings WiFi Settings Ethernet Settings

APN:

Save Read

1. Choose **GSM/GPRS** in the **Primary Connection** as shown in the screenshot.
2. GPRS Settings are enabled now and ready to get/put user configuration.
3. **APN:** Provide APN for the connection. Ex: for Airtel it is "tp://airtelgprs.com".
4. Click Save will save these settings in the memory.
5. Clicking on Read will display the configuration that is already saved.



6.3. WiFi Settings

Primary Connection: WiFi

Save Read

GPRS Settings WiFi Settings Ethernet Settings

SSID:

Password:

☒ Static ☐ DHCP

IP:

Subnet Mask:

Gateway:

Save Read

1. Choose **WiFi** in the **Primary Connection** as shown in the screenshot.
2. WiFi Settings are enabled now and ready to get/put user configuration.
3. **SSID:** Provide SSID (username) of the WiFi connection(/Router).
Ex: rdl123
4. **Password:** Provide Password of the WiFi connection(/Router).
Ex: password
5. Choose whether the WiFi connection is a Static IP or DHCP.
6. **Subnet Mask:** Provide subnet mask of the WiFi connection(/Router). Ex: 255.255.240.0
7. **Gateway:** Provide Gateway of the WiFi connection(/Router). Ex: 192.168.0.1
8. Click Save will save these settings in the memory.
9. Clicking on Read will display the configuration that is already saved.



6.4. Ethernet Settings

Primary Connection: Ethernet

Save Read

GPRS Settings WiFi Settings Ethernet Settings

IP Address:

☒ Static ☐ DHCP

Subnet Mask:

Gateway:

DNS Proxy:

DNS Server:

Save Read

1. Choose **Ethernet** in the **Primary Connection** as shown in the screenshot.
2. Ethernet Settings are enabled now and ready to get/put user configuration.
3. **IP Address:** Provide IP address of the Ethernet connection. Ex: "tp://airtelgprs.com".
4. Choose whether the connection is a Static IP or DHCP.
5. **Subnet Mask:** Provide subnet mask of the Ethernet connection. Ex: 255.255.240.0
6. **Gateway:** Provide Gateway of the Ethernet connection. Ex: 192.168.0.1
7. **DNS Proxy:** Provide Gateway of the Ethernet connection. Ex: 4.3.3.3
8. **DNS Server:** Provide Gateway of the Ethernet connection. Ex: 8.8.8.8
9. Click Save will save these settings in the memory.
10. Clicking on Read will display the configuration that is already saved.



7. Protocol Settings

7.1. Choose Protocol

☒ FTP ☐ JSON ☐ MQTT ☐ None

Apply

Read

This setting will choose the protocol to be used for data logging.

1. **FTP:** Data logging happens to FTP server.
2. **JSON:** Data logging happens to JSON server.
3. **MQTT:** Data logging happens to MQTT server.
4. **None:** Data logging is disabled.
5. Click Save will save these settings in the memory.
6. Clicking on Read will display the configuration that is already saved.

7.2. FTP

☒ FTP ☐ JSON ☐ MQTT ☐ None

Apply

Read

FTP JSON MQTT

FTP Server IP:

Username:

Password:

Port Number:

IO Data Log Folder:

Sys Log Folder:

Apply

Read



1. Choose **FTP** as shown in the screenshot.
2. FTP Settings are enabled now and ready to get/put user configuration.
3. **FTP Server IP:** Provide IP address for the FTP connection. Ex: "tp://airtelgprs.com" if IP Setting is GSM?GPRS and Provider is Airtel.
4. **Username:** Provide Username for the FTP Server. Ex: rdl123
5. **Password:** Provide Password for the FTP Server. Ex: password
6. **Port Number:** Provide Port number for the FTP Server. Ex: 80
7. **IO Data Log Folder:** Provide folder name for the FTP Server. Ex: Data_Logger.
8. **Sys Log Folder:** Provide folder name for the FTP Server. Ex: Data_Logger.
9. Click Save will save these settings in the memory.
10. Clicking on Read will display the configuration that is already saved.

7.3. JSON

☐ FTP ☒ JSON ☐ MQTT ☐ None

FTP JSON MQTT

Post URL:

Hash Key:

Path:

Content Type:

1. Choose **JSON** as shown in the screenshot.
2. JSON Settings are enabled now and ready to get/put user configuration.
3. **Post URL:** Provide Server URL. Ex: "datalog.in"
4. **Hash Key:** Provide AES encryption key for security.
5. **Path:** Provide Path for the URL. Ex: "/datalogserver/datainsert.php"
6. **Content Type:** Choose from dropdown. Ex: application/json
7. Click Save will save these settings in the memory.
8. Clicking on Read will display the configuration that is already saved.



7.4. MQTT

☐ FTP ☐ JSON ☒ MQTT ☐ None

FTP JSON **MQTT**

Cloud ServerName:

Cloud UserName:

Password:

Port:

Topic:

1. Choose **MQTT** as shown in the screenshot.
2. MQTT Settings are enabled now and ready to get/put user configuration.
3. **Cloud ServerName** : Provide Server Name. Ex: "m11.cloudmqtt.com"
4. **Cloud UserName** : Provide MQTT cloud User Name.
5. **Password**: Provide MQTT cloud Password.
6. **Port**: Provide Port number for MQTT cloud. Ex: password
7. **Topic**: Provide Topic for v. Ex: RDL
8. Click Save will save these settings in the memory.
9. Clicking on Read will display the configuration that is already saved.



7.5. None

☐ FTP ☐ JSON ☐ MQTT ☒ None

Apply

Read

FTP JSON MQTT

Cloud ServerName:

Cloud UserName:

Password:

Port:

Topic:

Apply

Read

1. When **None** is chosen, all the protocol gets disabled.