

This BOM is generated using Octopart. Please visit for up-to-date component prices and materials:<http://www.alperyazar.com/r/isoUSBRs422BOMv1> Generated @ 15386

Qty	Line Item	Manufacturer	MPN	Schematic Reference	Description
2	PSM712LFT7	Protek Devices	PSM712-LF-T7	D104 D105	
1	MI0805K601R-10	Laird	MI0805K601R-10	FB101	
1	MF-MSMF050-2	Bourns	MF-MSMF050-2	TH101	
1	FT230XS-R	FTDI	FT230XS-R	U101	
3	SN74LVC2T45DCUR	Texas Instruments	SN74LVC2T45DCUR	U102 U103 U105	
1	ADM2682EBRIZ	Analog Devices	ADM2682EBRIZ	U104	
7	0805YC475KAT2A	AVX	0805YC475KAT2A	C105 C107 C112 C115 C122 C123 C126	Alternatives with the same capacitance and package size may be used. Not so critical.
3	C0603C103K5RACTU	Kemet	C0603C103K5RACTU	C106 C113 C117	Alternatives with the same capacitance and package size may be used. Not so critical.
2	C0603C470J5GACTU	Kemet	C0603C470J5GACTU	C101 C102	Alternatives with the same capacitance and package size may be used. Not so critical.
2	1206YC106KAT2A	AVX	1206YC106KAT2A	C114 C119	Alternatives with the same capacitance and package size may be used. Not so critical.
12	C0603C104K4RACTU	Kemet	C0603C104K4RACTU	C103 C104 C108 C109 C110 C111 C116 C118 C120 C121 C124 C125	Alternatives with the same capacitance and package size may be used. Not so critical.
1	ADA724	Adafruit Industries	ADA724	J102 J103 J104	Just randomly chosen 3.5mm pitch 2 pin screw terminals.
1	61400416121	Würth Elektronik	61400416121	J101	Just randomly chosen an USB Type-B connector.
6	CR0603-J/-000ELF	Bourns	CR0603-J/-000ELF	R113 R114 R116 R117 R118 R119	Just randomly chosen 0 ohms. You may even make a solder bridge insted of a resistor!
2	CR0603-FX-27R0ELF	Bourns	CR0603-FX-27R0ELF	R101 R102	Alternatives with the same resistance, tolerance and package size may be used.
1	CR0603-FX-1210ELF	Bourns	CR0603-FX-1210ELF	R115	THERE IS A PROBLEM WITH THIS RESISTOR. SEE "KNOWN PROBLEMS". Alternatives with the same resistance, tolerance and package size may be used.

2	CR0603-FX-2700GLF	Bourns	CR0603-FX-2700GLF	<i>R104 R105</i>	Alternatives with the same resistance, tolerance and package size may be used.
1	CR0603-FX-3300GLF	Bourns	CR0603-FX-3300GLF	<i>R103</i>	Alternatives with the same resistance, tolerance and package size may be used.
8	CR0603-FX-1002GLF	Bourns	CR0603-FX-1002GLF	<i>R106 R107 R108 R109 R110 R111 R112 R120</i>	Alternatives with the same resistance, tolerance and package size may be used.
2	HSMS-C680	Avago	HSMS-C680	<i>D101 D103</i>	Actually, I used LED from another brand but it is hard to find the same part on the market. Therefore, you should be able to use this LED without having so much trouble. However, I didn't verify this part.
1	HSMG-C680	Avago	HSMG-C680	<i>D102</i>	Actually, I used LED from another brand but it is hard to find the same part on the market. Therefore, you should be able to use this LED without having so much trouble. However, I didn't verify this part.